

[manuals.plus](#) /› [TEEHO](#) /› [TEEHO Keyless Entry Keypad Door Lock with Handle \(Model TE003\) - Instruction Manual](#)**TEEHO TE003**

TEEHO Keyless Entry Keypad Door Lock with Handle (Model TE003) - Instruction Manual

Your guide to installation, operation, and maintenance.

1. INTRODUCTION

This manual provides detailed instructions for the TEEHO Keyless Entry Keypad Door Lock with Handle, model TE003. Please read this manual thoroughly before installation and operation to ensure proper function and longevity of your lock.

1.1 Package Contents

Verify that all components are present before beginning installation.

- Keypad Door Knob (Exterior Assembly)
- Interior Handle Assembly
- Mounting Plate
- Screws (various sizes)
- Latch
- Strike Plate
- 2 Backup Keys
- Instructions Manual (this document)



Image 1.1: TEEHO Keyless Entry Keypad Door Lock with Handle and included backup keys.

2. SPECIFICATIONS

The TEEHO TE003 lock is designed for robust performance and ease of use. Below are its key specifications and features.

Feature	Description
Brand	TEEHO
Model Name	TE003
Lock Type	Keypad, Combination Lock
Material	Aluminum

Dimensions (L x W x H)	5.43 x 3 x 3.5 inches
Item Weight	2.73 Pounds
Power Source	Batteries Required (Not Included)
Special Features	Passage Mode, Back-Lit Keypad, 20 Individual User Codes, One-time Access, Auto Lock, One-touch Lock, Anti-peeping Password, Vacation Mode, Mute Mode, Wrong Entry Limit, IP54 Waterproof
Certifications	ANSI Grade 3 Certified, BHMA Certified




Image 2.1: The lock features IP54 waterproofing and resistance to extreme temperatures.



Image 2.2: The lock is BHMA and ANSI Grade 3 certified, indicating durability and security through various tests.

3. INSTALLATION

The TEEHO TE003 lock is designed for easy installation, typically requiring only a screwdriver and approximately 10 minutes. No drilling is required for standard installations.

3.1 Pre-Installation Checks

Before installation, confirm your door's dimensions match the lock's requirements:

- **Door Thickness:** 1-3/8" to 2" (35mm-50mm)
- **Backset:** 2-3/8" (60mm) or 2-3/4" (70mm)
- **Latchbolt Throw:** 3/4" (20mm)
- **Hole Diameter:** 2-1/8" (54mm)

Confirm Fit Before Purchase

1 Door Thickness

1-3/8" to 2" (35mm-50mm)

2 Backset

2-3/8"(60mm) or 2-3/4"(70mm)

3 Latchbolt Throw

3/4"(20mm)

4 Hole Diameter

2-1/8" (54mm)




Left

Handed Door



Right

Handed Door



3" (76mm)



2.7" (68mm)



3.5" (90mm)



3.8" (96mm)

6.2" (157mm)

Image 3.1: Confirm door fit before purchase by checking these critical dimensions.



Image 3.2: Detailed measurements for backset, bore diameter, hole diameter, and door thickness.

3.2 Installation Steps

Follow the step-by-step instructions provided in the included quick start guide for precise installation. Ensure all components are aligned correctly for optimal performance. The lock automatically identifies left and right-handed doors.



Image 3.3: The lock automatically adjusts for left or right-handed door configurations.

Stronger and More Durable



IP54 Water Proof



BHMA Certified



ANSI Certified



Low Battery Alert



Others

Plastic

✗ Lightweight

✗ Deforms Easily

✗ Not Weatherproof

✗ Weak Anti-theft

TECHO

Aluminum Alloy



✓ Heavy-duty

✓ Stable & Durable

✓ Weather Resistant

✓ Enhanced Security

Image 3.4: Installation is straightforward and can be completed with a single screwdriver.

Inside Locking for Privacy



Image 3.5: The lock is compatible with various existing door hardware configurations.

4. OPERATION

The TEEHO TE003 offers multiple convenient ways to secure and access your door.

4.1 Unlocking Methods

- **Keypad Code:** Program up to 20 unique user passwords for regular access.
- **Physical Keys:** Use the two provided backup keys for traditional unlocking.
- **One-Time Code:** Generate temporary codes for guests or service personnel that expire after a single use.
- **Passage Mode:** Disable automatic locking for continuous access during specific periods.



Image 4.1: Multiple unlocking options provide flexibility and convenience.




Image 4.2: Program up to 20 unique user codes for various individuals.



Image 4.3: Easily share temporary access codes with others.

One-Time Code



The Entry Code
is **135194**



Family



Friends



Repairman



Courier

Okay, I'm in.
Thanks



Image 4.4: One-time codes are ideal for temporary access for visitors or service providers.

Backup Keys

Don't worry about forgetting your password



Image 4.5: Backup keys provide an alternative entry method.

4.2 Locking Methods

- **Automatic Lock:** The lock can be set to automatically lock within 10-99 seconds after the door closes.
- **One-Touch Lock:** Manually lock the door from the outside by holding any key on the keypad for 2 seconds.

Worry-Free Auto Lock



Image 4.6: The lock offers both automatic and one-touch manual locking.




Image 4.7: Activate one-touch locking by holding any key for 2 seconds.



Image 4.8: The auto-lock feature can be enabled or disabled as needed.




Image 4.9: Disable auto-lock for periods of frequent entry and exit.

4.3 Advanced Features

- **Anti-Peeping Password:** Enter random digits before or after your actual code to prevent others from guessing your password.

- **Wrong Code Entry Limit:** The lock will temporarily disable after multiple incorrect code attempts, enhancing security.
- **Vacation Mode:** A security feature for extended absences.
- **Mute Mode:** Silence keypad tones for quiet operation.




Image 4.10: Use the anti-peeping feature to protect your code from onlookers.



Image 4.11: Enable mute mode for silent keypad operation.





Image 4.12: Vacation mode provides enhanced security when you are away.

Easy Installation, No Professional Needed



Garage



Bedroom



Office

Image 4.13: The interior handle includes a privacy lock for added security from within.

5. MAINTENANCE

5.1 Battery Replacement

The TEEHO TE003 lock requires batteries for operation. Rechargeable batteries are not recommended. The lock features a low battery alert to notify you when replacement is needed.



Image 5.1: The lock provides a low battery alert and features a backlit keypad for visibility.

5.2 Cleaning

To clean the lock, use a soft, damp cloth. Avoid abrasive cleaners or solvents that could damage the finish or electronic components.

6. TROUBLESHOOTING

If you encounter issues with your TEEHO TE003 lock, consider the following common solutions:

- **Lock not responding:** Check battery levels and replace if necessary. Ensure the keypad is clean and free of debris.
- **Lock not latching properly:** Verify that the installation alignment is correct. Minor adjustments to the strike plate or latch may be needed. Environmental factors like door frame swelling can affect alignment over time.
- **Code not working:** Re-enter the code carefully. Ensure you are not in vacation mode or that the one-time code has not expired.
- **Keypad unresponsive:** If the keypad is completely unresponsive, check battery connections.

For persistent issues, please refer to the warranty and support section for customer service contact information.

7. WARRANTY AND SUPPORT

TEEHO is committed to customer satisfaction and provides comprehensive support for your product.

7.1 Warranty Information

TEEHO offers a **30-day customer commitment**, a **1-year product support** on all parts, and **lifetime after-sales customer service**.

7.2 Customer Service



For assistance, please contact TEEHO customer service:

- **Online Phone Support:** Monday to Friday, 9 AM to 5 PM PST
- **Online Email Service:** Available 24/7

Refer to your product packaging or the official TEEHO website for specific contact details.

© 2025 TEEHO. All rights reserved.

Related Documents - TE003

	<p><u>TEEHO Smart Lock Programming Instructions and Troubleshooting Guide</u></p> <p>Comprehensive guide to programming TEEHO smart locks, including setting master/user PIN codes, auto-lock, silent mode, vacation mode, and troubleshooting common issues for models like the TE004.</p>
	<p><u>TEEHO TE002 Fingerprint Door Lock Installation and Programming Guide</u></p> <p>Comprehensive guide for installing and programming the TEEHO TE002 Fingerprint Door Lock, covering door preparation, parts identification, installation steps, and various programming functions.</p>
	<p><u>TEEHO TE001/TE001K Keyless Entry Door Lock Programming Instructions</u></p> <p>Comprehensive programming instructions for the TEEHO TE001 and TE001K keyless entry door locks, covering installation, usage, feature settings, and troubleshooting.</p>
	<p><u>TEEHO TE002K Fingerprint Door Lock Installation Guide</u></p> <p>Comprehensive installation instructions for the TEEHO TE002K Fingerprint Door Lock, detailing door preparation, parts identification, and step-by-step assembly for a secure and easy setup.</p>
	<p><u>TEEHO TZ001 Keypad Door Lock Installation Instructions</u></p> <p>Comprehensive installation guide for the TEEHO TZ001 Keypad Door Lock, detailing door preparation, parts identification, and step-by-step assembly for a secure and functional smart lock.</p>
	<p><u>TEEHO Keyless Entry Door Lock Programming Instructions</u></p> <p>Comprehensive programming instructions for TEEHO keyless entry electronic door locks, covering setup, features, and troubleshooting for model TK004.</p>

Documents - TEEHO – TE003

The image shows the front cover of the Teeho Installation Manual. The cover is white with a blue header containing the brand name 'TEEOHO' in a bold, sans-serif font. Below the header is a large, bold, black title 'Installation Manual'. Underneath the title is a blue horizontal bar with the text 'Model No. TE003' in white. The main body of the cover features a large, bold, black text 'Need Help? Contact Us!' followed by a smaller line of text 'If you have any questions, please contact us at'. Below this text are four contact icons: a telephone icon with the phone number '+1 (833) 878-3346' and the note '(Monday-Friday 9:00 am-5:00 pm PST)'; an envelope icon with the email address 'support@teeho.com'; and a globe icon with the website 'teeho.com'. At the bottom of the cover is a large, square QR code. To the right of the QR code is the text 'Scan the QR code and search TE003' with a magnifying glass icon. Below the QR code is the text 'Please watch these videos first and use this manual as a guide.'

Quick Set up

TE003 / TE004

IMPORTANT: The earliest date is 12/24/07, it is required that you change this date	
Change User Code	<input type="button" value="User Code 1"/> <input type="button" value="User Code 2"/> <input type="button" value="User Code 3"/> <input type="button" value="User Code 4"/> <input type="button" value="User Code 5"/> <input type="button" value="User Code 6"/> <input type="button" value="User Code 7"/> <input type="button" value="User Code 8"/> <input type="button" value="User Code 9"/> <input type="button" value="User Code 10"/> <input type="button" value="User Code 11"/> <input type="button" value="User Code 12"/> <input type="button" value="User Code 13"/> <input type="button" value="User Code 14"/> <input type="button" value="User Code 15"/> <input type="button" value="User Code 16"/> <input type="button" value="User Code 17"/> <input type="button" value="User Code 18"/> <input type="button" value="User Code 19"/> <input type="button" value="User Code 20"/> <input type="button" value="User Code 21"/> <input type="button" value="User Code 22"/> <input type="button" value="User Code 23"/> <input type="button" value="User Code 24"/> <input type="button" value="User Code 25"/> <input type="button" value="User Code 26"/> <input type="button" value="User Code 27"/> <input type="button" value="User Code 28"/> <input type="button" value="User Code 29"/> <input type="button" value="User Code 30"/> <input type="button" value="User Code 31"/> <input type="button" value="User Code 32"/> <input type="button" value="User Code 33"/> <input type="button" value="User Code 34"/> <input type="button" value="User Code 35"/> <input type="button" value="User Code 36"/> <input type="button" value="User Code 37"/> <input type="button" value="User Code 38"/> <input type="button" value="User Code 39"/> <input type="button" value="User Code 40"/> <input type="button" value="User Code 41"/> <input type="button" value="User Code 42"/> <input type="button" value="User Code 43"/> <input type="button" value="User Code 44"/> <input type="button" value="User Code 45"/> <input type="button" value="User Code 46"/> <input type="button" value="User Code 47"/> <input type="button" value="User Code 48"/> <input type="button" value="User Code 49"/> <input type="button" value="User Code 50"/> <input type="button" value="User Code 51"/> <input type="button" value="User Code 52"/> <input type="button" value="User Code 53"/> <input type="button" value="User Code 54"/> <input type="button" value="User Code 55"/> <input type="button" value="User Code 56"/> <input type="button" value="User Code 57"/> <input type="button" value="User Code 58"/> <input type="button" value="User Code 59"/> <input type="button" value="User Code 60"/> <input type="button" value="User Code 61"/> <input type="button" value="User Code 62"/> <input type="button" value="User Code 63"/> <input type="button" value="User Code 64"/> <input type="button" value="User Code 65"/> <input type="button" value="User Code 66"/> <input type="button" value="User Code 67"/> <input type="button" value="User Code 68"/> <input type="button" value="User Code 69"/> <input type="button" value="User Code 70"/> <input type="button" value="User Code 71"/> <input type="button" value="User Code 72"/> <input type="button" value="User Code 73"/> <input type="button" value="User Code 74"/> <input type="button" value="User Code 75"/> <input type="button" value="User Code 76"/> <input type="button" value="User Code 77"/> <input type="button" value="User Code 78"/> <input type="button" value="User Code 79"/> <input type="button" value="User Code 80"/> <input type="button" value="User Code 81"/> <input type="button" value="User Code 82"/> <input type="button" value="User Code 83"/> <input type="button" value="User Code 84"/> <input type="button" value="User Code 85"/> <input type="button" value="User Code 86"/> <input type="button" value="User Code 87"/> <input type="button" value="User Code 88"/> <input type="button" value="User Code 89"/> <input type="button" value="User Code 90"/> <input type="button" value="User Code 91"/> <input type="button" value="User Code 92"/> <input type="button" value="User Code 93"/> <input type="button" value="User Code 94"/> <input type="button" value="User Code 95"/> <input type="button" value="User Code 96"/> <input type="button" value="User Code 97"/> <input type="button" value="User Code 98"/> <input type="button" value="User Code 99"/> <input type="button" value="User Code 100"/> <input type="button" value="User Code 101"/> <input type="button" value="User Code 102"/> <input type="button" value="User Code 103"/> <input type="button" value="User Code 104"/> <input type="button" value="User Code 105"/> <input type="button" value="User Code 106"/> <input type="button" value="User Code 107"/> <input type="button" value="User Code 108"/> <input type="button" value="User Code 109"/> <input type="button" value="User Code 110"/> <input type="button" value="User Code 111"/> <input type="button" value="User Code 112"/> <input type="button" value="User Code 113"/> <input type="button" value="User Code 114"/> <input type="button" value="User Code 115"/> <input type="button" value="User Code 116"/> <input type="button" value="User Code 117"/> <input type="button" value="User Code 118"/> <input type="button" value="User Code 119"/> <input type="button" value="User Code 120"/> <input type="button" value="User Code 121"/> <input type="button" value="User Code 122"/> <input type="button" value="User Code 123"/> <input type="button" value="User Code 124"/> <input type="button" value="User Code 125"/> <input type="button" value="User Code 126"/> <input type="button" value="User Code 127"/> <input type="button" value="User Code 128"/> <input type="button" value="User Code 129"/> <input type="button" value="User Code 130"/> <input type="button" value="User Code 131"/> <input type="button" value="User Code 132"/> <input type="button" value="User Code 133"/> <input type="button" value="User Code 134"/> <input type="button" value="User Code 135"/> <input type="button" value="User Code 136"/> <input type="button" value="User Code 137"/> <input type="button" value="User Code 138"/> <input type="button" value="User Code 139"/> <input type="button" value="User Code 140"/> <input type="button" value="User Code 141"/> <input type="button" value="User Code 142"/> <input type="button" value="User Code 143"/> <input type="button" value="User Code 144"/> <input type="button" value="User Code 145"/> <input type="button" value="User Code 146"/> <input type="button" value="User Code 147"/> <input type="button" value="User Code 148"/> <input type="button" value="User Code 149"/> <input type="button" value="User Code 150"/> <input type="button" value="User Code 151"/> <input type="button" value="User Code 152"/> <input type="button" value="User Code 153"/> <input type="button" value="User Code 154"/> <input type="button" value="User Code 155"/> <input type="button" value="User Code 156"/> <input type="button" value="User Code 157"/> <input type="button" value="User Code 158"/> <input type="button" value="User Code 159"/> <input type="button" value="User Code 160"/> <input type="button" value="User Code 161"/> <input type="button" value="User Code 162"/> <input type="button" value="User Code 163"/> <input type="button" value="User Code 164"/> <input type="button" value="User Code 165"/> <input type="button" value="User Code 166"/> <input type="button" value="User Code 167"/> <input type="button" value="User Code 168"/> <input type="button" value="User Code 169"/> <input type="button" value="User Code 170"/> <input type="button" value="User Code 171"/> <input type="button" value="User Code 172"/> <input type="button" value="User Code 173"/> <input type="button" value="User Code 174"/> <input type="button" value="User Code 175"/> <input type="button" value="User Code 176"/> <input type="button" value="User Code 177"/> <input type="button" value="User Code 178"/> <input type="button" value="User Code 179"/> <input type="button" value="User Code 180"/> <input type="button" value="User Code 181"/> <input type="button" value="User Code 182"/> <input type="button" value="User Code 183"/> <input type="button" value="User Code 184"/> <input type="button" value="User Code 185"/> <input type="button" value="User Code 186"/> <input type="button" value="User Code 187"/> <input type="button" value="User Code 188"/> <input type="button" value="User Code 189"/> <input type="button" value="User Code 190"/> <input type="button" value="User Code 191"/> <input type="button" value="User Code 192"/> <input type="button" value="User Code 193"/> <input type="button" value="User Code 194"/> <input type="button" value="User Code 195"/> <input type="button" value="User Code 196"/> <input type="button" value="User Code 197"/> <input type="button" value="User Code 198"/> <input type="button" value="User Code 199"/> <input type="button" value="User Code 200"/> <input type="button" value="User Code 201"/> <input type="button" value="User Code 202"/> <input type="button" value="User Code 203"/> <input type="button" value="User Code 204"/> <input type="button" value="User Code 205"/> <input type="button" value="User Code 206"/> <input type="button" value="User Code 207"/> <input type="button" value="User Code 208"/> <input type="button" value="User Code 209"/> <input type="button" value="User Code 210"/> <input type="button" value="User Code 211"/> <input type="button" value="User Code 212"/> <input type="button" value="User Code 213"/> <input type="button" value="User Code 214"/> <input type="button" value="User Code 215"/> <input type="button" value="User Code 216"/> <input type="button" value="User Code 217"/> <input type="button" value="User Code 218"/> <input type="button" value="User Code 219"/> <input type="button" value="User Code 220"/> <input type="button" value="User Code 221"/> <input type="button" value="User Code 222"/> <input type="button" value="User Code 223"/> <input type="button" value="User Code 224"/> <input type="button" value="User Code 225"/> <input type="button" value="User Code 226"/> <input type="button" value="User Code 227"/> <input type="button" value="User Code 228"/> <input type="button" value="User Code 229"/> <input type="button" value="User Code 230"/> <input type="button" value="User Code 231"/> <input type="button" value="User Code 232"/> <input type="button" value="User Code 233"/> <input type="button" value="User Code 234"/> <input type="button" value="User Code 235"/> <input type="button" value="User Code 236"/> <input type="button" value="User Code 237"/> <input type="button" value="User Code 238"/> <input type="button" value="User Code 239"/> <input type="button" value="User Code 240"/> <input type="button" value="User Code 241"/> <input type="button" value="User Code 242"/> <input type="button" value="User Code 243"/> <input type="button" value="User Code 244"/> <input type="button" value="User Code 245"/> <input type="button" value="User Code 246"/> <input type="button" value="User Code 247"/> <input type="button" value="User Code 248"/> <input type="button" value="User Code 249"/> <input type="button" value="User Code 250"/> <input type="button" value="User Code 251"/> <input type="button" value="User Code 252"/> <input type="button" value="User Code 253"/> <input type="button" value="User Code 254"/> <input type="button" value="User Code 255"/> <input type="button" value="User Code 256"/> <input type="button" value="User Code 257"/> <input type="button" value="User Code 258"/> <input type="button" value="User Code 259"/> <input type="button" value="User Code 260"/> <input type="button" value="User Code 261"/> <input type="button" value="User Code 262"/> <input type="button" value="User Code 263"/> <input type="button" value="User Code 264"/> <input type="button" value="User Code 265"/> <input type="button" value="User Code 266"/> <input type="button" value="User Code 267"/> <input type="button" value="User Code 268"/> <input type="button" value="User Code 269"/> <input type="button" value="User Code 270"/> <input type="button" value="User Code 271"/> <input type="button" value="User Code 272"/> <input type="button" value="User Code 273"/> <input type="button" value="User Code 274"/> <input type="button" value="User Code 275"/> <input type="button" value="User Code 276"/> <input type="button" value="User Code 277"/> <input type="button" value="User Code 278"/> <input type="button" value="User Code 279"/> <input type="button" value="User Code 280"/> <input type="button" value="User Code 281"/> <input type="button" value="User Code 282"/> <input type="button" value="User Code 283"/> <input type="button" value="User Code 284"/> <input type="button" value="User Code 285"/> <input type="button" value="User Code 286"/> <input type="button" value="User Code 287"/> <input type="button" value="User Code 288"/> <input type="button" value="User Code 289"/> <input type="button" value="User Code 290"/> <input type="button" value="User Code 291"/> <input type="button" value="User Code 292"/> <input type="button" value="User Code 293"/> <input type="button" value="User Code 294"/> <input type="button" value="User Code 295"/> <input type="button" value="User Code 296"/> <input type="button" value="User Code 297"/> <input type="button" value="User Code 298"/> <input type="button" value="User Code 299"/> <input type="button" value="User Code 300"/> <input type="button" value="User Code 301"/> <input type="button" value="User Code 302"/> <input type="button" value="User Code 303"/> <input type="button" value="User Code 304"/> <input type="button" value="User Code 305"/> <input type="button" value="User Code 306"/> <input type="button" value="User Code 307"/> <input type="button" value="User Code 308"/> <input type="button" value="User Code 309"/> <input type="button" value="User Code 310"/> <input type="button" value="User Code 311"/> <input type="button" value="User Code 312"/> <input type="button" value="User Code 313"/> <input type="button" value="User Code 314"/> <input type="button" value="User Code 315"/> <input type="button" value="User Code 316"/> <input type="button" value="User Code 317"/> <input type="button" value="User Code 318"/> <input type="button" value="User Code 319"/> <input type="button" value="User Code 320"/> <input type="button" value="User Code 321"/> <input type="button" value="User Code 322"/> <input type="button" value="User Code 323"/> <input type="button" value="User Code 324"/> <input type="button" value="User Code 325"/> <input type="button" value="User Code 326"/> <input type="button" value="User Code 327"/> <input type="button" value="User Code 328"/> <input type="button" value="User Code 329"/> <input type="button" value="User Code 330"/> <input type="button" value="User Code 331"/> <input type="button" value="User Code 332"/> <input type="button" value="User Code 333"/> <input type="button" value="User Code 334"/> <input type="button" value="User Code 335"/> <input type="button" value="User Code 336"/> <input type="button" value="User Code 337"/> <input type="button" value="User Code 338"/> <input type="button" value="User Code 339"/> <input type="button" value="User Code 340"/> <input type="button" value="User Code 341"/> <input type="button" value="User Code 342"/> <input type="button" value="User Code 343"/> <input type="button" value="User Code 344"/> <input type="button" value="User Code 345"/> <input type="button" value="User Code 346"/> <input type="button" value="User Code 347"/> <input type="button" value="User Code 348"/> <input type="button" value="User Code 349"/> <input type="button" value="User Code 350"/> <input type="button" value="User Code 351"/> <input type="button" value="User Code 352"/> <input type="button" value="User Code 353"/> <input type="button" value="User Code 354"/> <input type="button" value="User Code 355"/> <input type="button" value="User Code 356"/> <input type="button" value="User Code 357"/> <input type="button" value="User Code 358"/> <input type="button" value="User Code 359"/> <input type="button" value="User Code 360"/> <input type="button" value="User Code 361"/> <input type="button" value="User Code 362"/> <input type="button" value="User Code 363"/> <input type="button" value="User Code 364"/> <input type="button" value="User Code 365"/> <input type="button" value="User Code 366"/> <input type="button" value="User Code 367"/> <input type="button" value="User Code 368"/> <input type="button" value="User Code 369"/> <input type="button" value="User Code 370"/> <input type="button" value="User Code 371"/> <input type="button" value="User Code 372"/> <input type="button" value="User Code 373"/> <input type="button" value="User Code 374"/> <input type="button" value="User Code 375"/> <input type="button" value="User Code 376"/> <input type="button" value="User Code 377"/> <input type="button" value="User Code 378"/> <input type="button" value="User Code 379"/> <input type="button" value="User Code 380"/> <input type="button" value="User Code 381"/> <input type="button" value="User Code 382"/> <input type="button" value="User Code 383"/> <input type="button" value="User Code 384"/> <input type="button" value="User Code 385"/> <input type="button" value="User Code 386"/> <input type="button" value="User Code 387"/> <input type="button" value="User Code 388"/> <input type="button" value="User Code 389"/> <input type="button" value="User Code 390"/> <input type="button" value="User Code 391"/> <input type="button" value="User Code 392"/> <input type="button" value="User Code 393"/> <input type="button" value="User Code 394"/> <input type="button" value="User Code 395"/> <input type="button" value="User Code 396"/> <input type="button" value="User Code 397"/> <input type="button" value="User Code 398"/> <input type="button" value="User Code 399"/> <input type="button" value="User Code 400"/> <input type="button" value="User Code 401"/> <input type="button" value="User Code 402"/> <input type="button" value="User Code 403"/> <input type="button" value="User Code 404"/> <input type="button" value="User Code 405"/> <input type="button" value="User Code 406"/> <input type="button" value="User Code 407"/> <input type="button" value="User Code 408"/> <input type="button" value="User Code 409"/> <input type="button" value="User Code 410"/> <input type="button" value="User Code 411"/> <input type="button" value="User Code 412"/> <input type="button" value="User Code 413"/> <input type="button" value="User Code 414"/> <input type="button" value="User Code 415"/> <input type="button" value="User Code 416"/> <input type="button" value="User Code 417"/> <input type="button" value="User Code 418"/> <input type="button" value="User Code 419"/> <input type="button" value="User Code 420"/> <input type="button" value="User Code 421"/> <input type="button" value="User Code 422"/> <input type="button" value="User Code 423"/> <input type="button" value="User Code 424"/> <input type="button" value="User Code 425"/> <input type="button" value="User Code 426"/> <input type="button" value="User Code 427"/> <input type="button" value="User Code 428"/> <input type="button" value="User Code 429"/> <input type="button" value="User Code 430"/> <input type="button" value="User Code 431"/> <input type="button" value="User Code 432"/> <input type="button" value="User Code 433"/> <input type="button" value="User Code 434"/> <input type="button" value="User Code 435"/> <input type="button" value="User Code 436"/> <input type="button" value="User Code 437"/> <input type="button" value="User Code 438"/> <input type="button" value="User Code 439"/> <input type="button" value="User Code 440"/> <input type="button" value="User Code 441"/> <input type="button" value="User Code 442"/> <input type="button" value="User Code 443"/> <input type="button" value="User Code 444"/> <input type="button" value="User Code 445"/> <input type="button" value="User Code 446"/> <input type="button" value="User Code 447"/> <input type="button" value="User Code 448"/> <input type="button" value="User Code 449"/> <input type="button" value="User Code 450"/> <input type="button" value="User Code 451"/> <input type="button" value="User Code 452"/> <input type="button" value="User Code 453"/> <input type="button" value="User Code 454"/> <input type="button" value="User Code 455"/> <input type="button" value="User Code 456"/> <input type="button" value="User Code 457"/> <input type="button" value="User Code 458"/> <input type="button" value="User Code 459"/> <input type="button" value="User Code 460"/> <input type="button" value="User Code 461"/> <input type="button" value="User Code 462"/> <input type="button" value="User Code 463"/> <input type="button" value="User Code 464"/> <input type="button" value="User Code 465"/> <input type="button" value="User Code 466"/> <input type="button" value="User Code 467"/> <input type="button" value="User Code 468"/> <input type="button" value="User Code 469"/> <input type="button" value="User Code 470"/> <input type="button" value="User Code 471"/> <input type="button" value="User Code 472"/> <input type="button" value="User Code 473"/> <input type="button" value="User Code 474"/> <input type="button" value="User Code 475"/> <input type="button" value="User Code 476"/> <input type="button" value="User Code 477"/> <input type="button" value="User Code 478"/> <input type="button" value="User Code 479"/> <input type="button" value="User Code 480"/> <input type="button" value="User Code 481"/> <input type="button" value="User Code 482"/> <input type="button" value="User Code 483"/> <input type="button" value="User Code 484"/> <input type="button" value="User Code 485"/> <input type="button" value="User Code 486"/> <input type="button" value="User Code 487"/> <input type="button" value="User Code 488"/> <input type="button" value="User Code 489"/> <input type="button" value="User Code 490"/> <input type="button" value="User Code 491"/> <input type="button" value="User Code 492"/> <input type="button" value="User Code 493"/> <input type="button" value="User Code 494"/> <input type="button" value="User Code 495"/> <input type="button" value="User Code 496"/> <input type="button" value="User Code 497"/> <input type="button" value="User Code 498"/> <input type="button" value="User Code 499"/> <input type="button" value="User Code 500"/> <input type="button" value="User Code 501"/> <input type="button" value="User Code 502"/> <input type="button" value="User Code 503"/> <input type="button" value="User Code 504"/> <input type="button" value="User Code 505"/> <input type="button" value="User Code 506"/> <input type="button" value="User Code 507"/> <input type="button" value="User Code 508"/> <input type="button" value="User Code 509"/> <input type="button" value="User Code 510"/> <input type="button" value="User Code 511"/> <input type="button" value="User Code 512"/> <input type="button" value="User Code 513"/> <input type="button" value="User Code 514"/> <input type="button" value="User Code 515"/> <input type="button" value="User Code 516"/> <input type="button" value="User Code 517"/> <input type="button" value="User Code 518"/> <input type="button" value="User Code 519"/> <input type="button" value="User Code 520"/> <input type="button" value="User Code 521"/> <input type="button" value="User Code 522"/> <input type="button" value="User Code 523"/> <input type="button" value="User Code 524"/> <input type="button" value="User Code 525"/> <input type="button" value="User Code 526"/> <input type="button" value="User Code 527"/> <input type="button" value="User Code 528"/> <input type="button" value="User Code 529"/> <input type="button" value="User Code 530"/> <input type="button" value="User Code 531"/> <input type="button" value="User Code 532"/> <input type="button" value="User Code 533"/> <input type="button" value="User Code 534"/> <input type="button" value="User Code 535"/> <input type="button" value="User Code 536"/> <input type="button" value="User Code 537"/> <input type="button" value="User Code 538"/> <input type="button" value="User Code 539"/> <input type="button" value="User Code 540"/> <input type="button" value="User Code 541"/> <input type="button" value="User Code 542"/> <input type="button" value="User Code 543"/> <input type="button" value="User Code 544"/> <input type="button" value="User Code 545"/> <input type="button" value="User Code 546"/> <input type="button" value="User Code 547"/> <input type="button" value="User Code 548"/> <input type="button" value="User Code 549"/> <input type="button" value="User Code 550"/> <input type="button" value="User Code 551"/> <input type="button" value="User Code 552"/> <input type="button" value="User Code 553"/> <input type="button" value="User Code 554"/> <input type="button" value="User Code 555"/> <input type="button" value="User Code 556"/> <input type="button" value="User Code 557"/> <input type="button" value="User Code 558"/> <input type="button" value="User Code 559"/> <input type="button" value="User Code 560"/> <input type="button" value="User Code 561"/> <input type="button" value="User Code 562"/> <input type="button" value="User Code 563"/> <input type="button" value="User Code 564"/> <input type="button" value="User Code 565"/> <input type="button" value="User Code 566"/> <input type="button" value="User Code 567"/> <input type="button" value="User Code 568"/> <input type="button" value="User Code 569"/> <input type="button" value="User Code 570"/> <input type="button" value="User Code 571"/> <input type="button" value="User Code 572"/> <input type="button" value="User Code 573"/> <input type="button" value="User Code 574"/> <input type="button" value="User Code 575"/> <input type="button" value="User Code 576"/> <input type="button" value="User Code 577"/> <input type="button" value="User Code 578"/> <input type="button" value="User Code 579"/> <input type="button" value="User Code 580"/> <input type="button" value="User Code 581"/> <input type="button" value="User Code 582"/> <input type="button" value="User Code 583"/> <input type="button" value="User Code 584"/> <input type="button" value="User Code 585"/> <input type="button" value="User Code 586"/> <input type="button" value="User Code 587"/> <input type="button" value="User Code 588"/> <input type="button" value="User Code 589"/> <input type="button" value="User Code 590"/> <input type="button" value="User Code 591"/> <input type="button" value="User Code 592"/> <input type="button" value="User Code 593"/> <input type="button" value="User Code 594"/> <input type="button" value="User Code 595"/> <input type="button" value="User Code 596"/> <input type="button" value="User Code 597"/> <input type="button" value="User Code 598"/> <input type="button" value="User Code 599"/> <input type="button" value="User Code 600"/> <input type="button" value="User Code 601"/> <input type="button" value="User Code 602"/> <input type="button" value="User Code 603"/> <input type="button" value="User Code 604"/> <input type="button" value="User Code 605"/> <input type="button" value="User Code 606"/> <input type="button" value="User Code 607"/> <input type="button" value="User Code 608"/> <input type="button" value="User Code 609"/> <input type="button" value="User Code 610"/> <input type="button" value="User Code 611"/> <input type="button" value="User Code 612"/> <input type="button" value="User Code 613"/> <input type="button" value="User Code 614"/> <input type="button" value="User Code 615"/> <input type="button" value="User Code 616"/> <input type="button" value="User Code 617"/> <input type="button" value="User Code 618"/> <input type="button" value="User Code 619"/> <input type="button" value="User Code 620"/> <input type="button" value="User Code 621"/> <input type="button" value="User Code 622"/> <input type="button" value="User Code 623"/> <input type="button" value="User Code 624"/> <input type="button" value="User Code 625"/> <input type="button" value="User Code 626"/> <input type="button" value="User Code 627"/> <input type="button" value="User Code 628"/> <input type="button" value="User Code 629"/> <input type="button" value="User Code 630"/> <input type="button" value="User Code 631"/> <input type="button" value="User Code 632"/> <input type="button" value="User Code 633"/> <input type="button" value="User Code 634"/> <input type="button" value="User Code 635"/> <input type="button" value="User Code 636"/> <input type="button" value="User Code 637"/> <input type="button" value="User Code 638"/> <input type="button" value="User Code 639"/> <input type="button" value="User Code 640"/> <input type="button" value="User Code 641"/> <input type="button" value="User Code 642"/> <input type="button" value="User Code 643"/> <input type="button" value="User Code 644"/> <input type="button" value="User Code 645"/> <input type="button" value="User Code 646"/> <input type="button" value="User Code 647"/> <input type="button" value="User Code 648"/> <input type="button" value="User Code 649"/> <input type="button" value="User Code 650"/> <input type="button" value="User Code 651"/> <input type="button" value="User Code 652"/> <input type="button" value="User Code 653"/> <input type="button" value="User Code 654"/> <input type="button" value="User Code 655"/> <input type="button" value="User Code 656"/> <input type="button" value="User Code 657"/> <input type="button" value="User Code 658"/> <input type="button" value="User Code 659"/> <input type="button" value="User Code 660"/> <input type="button" value="User Code 661"/> <input type="button" value="User Code 662"/> <input type="button" value="User Code 663"/> <input type="button" value="User Code 664"/> <input type="button" value="User Code 665"/> <input type="button" value="User Code 666"/> <input type="button" value="User Code 667"/> <input type="button" value="User Code 668"/> <input type="button" value="User Code 669"/> <input type="button" value="User Code 670"/> <input type="button" value="User Code 671"/> <input type="button" value="User Code 672"/> <input type="button" value="User Code 673"/> <input type="button" value="User Code 674"/> <input type="button" value="User Code 675"/> <input type="button" value="User Code 676"/> <input type="button" value="User Code 677"/> <input type="button" value="User Code 678"/> <input type="button" value="User Code 679"/> <input type="button" value="User Code 680"/> <input type="button" value="User Code 681"/> <input type="button" value="User Code 682"/> <input type="button" value="User Code 683"/> <input type="button" value="User Code 684"/> <input type="button" value="User Code 685"/> <input type="button" value="User Code 686"/> <input type="button" value="User Code 687"/> <input type="button" value="User Code 688"/> <input type="button" value="User Code 689"/> <input type="button" value="User Code 690"/> <input type="button" value="User Code 691"/> <input type="button" value="User Code 692"/> <input type="button" value="User Code 693"/> <input type="button" value="User Code 694"/> <input type="button" value="User Code 695"/> <input type="button" value="User Code 696"/> <input type="button" value="User Code 697"/> <input type="button" value="User Code 698"/> <input type="button" value="User Code 699"/> <input type="button" value="User Code 700"/> <input type="button" value="User Code 701"/> <input type="button" value="User Code 702"/> <input type="button" value="User Code 703"/> <input type="button" value="User Code 704"/> <input type="button" value="User Code 705"/> <input type="button" value="User Code 706"/> <input type="button" value="User Code 707"/> <input type="button" value="User Code 708"/> <input type="button" value="User Code 709"/> <input type="button" value="User Code 710"/> <input type="button" value="User Code 711"/> <input type="button" value="User Code 712"/> <input type="button" value="User Code 713"/> <input type="button" value="User Code 714"/> <input type="button" value="User Code 715"/> <input type="button" value="User Code 716"/> <input type="button" value="User Code 717"/> <input type="button" value="User Code 718"/> <input type="button" value="User Code 719"/> <input type="button" value="User Code 720"/> <input type="button" value="User Code 721"/> <input type="button" value="User Code 722"/> <input type="button" value="User Code 723"/> <input type="button" value="User Code 724"/> <input type="button" value="User Code 725"/> <input type="button" value="User Code 726"/> <input type="button" value="User Code 727"/> <input type="button" value="User Code 728"/> <input type="button" value="User Code 729"/> <input type="button" value="User Code 730"/> <input type="button" value="User Code 731"/> <input type="button" value="User Code 732"/> <input type="button" value="User Code 733"/> <input type="button" value="User Code 734"/> <input type="button" value="User Code 735"/> <input type="button" value="User Code 736"/> <input type="button" value="User Code 737"/> <input type="button" value="User Code 738"/> <input type="button" value="User Code 739"/> <input type="button" value="User Code 740"/> <input type="button" value="User Code 741"/> <input type="button" value="User Code 742"/> <input type="button" value="User Code 743"/> <input type="button" value="User Code 744"/> <input type="button" value="User Code 745"/> <input type="button" value="User Code 746"/> <input type="button" value="User Code 747"/> <input type="button" value="User Code 748"/> <input type="button" value="User Code 749"/> <input type="button" value="User Code 750"/> <input type="button" value="User Code 751"/> <input type="button" value="User Code 752"/> <input type="button" value="User Code 753"/> <input type="button" value="User Code 754"/> <input type="button" value="User Code 755"/> <input type="button" value="User Code 756"/> <input type="button" value="User Code 757"/> <input type="button" value="User Code 758"/> <input type="button" value="User Code 759"/> <input type="button" value="User Code 760"/> <input type="button" value="User Code 761

TECHNO

User Manual

Model No. TE003

Need Help? Contact Us!


If you have any questions, please contact us at
 **+1 (833) 878-3346**
(Monday-Friday 9:00 am-5:00 pm PST)
 support@teeho.com
 teeho.com

Tutorial Video



Scan the QR code and search **TE001**

Please watch these videos first and then use this manual as a guide.



[Teccho TE003 Keyless Entry Door Lock Installation and Programming Guide](#)

Detailed installation, setup, and programming instructions for the Teccho TE003 keyless entry door lock. Covers door preparation, parts identification, step-by-step

installation, user code management, security features, and troubleshooting.

