

[Manuals.plus](#) /

› [ATTACK SHARK](#) /

› ATTACK SHARK X11 Lightweight Wireless Gaming Mouse User Manual

ATTACK SHARK X11

ATTACK SHARK X11 Lightweight Wireless Gaming Mouse Instruction Manual

Model: X11 | Brand: ATTACK SHARK

INTRODUCTION

Thank you for choosing the ATTACK SHARK X11 Lightweight Wireless Gaming Mouse. This manual provides essential information for setting up, operating, and maintaining your new gaming mouse. Please read it thoroughly to ensure optimal performance and longevity of your device.

The ATTACK SHARK X11 is a versatile gaming mouse featuring tri-mode connectivity (2.4G wireless, USB-C wired, Bluetooth), a high-performance PAW3311 optical sensor, 5 programmable buttons, and an RGB charging dock. Its ultralight ergonomic design is crafted for comfort during extended use.

PACKAGE CONTENTS

Ensure all items are present in the package:

- ATTACK SHARK X11 Wireless Gaming Mouse
- RGB Charging Dock
- USB-C to USB-A Cable (for wired connection and charging dock power)
- USB Receiver (dongle)
- Anti-slip Stickers (optional application)
- User Manual (this document)

SETUP

1. Charging the Mouse

Before first use, fully charge the mouse. You can charge it directly via the USB-C cable or using the RGB charging dock.

1. **Direct Charging:** Connect the USB-C cable to the mouse and the USB-A end to your computer or a USB power adapter.
2. **Charging Dock:**

- a. Connect the USB-C cable to the charging dock and the USB-A end to your computer or a USB power adapter.
- b. Place the mouse onto the charging dock. The magnetic connection will secure it, and the RGB lighting on the dock will indicate charging status.



Image: The ATTACK SHARK X11 mouse resting on its RGB charging dock, illustrating the magnetic charging connection.

2. Connecting the Mouse

The X11 mouse supports three connection modes: 2.4G Wireless, Bluetooth, and USB-C Wired.



Image: The ATTACK SHARK X11 mouse connected to a laptop via the 2.4G USB receiver, with the charging dock nearby.

1. 2.4G Wireless Mode:

- a. Locate the USB receiver (dongle) at the bottom of the mouse.
- b. Plug the USB receiver into an available USB port on your computer.
- c. Slide the mode switch on the bottom of the mouse to the "2.4G" position. The mouse should connect automatically.
- d. Alternatively, the USB receiver can be plugged into the USB port on the charging dock for convenience.

2. Bluetooth Mode:

- a. Slide the mode switch on the bottom of the mouse to the "BT" position.
- b. Press and hold the Bluetooth toggle button (usually near the mode switch) for 3 seconds to enter pairing mode. The mouse's indicator light will flash.
- c. On your computer or device, go to Bluetooth settings and search for "ATTACK SHARK X11" (or similar). Select it to pair.

- d. The mouse supports two Bluetooth channels (BT1, BT2). Short press the Bluetooth toggle button to switch between them.

3. USB-C Wired Mode:

- a. Connect the USB-C cable directly from the mouse to your computer.
- b. The mouse will automatically switch to wired mode and begin charging.

3. Applying Anti-slip Stickers (Optional)

The included anti-slip stickers can be applied to the mouse for enhanced grip and a personalized look. Carefully peel and apply them to the desired areas on the mouse body.



Image: The ATTACK SHARK X11 mouse with its anti-slip stickers applied, showing the textured surface for improved grip.

OPERATING THE MOUSE

1. DPI Adjustment

The mouse features 6 adjustable DPI levels (800-1600-2400-3200-5000-22000). Use the DPI switch button on the bottom of the mouse to cycle through the settings. Each DPI level is indicated by a different color light inside the mouse.



Image: An illustration highlighting the PAW3311 optical sensor and its performance specifications (22000 DPI, 300 IPS, 35G acceleration).

2. Programmable Buttons

The ATTACK SHARK X11 has 5 programmable buttons. To customize these buttons, adjust DPI, polling rate, LOD, shortcuts, and macros, download and install the official driver software from the ATTACK SHARK website.

BROADCOM'S MAIN CONTROL CHIP

Faster, stronger, more power-efficient



Image: Screenshot of the ATTACK SHARK X11 software interface, showing options for button settings, DPI adjustment, and macro management.

3. Ergonomic Design

The mouse is designed for comfort during long gaming sessions, weighing approximately 62g. Its ergonomic contours reduce hand fatigue.

MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the mouse and charging dock. Avoid using harsh chemicals or abrasive materials.
- **Storage:** When not in use, store the mouse in a dry, cool place. If using the charging dock, ensure it is connected to power to keep the mouse charged.
- **Battery Care:** To prolong battery life, avoid fully discharging the mouse frequently. Charge it regularly.

TROUBLESHOOTING

- **Mouse not responding:**
 - Ensure the mouse is charged.
 - Check the connection mode switch (2.4G, BT, Wired) on the bottom of the mouse.
 - For 2.4G, ensure the USB receiver is securely plugged in.
 - For Bluetooth, ensure the mouse is paired correctly in your device's Bluetooth settings.
 - Try connecting via USB-C cable to rule out wireless issues.
- **DPI not changing:**
 - Press the DPI switch button firmly.
 - Ensure the mouse is powered on.
 - If using custom settings, check the driver software.
- **Charging dock RGB not lighting up:**
 - Ensure the charging dock is connected to a power source via the USB-C cable.
 - Verify the mouse is correctly placed on the dock for charging.

SPECIFICATIONS

Feature	Detail
Model Name	X11
Brand	ATTACK SHARK
Connectivity Technology	Bluetooth, USB (2.4G Wireless, USB-C Wired)
Movement Detection Technology	Optical (PAW3311 Sensor)
DPI Levels	800-1600-2400-3200-5000-22000 (6 adjustable levels)
Tracking Speed	300 IPS
Acceleration Limit	35G
Response Speed	1000Hz
Switch Type	HUYU Switch, TTC Encoder Technology
Click Lifespan	20 million clicks
Programmable Buttons	5
Weight	Approximately 62g
Special Features	RGB Backlight Charging Dock, Anti-slip design
Compatible Devices	Desktop, Laptop, Personal Computer
Operating System Compatibility	Windows XP / VISTA / 7 / 8 / 10 / MAC

WARRANTY AND SUPPORT

For warranty information, technical support, or to download the latest driver software, please visit the official ATTACK SHARK website or contact their customer service. Keep your purchase receipt for warranty claims.

Official Website: [ATTACK SHARK Store on Amazon](#)

PRODUCT VIDEOS

ATTACK SHARK X11 Lightweight Wireless Gaming Mouse with RGB Charging Dock

Your browser does not support the video tag.

Video: An overview of the ATTACK SHARK X11 mouse, highlighting its lightweight design, tri-mode connectivity, and RGB charging dock features.

ATTACK SHARK X11 Lightweight Wireless Gaming Mouse

Your browser does not support the video tag.

Video: A detailed look at the ATTACK SHARK X11 mouse, focusing on its design, performance, and various functionalities.

© 2026 ATTACK SHARK. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

