

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

Manuals.plus /

- › [Elprico](#) /
- › Elprico 4G Portable WiFi Hotspot User Manual - Model Elpricog962hospd8

Elprico Elpricog962hospd8

Elprico 4G Portable WiFi Hotspot User Manual

Model: Elpricog962hospd8

INTRODUCTION

This manual provides instructions for the Elprico 4G Portable WiFi Hotspot, a mobile MiFi device designed to provide high-speed 4G internet access for up to 10 users. It features a 300 Mbps network capability and 4G LTE transmission speeds of up to 150 Mbps. The device is compact, lightweight, and includes a 3000 mAh battery for extended use. The Elprico 4G Portable WiFi Hotspot supports 4G LTE bands B1, 3, 7, 8, 20, 38, 40, 41 and 3G UMTS bands B1, 5, 8. It offers secure wireless connectivity with WPA and WPA2 encryption.



Image: The Elprico 4G Portable WiFi Hotspot connected to a laptop, illustrating its 4G and 3G support. The device screen shows network status and supported bands.

PACKAGE CONTENTS

- 1 x Elprico 4G Portable WiFi Hotspot
- 1 x Charging Cable

SETUP

1. **Insert SIM Card:** Locate the SIM card slot on the device. Carefully insert a standard SIM card (not included) into the designated slot. Ensure the SIM card is correctly oriented.



Image: Top-down view of the Elprico 4G Portable WiFi Hotspot, highlighting the screen and the area where the SIM card is inserted.

2. **Charge the Device:** Connect the provided charging cable to the USB port on the hotspot and to a power source (e.g., USB wall adapter, computer USB port). The device has a built-in 3000 mAh lithium battery.



Image: A close-up view of the USB-C charging port on the Elprico 4G Portable WiFi Hotspot.

3. **Power On:** Press and hold the power button until the screen illuminates. The device will automatically connect to the 4G network if a valid SIM card is inserted and network coverage is available.

OPERATING INSTRUCTIONS

Connecting Devices

The hotspot supports up to 10 devices simultaneously, including mobile phones, laptops, computers, smart televisions, and other Wi-Fi enabled devices.

1. **Find Network Name (SSID):** The Wi-Fi network name (SSID) and password (KEY) are displayed on the hotspot's screen. Look for "SSID: 4G-MIFI-XXXX" and "KEY: YYYYYYYYYY".



Image: A close-up view of the hotspot's screen, clearly showing the Wi-Fi network name (SSID) and password (KEY).

2. **Connect Your Device:** On your mobile phone, laptop, or other Wi-Fi enabled device, search for available Wi-Fi networks. Select the SSID matching your hotspot.
3. **Enter Password:** When prompted, enter the password (KEY) displayed on the hotspot's screen.
4. **Access Internet:** Once connected, your device will have internet access via the 4G network.

10 Devices Sharing
300Mbps network, 4G LTE up to 150Mbps
Up to 10 devices can be connected at the same time
Widely compatible with cell phones, laptops, computers, smart televisions and other devices



Image: The Elprico 4G Portable WiFi Hotspot actively sharing its internet connection with a laptop and a smartphone, demonstrating its multi-device sharing capability.

Security Features

The mobile WiFi router employs multiple security measures, including WPA and WPA2 WiFi encryption, to ensure advanced wireless security and prevent unauthorized network access.



Image: A detailed view of the Elprico 4G Portable WiFi Hotspot, highlighting its secure encryption capabilities.

MAINTENANCE

To ensure the longevity and optimal performance of your Elprico 4G Portable WiFi Hotspot, follow these maintenance guidelines:

- Keep the device dry and away from moisture.
- Avoid exposing the device to extreme temperatures (hot or cold).
- Clean the device gently with a soft, dry cloth. Do not use liquid cleaners or aerosols.
- Store the device in a cool, dry place when not in use for extended periods.
- Do not attempt to disassemble or repair the device yourself. Contact qualified service personnel if repairs are needed.

TROUBLESHOOTING

If you encounter issues with your Elprico 4G Portable WiFi Hotspot, refer to the following common problems and

solutions:

Problem	Possible Cause	Solution
No internet connection	<ul style="list-style-type: none">• SIM card not inserted correctly or not activated.• No 4G/3G network coverage.• Data plan exhausted or inactive.• Device not powered on.	<ul style="list-style-type: none">• Ensure SIM card is properly inserted and activated with a data plan.• Check the device screen for network signal strength. Move to an area with better coverage if needed.• Verify your data plan status with your service provider.• Press and hold the power button to turn on the device.
Slow internet speed	<ul style="list-style-type: none">• Weak network signal.• Too many devices connected.• Network congestion.	<ul style="list-style-type: none">• Move to an area with stronger 4G/3G signal.• Disconnect some devices to improve performance for others.• Try again later during off-peak hours.
Cannot connect to Wi-Fi	<ul style="list-style-type: none">• Incorrect SSID or password.• Device is out of range.• Hotspot Wi-Fi is off.	<ul style="list-style-type: none">• Verify the SSID and password on the hotspot's screen and re-enter them carefully.• Move closer to the hotspot.• Ensure the hotspot is powered on and its Wi-Fi function is active (indicated on the screen).
Short battery life	<ul style="list-style-type: none">• Heavy usage.• Aging battery.	<ul style="list-style-type: none">• Reduce the number of connected devices or usage time.• Ensure the device is fully charged before use.• Consider replacing the device if battery degradation is significant over time.

SPECIFICATIONS

Feature	Description
Model Name	Elpricog962hospd8
Brand	Elprico
Network Support	<ul style="list-style-type: none">• 4G LTE: B1, 3, 5, 7, 8, 20, 38, 40, 41• 3G UMTS: B1, 5, 8
Wireless Standard	802.11 b/g/n
Wireless Transmission Speed	Up to 150 Mbps (4G LTE)
Sharing Capacity	Up to 10 users
Battery	Built-in 3000 mAh Lithium Battery
SIM Card Slot	Standard SIM (not included)
Connectivity Technology	Bluetooth (as per specifications, though primarily Wi-Fi hotspot)
Special Features	Multi-device connectivity, WPA/WPA2 encryption
Recommended Uses	Travel, outdoor, small office

Feature	Description
Operating System	RouterOS (as per specifications, likely internal firmware)
Origin	China

WARRANTY AND SUPPORT

Information regarding specific warranty terms, spare parts availability, and guaranteed software updates is not provided in the product details. For any support inquiries, please refer to the seller or your point of purchase.

- **Spare Parts Availability:** Information unavailable.
- **Software Updates:** Information unavailable.

