

Untrammellife UNYH-PN-WS-01

Untrammellife Polished Nickel Wall Sconce

Model: UNYH-PN-WS-01

INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Untrammellife Polished Nickel Wall Sconce. Please read this manual thoroughly before installation and retain it for future reference. This modern vanity light fixture is designed to enhance various indoor spaces with its cleanlined design and dimmable functionality.

SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Use only E12 base bulbs. Do not exceed the maximum wattage of 60W.
- This fixture is designed for indoor use only.
- Ensure the mounting surface is structurally sound and can support the weight of the fixture.
- Handle glass components with care to prevent breakage.

PACKAGE CONTENTS

Verify that all components are present before beginning installation.

- Wall Sconce Fixture (Polished Nickel)
- Clear Glass Shade(s)
- E12 LED Bulb(s)
- Mounting Hardware (Mounting plate, screws, wire nuts)
- Instruction Manual



Image: Contents of the Untrammellife Polished Nickel Wall Sconce package, showing the main fixture, clear glass shades, the included E12 LED bulb, and various mounting hardware components like screws and wire nuts, alongside the instruction manual.

SPECIFICATIONS

Feature	Detail
Brand	Untrammellife
Model Number	UNYH-PN-WS-01
Color	Polished Nickel
Material	Glass, Metal
Style	Modern
Light Source Type	LED (Bulb Included)

Bulb Base	E12
Max Wattage	60 Watts (per bulb)
Voltage	120 Volts
Dimmable	Yes (with compatible dimmer switch, not included)
Product Dimensions	4.35"L x 3.95"W x 12.1"H
Item Weight	1.6 Pounds
Certifications	ETL Listed



Image: Detailed diagram illustrating the dimensions of the wall sconce (4.35"L x 3.95"W x 12.1"H) and highlighting the E12 base, indicating a maximum of 60W per bulb and that a bulb is included. Various compatible E12 bulb types are also shown.

SETUP AND INSTALLATION

Tools Required (Not Included): Screwdriver, Wire Strippers, Electrical Tape, Safety Glasses.

1. **Turn Off Power:** Before starting, ensure the power to the circuit is turned off at the main circuit breaker or fuse box to prevent electrical shock.
2. **Prepare Mounting Surface:** Ensure the electrical box is securely mounted in the wall.
3. **Attach Mounting Plate:** Secure the fixture's mounting plate to the electrical box using the provided screws. The metal part of the sconce is pre-installed to the mounting plate.



Image: Close-up view of the fixture's mounting plate, showing the circular bracket and wiring connections, ready to be attached to a standard electrical box.

4. **Wire Connections:** Connect the fixture's wires to the house wires using the provided wire nuts. Match black to black (Live), white to white (Neutral), and green/bare copper to green/bare copper (Ground). Ensure all connections are secure.
5. **Secure Fixture:** Carefully push the wired fixture onto the mounting plate and secure it with the decorative nuts or screws provided.
6. **Install Glass Shade:** Gently slide the clear glass shade(s) over the bulb socket and secure them according to the design (e.g., by twisting or using retaining rings).



Metal Structure



Clear Glass Shade



Safety E12 Base



Bulb Included

Image: A detailed view of the sconce's metal structure and how the clear glass shade is attached, illustrating the secure fit and polished finish.

- 7. Insert Bulb:** Screw the included E12 LED bulb into the socket.



Image: Close-up of the E12 bulb base, showing the socket and the included bulb, emphasizing the standard base type for easy replacement.

8. **Restore Power:** Once installation is complete, restore power at the circuit breaker and test the fixture.

OPERATING INSTRUCTIONS

The Untrammelife Polished Nickel Wall Sconce is designed for simple operation.

- **Power On/Off:** Control the light fixture using your standard wall switch.
- **Dimmable Functionality:** This fixture is fully dimmable when used with a compatible dimmable E12 bulb (included) and a separate dimmer switch (not included). Adjust the dimmer switch to achieve your desired light intensity.



Image: Two views of the wall sconce installed next to a mirror, one showing the light turned OFF and the other showing it turned ON, demonstrating its functionality and aesthetic appeal in both states.

MAINTENANCE

- **Cleaning:** To clean the fixture, ensure power is off. Wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents as they may damage the finish or glass.
- **Bulb Replacement:** Ensure power is off before replacing the bulb. Allow the bulb to cool completely. Unscrew the old bulb and screw in a new E12 base bulb, not exceeding 60W.
- **Anti-Rust Feature:** The polished nickel finish is designed to resist oxidation and color fading, requiring minimal maintenance to retain its appearance.

TROUBLESHOOTING

Problem	Possible Cause	Solution
---------	----------------	----------

Light does not turn on.	No power to the fixture. Loose wire connection. Faulty bulb.	Check circuit breaker/fuse. Verify all wire connections are secure (ensure power is off first). Replace bulb.
Light flickers.	Loose wire connection. Incompatible dimmer switch/bulb. Bulb not fully screwed in.	Check wire connections. Ensure dimmer and bulb are compatible (if dimmable). Tighten bulb.
Glass shade is loose.	Shade not properly secured.	Re-secure the glass shade by twisting or tightening retaining rings.

WARRANTY AND SUPPORT

Untrammelife proudly stands behind all of its products. This wall sconce has passed ETL certification, meeting high quality and safety standards. If you have any questions, concerns, or require professional after-sales support, please contact Untrammelife customer service. Refer to your purchase documentation for specific warranty details. For support, please visit the [Untrammelife Store on Amazon](#).

© 2024 Untrammelife. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

