

9MMML MA8043P6BK

9MMML Black Wagon Wheel Chandelier

MODEL: MA8043P6BK

Brand: 9MMML

1. INTRODUCTION AND OVERVIEW

Thank you for choosing the 9MMML Black Wagon Wheel Chandelier. This 6-light industrial pendant light features a 20-inch farmhouse design, combining quality and durability with a matte black metal body. It is designed to provide ample illumination and enhance the aesthetic of various spaces.

The chandelier's versatile design allows it to complement both modern and farmhouse decors. It is suitable for installation in dining rooms, living rooms, bedrooms, entryways, and foyers.



Front view of the 9MMML Black Wagon Wheel Chandelier, showcasing its matte black finish and six E26 bulb sockets.



The 9MMML Black Wagon Wheel Chandelier installed above a dining table, demonstrating its size and lighting effect in a home setting.

2. SAFETY INFORMATION

- Always turn off the main power at the circuit breaker before beginning any installation, cleaning, or maintenance.
- Consult a qualified electrician if you are unsure about the installation process.
- Use only E26 base bulbs. Bulbs are NOT INCLUDED with this fixture.
- Ensure all electrical connections are secure and comply with local codes.
- Do not exceed the maximum wattage of 42 watts for the fixture.
- If dimming functionality is desired, use a compatible dimmer switch and dimmable E26 bulbs.
- This fixture is designed for indoor use only and is not water resistant.

3. PACKAGE CONTENTS

Please verify that all components are present and undamaged before beginning installation.

- Wagon Wheel Chandelier Frame
- Ceiling Plate / Canopy
- Adjustable Hanging Chain (2 x 23.6 inch sections)
- Mounting Hardware (screws, wire nuts, etc.)
- Instruction Manual

4. SPECIFICATIONS

| Feature | Detail |
|-------------------------|--|
| Brand | 9MMML |
| Model Name | MA8043P6BK |
| Color | Matte Black |
| Material | Metal |
| Style | Farmhouse |
| Product Dimensions | 20"L x 20"W x 70"H (max height) |
| Item Weight | 8 Pounds |
| Power Source | Corded Electric |
| Installation Type | Simple Installation |
| Special Features | Adjustable Height, Energy Efficient |
| Light Source Type | E26 bulbs (Not Included) |
| Number of Light Sources | 6 |
| Voltage | 110 Volts (AC) |
| Wattage | 42 watts (max) |
| Brightness | 4800 Lumen (with appropriate bulbs) |
| Room Type | Bedroom, Dining Room, Entryway, Kitchen, Living Room |

5. SETUP AND INSTALLATION

The 9MMML Black Wagon Wheel Chandelier is designed for simple installation. Please follow these general steps. For detailed visual guidance, contact customer support for an installation video.

1. **Prepare for Installation:** Turn off power at the main circuit breaker. Clear the installation area.
2. **Assemble the Fixture:** Attach the hanging rods/chains to the main chandelier body. The chandelier offers a maximum height of 70 inches with its two 23.6-inch removable chains, allowing for adjustable hanging length.

3. **Mount the Ceiling Plate:** Secure the mounting bracket to your junction box. This fixture is compatible with flat, sloped, and vaulted ceilings.
4. **Connect Wiring:** Carefully connect the chandelier's wires to your household electrical wires according to standard electrical codes (usually black to black, white to white, and ground to ground). Use the provided wire nuts.
5. **Secure the Fixture:** Attach the chandelier to the mounting bracket on the ceiling plate.
6. **Install Bulbs:** Screw in 6 E26 base bulbs (not included) into the sockets.
7. **Restore Power:** Turn the power back on at the circuit breaker.

Specifcation

Suitable for various types of ceiling



Flat Ceiling



Length Adjustable



Sloped Ceiling



Vaulted Ceiling



Diagram illustrating the chandelier's dimensions, adjustable chain length, and compatibility with flat, sloped, and vaulted ceilings.



**High-Quality
Ceiling Plate**

**Matt
Black Finish**

**US Standard
E26 Socket**

**Wagon Wheel
Frame**

Detailed views of the high-quality ceiling plate, matte black finish, US standard E26 socket, and the durable wagon wheel frame.

6. OPERATING INSTRUCTIONS

Once installed and powered, the chandelier operates via your standard wall switch. To utilize the dimming feature, ensure you have a compatible dimmer switch installed and are using dimmable E26 bulbs.

The choice of E26 bulbs allows for customization of light color and brightness. You can select bulbs with different color temperatures (e.g., 3000K for warm white, 4000K for neutral white, 6000K for cool white) to create various atmospheres in your room.

Light ON



Light OFF



Comparison image showing the chandelier with lights turned ON (warm glow) and OFF (clear bulbs).

Different Color Temperatures Create Different Atmosphere

Compatible with E26 base bulbs
(Bulbs Not Included)



Visual representation of the chandelier's appearance with bulbs of different color temperatures: 3000K, 4000K, and 6000K.

7. MAINTENANCE

- **Cleaning:** To clean the fixture, ensure the power is off. Wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents as they may damage the finish. The durable metal construction is painted to resist rust and corrosion, ensuring easy maintenance.
- **Bulb Replacement:** Always turn off power before replacing bulbs. Allow bulbs to cool completely before touching them. Replace with E26 base bulbs of the appropriate wattage.

8. TROUBLESHOOTING

If you encounter issues with your chandelier, please refer to the following common troubleshooting steps:

- **Light does not turn on:**
 - Check if the power is on at the circuit breaker.
 - Ensure bulbs are securely screwed into their sockets.

- Verify that the bulbs are not burnt out.
- Check all wire connections for proper contact.
- **Lights flicker:**
 - Ensure all bulbs are fully tightened.
 - If using a dimmer, confirm it is compatible with your bulbs and the fixture.
 - Check for loose wiring connections.
- **Chandelier hangs unevenly:**
 - Adjust the hanging chain or rods to ensure even distribution.
 - Verify the mounting bracket is level and securely installed.

If these steps do not resolve the issue, please contact customer support for further assistance.

9. WARRANTY AND SUPPORT

Your satisfaction is our top priority. 9MMML offers a **2-Year after-sale service** on all our products, including this chandelier. This warranty covers defects in materials and workmanship under normal use.

If you have any questions, require assistance with installation, or need to report an issue, please contact us via Buyer Message. We are committed to responding to all inquiries within 24 hours to provide prompt and effective support.