



[Manuals.plus](#) /

› [Pedono](#) /

› PEDONO Dog Training Collar User Manual

Pedono A50

PEDONO Dog Training Collar User Manual

Model: A50

INTRODUCTION

Thank you for choosing the PEDONO Dog Training Collar. This manual provides comprehensive instructions for the safe and effective use of your new training system. Designed for small, medium, and large dogs weighing between 20 to 120 pounds, this collar offers humane and effective training modes to help correct unwanted behaviors and reinforce positive ones.

Please read this manual thoroughly before operating the device to ensure proper usage and to maximize the training benefits for your pet.

PACKAGE CONTENTS

Verify that all items listed below are included in your package:

- 1 x Remote Control
- 1 x Receiver Collar
- 1 x Dog Clicker
- 1 x Type-C Charging Cable
- 1 x Wrist Strap
- 1 x User Manual
- 1 x Test Light Tool
- 4 x Contact Points (2 short, 2 long)
- 2 x Silicone Caps

This video demonstrates the unboxing and contents of the PEDONO Dog Training Collar package, showing all included accessories.

PRODUCT OVERVIEW

Remote Control

The remote control features an intuitive design with a clear display and dedicated buttons for each function. It includes a unique shock-lock keypad to prevent accidental activation of the shock feature.



Image: The remote control and receiver collar, highlighting the main components.

UNIQUELY INDIVIDUALIZED SHOCK-LOCK

User-friendly Design



Safe in pocket



A lanyard for the remote

Image: Close-up of the remote control, showing the unique shock-lock keypad for enhanced safety.

Receiver Collar

The receiver collar is designed to be durable and comfortable for your dog. It is IPX7 waterproof, allowing your dog to play in water without damage (ensure charging port is sealed). The nylon strap is adjustable to fit various dog neck sizes.



Image: A dog wearing the IPX7 waterproof receiver collar while playing in water, demonstrating its water resistance.

SETUP

Charging the Devices

Before first use, fully charge both the remote control and the receiver collar. The remote charges in 2-3 hours and offers up to 90 days standby time (30 days working time). The receiver charges in 2-3 hours and offers 20-30 days standby time (10-15 days working time).

Use the provided Type-C cable for charging. Ensure the waterproof silicone plug on the receiver's charging port is securely closed after charging.

Q: Why doesn't the shock function respond to your dogs?

A: Possible causes are as follows!!

- 1: May be a lack of electricity;
- 2: Mistakenly switch to an unpaired channel;
- 3: The electronic collar worn by the dog is loose.



2-HOUR RAPID CHARGING & OUTLASTS YOUR ADVENTURE



USB POWER STRIP



COMPUTER



POWER BANK



POWER ADAPTER



Image: Illustration of the Type-C charging ports on both the remote and receiver, along with various charging methods.

Fitting the Collar

Proper fit of the receiver collar is crucial for effective and safe operation. The collar should be snug enough for the contact points to touch the dog's skin, but not so tight as to restrict breathing or cause discomfort. You should be able to fit one finger snugly under the strap.

The nylon strap can be trimmed to fit your dog's neck size, ranging from 8 to 24 inches. After trimming, carefully burn the end of the strap with a lighter to prevent fraying.

IDEAL FOR MULTI-PET FAMILIES

Channel xA supports controlling all collars, eliminating the need to re-remove multiple dog collars and re-pair them on the same channel (Channel x3 or 2 or 1)

**BEEP MODE
(STANDARD)**

**VIBRATION MODE
(LEVEL 0-9)**

**STATIC MODE
(LEVEL 0-9)**



Image: Diagram showing the adjustable nylon strap and how to trim it for a proper fit on dogs of different sizes.

This video demonstrates how to replace and adjust the nylon strap on the receiver collar, including trimming and sealing the end.

OPERATING MODES

The PEDONO Dog Training Collar offers three humane training modes:

- **Beep (Standard):** Emits an audible tone.
- **Vibration (Level 0-9):** Delivers a gentle vibration. The intensity can be adjusted from level 0 to 9.
- **Safe Shock (Level 0-9):** Provides a safe static stimulation. The intensity can be adjusted from level 0 to 9. This feature includes a unique shock-lock keypad to prevent accidental activation.

The remote control has a range of up to 1,600 feet in unobstructed areas, providing ample freedom for training.

IPX7 WATERPROOF COLLAR

Allows your dog to play freely in the water



Image: The remote control displaying the three training modes: Beep, Vibration (Level 0-9), and Static (Level 0-9).

This video provides an overview of the dog training collar, demonstrating its various training modes including beep, vibration, and static stimulation.

PAIRING THE DEVICES

To ensure the remote control communicates with the receiver collar, follow these pairing steps:

1. Turn on the receiver collar by pressing and holding the ON/OFF button for 3 seconds until you hear the first long beep.
2. Select the desired channel (Channel 1, 2, or 3) on the remote control.
3. Press and hold the ON/OFF button on the receiver collar again for 3 seconds. You will hear a second long beep, indicating successful pairing.

This video guides you through the process of pairing the remote control with the receiver collar, including how to pair additional receivers for multiple dogs.

MULTI-DOG CONTROL (CHANNEL A)

The PEDONO system supports training multiple dogs simultaneously. When multiple receiver collars are individually paired to different channels (Channel 1, 2, and 3), they can all be controlled at the same time through Channel A on the remote control.

This feature eliminates the need to re-pair collars on the same channel, making it ideal for households with multiple pets.



Image: Visual representation of controlling multiple dog collars simultaneously using Channel A on the remote.

MAINTENANCE

Cleaning

Regularly clean the receiver collar and remote control with a damp cloth. Ensure the charging port on the receiver is sealed when not charging, especially if the collar will be exposed to water.

Battery Care

To prolong battery life, avoid fully discharging the devices frequently. Store them in a cool, dry place when not in use.

Strap Replacement

The nylon strap is durable but may need replacement over time. Refer to the "Fitting the Collar" section for instructions on adjusting and trimming the strap, which also applies to replacement.

TROUBLESHOOTING

Shock Function Not Responding

If the shock function does not respond, consider the following:

- **Low Battery:** Ensure both the remote and receiver are fully charged.

- **Incorrect Channel:** Verify that the remote is set to the correct channel paired with the receiver.
- **Loose Collar:** The electronic collar may be too loose on the dog's neck, preventing proper contact. Adjust the fit.
- **Test with Tool:** Use the provided Test Light Tool to confirm the shock function is working. Place the tool over the contact points and activate the shock. If it flashes red, the function is operational.

This video demonstrates how to test the beep, vibration, and static stimulation functions of the collar using the remote and the included test light tool.

Other Issues

For any other issues or persistent problems, please contact PEDONO Customer Service for assistance.

SPECIFICATIONS

Feature	Detail
Model Number	A50
Brand	Pedono
Training Modes	Beep, Vibration (0-9), Safe Shock (0-9)
Remote Range	Up to 1600 feet (unobstructed)
Waterproof Rating	IPX7 (Receiver Collar)
Collar Adjustable Size	8 to 24 inches
Recommended Dog Weight	20 to 120 pounds
Battery Type	2 Lithium Polymer batteries (included)
Charging Time	2-3 hours
Remote Standby Time	Up to 90 days
Receiver Standby Time	20-30 days
Material	Plastic
Color	Black

WARRANTY AND SUPPORT

This PEDONO Dog Training Collar comes with a **1-year warranty** from the date of purchase. This warranty covers manufacturing defects and malfunctions under normal use.

For warranty claims, technical support, or any questions regarding your product, please contact PEDONO Customer Service. Please have your purchase information and product model number (A50) ready when contacting support.

Contact Information: Please refer to the contact details provided on the product packaging or the official Pedono website for the most up-to-date support information.

