

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Gradio](#) /
- › [Gradio DR-898 Portable DAB+ / FM Radio User Manual](#)

Gradio DR-898

Gradio DR-898 Portable DAB+ / FM Radio User Manual

Model: DR-898 | Brand: Gradio

INTRODUCTION

Welcome to your new Gradio DR-898 Portable DAB+ / FM Radio. This manual provides comprehensive instructions for the setup, operation, and maintenance of your device to ensure optimal performance and a satisfying listening experience. Please read this manual carefully before using the radio.

Genießen Sie Ihre Radiozeit jederzeit und überall



This image is a collage showing different scenarios where the Gradio DR-898 radio can be used, such as during outdoor activities, at home, or while traveling, emphasizing its portability and versatility.

PACKAGE CONTENTS

Please check the package for the following items:

- 1 x Gradio DR-898 DAB+ / FM Radio
- 1 x Headphone
- 1 x USB Type-C Charging Cable
- 1 x User Manual
- 1 x External Wire Antenna (Crocodile clip type)
- 1 x Reset Pin

Note: Additional accessories like the external wire antenna and reset pin may be included depending on the region or specific package.

PRODUCT OVERVIEW

Familiarize yourself with the components and controls of your Gradio DR-898 radio.

Greadio Digital DAB+ Radio Klein



80
Voreingestellter



Lock-Schalter



LCD-Anzeige



Schlafzeit-Timer



Wecker



This image shows the front of the Greadio DR-898 radio, highlighting its compact design, LCD screen, and control buttons. It also illustrates various DAB and FM frequencies it can receive. Key features like 80 presets, lock switch, LCD display, sleep timer, and alarm clock are indicated.

Key Features:

- **DAB/DAB+/FM Tuner:** For receiving digital and analog radio broadcasts.
- **LCD Display:** Clear screen for time, station, and other information.
- **Control Buttons:** Intuitive buttons for navigation and settings.
- **Telescopic Antenna:** Extendable for improved signal reception.
- **Built-in Speaker:** For audio playback without headphones.
- **Headphone Jack:** 3.5mm port for private listening.
- **USB Type-C Port:** For charging the internal battery.

SETUP

1. Initial Charging

Before first use, fully charge the radio's internal battery.

1. Connect the supplied USB Type-C cable to the radio's charging port.

2. Connect the other end of the cable to a USB power adapter (not included) or a computer's USB port.
3. The charging indicator on the display will show the charging status.
4. A full charge typically takes approximately **2.5 hours** and provides up to **18 hours** of continuous playback.

Wiederaufladbare Batterie
Aufladen mit einem Micro-USB-Kabel für eine lange Nutzungsdauer

1000 mAh
kann einen Tag lang ununterbrochen verwendet werden

STROMSPARENDE
TECHNOLOGIE

Ununterbrochene Radiowiedergabe
18 Stunden

Aufladen
2,5 Stunden

The image shows a dark blue Gradio DR-898 digital radio with a screen displaying 'AM 12:00', 'Willkommen bei Digitalradio', and 'Digital DAB+/FM Radio'. The radio is positioned on a white surface. Above it is a large blue arc graphic containing the text '1000 mAh' and 'kann einen Tag lang ununterbrochen verwendet werden'. To the right, there are two callout boxes: one with a battery icon and '18 Stunden' under 'Ununterbrochene Radiowiedergabe', and another with a USB-C cable icon and '2,5 Stunden' under 'Aufladen'. The background is a light grey with a blurred indoor scene.

This image illustrates the charging process of the Gradio DR-898 radio. It highlights the 1000mAh rechargeable battery, indicating it can be used for up to 18 hours and takes 2.5 hours to fully charge via a USB-C cable.

2. Setting Time and Date

The radio can automatically update its time and date from DAB signals. If manual setting is required:

1. Press the **MENU** button to access the system settings.
2. Navigate to the 'Time/Date' or 'System' menu using the navigation buttons.
3. Select 'Auto Update' and set it to 'From Any' (DAB or FM) for automatic synchronization.
4. You can also manually set the time, date, and 12/24 hour format if auto-update is not desired or available.

OPERATING INSTRUCTIONS

1. Power On/Off

- To power on, press and hold the **POWER** button for approximately 3 seconds.

- To power off, press and hold the **POWER** button again for approximately 3 seconds.

2. Mode Selection (DAB/DAB+, FM)

- Press the **BAND** button to switch between DAB/DAB+ and FM radio modes.

3. Station Scanning and Presets

The radio supports automatic scanning and manual saving of up to 40 DAB and 40 FM stations.

- **Auto Scan:** In DAB or FM mode, press and hold the **SCAN** or **MENU** button (refer to specific button labels on your device) to initiate an automatic scan for available stations. The radio will store them automatically or prompt you to save.
- **Manual Save:** Tune to your desired station. Press and hold the **ENTER** button to save it as a preset. Use the navigation buttons to select a preset number (1-40 for each mode) and press **ENTER** again to confirm.
- **Recall Presets:** Briefly press the **ENTER** button, then use the navigation buttons to select your desired preset station.

4. Volume Control

- Use the **Volume Up (+)** and **Volume Down (-)** buttons, usually located on the side or front, to adjust the audio level. The volume range is typically from 01 to 16.

5. Headphone Use

For private listening, connect headphones to the 3.5mm jack.

- Insert the 3.5mm headphone jack into the designated port on the radio.
- Audio will automatically switch from the internal speaker to the headphones, providing stereo sound in FM mode.

Kopfhörer & LOCK-Schalter

Genießen Sie Ihre Privatsphäre, ohne sich Sorgen machen zu müssen, berührt zu werden



This image shows a person listening to the Greadio DR-898 radio using headphones, emphasizing private listening. The image also points out the 'LOCK' button, which prevents accidental button presses.

6. Alarm Clock and Sleep Timer

The radio includes an alarm clock and a sleep timer function.

- **Alarm Clock:** Access the 'Alarm' setting via the **MENU** button. Set the alarm time and desired alarm source (e.g., buzzer or last listened station). The snooze interval is typically 5 minutes.
- **Sleep Timer:** Press and hold the **BACK** button (or refer to your device's specific button for sleep timer) to activate the sleep timer. You can set it to turn off the radio automatically after 10, 15, 30, 45, 60, or 90 minutes.

Schlafzeit-Timer

Drücken Sie lange auf die obere [BACK] Taste, um 10-90 Minuten Schlafzeit einzustellen



Wecker

Snooze-Intervall ist 5 Minuten und dann für Zyklen

This image demonstrates the sleep timer and alarm clock features of the Greadio DR-898 radio. It shows a person sleeping, indicating the radio can be set to turn off automatically after a set period (10-90 minutes) and also functions as an alarm clock with a 5-minute snooze interval.

7. Lock Function

To prevent accidental button presses, use the lock function.

- Press and hold the **LOCK** button (usually located on the side or front) to activate the key lock. A lock icon will appear on the display.
- Repeat the action to deactivate the key lock.

8. Display Information

The LCD display shows various information:

- **Time and Date:** Current time and date.
- **Station Name:** Current radio station.
- **Signal Strength:** Indication of reception quality.
- **Battery Level:** Current battery charge.
- **Program Information:** Song title, artist, news headlines (DAB/DAB+ only).
- Press the **INFO** button to cycle through additional information like frequency, audio quality (Kbps), and station location.

MAINTENANCE

- **Cleaning:** Wipe the radio with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Battery Care:** To prolong battery life, avoid fully discharging the battery frequently. Charge the radio regularly, even if not in use for extended periods.
- **Antenna Handling:** Extend the telescopic antenna gently for optimal reception. Avoid bending or forcing it, as this can cause damage.
- **Storage:** Store the radio in a cool, dry place away from direct sunlight and extreme temperatures.

TROUBLESHOOTING

If you encounter issues with your radio, refer to the following common problems and solutions:

- **No Reception or Poor Sound Quality:**
 - Ensure the telescopic antenna is fully extended.
 - Try repositioning the radio or moving to an area with better signal.
 - Perform a full station scan to update available stations.
 - For DAB/DAB+, check if you are in a coverage area.
- **Radio Does Not Turn On:**
 - Check if the battery is charged. Connect the radio to a power source.
 - Ensure the power button is pressed and held for the required duration (approx. 3 seconds).
- **Buttons Not Responding (Locked):**
 - Check if the lock function is activated. Press and hold the **LOCK** button to deactivate it.
- **Display Issues (Blank/Frozen):**
 - Try restarting the radio by powering it off and on.
 - If the issue persists, use the provided reset pin to perform a factory reset (locate the small reset hole, usually on the back or side).

SPECIFICATIONS

Technical details of the Greadio DR-898 Portable DAB+ / FM Radio:

Brand	Greadio
Model Number	DR-898
Color	Dark Grey
Special Features	Rechargeable
Battery Type	Lithium-polymer
Battery Capacity	1000 mAh
Continuous Playtime	Up to 18 hours

Charging Time	Approx. 2.5 hours
Dimensions (L x W x H)	10.5 x 5.8 x 1.8 cm (4.14 x 2.2 x 0.79 inches)
Weight	Approx. 88 grams (0.2 lbs)
Tuning Technology	DAB/DAB+/FM
FM Frequency Range	87.5 - 108 MHz

Kompaktes, klares LCD-Display

Einfach zu bedienender LCD-Bildschirm im Taschenformat mit hoher Helligkeit



Einhand-
Bedienung



Gehäusegröße:
5,8*1,8*1,05 CM



Bildschirmgröße:
5.08 CM



Länge der Antenne:
16.61 CM



This image displays the Gradio DR-898 radio being held, illustrating its compact size (4.14in H x 2.2in W x 0.79in D) and light weight (0.2lb). It also shows the screen size and antenna length.

WARRANTY AND SUPPORT

Gradio products are designed for reliability and performance. For warranty information or technical support, please refer to the warranty card included with your purchase or contact Gradio customer service through the retailer where you purchased the product. Our customer support team is available to assist you with any questions or concerns.

