Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

ILIFE V9 Pro

ILIFE V9 Pro Robot Vacuum and Mop Combo User Manual

Model: V9 Pro

Brand: ILIFE

1. Introduction

The ILIFE V9 Pro is an advanced robot vacuum and mop combo designed to provide efficient and hands-free cleaning for your home. Featuring a self-emptying station, powerful suction, and intelligent navigation, it simplifies daily floor maintenance. This manual provides essential information for setting up, operating, maintaining, and troubleshooting your V9 Pro to ensure optimal performance and longevity.



The ILIFE V9 Pro robot vacuum and mop combo with its self-emptying station and accessories.

2. What's in the Box

Upon unboxing your ILIFE V9 Pro, please ensure all components are present:

- 1 V9 Pro robot vacuum
- 1 Self-empty station
- 5 Dust bags (2.5L capacity each)
- 1 Remote control
- 1 Mopping bracket
- 1 Mop cloth
- 2 Extra side brushes
- 1 User manual

- 2 AAA batteries

3. Setup Guide

3.1 Initial Charging and Station Placement

Place the self-empty station against a wall in an open area, ensuring there are no obstacles within 1 meter (3 feet) to the front and 0.5 meters (1.5 feet) to the sides. Connect the power adapter to the station and plug it into a wall outlet. Place the V9 Pro robot onto the charging pins of the station to begin initial charging. Ensure the robot is properly aligned.

3.2 App Connection (ILIFEHOME App)

For smart control features, download the ILIFEHOME App from your smartphone's app store. Follow the in-app instructions to connect your V9 Pro to your home Wi-Fi network. Please note that the V9 Pro only supports 2.4GHz Wi-Fi networks.

3.3 Room Preparation

Before starting a cleaning cycle, it is recommended to tidy up the room. Collect and properly store any loose wires, small objects, or delicate items on the floor to prevent the robot from getting stuck or damaging them. This ensures a smoother and more efficient cleaning process.

Your browser does not support the video tag.

Official overview video of the ILIFE V9 Pro robot vacuum and mop combo, demonstrating its features and setup.

4. Operating Instructions

4.1 Cleaning Modes

The ILIFE V9 Pro offers multiple cleaning modes to suit various needs:

- **Zigzag Mode:** For general cleaning of large, open areas, covering the floor in systematic, parallel lines.
- **Spot Mode:** Concentrates cleaning on a specific small area with intense dirt or debris.
- **Edge Mode:** Cleans along walls and furniture edges to ensure thorough coverage.
- **Max Mode:** Provides maximum suction power for deeply embedded dirt and debris.



Illustration of the various cleaning modes available on the ILIFE V9 Pro.

4.2 Suction Power Adjustment

Adjust the suction power based on your cleaning requirements:

- **Quiet (500Pa):** For light cleaning and quiet operation.
- **Standard (1000Pa):** Default setting for everyday cleaning.
- **Strong (1500Pa):** For more stubborn dirt.
- **Max (3000Pa):** Provides the strongest suction for deep cleaning.



Choose from four suction modes to optimize cleaning for different debris types.

4.3 Smart Gyroscope Navigation

The V9 Pro utilizes gyroscope navigation to clean in systematic routes, ensuring maximum coverage and reducing missed spots. This intelligent path planning contributes to higher cleaning efficiency compared to random navigation systems.



The V9 Pro's systematic gyroscope navigation ensures thorough cleaning coverage.

4.4 Control Methods

Control your V9 Pro using various convenient methods:

- **ILIFEHOME App:** Customize cleaning schedules, adjust water flow volume, and suction power.
- **Voice Control:** Compatible with Amazon Alexa and Google Assistant for hands-free commands.
- **Remote Control:** Directly control the robot with the included remote.



Control your V9 Pro via the ILIFEHOME App, Alexa, or Google Assistant.



The included remote control provides direct operation of the robot vacuum.

4.5 Scheduling Cleaning

Set up daily or weekly cleaning schedules through the ILIFEHOME App. This allows the robot to automatically start cleaning at your preferred times, ensuring your floors are always clean without manual intervention.



Easily schedule cleaning times using the ILIFEHOME App.

4.6 3-in-1 Sweeping, Vacuuming & Mopping

The V9 Pro features an integrated 2-in-1 water tank (200ml dustbin and 200ml water tank), allowing it to sweep, vacuum, and mop simultaneously. This design eliminates the need to switch between different attachments, significantly reducing cleaning time.

5. Maintenance

5.1 Self-Emptying Station and Dust Bags

The self-empty station automatically transfers collected dirt and debris from the robot's dustbin into a 2.5L capacity dust bag. Each bag can hold up to 6 weeks of debris, providing up to 30 weeks of hands-free cleaning with the included five

dust bags. Replace the dust bag when full to maintain optimal emptying performance.



The self-emptying station provides extended hands-free cleaning convenience.

5.2 Mop Bracket and Mop Cloth

The V9 Pro features a tangle-free suction port, making it ideal for picking up pet hair. When cleaning carpets, it is important to remove the mop bracket and the mop cloth together to avoid dampening the carpet and ensure proper vacuuming performance.



The tangle-free suction port is designed for efficient pet hair pickup, and the mop bracket is easily removable.

5.3 Filter Cleaning

Regularly clean the HEPA filter to maintain strong suction power and prevent clogging. Tap out loose debris and, if washable, rinse with water and allow to air dry completely before reinserting.

5.4 Side Brushes and Wheels

Inspect and clean the side brushes and wheels periodically to remove tangled hair or debris. This ensures smooth movement and effective edge cleaning.

6. Troubleshooting

If you encounter issues with your ILIFE V9 Pro, refer to the common questions and solutions below:

- **Performance on Carpets:** The V9 Pro picks up limited debris and hair on carpets due to its brushless suction port. It works much better on hard floors. For heavily carpeted homes, consider ILIFE models with a main roller brush, such as the T20S.
- **Robot Takes Time Returning to Station:**Docking efficiency is optimal when cleaning in a single room or double-room layout. For multi-room layouts, models with laser navigation (e.g., T20S) can find charging stations more easily.
- **Does it have mapping navigation?** The V9 Pro is gyro-navigated and does not support real-time map creation. If mapping functionality is preferred, please consider ILIFE's LDS Laser-navigated models.
- **Problem Connecting to Wi-Fi:** Ensure your Wi-Fi network is 2.4GHz. Follow the step-by-step app connection video guidance provided within the ILIFEHOME App.



Common questions and answers for the ILIFE V9 Pro.

7. Specifications

Feature	Detail
Brand	ILIFE
Model Name	ILIFE V9 Pro
Color	Black
Product Dimensions	12.4"L x 12.4"W x 2.99"H
Filter Type	Hepa
Battery Life	90 minutes
Voltage	110 Volts
Dust Bag Capacity	2.5 Liters

Power Source	Battery Powered
Batteries Included	Yes (1 Lithium Ion battery required, included)
Compatible Devices	Amazon Echo (Alexa), Google Assistant
Form Factor	Circle
Item Weight	13 pounds
Country of Origin	China

8. Warranty and Support

For product support, technical assistance, or warranty inquiries, please contact the ILIFE Official Store or refer to the contact information provided with your purchase documentation. Additional protection plans may be available for extended coverage.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0D66L5413

More documents and user manuals: **https://manuals.plus/**