

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Jugbow](#) /

› [Jugbow Dog Shock Collar 2 Dogs \(10-120Lbs\) - 4200FT Dog Training Collars with Remote Control, IPX8 Waterproof Rechargeable E-Collars for Large Medium Small Dog Orange 2pcs](#)

Jugbow DT-682

Jugbow Dog Training Collar User Manual

Model: DT-682 | Brand: Jugbow

1. INTRODUCTION AND OVERVIEW

The Jugbow Dog Training Collar system is designed to assist in effective and humane dog training for pets weighing 10-120 lbs. This system includes a remote control and two IPX8 waterproof rechargeable e-collars, allowing for simultaneous training of two dogs. It offers a range of training modes to help correct undesirable behaviors and reinforce positive ones.



Image: The complete Jugbow Dog Training Collar system, showing the remote control and two orange receiver collars.

Key Features:

- **4 Humanized Training Modes:** Includes Beep (standard), Vibration (1-9 levels), Safe Shock (0-99 levels), and Shock Boost (10% higher intensity).
- **Extended 4200FT Range:** Provides extensive remote control range for training in various environments.
- **2-Channel System:** Capable of training two dogs simultaneously with memory function for settings.
- **IPX8 Waterproof Collars:** Designed for use in wet conditions without damage.
- **Adjustable & Lightweight Collar:** Fits neck sizes from 7.8 - 24.4 inches, suitable for dogs from 10-120 lbs.
- **User-friendly & Safe Design:** Features a safe lock button on the remote to prevent accidental activation.

2. PACKAGE CONTENTS

Before beginning, please ensure all components are present in your package:

- 1 x Remote Control
- 2 x Receiver Collars (Orange)
- 1 x Multi-charging Cable (charges remote and both collars simultaneously)
- 2 x Sets of Contact Points (short and long)
- 2 x Silicone Protective Covers
- 1 x Test Light Tool
- 1 x Wrist Strap for Remote
- User Manual (this document)

3. SETUP

3.1 Charging the Devices

Use the provided multi-charging cable to charge the remote control and both receiver collars simultaneously. A full charge typically takes 2 hours and provides up to 45 days of standby time for the remote and 35 days for the collars.



Image: Illustration of the multi-charging cable connected to the remote and two collars.

3.2 Attaching Contact Points and Silicone Covers

Select the appropriate contact points (short for short-haired dogs, long for long-haired dogs) and screw them onto the receiver. For added comfort and to prevent skin irritation, place the silicone protective covers over the contact points.

Your browser does not support the video tag.

Video: Demonstrates how to switch the shock metal prongs for a long-haired dog. This ensures proper contact and comfort.

Replaceable & Adjustable Collar Strap

24.4 inches



adjustable and can be cut off

10-120 LBS



Image: Close-up of the receiver collar showing the short and long contact points, and silicone covers.

3.3 Attaching the Wrist Strap to the Remote

For convenient carrying and to prevent dropping, attach the provided wrist strap to the remote control.

Your browser does not support the video tag.

Video: Instructions on how to thread the hanging rope through the remote for secure carrying.

3.4 Pairing the Receiver Collars with the Remote

To ensure the remote communicates with the correct collar, follow these pairing steps:

1. Turn on the remote control.

2. Turn on the receiver collar by pressing its power button.
3. On the remote, select the desired channel (1 or 2) for the collar.
4. Press and hold the channel button on the remote while locking and then unlocking the unlock button.
5. The receiver's status light will flash quickly. Select any function key on the front of the transmitter for pairing.
6. Once successfully paired, the receiver will beep once, and the status light will stop flashing.

Your browser does not support the video tag.

Video: Step-by-step guide on how to pair the second receiver collar with the remote control.

4. OPERATING INSTRUCTIONS

The Jugbow remote control features a clear layout for easy operation. It includes buttons for Beep, Vibration, and Shock modes, along with intensity level adjustments and a safety lock.

User-friendly & Safe Design



Security Lock
Safe in Pocket



Protective Rubber Covers
Prevent skin abrasions



Image: The remote control highlighting its user-friendly interface and safety features.

4.1 Training Modes:

- **Beep Mode:** Delivers an audible tone. Ideal for initial training and gaining your dog's attention.
- **Vibration Mode:** Provides a gentle vibration. Adjustable from levels 1-9.
- **Safe Shock Mode:** Delivers a static correction. Adjustable from levels 0-99. Start at the lowest effective level.
- **Shock Boost:** Provides a 10% higher static correction than the selected Safe Shock level. Use with caution.

4 Effective Training Modes

Correct Bad Behaviors in Time



Image: Visual representation of the four training modes available on the Jugbow collar.

4.2 Remote Lock Function:

Slide the lock button on the side of the remote upwards to prevent unintentional operation. This is crucial when carrying the remote in your pocket or during breaks in training.

4.3 Testing Functions:

Before placing the collar on your dog, it is recommended to test all functions to ensure they are working correctly.

Your browser does not support the video tag.

Video: Demonstrates how to confirm if all functions (beep, vibration, shock) are working properly on the receiver collar.

5. MAINTENANCE

5.1 Cleaning:

Clean the collar and receiver with a damp cloth as needed. Ensure the contact points are free of debris to maintain effective operation.

5.2 Battery Care:

Keep the devices charged regularly to ensure optimal performance. Avoid prolonged exposure to extreme heat or direct sunlight, which can affect battery life.

5.3 Storage:

When not in use for extended periods, store the collar and remote in a cool, dry place.

6. TROUBLESHOOTING

If you encounter any issues with your Jugbow Dog Training Collar, please refer to the following common solutions:

- **No Response from Collar:** Ensure both the remote and receiver are fully charged and powered on. Verify that the collar is correctly paired to the selected channel on the remote. Check that the contact points are making proper contact with your dog's skin.
- **Reduced Range:** Environmental factors such as terrain, weather, and electromagnetic interference can affect range. Try moving to an open area. Ensure the remote's antenna is not obstructed.
- **Collar Not Holding Charge:** Ensure the charging cable is securely connected to all devices. If issues persist, contact customer support.
- **Accidental Activations:** Always use the remote's lock button when not actively training to prevent unintended commands.

7. SPECIFICATIONS

Feature	Detail
Model Name	DT-682
Brand	Jugbow
Item Weight	14.4 ounces
Remote Range	Up to 4200FT
Waterproof Rating	IPX8 (Collars only, remote is not waterproof)
Dog Weight Capacity	10-120 lbs

Neck Girth (Adjustable)	7.8 - 24.4 inches
Battery Type	Rechargeable Lithium-ion (internal)
Charging Time	Approx. 2 hours
Standby Time	Remote: 45 days, Collars: 35 days
Material	Nylon strap

8. WARRANTY & SUPPORT

Your Jugbow Dog Training Collar comes with a **1-Year Warranty** from the date of purchase, covering manufacturing defects. Please retain your proof of purchase.

For technical assistance, troubleshooting, or warranty claims, please contact Jugbow customer support. Refer to the product packaging or the official Jugbow website for the most current contact information.

It is recommended to wear the collar continuously for a maximum of 12 hours. This product is *not* recommended for aggressive dogs.