Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

JVC SPPA5BT

JVC Illuminated Portable Wireless Speaker SPPA5BT User Manual

Model: SPPA5BT

1. Introduction

Thank you for purchasing the JVC Illuminated Portable Wireless Speaker SPPA5BT. This speaker is designed to provide powerful, dynamic sound with the convenience of wireless connectivity and multi-color illumination. Its durable, water-resistant design makes it ideal for both indoor and outdoor use. Please read this manual carefully before using the product to ensure proper operation and to maximize its lifespan.

2. Product Overview

The JVC SPPA5BT speaker combines robust audio performance with a portable, illuminated design. Key features include Bluetooth 5.0 for stable connections, TWS capability for stereo pairing, hands-free phone functions, and IPX5 water resistance.



Figure 2.1: JVC SPPA5BT Portable Wireless Speaker (Blue) showcasing its water-resistant design.



Figure 2.2: Overview of the speaker's main functionalities including powerful sound, hands-free calling, multi-color illumination, and a convenient carrying strap.



Figure 2.3: The TWS (True Wireless Stereo) function allows two speakers to connect for an immersive stereo sound experience.



Figure 2.4: The speaker boasts an IPX5 water resistance rating, making it suitable for outdoor adventures and poolside use.



Figure 2.5: Enjoy up to 5 hours of continuous playtime with the built-in rechargeable battery.



Figure 2.6: The speaker features multi-color illumination with selectable modes to enhance your listening experience.



Figure 2.7: The JVC SPPA5BT is available in three vivid colors: Blue, Black, and Green.

3. Setup

3.1 Charging the Speaker

Before first use, fully charge the speaker. A USB charging cable is included in the box.

1. Connect the USB-C end of the charging cable to the speaker's USB-C port.
2. Connect the USB-A end to a compatible USB power adapter (not included) or a computer's USB port.
3. The charging indicator light will illuminate. Charging time is approximately 3.5 hours.
4. The indicator light will change or turn off once charging is complete.

3.2 Powering On/Off

- To power on, press and hold the Power button for a few seconds until you hear an audible prompt and the illumination lights activate.
- To power off, press and hold the Power button again for a few seconds until the lights turn off and you hear an audible prompt.

4. Operating Instructions

4.1 Bluetooth Pairing

Connect your speaker to a Bluetooth-enabled device for wireless audio playback.

1. Ensure the speaker is powered on and in Bluetooth pairing mode (usually indicated by a blinking blue light). If not, briefly press the Bluetooth button.
2. On your device (smartphone, tablet, laptop), go to Bluetooth settings and enable Bluetooth.
3. Search for available devices. Select "JVC SPPA5BT" from the list.
4. Once connected, the speaker will provide an audible confirmation, and the Bluetooth indicator light will become

solid.

4.2 TWS (True Wireless Stereo) Function

Pair two JVC SPPA5BT speakers for a true stereo sound experience.

1. Ensure both speakers are powered on and not connected to any Bluetooth device.
2. On one speaker (this will be the primary speaker), press and hold the TWS button (often combined with the Bluetooth button or a dedicated button) until you hear a prompt.
3. The primary speaker will search for the secondary speaker. Once connected, you will hear a confirmation sound.
4. Now, connect your device to the primary speaker via Bluetooth as described in Section 4.1. Audio will play through both speakers in stereo.

4.3 Controls and Functions

Button/Port	Function
Power Button	Press and hold to Power On/Off.
Play/Pause Button	Press to Play/Pause music. Press and hold for 2 seconds to change illumination modes.
Volume + / Next Track	Press to increase volume. Press and hold to skip to the next track.
Volume - / Previous Track	Press to decrease volume. Press and hold to go to the previous track.
Bluetooth Button	Press to enter Bluetooth pairing mode.
USB-C Port	For charging the speaker.
AUX Input	Connect external audio devices via a 3.5mm audio cable.

4.4 Multi-Color Illumination

The speaker features dynamic multi-color LED illumination. To cycle through the different lighting modes, press and hold the Play/Pause button for 2 seconds. This will allow you to select your preferred lighting effect or turn the illumination off.

4.5 Hands-free Calling

When connected to your smartphone via Bluetooth, the speaker can be used for hands-free calls.

- **Answer Call:** Press the Play/Pause button once.
- **End Call:** Press the Play/Pause button once during a call.
- **Reject Call:** Press and hold the Play/Pause button for 2 seconds.

4.6 AUX Input Mode

For devices without Bluetooth, use the AUX input.

1. Connect one end of a 3.5mm audio cable (included) to the speaker's AUX port.
2. Connect the other end to the audio output of your device.

3. The speaker will automatically switch to AUX mode.

5. Maintenance

- **Cleaning:** Use a soft, dry cloth to clean the speaker's surface. Do not use abrasive cleaners or solvents.
- **Water Resistance:** While the speaker is IPX5 water resistant, it is not designed for submersion. Ensure the charging port cover is securely closed when near water. Dry the speaker thoroughly before charging if it has been exposed to water.
- **Storage:** Store the speaker in a cool, dry place away from direct sunlight and extreme temperatures. If storing for an extended period, charge the battery every few months to maintain its health.
- **Battery Care:** To prolong battery life, avoid fully discharging the speaker frequently.

6. Troubleshooting

Problem	Possible Solution
Speaker does not turn on.	Ensure the battery is charged. Connect to a power source and try again.
Cannot pair with Bluetooth device.	Make sure the speaker is in pairing mode (blinking blue light). Ensure Bluetooth is enabled on your device and it's within 10 meters (33 feet) of the speaker. Forget the device on your phone and try pairing again.
No sound or low volume.	Increase volume on both the speaker and your connected device. Ensure the speaker is properly connected via Bluetooth or AUX.
TWS pairing fails.	Ensure both speakers are powered on and not connected to any other Bluetooth devices. Try resetting both speakers and repeating the TWS pairing process.
Illumination lights are off.	Press and hold the Play/Pause button for 2 seconds to cycle through illumination modes, ensuring it's not set to 'off'.

7. Specifications

Feature	Detail
Model Name	JVC Dynamic Sound (SPPA5BT)
Speaker Type	Outdoor, Portable Wireless Speaker
Connectivity Technology	Bluetooth 5.0, USB, AUX
Speaker Maximum Output Power	20 Watts
Battery Life	Up to 5 Hours
Battery Capacity	2000 mAh
Charging Time	Approximately 3.5 Hours
Water Resistance Level	IPX5 (Water Resistant)

Feature	Detail
Product Dimensions	3.43"D x 2.67"W x 4.19"H
Item Weight	2.07 pounds
Bluetooth Range	Up to 10 Meters (33 Feet)
Included Components	User manual, USB Charging cable
Material	Acrylonitrile Butadiene Styrene (ABS)
Control Method	Touch (Buttons)
Audio Output Mode	Stereo
Special Features	Portable, LED Light, Waterproof, Stereo Pairing (TWS), USB Port, Hands-free Calling

8. Warranty and Support

This JVC product comes with a Limited Warranty. For detailed warranty information, terms, and conditions, please refer to the warranty card included with your product or visit the official JVC website. For technical support, troubleshooting assistance, or service inquiries, please contact JVC customer support through their official channels.

Online Support: Visit the official JVC website for FAQs, product registration, and contact information.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0D7R1N4F2

More documents and user manuals: **https://manuals.plus/**