

## IMOURLIVE LLJ50

# IMOURLIVE LLJ50 Cordless Hedge Trimmer User Manual

Model: LLJ50

[Overview](#)   [Setup](#)   [Operation](#)   [Safety Information](#)   [Product](#)   [Maintenance](#)   [Troubleshooting](#)   [Specifications](#)   [Warranty & Support](#)

## 1. SAFETY INFORMATION

Always read and understand all safety warnings, instructions, illustrations, and specifications provided with this power tool. Failure to follow all instructions listed below may result in electric shock, fire, and/or serious injury.

### General Safety Warnings:

- **Wear Eye Protection:** Always wear safety glasses or goggles to protect your eyes from flying debris.
- **Wear Hand Protection:** Use heavy-duty gloves to protect your hands from sharp blades and branches.
- **Keep Clear:** Ensure bystanders, children, and pets are at a safe distance (at least 50 feet/15 meters) from the work area.
- **Inspect Before Use:** Check the hedge trimmer for any damaged parts, loose screws, or worn blades before each use. Do not operate if damaged.
- **Avoid Electrical Hazards:** Do not operate the hedge trimmer near electrical cables, wires, or other power sources.
- **Maintain Firm Grip:** Always hold the hedge trimmer firmly with both hands during operation.
- **Remove Battery When Not in Use:** Disconnect the battery pack from the tool before making any adjustments, changing accessories, or storing the tool.
- **Use in Good Weather:** Avoid using the trimmer in wet conditions or rain.

## 2. PRODUCT OVERVIEW

The IMOURLIVE LLJ50 Cordless Hedge Trimmer is designed for efficient and precise trimming of hedges,

bushes, and shrubs. It features a powerful brushless motor, a 22-inch dual-action blade, and multiple speed settings for versatile use.

### Key Features:

- **Powerful Cutting Capacity:** 22-inch dual-action blade with a 3/4-inch cutting capacity.
- **Brushless Motor:** Provides increased efficiency, longer tool life, and reduced noise.
- **Three Speed Modes:** Offers adjustable speeds (up to 3000 SPM) for various trimming tasks and battery life optimization.
- **Lightweight Design:** Weighs approximately 4.4 lbs for comfortable extended use.
- **Cordless Operation:** Powered by a 21V 2.0AH lithium battery for unrestricted movement.
- **Extension Pole Compatible:** Can be used with an IMOURLIVE telescopic pole (sold separately) for reaching higher areas.

### Product Components:



Figure 1: Main components of the IMOURLIVE LLJ50 Hedge Trimmer. Includes 22-inch blade, splash guards, brushless motor, safety switch, aluminum base, and grease injection port.

## 3. SETUP

### 3.1 Charging the Battery

Before first use, fully charge the 21V lithium battery. Connect the charger to a power outlet and then connect the battery pack to the charger. The indicator lights on the battery will show the charging status.



Figure 2: The 21V 2.0AH lithium battery provides up to 60 minutes of working time.

### 3.2 Attaching the Battery

1. Align the battery pack with the battery port on the hedge trimmer handle.
2. Slide the battery into the port until it clicks securely into place. Ensure it is fully seated to prevent accidental disconnection during operation.

### 3.3 Removing the Blade Cover

Carefully remove the blade cover from the trimmer blade before operation. Store the blade cover in a safe place and reattach it after each use for protection.

### 3.4 Extension Pole (Optional)

This hedge trimmer is compatible with an IMOUMLIVE telescopic extension pole (sold separately). To attach, follow the instructions provided with the extension pole. This allows for multi-angle trimming and

reaching heights up to 11 feet.

## 4. OPERATING INSTRUCTIONS

### 4.1 Starting and Stopping the Trimmer

1. **To Start:** Press and hold the safety switch (usually located on the handle) with one hand, then squeeze the trigger switch with the other hand. The trimmer will begin operating.
2. **To Stop:** Release the trigger switch. The safety switch can then be released.

### 4.2 Selecting Speed Modes

The trimmer offers three speed modes to suit different cutting needs:

- **Lower Speed (e.g., 2000 SPM):** Ideal for lighter trimming tasks and extending battery life.
- **Higher Speed (e.g., 3000 SPM):** Provides maximum power for thicker branches and faster cutting.

Use the mode selection button on the tool to cycle through the available speeds.



Figure 3: The hedge trimmer features three operational modes for varied tasks.

### 4.3 Trimming Techniques

- **General Trimming:** Hold the trimmer with both hands, keeping the blade parallel to the hedge. Use a sweeping motion to cut evenly.
- **Cutting Capacity:** The 22-inch blade can cut branches up to 3/4-inch thick. Avoid forcing the blade through thicker material to prevent damage to the tool and potential injury.
- **Multi-Angle Trimming:** If using an extension pole, the pivoting head allows for trimming at various angles (0-180 degrees) to reach difficult areas without strain.



Figure 4: The 22-inch blade provides a cutting capacity of up to 3/4 inch thick.

# ULTRA LIGHTWEIGHT



Figure 5: The lightweight design (4.4 lbs) enhances user comfort during operation.

## 4.4 Instructional Video

Your browser does not support the video tag.

Video 1: Demonstrates the IMOUMLIVE Cordless Hedge Trimmer in use, highlighting its cutting capabilities and compatibility with an extension pole for reaching high hedges.

## 5. MAINTENANCE

Regular maintenance ensures optimal performance and extends the life of your hedge trimmer. Always remove the battery before performing any maintenance.

### 5.1 Blade Cleaning and Lubrication

1. **Clean Blades:** After each use, remove any sap, leaves, or debris from the blades using a stiff brush or cloth.
2. **Lubricate Blades:** Apply a light machine oil or blade lubricant along the cutting edge of the blades. This helps prevent rust and ensures smooth operation.

### 5.2 Battery Care

- **Storage:** Store the battery in a cool, dry place away from direct sunlight and extreme temperatures.
- **Charging:** Do not overcharge or completely discharge the battery. Follow the charging instructions provided.

### 5.3 Storage

When not in use, always reattach the blade cover. Store the hedge trimmer in a secure, dry location out of reach of children.

## 6. TROUBLESHOOTING

If you encounter issues with your IMOURLIVE LLJ50 Hedge Trimmer, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Trimmer does not start	Battery not charged or improperly installed; Safety switch not engaged; Trigger not pressed.	Ensure battery is fully charged and correctly inserted. Press safety switch before squeezing trigger.
Reduced cutting power	Dull or dirty blades; Low battery charge; Attempting to cut material too thick.	Clean and lubricate blades. Recharge battery. Do not force the trimmer through thick branches; use appropriate tools for larger cuts.
Excessive vibration or noise	Loose components; Damaged blade.	Check for loose screws and tighten them. Inspect blades for damage; replace if necessary. If problem persists, contact customer support.
Battery not charging	Charger not properly connected; Faulty charger or battery.	Ensure charger is securely plugged into outlet and battery. Test charger with another battery if possible. If issues persist, contact customer support.

## 7. SPECIFICATIONS

Feature	Detail
Brand	IMOURLIVE
Model Number	LLJ50
Power Source	Battery Powered (21V Lithium)
Blade Length	22 Inches
Cutting Capacity	0.75 Inches (3/4 inch)
Item Weight	4.4 Pounds
Motor Type	Brushless
Max SPM (Strokes Per Minute)	3000 RPM
Material	Aluminum (Base), Metal (Blade)

Feature	Detail
Product Dimensions (L x W x H)	5"L x 4"W x 33.2"H

## 8. WARRANTY & SUPPORT

---

IMOURLIVE products are manufactured to high-quality standards. For specific warranty details, please refer to the warranty card included with your product or visit the official IMOURLIVE website. Keep your purchase receipt as proof of purchase.

### **Customer Support:**

If you have any questions, require technical assistance, or need to claim warranty service, please contact IMOURLIVE customer support through the retailer where you purchased the product or via the contact information provided on the official IMOURLIVE website.