

Veout V1

Veout 16" Portable Monitor Instruction Manual

Model: V1

1. INTRODUCTION

The Veout 16-inch Portable Monitor is designed to enhance your productivity and entertainment on the go. Featuring a 1920x1200P IPS display, it offers vibrant colors, wide viewing angles, and eye-care comfort. Its ultra-slim and lightweight design makes it an ideal companion for travel, office work, and gaming. This manual provides essential information for setting up, operating, and maintaining your new portable monitor.



Figure 1: Veout 16-inch Portable Monitor in use.


2. WHAT'S IN THE BOX

Please check the package contents to ensure all items are present:

- Veout 16" Portable Monitor
- HDMI to Mini-HDMI Cable
- Type-C to Type-C Cable
- USB-C to USB-A Cable
- User Manual


ALUMINUM ALLOY VERSUS PVC PLASTIC

Others



- ✗ Daily Wear and Tear of Materials
- ✗ Release Harmful Substances
- ✗ Poor Thermal Conductivity
- ✗ Coarse and Low-quality

VEOUT



- ✓ Pressure-resistant and Drop-proof
- ✓ 100% Lead-free and Plasticizer-free
- ✓ Rapid screen heat dissipation
- ✓ CNC-machined aluminum body

Figure 2: Included accessories with the portable monitor.

3. SETUP GUIDE

The Veout portable monitor offers versatile connectivity options for various devices.

3.1 Single-Cable USB-C Connection (Recommended)

For devices with full-featured USB-C ports (supporting video output and power delivery), a single USB-C to USB-C cable is all you need for both power and display.

1. Connect one end of the Type-C to Type-C cable to your device's USB-C port.
2. Connect the other end of the Type-C to Type-C cable to either of the monitor's USB Type-C ports (Type-C1 or Type-C2).
3. The monitor should automatically detect the signal and power on.

Experience the Magic of FreeSync

Eliminate screen tearing and stuttering with our portable monitor equipped with FreeSync technology. Say goodbye to frustration and hello to smooth, responsive gameplay.

Note: Ensure your laptop has an AMD Radeon graphics card for optimal FreeSync performance.



Figure 3: Single USB-C connection for plug-and-play functionality.

3.2 HDMI + USB-A Connection

If your device does not have a full-featured USB-C port, you can use the HDMI and USB-A cables for display and power respectively.

1. Connect the Mini-HDMI end of the HDMI to Mini-HDMI cable to the monitor's Mini-HDMI port.
2. Connect the standard HDMI end to your device's HDMI port.
3. Connect the USB-C end of the USB-C to USB-A cable to one of the monitor's USB Type-C ports (Type-C1 or Type-C2).
4. Connect the USB-A end to a USB-A port on your device or a power adapter (not included) for power.



Plug & Play

Our portable screen for laptops offers seamless connectivity with just a single USB-C cable, making it incredibly convenient for travel. You can use it at home, in a coffee shop, at a friend's place, or even in the car, providing you with the flexibility to work or enjoy content almost

Figure 4: Two-cable connection using HDMI for video and USB-A for power.

3.3 Initial Power On

Once connected, the monitor should power on automatically. If not, press the power button located on the side of the monitor.

Your browser does not support the video tag.

Video 1: Demonstrates various connection methods for the Veout Portable Monitor.

4. OPERATING INSTRUCTIONS

4.1 Display Modes

The built-in kickstand allows for flexible viewing angles and orientation:

- **Landscape Mode:** Ideal for multitasking, video editing, and general use.
- **Portrait Mode:** Perfect for reading documents, coding, or browsing web pages, saving vertical space.

IPS178° Viewing Angle & Eye-Care Comfort

Enjoy a wide viewing angle of 178° and low blue light protection for comfortable, long-lasting screen time. Our portable monitor is designed to protect your eyes while immersing you in vivid, accurate visuals.



Figure 5: Monitor displaying content in both horizontal and vertical orientations.

4.2 On-Screen Display (OSD) Menu

Use the intuitive menu control wheel and buttons on the side of the monitor to adjust settings:

- **Brightness/Backlight:** Adjust the screen's illumination.
- **Volume:** Control the audio output from the built-in dual speakers.
- **Color Settings:** Fine-tune color temperature, red, green, and blue levels.
- **HDR Mode:** Enhance dynamic range for vivid contrast.
- **FreeSync:** Enable or disable FreeSync technology for smoother motion in compatible applications.

Your browser does not support the video tag.

Video 2: A brief overview of the Veout Portable Monitor's features and display quality.

5. SPECIFICATIONS

Feature	Detail
Screen Size	16.0 inches
Resolution	1920 x 1200 Pixels (1200P)
Aspect Ratio	16:10
Panel Type	IPS
Viewing Angle	178°
Brightness	300 Candela (CD/M^2)
Contrast Ratio	1200:1
Color Gamut	100% sRGB
Thickness	0.36 inches
Item Weight	1.58 pounds
Connectivity	2x USB Type-C, 1x Mini-HDMI
Audio	Built-in Dual Speakers, 3.5mm Audio Jack
Special Features	Built-in Kickstand, FreeSync, HDR, Low-Blue-Light, Flicker-Free

6. MAINTENANCE

To ensure the longevity and optimal performance of your Veout Portable Monitor, follow these maintenance guidelines:

- **Cleaning the Screen:** Use a soft, lint-free cloth slightly dampened with water or a non-abrasive screen cleaner. Avoid using alcohol-based cleaners or harsh chemicals.
- **Cleaning the Body:** Wipe the monitor's aluminum body with a dry, soft cloth.
- **Storage:** When not in use, fold the kickstand flat and store the monitor in a protective sleeve or bag to prevent scratches and damage.
- **Handling:** Avoid dropping the monitor or applying excessive pressure to the screen.

7. TROUBLESHOOTING

If you encounter any issues with your Veout Portable Monitor, refer to the common problems and solutions below:

- **Brightness Issues:** If your laptop's battery is below 30% and not plugged in, the screen will dim to save power and cannot be made brighter. Ensure your laptop is sufficiently charged or connected to power.
- **Sound Issues:** The screen volume syncs with your laptop's. For more volume, adjust both the screen's OSD

settings and your laptop's audio settings.

- **Flashing Screen:** This is usually due to low voltage or a loose connection. Check all power cables and ensure they are securely plugged into the correct ports.
- **Monitor Won't Turn On:** Your device might not support Type-C video output or power delivery. Try connecting with the HDMI cable for video and a separate USB-A to USB-C cable for power.

Your browser does not support the video tag.

Video 3: Common issues and troubleshooting tips for the Veout Portable Monitor.

8. WARRANTY AND SUPPORT

Veout is committed to providing high-quality products and excellent customer service.

- **Warranty:** Your Veout Portable Monitor comes with a 12-month warranty from the date of purchase.
- **Money Back Guarantee:** Enjoy a 30-day money-back guarantee.
- **Customer Support:** For any other issues or inquiries, please reach out to the Veout Amazon store. We aim to reply within 12 hours to assist you with product problems.