

Amico GYF-5

Amico 5-Light Farmhouse Vanity Light Fixture

INSTRUCTION MANUAL - MODEL GYF-5

Brand: Amico

1. Safety Information

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries.

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes and ordinances, National Electrical Code (NEC), and ANSI/NFPA 70-1999.
- Consult a qualified electrician if you are unsure about the installation process.
- Use only UL/ETL listed wire connectors.
- Do not exceed the maximum wattage specified for this fixture.
- Handle glass components with care to prevent breakage.

2. Package Contents

Verify that all components are present before beginning installation:

- Light Fixture Body (with wood-like finish and metal board)
- Bubble Glass Shades (5 pieces)
- Mounting Hardware Kit (screws, wire nuts, mounting plate)



Image: Key components of the Amico 5-Light Vanity Light Fixture, showing the seeded glass shade, wood arm, E26 bulb base, and metal mounting board.

3. Specifications

Feature	Detail
Model Number	GYF-5
Brand	Amico
Number of Lights	5
Bulb Base	E26 Medium
Max Wattage per Bulb	60 Watts
Voltage	130 Volts

Material	Metal, Glass
Finish Type	Painted, Wood-Like
Shade Material	Glass (Bubble Glass)
Product Dimensions	32.28" L x 5.51" W x 8.66" H
Installation Type	Semi Flush Mount, Wall Mount
Indoor/Outdoor Usage	Indoor
Special Features	Dimmable (with compatible bulb/dimmer), Bubble Glass Shade



Image: Dimensional diagram of the Amico 5-Light Vanity Light Fixture, indicating its length, height, and depth.

4. Installation Instructions

4.1. Before You Begin

Tools You May Need (not included): Screwdriver, wire strippers, electrical tape, pliers, safety glasses, ladder.

- Ensure the power is turned OFF at the circuit breaker before starting.
- Unpack all parts carefully and place them on a clean, flat surface.
- Keep the instruction manual for future reference.

4.2. Step-by-Step Installation

1. **Turn Off Power:** Locate the circuit breaker that supplies power to the light fixture location and turn it off.
2. **Remove Old Fixture (if applicable):** Carefully remove any existing light fixture, noting the wiring connections.
3. **Attach Mounting Plate:** Secure the mounting plate to the junction box using the provided screws. Ensure it is firmly attached.
4. **Wire Connections:** Connect the fixture's wires to the house wires:
 - Connect the **black** wire (live) from the fixture to the **black** wire from the junction box using a wire nut.
 - Connect the **white** wire (neutral) from the fixture to the **white** wire from the junction box using a wire nut.
 - Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box (or to the green ground screw on the mounting plate).

Ensure all connections are secure and covered with wire nuts.
5. **Mount Fixture Body:** Carefully tuck the wires into the junction box. Align the fixture body with the mounting plate and secure it with the provided screws.
6. **Install Glass Shades:** Gently attach each bubble glass shade to the fixture. Do not overtighten.
7. **Install Bulbs:** Screw in the required E26 base bulbs (not included) into each socket. Do not exceed 60W per bulb.
8. **Restore Power:** Turn the power back on at the circuit breaker. Test the light fixture.



Available Down



Available Up

Image: The Amico vanity light fixture can be installed with the lights facing either up or down, offering versatility in lighting direction.

5. Operating Instructions

This Amico vanity light fixture is designed for simple operation once installed.

- **Bulb Requirements:** The fixture uses 5 E26 base bulbs (not included). Compatible bulb types include incandescent, CFL, halogen, and LED bulbs, up to a maximum of 60 watts per bulb.
- **Dimmable Functionality:** The fixture is fully dimmable when used with dimmable E26 bulbs and a compatible dimmer switch (both sold separately).
- **Power On/Off:** Control the light fixture using a standard wall switch connected to the circuit.



Image: Examples of E26 base bulbs compatible with the fixture, including various shapes and styles.

6. Maintenance

Regular cleaning will help maintain the appearance and performance of your light fixture.

- **Cleaning:** Always turn off the power before cleaning. Use a soft, dry cloth to wipe the metal and wood-like surfaces. For the glass shades, a slightly damp cloth can be used, followed by a dry cloth to prevent water spots.
- **Do Not Use:** Avoid abrasive cleaners, solvents, or polishes as they may damage the finish or glass.
- **Bulb Replacement:** Ensure the power is off and bulbs have cooled before replacing them.

7. Troubleshooting

If you encounter issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Light does not turn on	1. Power is off 2. Loose wiring connection 3. Faulty bulb	1. Check circuit breaker/wall switch 2. Turn off power and check wire connections 3. Replace bulb(s)
Light flickers	1. Loose bulb 2. Incompatible dimmer switch/bulb 3. Loose wiring	1. Tighten bulb 2. Ensure dimmer and bulbs are compatible 3. Turn off power and check wire connections
Glass shade is loose	Retaining ring not tightened	Gently tighten the retaining ring holding the shade

If the problem persists after attempting these solutions, please contact customer support.

8. Warranty and Support

Amico offers a **24-month promise** for this product. If your vanity light fixture has any defects or stops working within 2 years of purchase, Amico will troubleshoot the issue or send a replacement.

For any questions or concerns regarding your product, please contact Amico customer support. They aim to respond within 24 hours.

Return Policy: This product is eligible for a refund or replacement within 30 days of purchase, subject to the retailer's return policy.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question