

i Cafilas ME2218

i Cafilas Portable Electric Espresso Coffee Maker ME2218 User Manual

Model: ME2218 | Brand: i Cafilas

INTRODUCTION

This manual provides comprehensive instructions for the safe and efficient use of your i Cafilas Portable Electric Espresso Coffee Maker, Model ME2218. This 2-in-1 device supports both ground coffee and NS capsules, offering a convenient way to enjoy espresso on the go. Please read this manual thoroughly before operating the device and retain it for future reference.

SAFETY INFORMATION

- Read all instructions before use.
- Do not immerse the main unit in water or other liquids.
- Keep out of reach of children.
- Use only with clean drinking water.
- Exercise caution when handling hot water and coffee to prevent burns.
- Ensure the device is fully charged before use, especially for heating functions.
- Do not operate if the device is damaged or malfunctioning.
- Only use the provided charging cable.
- This appliance is not dishwasher safe.

PACKAGE CONTENTS

Verify that all items are present in the package:

- i Cafilas Portable Electric Espresso Coffee Maker (Main Unit)
- USB-C Charging Cable
- Ground Coffee Adapter
- NS Capsule Adapter
- Coffee Scoop
- Cleaning Brush
- Carrying Pouch

- User Manual (this document)

ALL YOU NEED IS INCLUDED IN PACKAGE.



Image: All components included in the iCafilas Portable Electric Espresso Coffee Maker package.

PRODUCT OVERVIEW

The iCafilas ME2218 is a compact and versatile portable espresso machine designed for ease of use and high-quality espresso extraction. It features a 2-in-1 design, allowing the use of both ground coffee and NS capsules. The device is equipped with a 7500mAh rechargeable battery for self-heating functionality and 19 BAR pressure for rich crema.

- **2-in-1 Functionality:** Compatible with ground coffee and NS capsules.
- **Self-Heating:** Heats cold water in 3-4 minutes.
- **High Pressure:** Achieves 19 BAR for optimal espresso extraction and rich crema.
- **Long-lasting Battery:** 7500mAh battery supports 3-5 hot brews or over 200 cold brews on a full charge.
- **Portable Design:** Compact and lightweight for travel, camping, car use, and office.
- **One-Button Operation:** Simple and intuitive to use.

2 IN 1 DESIGN



Ground Coffee



Ne*presso Capsule

Image: The 2-in-1 design of the coffee maker, accommodating both ground coffee and capsules.

RICH CREAM EXTRACTING AND PURE FLAVOR BLOOMING

19 Bar Stable High-pressure
Extraction



high-pressure
extraction



One button
operation



Image: Illustration of the 19 BAR high-pressure extraction for rich crema.

SETUP

1. **Initial Charge:** Before first use, fully charge the device using the provided USB-C cable. Connect the cable to the charging port on the device and a compatible USB power source (laptop, car charger, power bank). The battery indicator lights will show charging progress.
2. **Clean Components:** Wash all removable parts (coffee cup, adapters) with warm soapy water and rinse thoroughly. Ensure they are completely dry before assembly.
3. **Familiarize Yourself:** Identify the main unit, coffee cup, ground coffee adapter, and capsule adapter.

MORE DURABLE AND CONVENIENT

7500 MAH Large
Lithium Battery

USB-TYPEC
CHARGING PORT



Laptop
charging



Car charging



Power bank
charging



Image: The device's battery and charging options.

OPERATING INSTRUCTIONS

The i Cafilas ME2218 offers two brewing methods: ground coffee and NS capsules, and supports both hot and cold water brewing.

Brewing with Ground Coffee:

1. Ensure the device is fully charged.
2. Unscrew the portafilter from the main unit.
3. Insert the ground coffee adapter into the portafilter.
4. Add approximately 8-10g of fine ground coffee into the adapter. Gently tamp the coffee if desired.
5. Screw the portafilter back onto the main unit tightly.
6. Unscrew the water tank lid and add water. For a single shot (30ml/1oz), fill to the 40ml mark. For a double shot (60ml/2oz), fill to the 70ml mark.


7. Screw the water tank lid back on.
8. Place the coffee maker directly over your cup.
9. **For Hot Brew:** Press the power button once to start. The device will heat the water and extract espresso automatically.
10. **For Cold Brew:** Press and hold the power button for 2 seconds to start. The device will extract espresso using cold water.
11. The device will automatically stop once brewing is complete.

Brewing with NS Capsules:


1. Ensure the device is fully charged.
2. Unscrew the portafilter from the main unit.
3. Insert the NS capsule adapter into the portafilter.
4. Place an NS capsule into the adapter.
5. Screw the portafilter back onto the main unit tightly.
6. Unscrew the water tank lid and add water. For a single shot (30ml/1oz), fill to the 40ml mark. For a double shot (60ml/2oz), fill to the 70ml mark.
7. Screw the water tank lid back on.
8. Place the coffee maker directly over your cup.
9. **For Hot Brew:** Press the power button once to start. The device will heat the water and extract espresso automatically.
10. **For Cold Brew:** Press and hold the power button for 2 seconds to start. The device will extract espresso using cold water.
11. The device will automatically stop once brewing is complete.

HOW TO USE


- 01** Full charged at home




- 02** Add original Nespresso capsule or ground coffee



- 03** Position the adapter into the portafilter



- 04** Screw the portafilter back on the coffee maker tightly and put the cup back on



- 05** Add hot or cold water to brew coffee



- 06** Enjoy coffee



Image: Visual guide for operating the coffee maker.

HOT / COLD WATER FOR A VARIETY OF DRINKING

HOT WATER

Press once
to start



COLD WATER

Press and hold for
2 seconds to start



Image: Instructions for hot and cold water brewing.

MORE OPTIONS FOR CAPACITY AND COLD/HOT WATER



50ml/70ml
For 1 or 2 cups

Self-Heating Allows the extraction of
Cold/Hot Water



Image: Water capacity markings for single or double shots.

Official Product Video:

Your browser does not support the video tag.

Video: This video demonstrates the operation of the i Cafilas portable electric espresso coffee machine (Model 2218), showcasing its features and ease of use for brewing espresso.

MAINTENANCE AND CLEANING

- **After Each Use:** Disassemble the portafilter and coffee cup. Rinse all parts that came into contact with coffee or water under running water. Use the provided cleaning brush to remove any coffee grounds.
- **Deep Cleaning:** Periodically, perform a deep clean by running a cycle with just water (no coffee) to flush out any residue.
- **Drying:** Ensure all components are completely dry before reassembling or storing to prevent mold or odors.
- **Storage:** Store the device in a cool, dry place.
- **Do Not Dishwash:** The main unit and electronic components are not dishwasher safe. Hand wash only.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Device not turning on.	Low battery.	Charge the device fully.
No coffee or weak extraction.	Insufficient water, coffee too coarse/fine, or portafilter not tightened.	Ensure adequate water, adjust coffee grind, or tighten portafilter securely.
Water not heating.	Low battery or incorrect button press.	Ensure full charge. Press the power button once for hot brew.
Leaking during operation.	Components not assembled correctly or seals are damaged.	Check that all parts are securely tightened. Inspect seals for damage.

SPECIFICATIONS

Model Name	Portable espresso maker
Item Model Number	ME2218
Brand	i Cafilas
Product Dimensions	2.95"D x 9.76"W x 2.95"H
Item Weight	2.1 pounds
Coffee Maker Type	Espresso Machine
Coffee Input Type	Ground, Capsule
Capacity	80 Milliliters
Voltage	10 Volts
Operation Mode	Manual (One-button automatic operation)
Special Feature	Compact, Supports capsule and ground coffee, Portable electric espresso coffee maker
Is Dishwasher Safe	No

WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the warranty card included in your product packaging or contact i Cafilas customer service directly. You can typically find contact details on the official i Cafilas website or through your retailer. Please have your model number (ME2218) and purchase date ready when contacting support.

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0D9N8KQLM>

More documents and user manuals: <https://manuals.plus/>