

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [LIORQUE](#) /

› [LIORQUE Digital Radio Alarm Clock User Manual](#)

## LIORQUE B02

# LIORQUE Digital Radio Alarm Clock User Manual

Model: B02

## 1. INTRODUCTION

Thank you for choosing the LIORQUE Digital Radio Alarm Clock. This device combines a versatile alarm clock with a 15W wireless charging station, Bluetooth speaker, FM radio, and a dynamic night light. Designed for convenience and functionality, it offers multiple features to enhance your daily routine and sleep environment. Please read this manual carefully to ensure proper use and maintenance of your device.



The LIORQUE Digital Radio Alarm Clock, featuring a large LED display and a wireless charging pad on top, with a smartphone actively charging.

# Kompakt und multifunktional



Kabelloses Laden



Nachtlicht



Doppelwecker



Schlafmusik



FM-Modus



BT-Modus

A compact and multifunctional view of the alarm clock, highlighting its key features: wireless charging, night light, dual alarms, sleep music, FM radio, and Bluetooth connectivity.

## 2. SAFETY INFORMATION

- Do not expose the device to extreme temperatures, direct sunlight, or high humidity.

- Keep away from water and other liquids.
- Do not disassemble or attempt to repair the device yourself. Refer to qualified service personnel.
- Use only the provided power adapter.
- Ensure proper ventilation around the device during operation.

### 3. PACKAGE CONTENTS

Please check the package for the following items:

- LIORQUE Digital Radio Alarm Clock (Model: B02)
- 24W Power Adapter
- User Manual
- 1 CR2032 Battery (pre-installed for backup)



Contents of the LIORQUE B02 package, including the alarm clock, power adapter, and user manual.

### 4. PRODUCT OVERVIEW

Familiarize yourself with the main components and controls of your alarm clock.

#### Front Panel:

- **LED Display:** Shows time, day, alarm status, and mode indicators.

#### Top Panel:

- **Wireless Charging Pad:** For Qi-compatible devices.
- **Snooze/Light Button:** Press to snooze alarm or adjust night light.

#### Rear Panel:

- **Power Input:** Connect the power adapter.
- **Control Buttons/Knobs:** For setting time, alarms, radio, and other functions. (Specific button functions are detailed in the 'Operating Instructions' section).
- **USB Port:** For additional charging (if available).
- **Headphone Jack:** For private listening.

## **5. SETUP**

### **5.1 Initial Power On**

1. Unpack the alarm clock and all accessories.
2. Connect the provided 24W power adapter to the 'Power Input' port on the rear of the alarm clock.
3. Plug the power adapter into a wall outlet. The display will light up.
4. The pre-installed CR2032 battery serves as a backup for time settings during power outages.

### **5.2 Setting the Time**

The alarm clock can automatically synchronize its time with your phone via Bluetooth. Alternatively, you can set it manually:

1. Locate the 'Time Set' button or knob on the rear panel.
2. Press/rotate to enter time setting mode.
3. Adjust hours and minutes using the designated controls.
4. Confirm the setting to save the time.

## **6. OPERATING INSTRUCTIONS**

### **6.1 15W Wireless Charging**

The top surface of the alarm clock features a Qi-certified wireless charging pad.

- Place your Qi-compatible smartphone or wireless earbuds case directly onto the charging pad.
- Ensure the device is centered on the pad for optimal charging.
- The charging output is up to 15W for Android devices, 7.5W for iPhones, and 5W for other compatible devices.

# Bunte Nachtlampe, Stufenlose Helligkeitsregelung, Automatischer Dimmer

0%

100%



A smartphone being charged wirelessly on the top surface of the LIORQUE alarm clock, illustrating the 15W fast wireless charging capability.



**15W**  
für Android-Handy



**7.5W**  
für iPhone



**5W**  
für alle Geräte mit  
kabelloser Ladefunktion



## Drahtlose Ohrhörer



APPLE



SONY



SAMSUNG

A visual representation of the wireless charging compatibility, showing different phone models and wireless earbuds that can be charged.

## 6.2 Setting Dual Alarms & Weekend Mode

The device supports two independent alarms (Alarm 1 and Alarm 2).

1. Press the 'Alarm 1' or 'Alarm 2' button to select the alarm you wish to set.
2. Use the time adjustment controls to set the desired wake-up time.
3. Select your preferred alarm sound (FM radio station or built-in sound).
4. To activate Weekend Mode, press the 'Weekend Mode' button. This allows you to mute alarms or set different times for Saturday and Sunday.
5. Confirm your settings.

# Musik zum Einschlafen

Sie können Musik und Nachtlicht einstellen, um Ihnen beim Einschlafen zu helfen, und die Sleep-Timer-Funktion verwenden, um einen Countdown zum Ausschalten einzustellen.



The alarm clock display showing indicators for two independent alarms and the days of the week, illustrating the dual alarm and weekend mode functionality.



A close-up of the alarm clock's display, clearly showing the days of the week (SUN, MON, TUE, WED, THU, FRI, SAT) for setting specific alarm schedules.

### 6.3 FM Radio Operation

The alarm clock has a built-in FM radio with automatic station search and memory function.

1. Press the 'FM' button to switch to FM radio mode.
2. Press and hold the 'Scan' button to automatically search for and save available stations (frequency range: 76.0-108.0 MHz).
3. Use the 'Tune' buttons to navigate through saved stations.
4. Adjust the volume using the 'Volume' controls.



24W Ladegerät

LIORQUE B02  
Wecker mit kabelloser Ladung

LIORQUE  
Alarm Clock with Wireless Charging  
Model: B02  
E-mail: support@liorque.net  
Bedienungsanleitung

The LIORQUE alarm clock displaying the time and indicating it is in radio mode, with visual representations of radio frequency waves.



A diagram illustrating the FM radio frequency range of the alarm clock, from 76 MHz to 108 MHz, with various frequencies highlighted.

#### 6.4 Bluetooth Pairing & Music Playback

Connect your smartphone or other Bluetooth-enabled devices to play music wirelessly.

1. Press the 'Bluetooth' button to enter Bluetooth pairing mode. The display will show 'BT' and flash.
2. On your smartphone, enable Bluetooth and search for 'B02' in the list of available devices.
3. Select 'B02' to pair. Once connected, the 'BT' indicator will stop flashing.
4. You can now play music from your device through the alarm clock's speaker.
5. The alarm clock can also automatically synchronize its time with your phone when connected via Bluetooth.

# Radio-Modus

Automatisches digitales Durchsuchen von  
Stationen mit Vorseicherung

Frequenzbereich **76-108MHz**



The LIORQUE alarm clock in Bluetooth mode, displayed alongside a smartphone showing its Bluetooth settings, ready for pairing.



A smartphone screen demonstrating music playback via Bluetooth, connected to the alarm clock, with album art visible.

## 6.5 Relaxing Sleep Sounds & Night Light

Enhance your sleep environment with soothing sounds and a colorful night light.

- Press the 'Sleep Sound' button to cycle through 25 built-in soothing sounds.
- Press the 'Light' button to activate the dynamic colorful night light.
- Press and hold the 'Light' button or use the 'Snooze/Light' button on top to adjust the brightness (stepless dimming from 0% to 100%).
- Set a sleep timer to automatically turn off the sounds and light after a set duration.

# Bluetooth-Modus

Mit dem Telefon verbinden, um die Uhrzeit automatisch einzustellen und Musik von Ihrem Handy über Bluetooth abzuspielen



A child sleeping peacefully in bed, with the LIORQUE alarm clock on the nightstand emitting soft, colorful light and playing sleep music.

# Doppelwecker & Wochenendmodus

Hilft Ihnen, Ihre Wecker-Einstellungen maximal anzupassen



The LIORQUE alarm clock showcasing its colorful night lamp feature, with a visual slider indicating stepless brightness control from 0% to 100% and automatic dimming.



# 10 Farboptionen für Licht



A side-by-side comparison of the alarm clock's display brightness, showing its appearance during the day and its automatically dimmed state at night.



A small image illustrating the 10 available color options for the night light feature of the alarm clock.

## 7. MAINTENANCE

- Clean the device with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- Keep the wireless charging pad free of dust and debris to ensure efficient charging.
- If the device will not be used for an extended period, unplug it from the power outlet.

## 8. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device does not power on.	Power adapter not connected or faulty outlet.	Ensure power adapter is securely plugged into the device and a working wall outlet.
Wireless charging not working.	Device not Qi-compatible or not properly aligned.	Ensure your device supports Qi wireless charging and is centered on the charging pad. Remove any thick phone cases.
Alarm does not sound.	Alarm not set or volume too low.	Verify alarm settings and ensure alarm volume is audible. Check if Weekend Mode is active.

Problem	Possible Cause	Solution
Bluetooth pairing fails.	Device too far or Bluetooth not enabled.	Ensure the alarm clock is in Bluetooth pairing mode and your phone's Bluetooth is enabled and searching. Keep devices within range.
Poor FM radio reception.	Weak signal or interference.	Adjust the position of the device or extend the antenna (if applicable). Rescan for stations.

## 9. SPECIFICATIONS

- **Brand:** LIORQUE
- **Model Number:** B02
- **Product Dimensions:** 11.5 x 3.81 x 9 cm
- **Weight:** 750 grams
- **Color:** Grey
- **Display Type:** Digital LED
- **Frame Material:** Plastic
- **Power Source:** AC Powered (with 1 CR2032 battery for backup, included)
- **Wireless Charging Output:** Up to 15W (Android), 7.5W (iPhone), 5W (others)
- **FM Radio Frequency:** 76.0-108.0 MHz
- **Special Features:** Dual Alarms, Weekend Mode, Bluetooth Music Playback, Sleep Sounds (25 types), Dynamic Colorful Night Light, Auto Dimmer

## 10. WARRANTY AND SUPPORT

LIORQUE products are designed and manufactured to the highest quality standards. For any questions, technical support, or warranty claims, please contact LIORQUE customer service through the retailer's platform or the official LIORQUE website. Please retain your proof of purchase for warranty purposes.