

[Manuals.plus](#) /

> [Qeeanmo](#) /

> Qeeanmo 60ft Smart Eave Lights User Manual

## Qeeanmo RM-EL3535DRGBW36-24V18M

# Qeeanmo 60ft Smart Eave Lights User Manual

Model: RM-EL3535DRGBW36-24V18M

Brand: Qeeanmo

## INTRODUCTION

---

This manual provides detailed instructions for the installation, operation, and maintenance of your Qeeanmo 60ft Smart Eave Lights. These permanent outdoor lights feature RGB+IC LED beads, smart control via app and voice assistants, music synchronization, and timer functions, designed for year-round outdoor decoration.

## WHAT'S IN THE BOX

---

- 10 x LED light strips
- 2 x Remote controls
- Power supply
- Bag of screws
- User manual



Image: Contents of the Qeeanmo Smart Eave Lights package, showing LED strips, remote controls, power supply, screws, and user manual.

Video description: This video demonstrates the unboxing and initial power-on of the Qeeanmo Smart Eave Lights, showing all included components and a brief display of the lights changing colors via remote control.

## SPECIFICATIONS

Feature	Detail
Brand	Qeeanmo
Model Number	RM-EL3535DRGBW36-24V18M
Color	Multicolor
Indoor/Outdoor Usage	Outdoor
Special Features	Dimmable, Waterproof, Color Changing, Water Resistant
Light Source Type	LED

Power Source	AC/DC
Number of Light Sources	36
Voltage	24 Volts
Control Method	App, Remote, Voice
Material	Polycarbonate
Waterproof Rating	IP67
Operating Temperature	-4°F to 140°F (-20°C to 60°C)

## SETUP AND INSTALLATION

Follow these steps for proper installation of your Qeeanmo Smart Eave Lights:

- 1. Prepare the Surface:** Ensure the installation surface is clean, dry, and smooth.
- 2. Positioning:** Install the string lights approximately 2-4 inches away from the wall surface for optimal lighting effect.
- 3. Adhesive Application:** Tear off the adhesive backing of each LED light unit.
- 4. Secure Attachment:** Firmly stick each eave light onto the desired location on the wall.
- 5. Reinforcement (Optional but Recommended):** If necessary, use the provided cable screw clips and screws to further secure the lights, especially in areas exposed to harsh weather.
- 6. Connect Power:** Connect the LED string light to the power supply unit.
- 7. Power On:** Plug the power supply into a suitable electrical outlet to turn on the lights.

**Kind Note: These string lights cannot be cut.**



Image: Step-by-step guide for installing the eave lights, illustrating adhesive application and optional screw reinforcement.

Video description: This video demonstrates the physical connection of the LED string lights to the power

supply and plugging it into an outlet, showing the lights illuminating.

## OPERATING INSTRUCTIONS

---

Your Qeeanmo Smart Eave Lights offer multiple control methods for a customized lighting experience.

### 1. Remote Control

The included RF remote control allows for basic functions such as turning the lights on/off, changing colors, and selecting preset modes.

Video description: This video segment shows a hand using the remote control to cycle through various colors and modes of the LED lights.

### 2. Smart App Control

For advanced features and customization, download the Rino Smart App (refer to the QR code in the app control video for download). The app allows you to:

- Select from 16 million colors and 212 preset scene modes.
- Adjust brightness and speed of dynamic effects.
- Set custom lighting sequences.
- Utilize music synchronization modes.
- Program automated lighting schedules with the timer function.

# App/Remote/Voice Control

Anytime, anywhere with smart control



Works with Hey Google | Works with Alexa

Rino Smart APP | Remote Control

Image: The Rino Smart App interface on a smartphone, demonstrating color selection and various functions, with the lights illuminating a house.

# More Functions Can be Achieved



Image: An overview of the advanced features accessible via the Rino Smart App, such as dimming, timers, DIY customization, and music sync.

## Connecting to the App:

1. Turn on the eave lights. Wait for the flashing to stop.
2. Open the Rino Smart App.
3. Long press the "ON" button on the remote control until the light flashes again to enter pairing mode.
4. In the app, click the "+" icon to add a device.
5. Allow Bluetooth connection and ensure your phone is connected to a 2.4G Wi-Fi network.
6. The app will automatically search for nearby devices. Select your eave lights from the list.
7. Enter your 2.4G Wi-Fi password to connect the lights to your network.
8. Once successfully matched, click "Finish".
9. Enter the eave light settings within the app to set the LED number (36 for this model) and the line sequence (RGB).

Video description: This video provides a detailed instruction on how to connect the Qeeanmo Smart Eave Lights to the mobile application, including pairing steps and initial setup.

Video description: This video demonstrates the process of connecting the lights to the Rino Smart App,

showing the interface for device discovery and Wi-Fi configuration.

### 3. Voice Control (Alexa & Google Assistant)

Once connected to the Rino Smart App, you can link your lights to Amazon Alexa or Google Assistant for convenient voice control. Use commands to adjust colors, brightness, and modes effortlessly.



*Image: Illustration of voice control functionality with Alexa and Google Assistant, showing a smart speaker and people enjoying the lights.*

### 4. Music Synchronization

The lights feature 8 built-in music modes that allow them to dynamically adjust to the beat of your music. Control the sensitivity via the app to create the perfect ambiance for any event.

# Music & MIC Sync Light changes with music



*Image: People enjoying an outdoor party with the eave lights displaying dynamic colors synchronized to music.*

## 5. Timer Function

Set automated lighting schedules using the built-in timer function via the Rino Smart App. Program specific on/off times to match your daily routine or special events, eliminating the need for manual switching. The lights also retain the last set mode with their memory function.

# Innovative Wall Lighting Effects



Image: A visual representation of the timer and schedule function within the app, showing lights turning on and off at set times.

## MAINTENANCE

---

To ensure the longevity and optimal performance of your Qeeanmo Smart Eave Lights, consider the following:

- **Cleaning:** Periodically wipe the light surfaces with a soft, damp cloth to remove dust and debris. Avoid harsh chemicals or abrasive cleaners.
- **Inspection:** Regularly inspect the cables and connections for any signs of wear, damage, or loose connections. Address any issues promptly.
- **Weather Protection:** While the lights are IP67 waterproof and designed for outdoor use, extreme weather conditions (e.g., severe storms, heavy snowfall) may warrant additional protection or temporary removal if possible.
- **Storage:** If storing the lights for an extended period, ensure they are clean, dry, and coiled neatly to prevent tangling or damage.

## TROUBLESHOOTING

---

If you encounter issues with your Qeeanmo Smart Eave Lights, refer to the following common problems and

solutions:

- **Lights not turning on:**

- Check if the power supply is securely plugged into a working outlet.
- Ensure all connections between the light strips and the power supply are firm.
- Verify that the remote control or app is sending the "On" command.

- **Lights not responding to remote/app:**

- For remote control, ensure there are no obstructions and the remote's battery is functional.
- For app control, check your phone's Bluetooth and Wi-Fi connection (2.4G network required).
- Try re-pairing the lights with the app by long-pressing the "ON" button on the remote until the lights flash.
- Restart the app and/or your phone.

- **Incorrect colors or effects:**

- In the Rino Smart App settings, ensure the correct LED number (36) and line sequence (RGB) are configured.
- Cycle through different modes or colors using the app or remote to see if the issue persists.

- **Wi-Fi connection issues:**

- Ensure your Wi-Fi network is 2.4GHz. These lights may not be compatible with 5GHz networks.
- Check your Wi-Fi password for accuracy.
- Move the lights closer to your Wi-Fi router to improve signal strength.
- Restart your Wi-Fi router.

If these steps do not resolve the issue, please contact Qeeanmo customer support for further assistance.

## **WARRANTY AND SUPPORT**

---

For warranty information and customer support, please refer to the documentation included with your product or visit the official Qeeanmo website. If you require technical assistance or have questions regarding your Smart Eave Lights, please contact Qeeanmo customer service.