Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

VEVSHAO V80

VEVSHAO V80 Smart DLP Projector User Manual

Model: V80
Brand: VEVSHAO

Introduction

Thank you for purchasing the VEVSHAO V80 Smart DLP Projector. This manual provides detailed instructions for setting up, operating, and maintaining your projector to ensure optimal performance and longevity. Please read this manual thoroughly before using the product and keep it for future reference.

Safety Information

To prevent fire or electric shock, do not expose this appliance to rain or moisture. Do not open the cabinet. Refer servicing to qualified personnel only.

- Do not block ventilation openings.
- Use only attachments/accessories specified by the manufacturer.
- Unplug this apparatus during lightning storms or when unused for long periods.
- Protect the power cord from being walked on or pinched.
- Do not look directly into the projector lens when the lamp is on.

Package Contents

Ensure all items are present in the package:

- VEVSHAO V80 Smart DLP Projector
- Remote Control
- Power Adapter
- User Manual (this document)

Product Overview

Front view of the VEVSHAO V80 Smart DLP Projector, showcasing its compact design and lens.

The V80 projector highlighting its powerful 20W x 2 built-in stereo speakers for immersive audio.

The VEVSHAO V80 is a high-performance DLP projector designed for various applications, from home cinema to business presentations. It features a true 1080p DMD display, 2200 ANSI lumens brightness, and runs on Android TV 11.0 with 4K support. Its compact design and auto-focus functionality make it highly versatile.

Visual comparison demonstrating the superior clarity and detail of the V80's Full HD 1080P resolution compared to other projectors.

Detailed view of the V80's connectivity ports, including USB, HDMI, AV, S/PDIF, LAN, and DC input, supporting various devices.

Setup

1. Placement

Place the projector on a stable, flat surface. Ensure there is adequate ventilation around the device. The V80 supports tabletop mounting and can be rotated 360 degrees for flexible projection angles.

The V80 projector's ability to rotate 360 degrees, offering freedom in placement and projection direction.

2. Power Connection

Connect the power adapter to the DC input port on the projector and then plug the adapter into a power outlet. The power indicator light will illuminate.

3. Initial Power On & Auto Focus

Press the power button on the projector or the remote control to turn on the device. The V80 features a standard TOF laser auto-focus system, which will automatically adjust the image clarity upon startup or movement. This eliminates the need for manual focus adjustments.

4. Network Connection (Wi-Fi)

Navigate to the settings menu on the Android TV interface. Select "Network & Internet" and choose your Wi-Fi network. Enter the password to connect. The projector supports Wi-Fi connectivity for seamless streaming.

The V80 projector demonstrating screen mirroring capabilities, allowing content from mobile devices to be displayed wirelessly.

Operating Instructions

1. Android TV Interface

The V80 runs on Android TV 11.0, providing a user-friendly interface. Use the remote control to navigate through menus, select applications, and adjust settings. Pre-installed apps like YouTube and Netflix are available, and you can download more from the app store.

The V80 projector displaying the Android TV interface with various streaming applications, ready for entertainment.

2. Media Playback

- **USB Input:** Connect a USB flash drive to the USB port to play local media files (videos, photos, music).
- **HDMI Input:** Connect external devices such as laptops, gaming consoles, or Blu-ray players via the HDMI port. Select the correct HDMI input source from the projector's menu.
- **Streaming Apps:** Utilize pre-installed or downloaded streaming applications like Netflix, YouTube, and Prime Video for online content.

3. 3D Functionality

The V80 projector is 3D ready. To enjoy 3D content, you will need compatible 3D glasses (sold separately) and 3D source material. Refer to the 3D glasses manual for pairing and usage instructions.

Experience your own private 3D cinema with the V80 projector, bringing movies to life with immersive depth.

4. Audio Output

The projector features two powerful built-in 20W stereo speakers, providing rich and clear audio. For external audio, you can connect to an external sound system via the S/PDIF port or other audio outputs if available.

Maintenance

1. Cleaning

- **Lens:** Use a soft, lint-free cloth specifically designed for optical lenses. Do not use abrasive cleaners or solvents.
- **Casing:** Wipe the projector's exterior with a soft, dry cloth. For stubborn stains, use a slightly damp cloth and then dry thoroughly.
- **Ventilation:** Ensure the ventilation openings are free from dust and debris to prevent overheating. The V80 is designed to be dust-resistant.

2. Storage

When not in use for extended periods, store the projector in a cool, dry place, away from direct sunlight and extreme temperatures. It is recommended to use the original packaging for storage to protect it from dust and physical damage.

Troubleshooting

Problem	Possible Cause	Solution
No image displayed	Power cable disconnected; Incorrect input source; Projector in standby mode.	Check power connection; Select correct HDMI/USB input; Press power button to wake up.
Image is blurry	Auto-focus issue; Projector moved.	Allow auto-focus to recalibrate; Ensure projector is stable.

Problem	Possible Cause	Solution
No sound	Volume too low; Muted; External device audio settings.	Increase volume; Unmute; Check audio output settings on connected device.
Wi-Fi connection unstable	Weak signal; Router issues.	Move projector closer to router; Restart router; Reconnect Wi-Fi.
Apps not working/compatible	App version outdated; Regional restrictions.	Update the app; Check for regional compatibility or alternative apps.

Specifications

Feature	Detail
Brand	VEVSHAO
Model Number	V80
Display Type	DLP
Native Resolution	1920 x 1080 Pixels (Full HD)
Brightness	2200 ANSI Lumens
Operating System	Android TV 11.0 (4K support)
Special Features	Auto Focus (TOF Laser), 3D Ready, Built-in Wi-Fi Receiver, Dust Resistant, Built-in Speakers
Speakers	2 x 20W Stereo Speakers
Connectivity Technology	HDMI, USB, Wi-Fi
Form Factor	Desktop
Mounting Type	Tabletop Mount
Item Weight	4.72 Kilograms
Shipping Dimensions	31.8 x 27.8 x 26.8 cm
Voltage	19 Volts
Included Components	User Manual, Remote Control, Power Adapter

Warranty and Support

The VEVSHAO V80 Smart DLP Projector comes with a standard manufacturer's warranty. Please refer to the warranty card included in your package for specific terms and conditions. For technical support, troubleshooting assistance, or warranty claims, please contact VEVSHAO customer service through their official website or the retailer where you purchased the product.
For more information, you may visit the VEVSHAO Store on Amazon.

Official Product Videos

No official product videos from the seller were found for this product in the provided data.

© 2024 VEVSHAO. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DDTG3PXR

More documents and user manuals: **https://manuals.plus/**