

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Neretva](#) /

› [Neretva Burr Coffee Grinder PE3766UWH Instruction Manual](#)

Neretva PE3766UWH

Neretva Burr Coffee Grinder PE3766UWH Instruction Manual

Model: PE3766UWH

INTRODUCTION

Welcome to the Neretva Burr Coffee Grinder instruction manual. This guide provides essential information for the safe and efficient operation of your new coffee grinder. Please read thoroughly before first use.

PRODUCT OVERVIEW AND COMPONENTS

The Neretva Burr Coffee Grinder is designed for precise coffee bean grinding with 30 adjustable settings and anti-static technology. It features durable stainless steel conical burrs and a 2-in-1 design for direct grinding into a portafilter or collection jar.

Components

- Burr Coffee Grinder (Main Unit)
- Ground Coffee Jar
- Cleaning Brush
- Silicone Air Blower
- User Manual

Compact size, Large Capacity

6.34oz bean hopper can make 15~20 cups of coffee at a time.



The Neretva Burr Coffee Grinder showing its main unit, bean hopper, control panel, and ground coffee container.

SETUP

Initial Setup

1. Unpack all components from the packaging.
2. Place the grinder on a stable, flat surface.
3. Ensure the bean hopper and ground coffee jar are clean and properly assembled.
4. Connect the power cord to a suitable electrical outlet.



A person unpacking the Neretva Burr Coffee Grinder from its protective foam packaging.

OPERATING INSTRUCTIONS

Grinding Coffee Beans

Adjusting Grind Settings

The grinder offers 30 precise grind settings. Rotate the bean hopper to select your desired fineness. Settings 1-10 are ideal for espresso, 10-20 for drip/pour over, and 20-30 for French press/cold brew. Turkish coffee is not recommended.

30 Adjustable Grind Setting



Close-up view of the Neretva Burr Coffee Grinder's adjustable grind setting dial, ranging from 0 to 30, with indicators for espresso, drip/pour over, and French press.

Filling the Bean Hopper

Remove the hopper lid and pour fresh coffee beans into the hopper. Replace the lid securely. The 6.34oz capacity can make 15-20 cups of coffee.



A hand pouring coffee beans into the transparent hopper of the Neretva Burr Coffee Grinder.

Grinding into a Portafilter

Place your 51-58mm portafilter into the adjustable cradle. Adjust the cradle height for a secure fit. Use the electronic timer to set the grinding duration (0.1s increments for 1-25s, 1s increments for 26-60s). Press the play button to start grinding directly into the portafilter.

Resistant Conical Burr

Ensures 100% uniform grinding.



The Neretva Burr Coffee Grinder dispensing ground coffee directly into a portafilter held by its adjustable cradle.

Grinding into the Collection Jar

Remove the portafilter cradle and place the provided ground coffee jar beneath the dispenser. Set the desired grinding time using the electronic timer and press play.



The Neretva Burr Coffee Grinder dispensing ground coffee into the included collection jar.

Using the Electronic Timer

The LED touch screen allows precise control over grinding time. Use the '+' and '-' buttons to adjust the duration. The manual pulse button (hand icon) can be used for small, incremental grinds.



Close-up of the grinder's LED touch screen displaying grinding time and control buttons for manual pulse, time adjustment, and start/pause.

Official Product Video: Neretva Burr Coffee Grinder in Action

An official product video demonstrating the Neretva Burr Coffee Grinder's features, including filling the hopper, adjusting grind settings, and grinding coffee into the portafilter and collection jar.

MAINTENANCE

Cleaning and Care

Regular cleaning ensures optimal performance and extends the life of your grinder.

1. Disconnect the power supply before cleaning.
2. Remove the bean hopper and grind disk for easy access.
3. Use the provided brush to clean residual coffee grounds from the burrs and dispenser.
4. The silicone air blower can be used to push out any remaining grounds from the grinding mechanism.
5. Wipe the exterior with a damp cloth. Do not immerse the unit in water.

De-static Technology, Keep Clean



A person demonstrating how to remove and clean the stainless steel conical burrs of the Neretva Burr Coffee Grinder using the provided brush.

TROUBLESHOOTING

Common Issues

- **Grinder not turning on:** Ensure the power cord is securely plugged in and the bean hopper is correctly seated. Check for any warning indicators on the LED screen.
- **Inconsistent grind:** Verify the grind setting is appropriate for your brewing method. Ensure the burrs are clean and free of obstructions.

- **Excessive static/clumping:** The grinder is equipped with a plasma generator to minimize static. If clumping occurs, ensure the unit is clean and try grinding in smaller batches.
- **Portafilter not fitting:** Adjust the height of the portafilter cradle using the side knobs to accommodate different portafilter sizes (51-58mm).

SPECIFICATIONS

- **Brand:** Neretva
- **Model:** PE3766UWH
- **Color:** White
- **Material:** Stainless Steel
- **Product Dimensions:** 4.92"L x 8.07"W x 13.03"H
- **Capacity:** 6.34 ounces (bean hopper)
- **Voltage:** 120 Volts
- **Grind Settings:** 30 precise levels
- **Special Features:** Anti-Static, 2-in-1 Portafilter/Jar Grinding, Electronic Timer

WARRANTY AND CUSTOMER SUPPORT

Neretva is committed to customer satisfaction. If you encounter any issues or require assistance, please contact our customer service. We offer 12-hour quick-response customer service.

For complete warranty details, please refer to the instruction booklet included in your product packaging.