

Ygpmoiki TCL 50 XL T702W

User Manual: TCL 50 XL T702W LCD Display Touch Screen Digitizer Replacement

Model: TCL 50 XL T702W | Brand: Ygpmoiki

1. INTRODUCTION

This manual provides comprehensive instructions for the installation, operation, maintenance, and troubleshooting of the Ygpmoiki Screen Replacement for TCL 50 XL T702W. This product is designed to restore full display and touch functionality to your device, addressing issues such as poor touch response or a damaged screen.

2. SAFETY INFORMATION

Please read and understand all safety precautions before attempting any repair. Improper handling can lead to personal injury or damage to your device.

- **Power Off Device:** Ensure your phone is completely powered off and disconnected from any power source before beginning the repair.
- **Static Electricity:** Discharge any static electricity from your body before touching internal components. Use an anti-static wrist strap if available.
- **Handle with Care:** Electronic components, especially flexible cables, are delicate. Avoid excessive force or bending.
- **Eye Protection:** Consider wearing eye protection to guard against small flying debris.
- **Ventilation:** If using adhesives or solvents, ensure adequate ventilation.
- **Battery Safety:** Exercise extreme caution when handling the battery. Do not puncture or bend it. If the battery is swollen, seek professional assistance.

3. SETUP AND INSTALLATION

This section outlines the steps for replacing the screen. Patience and careful attention to detail are crucial

for a successful repair. The process involves disassembling your phone, replacing the screen, and reassembling the device.

3.1. Tools Required

The screen replacement kit typically includes the necessary tools. Ensure you have:

- Small screwdrivers (usually three different sizes are provided)
- Plastic prying tools (spudgers)
- Suction cup
- Tweezers (optional, but helpful)
- Heat source (hair dryer or heat gun)
- Rubbing alcohol (isopropyl alcohol)
- Small magnet for screws (highly recommended)
- Adhesive for screen reattachment (usually provided)



Image 1: The replacement screen and the set of tools typically included in the kit, such as screwdrivers, prying tools, and a suction cup.

3.2. Disassembly Steps

1. **Power Off:** Completely power off your TCL 50 XL T702W phone.

2. **Heat the Back Cover:** Apply gentle heat to the edges of the phone's back cover using a hair dryer or heat gun. This softens the adhesive.
3. **Remove Back Cover:** Carefully use a thin prying tool or a razor blade to create a gap between the back cover and the phone frame. Slowly work your way around the edges, applying more heat and a small amount of rubbing alcohol if needed, to loosen the adhesive.
4. **Disconnect Battery:** Once the back cover is removed, locate the battery. It is often held in place with adhesive tape. Carefully cut the tape with a razor blade and gently pry the battery out. Disconnect the battery connector from the motherboard.
5. **Remove Internal Screws:** There are typically upper and lower black covers on the back of the phone that secure internal components. Remove all screws holding these covers in place. Use a small magnet to keep track of the screws.
6. **Disconnect Side Button Flex Cable:** Be aware of the flex cable connected to the side buttons (power/volume). This can be delicate and requires careful disconnection.
7. **Remove Old Screen:** Apply heat to the edges of the front screen. Use a suction cup to lift the screen slightly, then insert a prying tool or razor blade into the gap. Work slowly around the perimeter, applying heat and rubbing alcohol to soften the adhesive, until the old screen can be removed.

3.3. Assembly Steps

1. **Test New Screen: Before applying any adhesive,** connect the flexible cables of the new screen to the corresponding connectors on the phone's motherboard. There are usually two plug-ins, one lower and one upper. Ensure they are firmly seated. Power on the phone to test the display and touch functionality. If the lower connector is difficult to seat, you may need to carefully trim any rubber surrounding the slot.
2. **Apply Adhesive:** If the screen functions correctly, power off the phone and disconnect the new screen. Apply the provided adhesive evenly around the frame where the screen will sit.
3. **Install New Screen:** Carefully align the new screen and press it firmly into place.
4. **Reconnect Components:** Reconnect the battery and its connector. Reinstall the upper and lower black covers, securing them with all the screws.
5. **Reattach Back Cover:** Apply adhesive to the edges of the back cover if necessary, and carefully reattach it to the phone.
6. **Final Test:** Power on your phone and perform a thorough test of all screen functions, including touch, display clarity, and brightness.



Image 2: A detailed view of the flexible cable and its connection point, highlighting the delicate nature of this component.




Image 3: An alternative close-up showing the flexible cable and the integrated circuits, emphasizing the importance of careful handling.

Your browser does not support the video tag.

Video 1: An official product video demonstrating the features and possibly the installation process of the TCL 50 XL T702W LCD Screen Display Touch Digitizer.

4. OPERATING THE REPLACED SCREEN

Once successfully installed, the Ygpmoiki screen replacement will function identically to the original display of your TCL 50 XL T702W. All touch gestures, display clarity, and color reproduction should be restored to optimal performance.

- **Touch Sensitivity:** The new screen provides responsive touch input.
- **Display Quality:** Expect clear visuals and accurate colors.
- **Brightness Adjustment:** Use your phone's standard settings to adjust screen brightness.

5. MAINTENANCE

To ensure the longevity and optimal performance of your new screen, follow these maintenance guidelines:

- **Cleaning:** Use a soft, lint-free cloth (e.g., microfiber) to gently wipe the screen. For stubborn smudges, slightly dampen the cloth with water or a screen-specific cleaner. Avoid harsh chemicals or

abrasive materials.

- **Screen Protector:** It is highly recommended to install a high-quality screen protector immediately after installation to prevent scratches and minor impacts.
- **Protective Case:** Use a protective phone case to safeguard the entire device, including the screen, from accidental drops and impacts.
- **Avoid Pressure:** Do not apply excessive pressure to the screen, especially when carrying the phone in pockets or bags.

6. TROUBLESHOOTING

If you encounter issues after installing the new screen, consider the following troubleshooting steps:

Problem	Possible Cause	Solution
Screen not turning on / Black screen	Loose flex cable connection; Battery not connected; Damaged screen during installation.	1. Power off the phone, disconnect and reconnect all flex cables firmly. 2. Ensure battery is properly connected. 3. Re-test. If issue persists, the screen may be faulty or damaged.
Touch not responding or erratic	Loose touch flex cable; Software glitch; Screen defect.	1. Power off, disconnect and reconnect the touch flex cable. 2. Restart the phone. 3. If the problem continues, the screen's touch digitizer may be defective.
Display issues (lines, discoloration)	Loose display flex cable; Damaged display panel.	1. Power off, disconnect and reconnect the display flex cable. 2. If lines or discoloration persist, the display panel itself might be damaged.

If these steps do not resolve the issue, please contact customer support for further assistance.

7. SPECIFICATIONS

Feature	Detail
Compatible Model	TCL 50 XL T702W, T702
Screen Size	6.78 inches
Type	LCD Display Touch Screen Digitizer Assembly
Color	Black
Product Dimensions	6 x 3 x 0.39 inches
Item Weight	4.2 ounces

Feature	Detail
Manufacturer	Ygpmoiki

8. WARRANTY AND SUPPORT

For any questions, concerns, or issues regarding your Ygpmoiki screen replacement, please contact the seller directly through the platform where you made your purchase. Ensure you provide your order details for prompt assistance.

The product is tested well before dispatch to ensure quality. However, if you encounter any manufacturing defects or issues not covered by the troubleshooting guide, the seller "Pretty YiKi" is available to assist.