

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Solareye](#) /

› [Solareye B6-US Smart Bird Feeder with 2K HD Camera User Manual](#)

Solareye B6-US

Solareye B6-US Smart Bird Feeder with 2K HD Camera User Manual

Model: B6-US

INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your Solareye B6-US Smart Bird Feeder with 2K HD Camera. This device is designed to enhance your birdwatching experience with advanced features such as AI bird identification, high-definition video recording, and solar-powered operation.

WHAT'S INCLUDED

Upon unboxing your Solareye B6-US Smart Bird Feeder, verify that all components are present:

- Bird Feeder Unit with integrated 2K HD Camera
- Solar Panel with connecting cable
- Mounting Bracket (for various surfaces)
- Mounting Strap (for tree/pole attachment)
- Antenna
- USB Charging Cable
- Bird Perch
- Fruit Holder
- Jelly Feeder Cups
- Mounting Screws and Wall Anchors
- User Manual

Watch Birds in 2K HD Clarity



Image: All components included with the Solareye B6-US Smart Bird Feeder, including the main unit, solar panel, various mounting hardware, and feeding accessories.

SETUP INSTRUCTIONS

1. Initial Charging & Power On

- Before first use, fully charge the camera battery using the provided USB cable. The camera is located inside the feeder unit.
- Long press the power button on the camera until a tip sound is heard to turn it on.

2. App Installation & Connection

- Download and install the VicoHome app (or Ubox app, depending on manual instructions) from your device's app store (App Store for iOS, Google Play for Android).
- Register or log in to your account.
- Follow the in-app instructions to add a new device. Scan the QR code provided in the user manual or on the camera unit.
- Connect the bird feeder camera to your 2.4GHz Wi-Fi network. 5GHz Wi-Fi is not supported.

3. Physical Assembly & Mounting

The Solareye B6-US offers flexible mounting options:

- **Tree/Pole Mount:** Use the provided strap to secure the mounting bracket to a tree or pole.
- **Wall/Fence Mount:** Use the included screws and wall anchors to attach the mounting bracket to a flat surface.
- Once the bracket is secure, attach the bird feeder unit to the bracket using the thumb screw at the bottom.
- Connect the solar panel to the bird feeder unit. Position the solar panel to receive maximum direct sunlight for continuous charging.
- Screw the antenna onto the designated port on the back of the feeder unit.

Ideal Gift For Nature Lovers



Image: Illustration of the Solareye B6-US Smart Bird Feeder mounted in various outdoor locations, including a fence, tree, wall, and pole, demonstrating its versatile installation options.

4. Filling the Feeder

- Open the top lid of the bird feeder.
- Fill the spacious 1.8L seed bin with your preferred bird seed.
- Close the lid securely to protect the seed from weather.
- Attach the bird perch, fruit holder, or jelly feeder cups as desired to attract various bird species.

DIY Different Add-ons



Recyclable
Plastic Housing



Image: The Solareye B6-US Smart Bird Feeder with its top lid open, illustrating the ease of refilling the seed compartment.

OPERATING INSTRUCTIONS

1. Live View & Recording

- Access the live 2K HD video feed through the VicoHome app on your smartphone.
- The camera features color night vision, allowing for clear viewing day and night.
- The camera automatically captures and records events triggered by motion.

AI Bird Identification

with 10,000+ Species




Image: A vibrant cardinal enjoying the Solareye B6-US Smart Bird Feeder, with a smartphone showing the clear 2K HD live feed from the integrated camera.

2. AI Bird Identification

- The advanced AI system can identify over 10,000 bird species.
- Receive instant alerts on your phone when birds are detected, often with species identification. Note that some advanced AI features may require a subscription.

Keep Squirrels Away Anywhere, Anytime




Image: A Northern Cardinal at the Solareye B6-US Smart Bird Feeder, demonstrating the AI bird identification feature with a notification on a smartphone.

3. Motion Detection & Alerts

- The camera is equipped with motion detection to alert you to visitors at the feeder.
- Customize alert settings within the app.

4. Squirrel Deterrence

- Utilize the built-in siren and spotlight features via the app to deter unwanted visitors like squirrels.
- The two-way audio allows for real-time interaction, enabling you to speak through the camera to scare off pests.

One Charge Lasts 6 Months

Equipped with a solar panel for continuous power



Image: The Solareye B6-US Smart Bird Feeder illustrating its squirrel deterrence features, including a siren, spotlight, and two-way audio to keep pests away.

5. Sharing Moments

- Easily save recorded videos and images to your phone.
- Share your favorite birdwatching moments with friends and family directly through the app.

MAINTENANCE

1. Cleaning

- The feeder is designed with IP65 waterproofing, making it suitable for outdoor use in various weather conditions.
- Regularly clean the seed tray and camera lens to ensure optimal performance and hygiene for visiting birds.
- The easy-refill top simplifies access for cleaning the interior.

2. Battery & Solar Charging

- The integrated solar panel provides continuous power, extending battery life up to six months on a single charge under optimal sunlight conditions.
- Ensure the solar panel is positioned to receive maximum direct sunlight throughout the day.
- Monitor battery status via the VicoHome app.

Durable Outdoor Feeder



Image: The Solareye B6-US Smart Bird Feeder highlighting its long-lasting battery and solar charging capability, indicating up to 6 months of use on one charge.

TROUBLESHOOTING

- **No Wi-Fi Connection:** Ensure your Wi-Fi network is 2.4GHz. 5GHz networks are not supported. Check router proximity and signal strength.
- **Seed Not Dispensing:** Verify that the seed bin is not overfilled or clogged. Gently shake the feeder to dislodge any blockages.
- **Poor Image Quality:** Clean the camera lens with a soft, dry cloth. Ensure adequate lighting, especially for night vision.
- **Battery Draining Quickly:** Confirm the solar panel is receiving sufficient direct sunlight. Reduce motion detection sensitivity or frequency of live view access if necessary.

SPECIFICATIONS

Brand	Solareye
Model Number	B6-US

Product Dimensions	11" L x 9.4" W x 7.4" H
Item Weight	3.96 pounds
Material	Plastics
Power Source	Solar Powered
Battery	2 Lithium Ion batteries (included)
Special Features	360 Degree Perch, AI Bird Identification, Built-In Camera, Easy-Refill Top, Squirrel Proof
Mounting Type	Fence mount, Tree mount, Wall mount, Pole mount

OFFICIAL PRODUCT VIDEOS

Intro about Solareye Bird Feeder

Your browser does not support the video tag.

Video: An introductory overview of the Solareye Smart Bird Feeder, showcasing its design and primary features.

WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the contact details provided in the packaging or visit the official Solareye website. Each item includes a unique code for verification before shipping.

© 2026 Solareye. All rights reserved.