

Boytone BT-63K

Boytone BT-63K Bluetooth Party Speaker Karaoke Machine User Manual

Model: BT-63K | Brand: Boytone

INTRODUCTION

Thank you for purchasing the Boytone BT-63K Bluetooth Party Speaker Karaoke Machine. This all-in-one portable speaker is designed to deliver powerful audio and an immersive entertainment experience with its high-fidelity sound, vibrant LED lights, and versatile connectivity options. This manual provides essential information for setting up, operating, and maintaining your device to ensure optimal performance and longevity.



Image: The Boytone BT-63K speaker, a wired microphone, and a remote control. The speaker features a black casing with a large front grille and multi-colored LED lights around the speaker cone.

Safety Information

- Read all instructions carefully before using the product.
- Do not expose the device to water, moisture, or extreme temperatures.
- Keep the device away from direct sunlight and heat sources.
- Do not attempt to disassemble or repair the unit yourself. Refer all servicing to qualified personnel.
- Use only the specified charging adapter to avoid damage.
- Ensure proper ventilation around the speaker during operation.
- Dispose of batteries responsibly according to local regulations.

PACKAGE CONTENTS

Verify that all items are present in the package:

- Boytone BT-63K Party Speaker
- Wired Microphone
- Remote Control
- Charging Cable (AC/DC adapter not explicitly listed but implied for charging)
- User Manual (this document)

PRODUCT OVERVIEW

Front and Back Panels



Powerful Party Speaker

Back



Front



Image: The front of the speaker displays the LED-lit grille. The back panel shows various input ports and controls, including MIC IN, AUX IN, TF Card slot, USB port, DC 5V charging port, and a Power ON/OFF switch.

Top Panel Controls

TWS SYSTEM

You can pair two of our Bluetooth speakers together

Top



Image: The top panel of the speaker features volume controls (- and +), mode selection, track navigation (previous/next), play/pause, LED light control, and a record button.

- **MODE/TWS:** Press to switch between Bluetooth, FM, AUX, USB, TF Card modes. Long press for TWS pairing.
- **PREV/VOL-:** Press for previous track. Long press to decrease volume.
- **PLAY/PAUSE:** Press to play or pause audio.
- **NEXT/VOL+:** Press for next track. Long press to increase volume.
- **MENU/M.PRI:** Menu button, possibly for EQ or other settings.
- **LED:** Press to cycle through LED light modes or turn off.
- **REC:** Press to start/stop recording.

SETUP

Charging the Speaker

Before first use, fully charge the speaker. Connect the charging cable to the DC 5V port on the back of the speaker and plug the other end into a suitable power source. The charging indicator will illuminate. Once fully charged, the

indicator may change color or turn off.

The built-in 3600mAh battery provides approximately 6-10 hours of playback depending on volume level and usage.

Microphone Connection

Insert the wired microphone's plug into the "MIC IN" port on the back panel of the speaker.

OPERATING INSTRUCTIONS

Power On/Off

Locate the Power ON/OFF switch on the back panel of the speaker. Slide the switch to "ON" to power on the device. Slide it to "OFF" to power off.

Bluetooth Pairing

1. Power on the speaker. It will automatically enter Bluetooth pairing mode, indicated by a voice prompt or flashing LED.
2. Enable Bluetooth on your mobile device (smartphone, tablet, etc.).
3. Search for "BT-63K" in the list of available Bluetooth devices.
4. Select "BT-63K" to connect. Once paired, you will hear a confirmation sound.

Bluetooth Connection



Image: A visual representation of a smartphone wirelessly connecting to the Boytone BT-63K speaker via Bluetooth, indicated by signal waves.

The Bluetooth working distance is up to 100 feet (30 meters) in an open area.

TWS (True Wireless Stereo) Function

The TWS function allows you to pair two BT-63K speakers together for a true stereo sound experience.

1. Ensure both BT-63K speakers are powered on and not connected to any Bluetooth device.
2. On one of the speakers (this will be the primary speaker), long press the "MODE/TWS" button. You will hear a prompt indicating TWS pairing mode.
3. The two speakers will automatically connect to each other. Once connected, you will hear a confirmation sound.
4. Now, connect your mobile device to the primary speaker via Bluetooth as described in the "Bluetooth Pairing" section. Both speakers will play audio in stereo.

TWS SYSTEM

You can pair two of our Bluetooth speakers together

Top



Image: Two Boytone BT-63K speakers are shown, one from the front and one from the top, demonstrating their ability to pair together for a TWS system.

FM Radio

1. Press the "MODE" button repeatedly until you enter FM Radio mode.
2. Press the "PLAY/PAUSE" button to automatically scan and save available FM stations.
3. Use the "PREV" and "NEXT" buttons to navigate between saved stations.

USB/TF Card Playback

Insert a USB flash drive or a TF (microSD) card into the respective port on the back panel. The speaker will automatically detect the storage device and begin playing compatible audio files (e.g., MP3).

- Use "PREV" and "NEXT" buttons to skip tracks.
- Use "PLAY/PAUSE" to pause or resume playback.

AUX Input

Connect an external audio device (e.g., smartphone, MP3 player) to the "AUX IN" port on the back panel using a 3.5mm audio cable. The speaker will automatically switch to AUX mode or you may need to press the "MODE" button to select AUX.

Recording Function

To record audio (e.g., your voice through the microphone):

1. Ensure a USB flash drive or TF card is inserted into the speaker.
2. Connect the microphone.
3. Press the "REC" button on the top panel to start recording.
4. Press "REC" again to stop recording. The recorded file will be saved to the USB drive or TF card.

EQ Adjustment

The speaker features EQ adjustments. Press the "MENU/M.PRI" button to access EQ settings and use the volume buttons to adjust. Refer to the on-screen display for specific options.

LED Lights

The speaker features dynamic, multi-colored LED lights. Press the "LED" button on the top panel to cycle through different light modes or to turn the lights off.



Image: A detailed view of the speaker's internal components, highlighting the subwoofer and the vibrant, multi-colored LED lighting effect around the speaker cone.

MAINTENANCE

Cleaning

Wipe the speaker's exterior with a soft, dry cloth. Do not use abrasive cleaners, waxes, or solvents. Ensure no liquids enter the speaker's openings.

Storage

When not in use for extended periods, store the speaker in a cool, dry place away from direct sunlight and extreme temperatures. It is recommended to charge the battery periodically (e.g., every 3 months) to maintain its lifespan.

TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Battery is depleted; Power switch is off.	Charge the speaker; Ensure power switch is in "ON" position.
No sound	Volume is too low; Incorrect mode selected; Device not connected.	Increase volume; Press MODE button to select correct input; Re-pair Bluetooth device or check AUX/USB connection.
Bluetooth connection fails	Speaker is too far from device; Speaker is connected to another device; Bluetooth not enabled on device.	Move device closer to speaker; Disconnect from other devices; Enable Bluetooth on your device and re-pair.
Microphone not working	Microphone not properly plugged in; Microphone volume too low.	Ensure microphone is fully inserted into "MIC IN" port; Check microphone volume settings on the speaker.
TWS pairing fails	Speakers are too far apart; One speaker is already connected to a Bluetooth device.	Ensure speakers are within close proximity; Disconnect any Bluetooth devices from both speakers before attempting TWS pairing.

SPECIFICATIONS

Product Type: Bluetooth Portable Speaker

Model Number: BT-63K

Bluetooth Version: 5.0

Bluetooth Working Distance: Up to 100ft (30m)

Speaker Output Power: 30W

Speaker Unit: 2 x 6" woofer

Frequency Response: 80Hz-20KHz

Playing Time: Approximately 6-10 hours (depends on playing volume)

Battery Capacity: 3.5V 3600mAh (Lithium Ion)

Connectivity: Bluetooth, USB MP3 music player, TF Card, AUX, USB Port

Features: Microphones (Wired & Wireless), Remote Control, FM Radio, TWS Function, Recorder Function, EQ Adjustment, LED Lights

Audio Input: AUX, Microphone (Wired & Wireless)

Product Dimensions (L x W x H): 8.1 x 7.1 x 17.1 inches

Item Weight: 8.2 pounds

Material: Metal, Plastic
Power Source: AC/DC

WARRANTY AND SUPPORT

Boytone products are designed for reliability and performance. For any questions, technical support, or warranty inquiries, please contact Boytone customer service. As a U.S.-based company, Boytone is available to assist you. While specific warranty terms are not detailed here, please retain your proof of purchase for any warranty claims. Protection plans may be available for extended coverage.

Note: For the most current support information, please refer to the official Boytone website or contact details provided with your product packaging.







We're a U.S.-based company

You're just a phone call away from reaching us.

Image: An American flag graphic with text emphasizing the company's U.S. base and accessibility for customer support.

Related Documents

<div><div>USER'S MANUAL MODEL: T16</div><div></div></div>	<p>Boytone T16 Portable Bluetooth Speaker User Manual</p> <p>User manual for the Boytone T16 portable Bluetooth speaker, covering product features, technical specifications, connectivity, unit operation, and remote control instructions.</p>
<div><div><div>Boytone BT-324F 2.1CH Multimedia Speaker System User Manual</div></div></div>	<p>Boytone BT-324F 2.1CH Multimedia Speaker System User Manual</p> <p>User manual for the Boytone BT-324F 2.1CH Multimedia Speaker System, detailing specifications, features, front panel and remote control operations, Bluetooth connectivity, rear panel connections, and important usage notes.</p>
<div><div><div>Boytone C2901 2.1CH Multimedia Speaker System User Manual</div></div></div>	<p>Boytone 2.1CH Multimedia Speaker System C2901 User Manual</p> <p>User manual for the Boytone 2.1CH Multimedia Speaker System, Model C2901. Provides details on specifications, features, operation, remote control functions, system connections, and FCC compliance.</p>
<div><div>BOYTONE® Turntable with CD Player, AM/FM Radio, Cassette Player & MP3 Decoding</div><div></div><div>MODEL(S): BT28SPB / BT28SPS Operating Instructions Manual</div></div>	<p>Boytone BT28SPB/BT28SPS Turntable Operating Instructions</p> <p>Comprehensive operating instructions for the Boytone BT28SPB and BT28SPS turntable, featuring CD player, AM/FM radio, cassette player, and MP3 encoding capabilities. Learn how to set up, operate, and maintain your Boytone audio system.</p>



[\[pdf\]](#) Test Report

Measurement Report Kent Test report Jadmam Corp BR37K PORTABLE SPEAKER 2BGOZ

2BGOZBR37K br37k

Shenzhen DL Testing Technology Co., Ltd. Report No.: DL-240506028E FCC Part

15C Test Report FCC ID ... strict, Shenzhen, China PORTABLE SPEAKER

Boytone/Berlington BR-37K BR-35K, BT-33K, BT-61K, BR-62K, **BT-63K**, BR-64K, BT-65K, BR-66K, BT-67K, BR-68K, BT-69K, BR-70K, BT-71K, BR-72K, BT-73K, BR-74K, BT-7...

lang:en **score:12** filesize: 1.88 M page_count: 31 document date: 2024-05-29