

## TONOR TGP1

# TONOR Modmic TGP1 Wireless Attachable Gaming Microphone User Manual

Model: TGP1

## 1. PRODUCT OVERVIEW

The TONOR Modmic TGP1 is a wireless attachable gaming microphone designed to enhance your audio experience across multiple platforms. It features a magnetic attachment for secure placement on any gaming headset, ensuring stable connectivity and clear communication.

Key features include:

- **Headset Voice Innovation:** Compatible with PC, laptop, PS4, and PS5, offering multi-platform versatility.
- **Crisp Audio Quality:** Delivers exceptional audio with a 16-bit, 48 kHz sampling rate, clear sound, and rich tones.
- **Noise Reduction:** One-touch activation to minimize background noise for uninterrupted audio clarity.
- **Long-Lasting Battery:** Provides up to 17 hours of continuous use, with a quick 10-minute charge adding an extra hour.
- **Versatile Control:** Easy mute function and microphone volume adjustment directly on the transmitter.



Image: The TONOR Modmic TGP1 in use with a gaming headset, connected wirelessly to a laptop during a gaming session.

## 2. PACKAGE CONTENTS

Please check the box for the following items:

- 1 x Transmitter (TX)
- 1 x Receiver (RX)
- 1 x USB Charging Cable (USB-A to Type-C)
- 1 x Storage Bag
- 3 x Foam Covers (for pop noise protection)
- 3 x Double-sided Adhesive Pads (for securing the transmitter)
- 1 x User Manual



Image: Contents of the TONOR Modmic TGP1 package, including the microphone transmitter, USB receiver, charging cable, storage bag, foam covers, and adhesive pads.

## 3. SETUP INSTRUCTIONS

### 3.1 Attaching the Microphone

1. **Clean the Headset Surface:** Before installation, ensure the surface of your headset where the microphone will attach is clean and dry.
2. **Apply Adhesive Pad:** Peel off the protective film from one of the double-sided adhesive pads. Carefully stick the pad onto a flat area of your headset. Press firmly for a few seconds.
3. **Wait for Adhesion:** Allow at least five minutes for the adhesive to set properly before attaching the microphone. This ensures a strong and stable connection.
4. **Attach Microphone:** The TGP1 transmitter features a powerful magnetic patch. Align the transmitter with the adhesive pad on your headset; it will securely snap into place.

# Diseño magnético

Conexión estable, ajuste suave

**Nota: Por favor, limpia los auriculares antes de la instalación.**



Pega el adhesivo 3M en un área plana de los auriculares y espera cinco minutos antes de usar.

Image: The magnetic design of the TGP1 allows for stable and smooth attachment to your headset. Remember to clean the headset surface and allow the adhesive to set for optimal performance.

## 3.2 Connecting the Receiver & Pairing

1. **Connect Receiver:** Plug the USB receiver into an available USB port on your PC, laptop, PS4, or PS5.
2. **Power On Microphone:** Press and hold the power button on the TGP1 transmitter to turn it on.
3. **Automatic Pairing:** The transmitter and receiver will automatically pair. The indicator lights on both devices will show a stable connection (e.g., solid blue or green light).
4. **System Settings:** On your device (PC/Mac/PS4/PS5), navigate to your audio settings and select "TONOR TGP1" as the input device.



Image: Wireless connection diagram illustrating the pairing process between the TGP1 microphone transmitter and the USB receiver.

### 3.3 Compatibility

The TONOR Modmic TGP1 is compatible with:

- Desktop PCs
- Laptops
- PlayStation 4 (PS4)
- PlayStation 5 (PS5)
- Mac
- Android devices (via USB-C adapter, not included)
- iOS devices (via Lightning adapter, not included)

**Note:** This microphone is **not compatible** with Xbox consoles or directly with mobile phones without appropriate adapters.



Image: Multiplatform compatibility overview for the TGP1, indicating support for PC, laptop, PS4/5, and incompatibility with Xbox and phones.

## 4. OPERATING INSTRUCTIONS

### 4.1 Controls Overview

The TGP1 transmitter features intuitive controls for easy management of your audio:

- **Power Button:** Press and hold to power the microphone on or off.
- **Mute Button:** A single tap on the mute button will mute/unmute the microphone. A red indicator light signifies that the microphone is muted.
- **Noise Reduction:** Press and hold the mute button for 2 seconds to activate or deactivate the noise reduction feature. A green light indicates noise reduction is active.
- **Volume Adjustment:** Use the '+' and '-' buttons to adjust the microphone's input volume (gain level).



Image: Detailed description of the TGP1 transmitter buttons, showing power, volume controls, one-touch mute, and long-press for noise reduction.

## 4.2 Battery and Charging

The TGP1 is equipped with an efficient lithium battery:

- **Battery Life:** Enjoy up to 17 hours of continuous use on a full charge.
- **Quick Charge:** A 10-minute charge provides approximately 1 hour of additional use.
- **Charging:** Connect the included USB-A to Type-C charging cable to the transmitter and a power source (e.g., computer USB port, USB wall adapter). The charging indicator light will show the charging status.



Image: Battery life and quick charge feature of the TGP1, highlighting 17 hours of battery duration and rapid charging capabilities.



Image: Close-up view of the TGP1's charging pins and an active blue indicator light, signifying charging or connection status.

---

## 5. MAINTENANCE

To ensure the longevity and optimal performance of your TONOR Modmic TGP1, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to wipe the microphone and receiver. Avoid using harsh chemicals or abrasive materials. Ensure the headset surface is clean before reapplying adhesive pads.
- **Storage:** When not in use, store the microphone and its accessories in the provided storage bag to protect them from dust and physical damage.
- **Battery Care:** To preserve battery health, avoid fully discharging the microphone frequently. Charge it regularly, even if not in constant use. Store in a cool, dry place.
- **Foam Covers:** Replace the foam covers periodically, especially if they become worn or dirty, to maintain optimal pop noise protection.

---

## 6. TROUBLESHOOTING

If you encounter issues with your TONOR Modmic TGP1, please refer to the following common solutions:

- **No Sound/Poor Sound Quality:**
  - Ensure the microphone is powered on and properly paired with the receiver (check indicator lights).
  - Verify that "TONOR TGP1" is selected as the input device in your device's audio settings.
  - Adjust the microphone volume using the '+' and '-' buttons on the transmitter.
  - Check for obstructions between the microphone and receiver that might interfere with the wireless signal.
  - If sound is distorted or unclear, try activating/deactivating the noise reduction feature.
- **Connectivity Issues:**
  - Ensure the USB receiver is securely plugged into your device.
  - Try plugging the receiver into a different USB port.
  - Restart both the microphone transmitter and your connected device.
  - Ensure the microphone is within the 10-meter operating range of the receiver.
- **Microphone Not Attaching Securely:**

- Ensure the headset surface was thoroughly cleaned before applying the adhesive pad.
- Allow sufficient time (at least 5 minutes) for the adhesive pad to cure after application before attaching the microphone.
- If the adhesive pad is worn, replace it with a new one from the included accessories.

- **Battery Not Charging/Holding Charge:**

- Verify that the charging cable is correctly connected to both the microphone and the power source.
- Try using a different USB port or power adapter.
- If the battery life has significantly decreased over time, it may be reaching the end of its lifespan.

## 7. SPECIFICATIONS

Feature	Detail
Model Name	TGP1
Connectivity Technology	Wireless
Connector Type	USB
Special Features	Mute, Gain Control, Noise Reduction
Compatible Devices	PS4, PS5, PC, Laptop
Color	Black
Polar Pattern	Cardioid
Microphone Form Factor	Headset (Attachable)
Power Source	Battery (1 Lithium-metal battery included)
Frequency Response	100 Hz (minimum listed)
Product Dimensions	11.99 x 10.01 x 5 cm; 150 g
Material	Acrylonitrile Butadiene Styrene (ABS)

## 8. WARRANTY AND SUPPORT

### 8.1 Warranty Information

TONOR products are manufactured to high-quality standards. For specific warranty details, including duration and coverage, please refer to the warranty card included in your product packaging or visit the official TONOR website. Keep your proof of purchase for warranty claims.

### 8.2 Customer Support

If you have any questions, require technical assistance, or need to report an issue with your TONOR Modmic TGP1, please contact TONOR customer support through their official website or the retailer where you purchased the product. Provide your

model number (TGP1) and a detailed description of the issue for faster service.

© 2026 TONOR. All rights reserved.