

[Manuals.plus](#) /

› [pTron](#) /

› pTron Fusion Mount V2 Mini Bluetooth Speaker User Manual

pTron Fusion

User Manual

PTRON FUSION MOUNT V2 MINI BLUETOOTH SPEAKER

Model: Fusion | Brand: pTron

Introduction

The pTron Fusion Mount V2 is a compact and portable Bluetooth speaker designed to deliver high-quality audio with enhanced features. It offers 12W euphonic sound, long playtime, vibrant RGB lights, and multiple playback options, making it suitable for various indoor and outdoor activities.

This manual provides essential information on how to set up, operate, maintain, and troubleshoot your pTron Fusion Mount V2 speaker to ensure optimal performance and longevity.

Package Contents

Please check the box for the following items:

- pTron Fusion Mount V2 Mini Bluetooth Speaker
- Power Cable (Type-C)
- Quick Start Guide

Product Overview

Familiarize yourself with the speaker's components and controls.



Image: Front view of the pTron Fusion Mount V2 Mini Bluetooth Speaker in Silk Blue, showcasing its cylindrical design, mesh grille, and top-mounted RGB light ring. A lanyard is attached for portability.



Image: Infographic highlighting key features of the pTron Fusion Mount V2 speaker, including its cylindrical shape, portability, 12W immersive sound, 10 hours playback, RGB lights, Bluetooth V5.1, TWS pairing, built-in controls, and Type-C fast charging.

Controls and Ports:

- **Power Button:** Press and hold to turn on/off.
- **Volume Up (+):** Short press to increase volume. Long press for next track.
- **Volume Down (-):** Short press to decrease volume. Long press for previous track.
- **Play/Pause Button:** Press to play or pause music. Press to answer/end calls.
- **Mode Button (M):** Press to switch between Bluetooth, TF Card, and Aux-in modes.
- **Type-C Charging Port:** For charging the speaker.
- **TF Card Slot:** For inserting a MicroSD/TF card.
- **Aux-in Port:** For wired audio connection.
- **RGB Light Ring:** Located on top, indicates status and provides ambient lighting.

Setup

1. Charging the Speaker:

1. Connect the provided Type-C charging cable to the speaker's charging port.
2. Connect the other end of the cable to a USB power adapter (DC5V-1A max.) or a computer's USB port.
3. The charging indicator light will illuminate. The speaker takes approximately 2 hours to fully charge.
4. Once fully charged, the indicator light will change or turn off.

2. Powering On/Off:

- To power on, press and hold the Power button until you hear an audible prompt and the RGB lights activate.
- To power off, press and hold the Power button again until you hear an audible prompt and the lights turn off.

3. Bluetooth Pairing:

1. Ensure the speaker is powered on and in Bluetooth mode (indicated by a flashing RGB light).
2. On your device (smartphone, tablet, laptop), enable Bluetooth and search for available devices.
3. Select "pTron Fusion Mount V2" from the list of devices.
4. Once paired, you will hear a confirmation sound, and the RGB light will become steady.

Bluetooth 5.1

Reliable **Connection**,
Superior Performance



Image: A couple relaxing on a beach with the pTron Fusion Mount V2 speaker, symbolizing its reliable Bluetooth 5.1 connection and superior performance for outdoor use.

4. TWS (True Wireless Stereo) Pairing:

To achieve a 360° stereo sound experience, you can pair two pTron Fusion Mount V2 speakers together.

1. Ensure both speakers are powered on and not connected to any Bluetooth device.
2. On one of the speakers (this will be the primary speaker), double-press the Play/Pause button. You will hear a prompt indicating TWS pairing mode.
3. The two speakers will automatically search for and connect to each other. Once connected, you will hear a confirmation sound.
4. Now, connect your device to the primary speaker via Bluetooth as described in step 3. Both speakers will play audio simultaneously.

Pair **Up** for Power

24W Output with **Dual TWS** Connectivity



Image: A group of people dancing outdoors with two pTron Fusion Mount V2 speakers, illustrating the enhanced audio experience provided by TWS (True Wireless Stereo) pairing for a 24W output.

Operating Instructions

1. Playback Modes:

- **Bluetooth Mode:** After successful pairing, audio from your connected device will play through the speaker.
- **TF Card Mode:** Insert a MicroSD/TF card with audio files into the TF card slot. The speaker will automatically switch to TF card mode and begin playback.
- **Aux-in Mode:** Connect an audio device using a 3.5mm Aux cable to the Aux-in port. The speaker will automatically switch to Aux-in mode.
- Press the **Mode (M)** button to cycle through available playback modes.

2. Music Control:

- **Play/Pause:** Short press the Play/Pause button.

- **Volume Up:** Short press the '+' button.
- **Volume Down:** Short press the '-' button.
- **Next Track:** Long press the '+' button.
- **Previous Track:** Long press the '-' button.

3. Hands-free Calling:

- **Answer Call:** Short press the Play/Pause button when an incoming call rings.
- **End Call:** Short press the Play/Pause button during a call.
- **Reject Call:** Long press the Play/Pause button when an incoming call rings.

4. RGB Lights:

The speaker features prismatic RGB lights that enhance the listening experience. The lights typically react to the music rhythm. There is no specific button to control the RGB light modes; they are integrated with the speaker's operation.



Image: A group of friends enjoying music and dancing on a beach, with the pTron Fusion Mount V2 speaker in the foreground, emphasizing its 10-hour playtime and vibrant RGB lights for a lively atmosphere.

Maintenance

Cleaning:

- Wipe the speaker with a soft, dry, lint-free cloth.
- Do not use abrasive cleaners, alcohol, benzene, or other chemical solvents, as these may damage the casing or finish.

Storage:

- Store the speaker in a cool, dry place away from direct sunlight and extreme temperatures.
- If storing for an extended period, charge the battery to approximately 50% every few months to preserve battery life.

Battery Care:

- Avoid fully discharging the battery frequently.
- Do not expose the battery to high temperatures or direct heat.
- Use only the provided charging cable or a certified Type-C cable.

Water Resistance (IPX4):

The pTron Fusion Mount V2 is IPX4 water resistant, meaning it is protected against splashing water from any direction. It is not designed to be submerged in water. Ensure the charging port and other openings are dry before charging.

IPX4 **Water** Resistant



Image: The pTron Fusion Mount V2 speaker with water splashing around it, visually representing its IPX4 water resistance rating, which protects it from splashes.

Troubleshooting

Problem	Possible Cause	Solution
Speaker does not turn on.	Low battery.	Charge the speaker fully.
Cannot pair via Bluetooth.	Speaker not in pairing mode; device Bluetooth off; too far from speaker.	Ensure speaker is in pairing mode (flashing RGB light). Turn on Bluetooth on your device. Move device closer to speaker (within 10 meters). Forget previous pairings on your device and try again.

Problem	Possible Cause	Solution
No sound.	Volume too low; incorrect mode; speaker not connected.	Increase speaker and device volume. Press Mode button to select correct input (Bluetooth, TF Card, Aux-in). Ensure speaker is successfully paired/connected.
TWS pairing fails.	Speakers already connected to another device; not in TWS pairing mode.	Ensure both speakers are disconnected from any Bluetooth device. Follow TWS pairing instructions carefully (double-press Play/Pause on one speaker).
Poor sound quality.	Low battery; interference; source audio quality.	Charge the speaker. Move speaker away from other electronic devices. Try a different audio source or file.

Specifications

Feature	Detail
Model Name	Fusion
Speaker Type	Portable Speaker
Output Power	12 Watts
Bluetooth Version	5.1
Wireless Range	10 meters
Playtime	Up to 10 hours (at 50% volume)
Charging Time	Approx. 2 hours
Charging Port	Type-C (DC5V-1A max.)
Battery Type	Lithium Ion
Water Resistance	IPX4
Dimensions (D x W x H)	7D x 7W x 11H Centimeters
Item Weight	296 Grams
Material	Acrylonitrile Butadiene Styrene (ABS)
Multi-Playback Modes	Bluetooth, TF Card, Aux-in
Special Features	Hi Res Audio, LED Light, Portable, Stereo Pairing (TWS), USB Port

12W **Portable** Powerhouse

2.5 inches Dynamic Speaker
packed with precision audio.



Image: An exploded diagram of the pTron Fusion Mount V2 speaker, illustrating its 2.5-inch dynamic speaker and internal components, highlighting its 12W portable powerhouse audio capability.



Compact Durable Outdoor Ready

Image: A person with a backpack and the pTron Fusion Mount V2 speaker attached, demonstrating its compact, durable, and outdoor-ready design, suitable for adventures.

Warranty and Support

The pTron Fusion Mount V2 comes with a **1-year manufacturer warranty** against manufacturing defects from the date of purchase.

For any assistance, support, or warranty claims, please contact pTron customer care:

- **Email:** support@ptron.in
- **Phone:** 040-67138888

Importer: PALRED ELECTRONICS PVT. LTD., SY.NO. 56, 1ST FLOOR, GUNDLAPOCHAMPALLY VILLAGE, TECH PARK MTP, TSIIIC-IALA NACHARAM, HYDERABAD - 500076, TELANGANA, INDIA

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question