PEJE ZW02

PEJE Smart Watch User Manual

Model: ZW02

Introduction

Thank you for choosing the PEJE Smart Watch. This manual provides comprehensive instructions on how to set up, operate, and maintain your new smartwatch. Please read this manual carefully before use to ensure optimal performance and longevity of your device.



Image: The PEJE Smart Watch, featuring a silver casing and a white silicone strap. The display shows various health metrics and time.

What's in the Box

Upon opening your PEJE Smart Watch package, you should find the following items:

- PEJE Smart Watch (Model ZW02)
- Spare Smartwatch Strap
- Magnetic USB Charging Cable
- User Manual (this document)



Image: An illustration showing the contents of the product box, including the smartwatch, an extra strap, the charging cable, and the user manual.

Setup

1. Charging the Smart Watch

Before first use, fully charge your PEJE Smart Watch. This typically takes 2.5 to 3 hours.

1. Connect the magnetic end of the USB charging cable to the charging points on the back of the watch. Ensure it snaps into place securely.
2. Plug the USB-A end of the cable into a standard USB power adapter (e.g., phone charger, computer USB port).
3. The watch display will indicate charging status.



Image: The smartwatch being charged via its magnetic USB cable, with the screen displaying a full battery icon and charging information.

2. Pairing with Your Smartphone

To unlock all features, pair your PEJE Smart Watch with your Android or iOS smartphone via Bluetooth 5.2.

1. Download the official PEJE Smart Watch application from your phone's app store (Google Play Store for Android, Apple App Store for iOS).
2. Ensure Bluetooth is enabled on your smartphone.
3. Open the PEJE Smart Watch application and follow the on-screen instructions to search for and connect to your watch.
4. Confirm the pairing request on both your phone and the watch.

Operating Instructions

Navigating the Touch Screen

The PEJE Smart Watch features a 1.28" HD TFT full touch screen for intuitive navigation.

- **Swipe Up/Down:** Scroll through menus and notifications.
- **Swipe Left/Right:** Access quick functions or different data screens.
- **Tap:** Select an item or confirm an action.
- **Press and Hold:** Customize watch faces or access specific settings.



Image: The smartwatch showcasing different watch face options, alongside a smartphone screen demonstrating how to select and apply new watch faces through the companion app.

Bluetooth Calling

With its built-in microphone and high-fidelity speaker, the PEJE Smart Watch allows you to make and receive calls directly from your wrist when connected to your smartphone.

- **Answering Calls:** When a call comes in, tap the green answer icon on the watch screen.
- **Rejecting Calls:** Tap the red reject icon to decline a call.

- **Making Calls:** Access your call lists or contacts directly from the watch interface to initiate a call.



Image: The smartwatch on a user's wrist, showing an active call screen. Icons for various communication applications are displayed around the watch, indicating its connectivity features.

Sports Modes and Activity Tracking

The watch supports over 123 sports modes and tracks your daily activities, including steps, calories, distance, and active minutes.

- Navigate to the "Sports" section on your watch.
- Select your desired activity (e.g., running, cycling, weightlifting).
- The watch will begin tracking relevant metrics for your chosen activity.
- Your activity data is synchronized with the PEJE app on your smartphone for detailed analysis.



Image: A user engaged in weightlifting, wearing the smartwatch. Below, smaller images depict various other sports and fitness activities that the watch can track.

Health Monitoring

Monitor your health metrics directly from your wrist:

- **Heart Rate:** Access the heart rate monitor to get real-time readings.
- **Sleep Tracking:** Wear the watch to bed to monitor your sleep patterns, including light sleep, deep sleep, and REM cycles.
- **Daily Activity:** View your daily calories burned, steps taken, and distance covered.



Image: The smartwatch on a user's wrist during a hike, with an overlay showing various health metrics such as calories, steps, distance, and heart rate.



Image: The smartwatch on a user's wrist during sleep, accompanied by a chart detailing different sleep stages and their durations.

Maintenance

Water Resistance (IP67)

The PEJE Smart Watch is IP67 waterproof, meaning it is protected against dust ingress and can withstand immersion in water up to 1 meter for up to 30 minutes. It is suitable for daily use, such as hand washing or light rain.

- Do not use the watch for swimming, diving, or showering with hot water.
- Avoid exposing the watch to high-pressure water or strong detergents.
- If the watch gets wet, wipe it dry with a soft cloth before charging or operating.

Cleaning

To keep your watch clean and in good condition:

- Wipe the screen and body with a soft, lint-free cloth.
- For stubborn dirt, slightly dampen the cloth with water. Do not use harsh chemicals or abrasive materials.
- Clean the charging contacts regularly to ensure proper charging.

Battery Care

- Avoid fully discharging the battery frequently.
- Store the watch in a cool, dry place if not used for extended periods.
- Use only the provided charging cable.

Troubleshooting

Problem	Possible Solution
Watch does not turn on	Ensure the watch is fully charged. Connect it to the charger for at least 30 minutes.
Cannot pair with smartphone	Ensure Bluetooth is enabled on your phone. Make sure the watch is within range of your phone. Restart both the watch and your phone. Clear Bluetooth cache on your phone (Android) or forget the device and re-pair (iOS/Android).
Inaccurate health data	Ensure the watch is worn snugly on your wrist, about one finger's width above the wrist bone. Clean the sensors on the back of the watch.
Short battery life	Reduce screen brightness. Disable unnecessary notifications. Limit continuous heart rate monitoring if not needed. Ensure the watch is fully charged each time.

Specifications

Feature	Detail
Model	ZW02
Display	1.28" HD TFT Touch Screen (240*240 resolution)
Waterproof Rating	IP67

Feature	Detail
Chipset	Jerry JL7012F6
Memory (ROM+RAM)	640KB + 64Mb External Memory
Bluetooth Version	5.2
Battery Type	Polymer Battery
Battery Capacity	230mAh
Charging Time	2.5 - 3 Hours
Theoretical Standby Time	10 - 15 Days
Normal Use Time	5 - 7 Days
Outlook & Material	PC plastic case + Anti-static silicone strap
Sports Modes	123+
Operating System	Android Wear 2.9 (Compatible with Android and iOS)
Special Features	Shockproof

Warranty and Support

For warranty information and customer support, please refer to the warranty card included in your product packaging or visit the official PEJE website. If you encounter any issues not covered in this manual, please contact our customer service team for assistance.
Please retain your proof of purchase for warranty claims.

© 2025 PEJE. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question