

1Mii E3Pro

1Mii Wireless Earbuds for TV Watching

MODEL: E3Pro - INSTRUCTION MANUAL

1. Introduction

The 1Mii E3Pro Wireless Earbuds with Transmitter Charging Base are designed to provide a private, high-quality audio experience for TV watching. Featuring ultra-low latency 2.4G wireless technology, these earbuds ensure perfectly synchronized sound, allowing you to enjoy your favorite shows and movies without disturbing others. The system is plug-and-play, offering easy setup and broad compatibility with various TV audio outputs.



Enjoy private viewing with the 1Mii E3Pro Wireless Earbuds, perfect for late-night sessions.



Experience smooth, lag-free sound for your TV shows and movies with low latency technology.

2. What's in the Box

Verify that all items are present in your package:

- TURE Wireless Earbuds
- Transmitter Charging Base
- USB-C Charging Cable
- Optical Audio Cable
- RCA to 3.5mm Audio Cable
- 3.5mm AUX Audio Cable
- User Manual
- Power Adapter
- S/M/L Ear Caps



All components included in the 1Mii E3Pro Wireless Earbuds package.

Official 1Mii E3Pro Unboxing Video, demonstrating the contents of the package.

3. Setup

Follow these steps to set up your 1Mii E3Pro Wireless Earbuds:

1. **Power Connection:** Connect the USB-C charging cable to the transmitter base and the power adapter. Plug the power adapter into a wall outlet. The base will power on automatically.



Connect the transmitter base to power.

2. **Connect to TV:** Choose the appropriate audio cable (Optical, AUX 3.5mm, or RCA to 3.5mm) based on your TV's available audio output ports. Connect one end of the cable to your TV's audio output and the other end to the corresponding input on the transmitter base.

Flexible Compatibility

Works with TVs and audio devices featuring optical, RCA, or 3.5mm outputs.



Flexible compatibility with Optical, RCA, or 3.5mm audio outputs.



Ensure your TV has compatible audio output ports.

Video demonstrating how to connect the 1Mii E3Pro to a TV using an RCA/3.5mm cable.

Video demonstrating how to connect the 1Mii E3Pro to a TV using an optical cable.

3. **TV Audio Settings:** Access your TV's audio settings menu. Change the audio output to the corresponding port you used (e.g., Optical Out, External Speakers). For optical connections, ensure the TV's digital audio output format is set to PCM.



Adjust your TV's audio output settings for proper sound transmission.

4. **Earbud Pairing:** The earbuds and transmitter are pre-paired from the factory. Simply take the earbuds out of the charging base, and they will automatically connect to the transmitter.

4. Operating Instructions

Wearing the Earbuds

Select the ear cap size (S, M, L) that provides the most comfortable and secure fit for extended use. Gently insert the earbuds into your ears.



Choose from three sizes of ear tips for a snug and comfortable fit.

Controls

The earbuds feature touch controls for easy operation:

- **Volume Up:** Click once on the Right (R) earbud.
- **Volume Down:** Click once on the Left (L) earbud.
- **Music/Gaming Mode:** Click twice on either the Left (L) or Right (R) earbud to switch between modes.



Earbud touch controls for volume and mode selection.

Bypass Function

The unique bypass function allows simultaneous audio output through both the earbuds and external wired speakers. This means you can listen privately while others in the room can hear the TV audio through connected speakers.

- Connect your wired speakers to the corresponding output ports (Optical Out or AUX Out) on the transmitter base.
- Ensure the input and output cable types match (e.g., Optical IN to Optical OUT, 3.5mm IN to 3.5mm OUT).

Share Sound with Bypass Function

Listen privately with wireless earbuds and share sound with family through wired speakers.



Share sound with others using the bypass function.

Video demonstrating how to use the bypass mode with an optical connection.

Video demonstrating how to use the bypass mode with an RCA/3.5mm connection.

Charging and Battery Life

The earbuds provide up to 5 hours of uninterrupted audio on a single charge. When not in use, simply place the earbuds back into the transmitter charging base to automatically recharge. A full charge takes approximately 2 hours.

Effortless Charging, Instant Listening

Charge for 2 hours, use for 5. Simply store in the base and enjoy wireless sound at your convenience.



2 Hrs Charging | 5 Hrs Playtime

Effortless charging by simply placing earbuds in the base.

5. Maintenance

To ensure the longevity and optimal performance of your 1Mii E3Pro Wireless Earbuds:

- Clean the earbuds and charging contacts regularly with a soft, dry cloth.
- Avoid exposing the device to extreme temperatures, humidity, or direct sunlight.
- Do not use abrasive cleaners or solvents.
- Store the earbuds in their charging base when not in use to keep them charged and protected.

6. Troubleshooting

If you encounter issues with your 1Mii E3Pro, refer to the following common problems and solutions:

- **No Sound or Abnormal Sound from One Earbud:**

Ensure both earbuds are properly seated in the charging base and fully charged. Check for any debris blocking the charging contacts or earbud nozzles. If the issue persists, try resetting the transmitter base by

pressing and holding the button for 10 seconds until the red light turns on, then release. Re-insert the earbuds to re-establish connection.

Video providing a solution for when one earbud has no sound or abnormal sound.

- **No Sound from TV:**
Verify that the audio cables are securely connected to both the TV and the transmitter base. Check your TV's audio output settings to ensure it's configured to output sound through the connected port (Optical, AUX, or RCA). For optical connections, confirm the TV's digital audio output format is set to PCM.
- **Earbuds Not Connecting:**
Ensure the transmitter base is powered on. Place the earbuds back into the charging base for a few seconds, then remove them to trigger automatic reconnection. Remember, these earbuds use 2.4G wireless technology and cannot connect to other Bluetooth devices.
- **Short Battery Life:**
Ensure the earbuds are fully charged before use. Battery life can vary based on volume levels and usage patterns. If battery life significantly degrades, contact customer support.

7. Specifications

Feature	Specification
Product Dimensions	4.33 x 2.36 x 2.09 inches
Item Weight	4.3 ounces
Item Model Number	E3Pro
Batteries	2 A batteries required. (included)
Connectivity Technology	RCA, Optical, AUX 3.5mm, 2.4G Wireless
Power Source	Corded Electric
Material	Acrylonitrile Butadiene Styrene (ABS)
Manufacturer	1Mii
Country of Origin	China







8. Safety Information

- Do not use or charge the device while sleeping.
- Keep the device away from heat and moisture.
- Dispose of used batteries according to local regulations.
- Do not expose the device to extreme temperatures.
- Avoid using the device near other wireless devices to prevent interference.

9. Warranty and Support

For warranty information or technical support, please refer to the official 1Mii website or contact their customer service directly. The user manual (PDF) is also available for download from the product's Amazon page.

Related Documents - E3Pro

	<p>1Mii E3Pro Wireless Earbuds Transmitter Set for TV User Manual</p> <p>User manual for the 1Mii E3Pro wireless earbuds and transmitter set, enabling low-latency audio transmission from your TV. Features plug-and-play setup for Optical, AUX, and RCA audio outputs, with detailed instructions for connection, operation, and troubleshooting.</p>
	<p>1Mii B03 Bluetooth 5.0 Transmitter Receiver User Guide</p> <p>Comprehensive user guide for the 1Mii B03 Long Range Bluetooth 5.0 Transmitter and Receiver. Learn how to connect your TV or home stereo for wireless audio with aptX Low Latency support.</p>
	<p>1Mii B03 Bluetooth 5.3 Transmitter Receiver User Manual</p> <p>User manual for the 1Mii B03 Bluetooth 5.3 Transmitter Receiver, detailing its features, operation, and troubleshooting for home stereo audio transmission with aptX Low Latency and HD support.</p>
	<p>1Mii B06TX Bluetooth Transmitter Setup Guide</p> <p>A concise guide to setting up and pairing the 1Mii B06TX Bluetooth 5.0 transmitter for wireless audio connections to TVs, headphones, and speakers.</p>
	<p>1Mii B06TX Bluetooth 5.2 Transmitter User Manual</p> <p>User manual for the 1Mii B06TX Bluetooth 5.2 Transmitter, detailing its features, setup, and operation for connecting TVs to wireless headphones or speakers.</p>
	<p>1Mii B03Pro Bluetooth 5.0 Transmitter and Receiver User Manual</p> <p>User manual for the 1Mii B03Pro Bluetooth 5.0 audio transmitter and receiver. Features include aptX HD, Low Latency, ESS DAC, Optical/RCA/AUX connectivity, and dual-link for high-fidelity wireless audio streaming.</p>