Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

PEJE ZW13

PEJE ZW13 Smartwatch User Manual

Model: ZW13

Introduction

This manual provides essential instructions for setting up, operating, maintaining, and troubleshooting your PEJE ZW13 Smartwatch. Please read this guide thoroughly to ensure proper use and to maximize the device's features. Keep this manual for future reference.

Package Contents

Verify that all items listed below are included in your package:

- PEJE ZW13 Smartwatch
- Extra Watch Strap
- Magnetic USB Charging Cable
- User Manual (this document)



Figure 1: Package Contents. This image displays the PEJE ZW13 Smartwatch, an additional watch strap, and the magnetic USB charging cable included in the box.

Setup

1. Charging the Smartwatch

Before first use, fully charge your smartwatch. Connect the magnetic charging cable to the charging points on the back of the watch and plug the USB end into a power adapter (not included) or a computer's USB port.

- Charging Time: Approximately 2 hours for a full charge.
- Battery Life: Up to 5-7 days of typical use, up to 30 days in standby mode.

2. Downloading and Installing the "Da Fit" App

The PEJE ZW13 Smartwatch requires the "Da Fit" application for full functionality and synchronization with your smartphone.

1. Open the Google Play Store (for Android) or Apple App Store (for iOS) on your smartphone.
2. Search for "Da Fit".
3. Download and install the application.



Figure 2: Da Fit App Download. This image shows the smartwatch display, illustrating the context for downloading and installing the "Da Fit" application.

3. Pairing the Smartwatch via Bluetooth

Ensure Bluetooth is enabled on your smartphone before proceeding.

1. Open the "Da Fit" app on your smartphone.
2. Navigate to the "Device" or "Add Device" section within the app.
3. The app will search for nearby devices. Select "ZW13" or "ZW Luxo" from the list to connect.
4. Confirm the pairing request on both your smartphone and smartwatch if prompted.

4. Setting Up Bluetooth Calling

To use the call function, an additional Bluetooth connection is required.

1. After initial pairing, go to your smartphone's Bluetooth settings.
2. Look for a second Bluetooth device named "ZW Luxo" (or similar, often with a headset icon) and pair with it.
3. Ensure that the "Call Audio" or "Phone Audio" option is enabled for this connection in your phone's Bluetooth settings.
4. On the smartwatch, activate the Bluetooth call function (usually found in the watch's settings or a quick access menu).



Figure 3: Bluetooth Calling Setup. This image demonstrates the process of connecting the smartwatch for making and receiving calls via Bluetooth.

Operating Instructions

1. Basic Navigation

- **Touch Screen:** Swipe left/right, up/down, and tap to navigate through menus and select options.

- **Side Buttons:** Use the physical buttons on the side for power on/off, returning to the home screen, or quick access to certain functions.

2. Customizing Watch Faces

The PEJE ZW13 offers over 200 customizable watch faces through the "Da Fit" app.

1. Open the "Da Fit" app.
2. Go to the "Watch Faces" or "Dial Settings" section.
3. Browse and select your preferred watch face, or upload a custom image.
4. Synchronize the selection to your smartwatch.



Figure 4: Watch Face Customization. This image illustrates the variety of watch faces available for the PEJE ZW13 Smartwatch.

3. Making and Receiving Calls

Once Bluetooth calling is set up, you can manage calls directly from your smartwatch.

- **Making Calls:** Access the dial pad or contact list on your smartwatch to initiate a call.
- **Receiving Calls:** When a call comes in, the smartwatch will display the caller ID. You can answer or reject the call directly from the watch.

4. Receiving Notifications

Enable app notifications in the "Da Fit" app to receive alerts for messages, social media (Facebook, WhatsApp, Instagram, Twitter), and other applications directly on your smartwatch.

5. Health Monitoring

The smartwatch continuously monitors various health metrics. All data is for personal wellness reference and not for medical purposes.

- **Heart Rate Monitoring:** Provides continuous heart rate data.
- **Sleep Tracking:** Analyzes sleep patterns (deep, light, awake) to provide comprehensive sleep data.
- **Calorie Tracking:** Monitors calories burned throughout the day.



Figure 5: Sleep Monitoring. This image illustrates the smartwatch's ability to track and analyze sleep patterns.

6. Sports Modes

The PEJE ZW13 supports over 120 sports modes to help you track your athletic performance.

1. Select your desired sport from the watch's sports menu.
2. The watch will monitor key data such as heart rate, distance, and movement speed.
3. Review your workout summaries in the "Da Fit" app.



Figure 6: Activity Tracking. This image demonstrates the smartwatch's capability to track various sports activities and display performance data.

7. Other Features

The smartwatch includes additional functionalities:

- **Smart Voice Assistant:** Access your phone's voice assistant directly from the watch.
- **Camera Control:** Remotely control your smartphone's camera.
- **Timer/Stopwatch:** Built-in timing functions.
- **Sedentary Reminder:** Alerts you to move after periods of inactivity.
- **Do Not Disturb Mode:** Mutes notifications during specific times.
- **Weather Forecast:** Displays current weather information.
- **Alarm Function:** Set alarms directly on the watch.

Maintenance

Proper maintenance ensures the longevity and optimal performance of your PEJE ZW13 Smartwatch.

1. **Keep it Clean:** Regularly clean the display and strap with a soft, dry cloth. Avoid using chemical solvents or abrasive materials.
2. **Water Resistance (IP68):** The watch is IP68 water-resistant, suitable for daily use like washing hands or rainy days. **Do not use it in hot water, seawater, or during diving.** Avoid prolonged submersion.
3. **Software Updates:** Periodically check for and install software updates via the "Da Fit" app to ensure optimal performance and access to new features.
4. **Battery Management:** Avoid completely draining the battery frequently. Charge the watch before it reaches critically low levels. For long-term storage, charge the battery to about 50% to prevent aging effects.
5. **Preventing Damage:** Avoid strong impacts or falls. Remove the watch during intense sports or activities where it

might be damaged.

6. **Regular Inspection:** Periodically check the strap for wear and tear. Ensure the charging contacts are clean and free of debris.
7. **Storage:** When not in use for an extended period, store the watch in a cool, dry place.



Figure 7: Water Resistance. This image highlights the IP68 water resistance feature of the smartwatch.



Figure 8: Smartwatch Maintenance. This image provides a visual context for general care and maintenance tips to prolong the life of your PEJE ZW13 Smartwatch.

Troubleshooting

If you encounter issues with your smartwatch, refer to the following common solutions:

Problem	Solution
Smartwatch won't turn on or respond.	Ensure the watch is fully charged. Connect it to the charger for at least 30 minutes. If unresponsive, try a forced restart (refer to the device's specific restart procedure, usually holding a button for 10-15 seconds).

Problem	Solution
Cannot pair with the "Da Fit" app.	• Ensure Bluetooth is enabled on your phone. • Make sure the watch is charged and powered on. • Restart both your phone and the smartwatch. • Ensure the "Da Fit" app has necessary permissions (location, Bluetooth). • Try unpairing any previous Bluetooth connections to the watch on your phone.
Bluetooth calling not working.	• Verify that the second Bluetooth connection for calls ("ZW Luxo") is paired and connected in your phone's Bluetooth settings. • Check if "Call Audio" is enabled for this connection. • Ensure the Bluetooth call function is activated on the smartwatch itself.
Notifications are not received.	• Check notification settings within the "Da Fit" app. • Ensure your phone's notification access is granted to the "Da Fit" app. • Disable "Do Not Disturb" mode on both your phone and smartwatch. • Ensure the app is running in the background on your phone.
Inaccurate health data.	• Ensure the watch is worn snugly on your wrist, not too loose or too tight. • Clean the sensors on the back of the watch. • Avoid excessive movement during measurements. • Remember that data is for wellness reference only and not medical diagnosis.

Specifications

Feature	Detail
Model	ZW13
Display	1.43-inch AMOLED Full Touch Screen
Resolution	466 x 466 pixels
Operating System	AsteroidOS
Memory Storage	128 MB
Connectivity	Bluetooth
GPS	No
Water Resistance	IP68 (up to 1 meter depth)
Battery Capacity	280 mAh Lithium Polymer
Battery Life (Typical Use)	5-7 days

Feature	Detail
Standby Time	Up to 30 days
Charging Time	Approximately 2 hours
Strap Material	Silicone
Compatible Devices	Smartphones (Android/iOS)
Health Monitoring	Heart Rate, Sleep Patterns, Calories Burned
Sports Modes	120+ modes
Special Features	Bluetooth Calling, Voice Control, Camera Control, Timer, Sedentary Reminder, Weather, Alarm

Warranty and Support

Warranty Information

The PEJE ZW13 Smartwatch comes with a **1-year limited warranty** against manufacturing defects. This warranty does not cover damage caused by misuse, accidents, unauthorized modifications, or failure to follow the instructions in this manual. Please retain your proof of purchase for warranty claims.

Customer Support

For technical assistance, troubleshooting beyond this manual, or warranty inquiries, please contact PEJE customer support through the retailer where you purchased the product or visit the official PEJE brand store online:
Official PEJE Brand Store: Visit PEJE Store

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DK9CYXRV

More documents and user manuals: **https://manuals.plus/**