Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Panta HC028

Panta HC028 Adjustable Bed Rail for Seniors

Model: HC028 | Brand: Panta

1. Introduction

The Panta HC028 Adjustable Bed Rail is designed to provide stability and assistance for individuals, particularly seniors, in getting in and out of bed safely. This durable bed rail features a robust steel construction, adjustable height settings, a motion-activated light for nighttime visibility, and a convenient storage pocket. Please read this manual thoroughly before installation and use to ensure proper function and safety.

2. Safety Information

- This bed rail has passed ASTM F3186-17 safety standards.
- The bed rail supports a maximum weight capacity of 350 lbs (158.8 kg).
- Always ensure the bed rail is securely fastened to the bed frame using the provided safety strap to prevent movement.
- The flat tube design helps prevent mattress deformation and ensures a comfortable sleep surface.
- Anti-slip mats on the support legs and non-slip foam on the handle enhance stability and grip.
- Do not use the bed rail for climbing or as a substitute for professional medical assistance.
- Ensure the distance between your bed frame and the floor is greater than 32 cm (12.6 inches) for proper installation of the support legs.

3. Package Contents

Verify that all the following components are included in your package:

- 1 x Handle Bar
- 1 x U-Shaped Flat Tube
- 2 x Connection Tubes
- 2 x Anti-slip Foot Mats
- 2 x Support Legs
- 1 x Motion Light
- 1 x Storage Bag

- 2 x Soft Magnetic Sheets
- 2 x Iron pieces
- 1 x Safety Strap
- 1 x USB Data Cable (for charging motion light)



This image provides a detailed view of all individual components included in the Panta Bed Rail package. Each part is numbered and labeled, including the handle bar, U-shaped flat tube, connection tubes, anti-slip foot mats, support legs, motion light, storage bag, soft magnetic sheets, iron pieces, and the safety strap.

4. Setup and Installation

The Panta Bed Rail is designed for quick and easy installation, typically within minutes and without the need for additional tools. Follow these general steps:

1. **Assemble the Frame:** Connect the Handle Bar to the U-Shaped Flat Tube using the Connection Tubes. Ensure all connections are secure.
2. **Attach Support Legs:** Insert the Support Legs into the designated slots on the main frame.

3. **Adjust Height:** Adjust the height of the handle bar and the support legs to your desired level. The handle height is adjustable from 38.5 to 48.5 cm (15.16 to 19.08 inches) and the support leg height from 32 to 50 cm (12.6 to 19.69 inches). Ensure the bed rail is stable at the chosen height.
4. **Position the Bed Rail:** Place the U-Shaped Flat Tube under your mattress, ensuring the bed rail is positioned securely next to the bed.
5. **Secure with Safety Strap:** Thread the safety strap through the bed rail frame and around the bed frame or box spring on the opposite side of the bed. Tighten the strap firmly to secure the bed rail in place and prevent it from shifting.
6. **Attach Motion Light and Storage Bag:** Affix the motion light to the handle bar and attach the storage bag as desired.



This image displays the Panta Bed Rail fully assembled next to a bed, emphasizing its flat tube design to prevent mattress deformation. Key features like high-quality alloy steel, anti-slip mats, easy installation, and the integrated motion light are pointed out.



This diagram illustrates the adjustable height features of the bed rail, detailing measurements from the frame to the handle (15.16-19.08 inches) and from the frame to the floor (12.6-19.69 inches). It also shows the 63-inch safety strap and confirms a weight capacity of 350 lbs.

5. Operating Instructions

5.1 Motion Light Operation

The integrated motion light provides illumination for safe entry and exit from bed, especially at night. It features three adjustable modes:

- **Daytime Off Mode:** The light remains off during daylight hours.
- **Night Automatic Mode:** The sensor light automatically activates when motion is detected within a 16-foot range and a 120-degree sensing angle, providing light for nighttime movements.
- **Always On Mode:** The light remains continuously on until manually turned off.

The motion light is rechargeable via the included USB data cable. If the sensor light runs out of power, connect it to a USB power source for charging.



This image explains the three operational modes of the bed rail's motion-sensing light: 'Daytime Off Mode', 'Night Automatic Mode' which activates upon detecting movement within 16 feet and a 120-degree range, and 'Always On Mode'. A note indicates USB charging for the sensor light.

5.2 Using the Storage Pocket

The removable storage pocket features three compartments, providing convenient storage for personal items such as remote controls, glasses, or books, keeping them within easy reach.



This image focuses on the removable storage pouch of the bed rail, demonstrating its three pockets filled with items for easy access. It also provides a close-up view of the non-slip foam on the handle, designed for comfort and secure grip.

6. Maintenance

To maintain the cleanliness and longevity of your Panta Bed Rail, simply wipe it with a dry cloth as needed. Avoid using harsh chemicals or abrasive cleaners.

7. Troubleshooting

If you encounter any issues with your Panta Bed Rail, please review the installation steps to ensure all components are correctly assembled and securely fastened. For problems related to the motion light, ensure it is charged. If problems persist, please contact customer support for assistance.

8. Specifications

Feature	Specification
Model Number	HC028
Material	Metal
Color	Black
Product Dimensions (L x W x H)	5.05 x 31.5 x 100.51 cm (2 x 12.4 x 39.6 inches)
Item Weight	2.78 kg (6.13 lbs)
Adjustable Handle Height	38.5 to 48.5 cm (15.16 to 19.08 inches)
Adjustable Support Leg Height	32 to 50 cm (12.6 to 19.69 inches)
Weight Capacity	158.8 kg (350 lbs)
Motion Light Sensing Distance	Up to 16 feet
Motion Light Sensing Range	120 degrees
Compatibility	King, Queen, Twin, and Medium Beds (requires >32cm clearance from bed frame to floor)

9. Customer Support

If you have any questions, concerns, or require assistance with your Panta Bed Rail, please do not hesitate to contact our professional after-sales support team. We are committed to providing satisfactory solutions.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DL5LQC8R

More documents and user manuals: **https://manuals.plus/**