

[manuals.plus](#) /› [GEARit](#) /› **GEARit Wireless Bluetooth Headset with Mic - MONO Headset (Model GI-HSET-BT-MONO-BK-2) User Manual**

GEARit GI-HSET-BT-MONO-BK-2

GEARit Wireless Bluetooth Headset with Mic - MONO Headset (Model GI-HSET-BT-MONO-BK-2) User Manual

Your guide to setting up and using your GEARit Wireless Bluetooth Headset.

INTRODUCTION

Thank you for choosing the GEARit Wireless Bluetooth MONO Headset. This headset is designed to provide crystal-clear audio for calls and music, featuring an advanced Environmental Noise Cancelling (ENC) microphone to eliminate background noise. With its comfortable design, long battery life, and seamless Bluetooth 5.2 connectivity, it is an ideal solution for home, office, and on-the-go use.

This manual provides detailed instructions to help you set up, operate, and maintain your headset for optimal performance.



Image: The GEARit Wireless Bluetooth MONO Headset, showcasing its sleek black design and single earcup.

Advanced Environmental Noise Cancellation (ENC)

Eliminates **99% off** background noise for
clearer communication



GEARit

Image: A person wearing the GEARit headset in an office environment, illustrating the effectiveness of the Environmental Noise Cancellation (ENC) feature for clearer communication.

Road-Ready Comfort

Lightweight, on-ear design stays comfortable for hours



GEARit

Image: A truck driver wearing the GEARit headset, highlighting its road-ready comfort and suitability for professional use in various environments.

PRODUCT OVERVIEW AND COMPONENTS

Familiarize yourself with the various parts and controls of your GEARit headset.



Image: A detailed diagram highlighting the key components of the headset, including the adjustable headband, soft padded earcup, padded pillow, volume controls, power button, multi-function button, LED indicator, rotating microphone, and mute button.

- **Adjustable Headband:** For a customizable and comfortable fit.
- **Soft Padded Earcup:** Designed for comfort during extended use.
- **Padded Pillow:** Provides additional cushioning for the head.
- **Volume +/- Buttons:** Adjust the audio output level.
- **Power Button:** Turns the headset on or off.
- **Multi-Function Button (MFB):** Controls calls and music playback.
- **LED Indicator:** Displays status such as power, pairing, and charging.
- **270° Rotating Microphone:** Allows flexible positioning for optimal voice capture and can be worn on either ear.
- **Mute Button:** Quickly mute or unmute the microphone.

SETUP

1. Charging the Headset

Before first use, fully charge your headset. A full charge provides up to 45 hours of battery life.

1. Connect the included USB-C charging cable to the charging port on the headset.
2. Connect the other end of the cable to a USB power source (e.g., computer, wall adapter).
3. The LED indicator will show charging status (e.g., red for charging, blue for fully charged).



Image: The GEARit headset with a graphic indicating its extended battery life of up to 45 hours.

Everything You Need

Complete convenience, all in one



GEARit

Image: The GEARit headset positioned next to its USB-C to USB-A charging cable, illustrating the charging accessory.

2. Bluetooth Pairing

The headset uses Bluetooth 5.2 for a stable connection up to 33 feet. It also supports multipoint connectivity, allowing connection to two devices simultaneously.

- Power On:** Press and hold the Power Button until the LED indicator flashes blue and red, indicating pairing mode.
- Activate Bluetooth:** On your device (smartphone, computer, tablet), enable Bluetooth.
- Select Headset:** In your device's Bluetooth settings, search for "GEARit Headset" (or similar) and select it to connect.
- Confirmation:** The LED indicator will turn solid blue, and you may hear an audio prompt confirming successful connection.

Extended Battery Life

Includes USB-C charging cable

45 Hours

Music Time

35 Hours

Talk Time

300 Hours

Stand-by Time

UP to

45
Hours

GEARit

Image: The GEARit headset connected wirelessly to both a laptop and a smartphone, demonstrating its multipoint connectivity feature.

OPERATING INSTRUCTIONS

Power On/Off

- Power On:** Press and hold the Power Button for approximately 3 seconds. The LED will flash blue.
- Power Off:** Press and hold the Power Button for approximately 5 seconds. The LED will turn off.

Volume Control

- Increase Volume:** Press the Volume + button.
- Decrease Volume:** Press the Volume - button.

Call Management

- Answer/End Call:** Press the Multi-Function Button once.
- Reject Call:** Press and hold the Multi-Function Button for 2 seconds.
- Mute/Unmute Microphone:** Press the Mute Button on the microphone boom.

Music Playback

- **Play/Pause:** Press the Multi-Function Button once.
- **Next Track:** Press and hold the Volume + button.
- **Previous Track:** Press and hold the Volume - button.

Microphone Adjustment

The microphone can rotate 270 degrees, allowing you to wear the headset on either your left or right ear. Position the microphone approximately 1-2 inches from your mouth for optimal voice clarity.



Image: A visual representation of the microphone's 270-degree rotation, demonstrating its flexibility for positioning.

Versatile Solution for Everyday Use

Online Classes

Commuting/Trucker

Work From Home

Music

Video Conferences

Phone Calls

GEARit

Image: A collage of images showing the GEARit headset being used in various scenarios, including online classes, trucking, work-from-home, video conferences, phone calls, and listening to music, highlighting its versatility.

MAINTENANCE

- Cleaning:** Use a soft, dry cloth to clean the headset. Avoid using harsh chemicals or abrasive materials.
- Storage:** Store the headset in a cool, dry place away from direct sunlight and extreme temperatures.
- Battery Care:** To prolong battery life, avoid fully discharging the headset frequently. Charge it regularly, even if not in use for extended periods.
- Water Resistance:** This headset is not water-resistant. Avoid exposure to liquids.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Headset does not power on.	Low battery.	Charge the headset fully.
Cannot pair with device.	Bluetooth is off on device; headset not in pairing mode; too far from device.	Ensure Bluetooth is enabled. Put headset in pairing mode (flashing blue/red LED). Move headset closer to device (within 33 feet).
No sound or low volume.	Device volume too low; headset volume too low; headset not selected as audio output.	Increase volume on both the headset and your connected device. Check device's audio settings to ensure headset is selected.
Microphone not working.	Microphone muted; incorrect microphone selected on device; microphone not positioned correctly.	Press the Mute Button to unmute. Check device's audio input settings. Adjust microphone position closer to your mouth.
Intermittent connection.	Too far from device; interference from other wireless devices.	Move closer to the connected device. Reduce interference by moving away from other wireless devices.

SPECIFICATIONS

Model Name	GI-HSET-BT-MONO-BK-2
Brand	GEARit
Connectivity Technology	Wireless (Bluetooth)
Bluetooth Version	5.2
Bluetooth Range	33 Feet
Battery Life	Up to 45 Hours
Item Weight	3.52 ounces
Ear Placement	On Ear
Form Factor	Over Ear

Earpiece Shape	Over Ear
Noise Control	Environmental Noise Cancelling (ENC) Microphone
Headphones Jack	No Jack
Water Resistance Level	Not Water Resistant
Compatible Devices	Smartphones, Computers, Tablets, Laptops, Desktops
UPC	810166801676

WARRANTY AND SUPPORT

For warranty information, please refer to the product packaging or visit the official GEARit website. If you encounter any issues or require further assistance, please contact GEARit customer support through their official channels.

You can often find support contact details on the manufacturer's website or within the product packaging.