



Manuals.plus /

- › Aiwa /
- › Aiwa SP-03-BL Bluetooth Speaker User Manual

Aiwa AWS-SP-03-BL

Aiwa SP-03-BL Bluetooth Speaker User Manual

Model: AWS-SP-03-BL

1. INTRODUCTION

Thank you for purchasing the Aiwa SP-03-BL Bluetooth Speaker. This portable speaker is designed to deliver clear, balanced sound with enhanced bass, dynamic RGB lighting, and multiple connectivity options. Its IPX4 splash resistance makes it suitable for various environments. Please read this manual carefully before using the product to ensure proper operation and to maximize your listening experience.



Image: Aiwa SP-03-BL Bluetooth Speaker, showcasing its compact design and carrying handle.

2. SAFETY INFORMATION

- Do not expose the speaker to extreme temperatures, direct sunlight, or high humidity.
- Avoid dropping or subjecting the speaker to strong impacts.
- Keep the speaker away from water sources, despite its IPX4 rating, to prevent damage.
- Do not attempt to disassemble, repair, or modify the speaker yourself. Contact qualified service personnel.
- Use only the provided USB-C cable for charging.
- Keep out of reach of children.

3. PACKAGE CONTENTS

Ensure all items are present in the package:

- 1 x Aiwa SP-03-BL Bluetooth Speaker
- 1 x USB-C Charging Cable

- 1 x Instruction Manual

4. PRODUCT FEATURES

- **Powerful Audio:** 15W RMS output for clear and balanced sound.
- **Enhanced Bass:** Passive radiator technology for deeper and more impactful bass.
- **Long Battery Life:** Up to 12 hours of continuous playback on a single charge.
- **Splash Resistant:** IPX4 certified for protection against liquid splashes.
- **True Wireless Sound (TWS):** Connect two SP-03-BL speakers for an immersive stereo experience.
- **Bluetooth 5.3:** Stable, efficient, and low-power wireless connectivity.
- **Dynamic RGB Lights:** Three multi-colored light modes to enhance your music.
- **Multiple Connectivity:** Supports Micro SD card, USB drive, and USB-C for charging.
- **Portable Design:** Compact and lightweight with a convenient carrying handle.
- **App Control:** Adjust equalization, DJ effects, and light intensity via the AIWA Brazil app.



O radiador passivo atua em conjunto com o alto-falante para entregar graves mais **profundos e impactantes**

Image: The Aiwa SP-03-BL speaker, emphasizing its 15W RMS power output.

IPX4: PROTEÇÃO CONTRA RESPINGOS DE ÁGUA

Curta seu som à beira da piscina numa boa!



Image: The Aiwa SP-03-BL speaker, illustrating its IPX4 splash resistance.

5. SETUP AND INITIAL USE

5.1 Charging the Speaker

Before first use, fully charge the speaker. Connect the provided USB-C cable to the speaker's USB-C port and the other end to a USB power adapter (not included) or a computer's USB port. The LED indicator will show charging status and turn off when fully charged. A full charge takes approximately 3 hours.

5.2 Powering On/Off

- **To Power On:** Press and hold the Power button for a few seconds until you hear an audible prompt and the LED lights illuminate.
- **To Power Off:** Press and hold the Power button again for a few seconds until you hear an audible prompt and the LED lights turn off.

5.3 Bluetooth Pairing

1. Ensure the speaker is powered on and in Bluetooth pairing mode (the LED indicator will flash).
2. On your mobile device, enable Bluetooth and search for available devices.

3. Select "Aiwa SP-03-BL" from the list of devices.
4. Once paired, the speaker will emit an audible confirmation, and the LED indicator will stop flashing.



Bluetooth® 5.3

Conexão super-rápida, mais estável
e com menor consumo de energia

Image: The Aiwa SP-03-BL speaker, indicating its Bluetooth 5.3 connectivity.

5.4 True Wireless Sound (TWS) Pairing

To connect two Aiwa SP-03-BL speakers for stereo sound:

1. Ensure both speakers are powered on and not connected to any Bluetooth device.
2. On one speaker (this will be the primary speaker), press and hold the TWS button (usually indicated by a chain link or TWS icon) for a few seconds.
3. The primary speaker will search for the secondary speaker. Once connected, both speakers will emit an audible confirmation.
4. Now, pair your mobile device to the primary speaker via Bluetooth as described in section 5.3.



Conecte dois Speakers AWS-SP-03-BL e tenha um som amplo envolvente!



Image: Two Aiwa SP-03-BL speakers demonstrating True Wireless Sound (TWS) connection for stereo audio.

5.5 Using Micro SD Card or USB Drive

Insert a Micro SD card or USB drive (with supported audio files) into the respective port on the speaker. The speaker will automatically detect the storage device and begin playing music. Use the speaker's control buttons to navigate tracks.

VÁRIAS CONEXÕES

- ✓ 1 ENTRADA MICRO SD
- ✓ 1 ENTRADA USB
- ✓ 1 ENTRADA PARA CARREGAMENTO
USB TIPO-C



Image: Close-up of the Aiwa SP-03-BL speaker's top panel, highlighting the Micro SD, USB, and USB-C ports for various connections.

6. OPERATING THE SPEAKER

6.1 Basic Controls

Button/Function	Action
Power Button	Press and hold to Power On/Off.
Play/Pause Button	Press to Play or Pause music.
Volume Up (+)	Short press to increase volume. Long press for next track.
Volume Down (-)	Short press to decrease volume. Long press for previous track.
Mode Button	Press to switch between Bluetooth, Micro SD, and USB modes.
Light Button	Press to cycle through RGB light modes or turn lights off.
TWS Button	Press and hold to initiate TWS pairing.

6.2 RGB Light Modes

The speaker features dynamic RGB LED lights. Press the Light button to cycle through the available light modes. There are three distinct multi-colored effects. Pressing the button again will turn the lights off.



Adicione efeito multicolorido à sua música com os 3 modos de luzes dinâmicas

6.3 Using the AIWA Brazil App

For enhanced control, download the AIWA Brazil app from your smartphone's app store. The app allows you to:

- Adjust equalization settings (Bass, Mid, Treble).
- Control DJ effects.
- Change playback modes.
- Adjust the intensity of the portable speaker lights.



APP aiwa

Faça tudo pelo seu smartphone:

Comande a equalização, dê o play nas suas músicas, ajuste o volume ou desligue a caixa de som



*App Store® é marca registrada da Apple Inc., registrada nos EUA e em outros países.

*Google Play e o logotipo do Google Play são marcas registradas da Google LLC.

Image: A smartphone screen displaying the AIWA app interface with equalization and DJ effects controls.

7. MAINTENANCE

7.1 Cleaning

Wipe the speaker with a soft, dry, or slightly damp cloth. Do not use abrasive cleaners, alcohol, or chemical solvents, as these may damage the surface.

7.2 Storage

When not in use for extended periods, store the speaker in a cool, dry place away from direct sunlight and extreme temperatures. It is recommended to charge the battery at least once every three months to maintain its lifespan.

7.3 Battery Care

To prolong battery life, avoid fully discharging the speaker frequently. Charge the speaker when the low battery indicator appears.

8. TROUBLESHOOTING

Problem	Possible Solution
Speaker does not power on.	Ensure the battery is charged. Connect to a power source and try again.
Cannot pair via Bluetooth.	Ensure the speaker is in pairing mode. Turn off and on your device's Bluetooth. Move closer to the speaker. Forget previous pairings on your device.
No sound or low volume.	Increase volume on both the speaker and your connected device. Ensure the speaker is not muted. Check if the correct input mode (Bluetooth, SD, USB) is selected.
TWS pairing fails.	Ensure both speakers are powered on and not connected to any other Bluetooth device. Try resetting both speakers and repeating the TWS pairing process.
Speaker not charging.	Check the USB-C cable and power adapter. Ensure connections are secure. Try a different cable or power source.

9. SPECIFICATIONS

Feature	Detail
Brand	Aiwa
Model Number	AWS-SP-03-BL
Speaker Maximum Output Power	15 Watts RMS
Connectivity Technology	Bluetooth 5.3
Water Resistance Rating	IPX4 (Splash Resistant)
Battery Type	Rechargeable Lithium-ion
Battery Capacity	2000 mAh
Battery Average Life	Up to 12 Hours
Battery Charge Time	Approximately 3 Hours
Control Method	Touch Buttons, AIWA App
Item Dimensions (D x W x H)	13.3 x 11.6 x 11.3 Centimeters
Item Weight	0.54 Kilograms
Compatible Devices	Laptop, Smartphone, Tablet, Television
Input Ports	Micro SD, USB, USB-C (Charging)

537 g

aiwa



Image: The Aiwa SP-03-BL speaker, illustrating its physical dimensions and weight.

10. WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the warranty card included in your package or visit the official Aiwa website. You may also contact Aiwa customer service through the contact details provided on their website.

Aiwa Official Website: Visit the Aiwa Store on Amazon