



Manuals.plus /

› JUFINX /

› JUFINX X21 Cordless Leaf Blower User Manual

## JUFINX X21

# JUFINX X21 Cordless Leaf Blower User Manual

Model: X21

## INTRODUCTION

---

Thank you for choosing the JUFINX X21 Cordless Leaf Blower. This powerful and versatile tool is designed for efficient cleaning of leaves, snow, dust, and debris from various surfaces, including gardens, driveways, cars, and indoor spaces. Its lightweight, portable design and advanced features ensure ease of use and reliable performance. Please read this manual thoroughly before operation to ensure safe and optimal use of your device.



## JUFINX

- ✓ Cordless Leaf Blower
- ✓ 2.53 lbs Weightlight
- ✓ Portable Size
- ✓ Effortless one-handed Operation
- ✓ 30W Fast charging
- ✓ With Battery and Charger

# VS

## OTHERS

- ✗ Plug-in Leaf Blower
- ✗ 6.5 lbs Heavy Weight
- ✗ Bulky and Heavy Size
- ✗ Not Portable

Image: The JUFINX X21 Cordless Leaf Blower (left) is shown to be lightweight and portable compared to a traditional plug-in leaf blower (right), highlighting its ease of use and mobility.

## SAFETY INSTRUCTIONS

Always follow basic safety precautions when using electrical appliances to reduce the risk of fire, electric shock, and personal injury.

- Read all instructions before using the appliance.
- Do not operate the blower in wet conditions or rain.
- Keep children and bystanders away while operating the blower.
- Wear appropriate personal protective equipment (PPE) such as safety glasses, hearing protection, and gloves.
- Ensure the air inlet and outlet are clear of obstructions during operation.
- Do not point the blower nozzle at people or animals.

- Turn off and unplug the blower before cleaning, servicing, or storing.
- Use only the charger and accessories specified by the manufacturer.
- Store the blower in a dry, secure place out of reach of children.
- The device features NTC temperature protection, automatically shutting off the motor at 150°C to prevent overheating.
- The fan will automatically turn off after 3 minutes of inactivity to conserve battery and enhance safety.

## PACKAGE CONTENTS

---

Verify that all items are present and in good condition upon opening the package:

- JUFINX X21 Cordless Leaf Blower
- Fast Charging Charger
- Fast Charging Cable (Type-C)
- User Manual

# Packing List



Image: A visual representation of the items included in the JUFINX X21 package: the leaf blower, a fast charging cable, a fast charging charger, and the user manual.

## PRODUCT OVERVIEW

---

Familiarize yourself with the components of your JUFINX X21 Cordless Leaf Blower:



Image: The JUFINX X21 Cordless Leaf Blower, along with its fast charging cable and charger, presented from a front-facing perspective.



Image: A detailed diagram illustrating the key parts of the JUFINX X21 blower, such as the air outlet, air inlet, charging port, power button, stepless speed trigger, and the non-slip silicone handle.

- **Air Outlet:** Where the concentrated airflow exits.

- **Air Inlet:** Where air is drawn into the motor.
- **Stepless Speed Trigger:** Controls the airflow intensity.
- **Power Button:** Turns the device on/off.
- **Charging Port (Type-C):** For connecting the charging cable.
- **Non-slip Silicone Handle:** Provides a comfortable and secure grip.

## SETUP

---

### Charging the Battery

The JUFINX X21 comes with a built-in 3000mAh\*8 power battery (756Wh) and supports 30W fast charging. Before first use, fully charge the device.

1. Connect the Type-C fast charging cable to the charging port on the blower.
2. Plug the fast charging charger into a standard wall outlet.
3. The charging indicator (if present, typically an LED) will show the charging status. A full charge takes approximately 3 hours.
4. Once fully charged, disconnect the charger and cable.

# 6000mAh

## Power Battery



Image: The JUFINX X21 blower highlighting its internal 6000mAh power battery, fast charging capability, and integrated intelligent safety protection system.

## OPERATING INSTRUCTIONS

---

### Powering On/Off

- To turn on the blower, press the Power Button located on the handle.
- To turn off the blower, press the Power Button again.

### Adjusting Airflow (Stepless Speed)

The blower features an infinitely variable speed control, allowing precise adjustment of airflow from 100g to 1200g of thrust.

- Gently press the Stepless Speed Trigger to start the airflow at a low speed.

- Increase pressure on the trigger to gradually increase the airflow intensity.
- For maximum power (Turbo mode), long-press the Stepless Speed Trigger.



Image: The JUFINX X21 blower illustrating its stepless speed feature, with approximate run times of 60 minutes at low speed, 30 minutes at medium speed, and 10 minutes at high speed.

## Applications

The JUFINX X21 is suitable for a wide range of cleaning tasks:

- **Outdoor Cleaning:** Clearing fallen leaves from yards, driveways, and patios. Blowing snow from vehicles or pathways.
- **Vehicle Cleaning:** Drying water spots on cars after washing, blowing dust and debris from car interiors.
- **Household Cleaning:** Removing dust from computer hosts, keyboards, sofas, and other hard-to-reach areas.



# MULTIPLE USES



**Fallen Leaves**



**Snow**



**Water**



**Sofa**

Image: A collage demonstrating the versatile applications of the JUFINX X21, including clearing leaves, removing snow, drying car surfaces, and cleaning furniture.



Image: An individual operating the JUFINX X21 Cordless Leaf Blower to clear autumn leaves from a paved area, showcasing its

## MAINTENANCE

---

### Cleaning

- Ensure the blower is turned off and disconnected from the charger before cleaning.
- Wipe the exterior of the blower with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Periodically check the air inlet and outlet for any debris or blockages and clear them carefully.

### Battery Care and Storage

- Store the blower in a cool, dry place, away from direct sunlight and extreme temperatures (-20°C to +60°C operating temperature range).
- For long-term storage, it is recommended to charge the battery to approximately 50% to prolong its lifespan.
- Avoid fully discharging the battery frequently, as this can reduce its overall lifespan.

## TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Blower does not turn on.	Battery is depleted.	Charge the battery fully.
Blower stops unexpectedly during use.	Overheating protection activated.	Allow the blower to cool down. Ensure air inlets/outlets are not blocked.
Reduced airflow.	Air inlet/outlet blocked.	Clear any obstructions from the air inlet and outlet.
Battery drains quickly.	Operating at high speed continuously; battery degradation over time.	Optimize usage by varying speed. Ensure full charge before use. Contact support if issue persists.

## SPECIFICATIONS

---

Feature	Detail
Brand	JUFINX
Model Name	JUFINX X21
Power Source	Battery Powered
Motor Type	64mm Super Powerful Brushless Motor
Wind Pressure	1200G (Max)
Battery Capacity	3000mAh*8 (Equivalent to 6000mAh total, as per A+ content image)
Charging Power	30W Fast Charging
Full Charge Time	Approx. 3 hours
Run Time (Low Speed)	Up to 60 minutes
Run Time (Medium Speed)	Up to 30 minutes
Run Time (High Speed)	Up to 10 minutes
Item Weight	2.53 Pounds (1150g)
Product Dimensions (L x W x H)	28.6cm x 8.2cm x 17.6cm (11.3" x 3.2" x 6.9")
Material	Plastic (High hardness, quick heat dissipation)
Operating Temperature	-20°C to +60°C
UPC	663899846236



Image: A visual representation of the JUFINX X21 Cordless Leaf Blower's dimensions (length, width, height) and weight, shown next to a microphone for scale.

## WARRANTY AND SUPPORT

---

The JUFINX X21 Cordless Leaf Blower is backed by a 24-month warranty.

- For warranty claims or technical support, please contact JUFINX customer service.
- Dedicated customer service ensures prompt responses within 24 hours.
- Replacement and accessories are available within 365 days.

For further assistance, please visit the official JUFINX store or contact their support channels.



Image: A customer service representative ready to assist, representing the support available for the product.