

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [SEEKONE](#) /

> [SEEKONE Cordless Mini Heat Gun User Manual](#)

SEEKONE HG2466-NEW

SEEKONE Cordless Mini Heat Gun User Manual

MODEL: HG2466-NEW



An overview of the SEEKONE Cordless Mini Heat Gun, including the main unit, reflector nozzle, USB charging cable, and a stand.

Introduction

The SEEKONE Cordless Mini Heat Gun is a versatile and portable tool designed for various applications such as heat shrink tubing, resin curing, small paint surface heating, and paint removal. Its cordless design, precise temperature control, and safety features make it an ideal tool for both professional and DIY projects.

Important Safety Instructions

Please read and understand all safety instructions before operating the heat gun to prevent injury or damage.

- **Safe Start Function:** To prevent accidental activation during transport or storage, the heat gun features a safety

lock. It must be unlocked before first use and can be re-locked for safety.

- **Overheat Protection:** The heat gun is equipped with an automatic overheat protection system that will shut down the unit if the temperature becomes too high. Allow the unit to cool down before resuming operation.
- **Charging Safety:** Do not use the heat gun while it is charging. Ensure the unit is fully charged before use. For long-term storage, charge the battery every 3 to 6 months.
- **Ventilation:** Ensure adequate ventilation when using the heat gun, especially when working with materials that may emit fumes.
- **Keep Away from Flammable Materials:** Do not direct hot air towards flammable liquids, gases, or materials.
- **Do Not Block Air Vents:** Ensure the air intake and exhaust vents are clear of obstructions during operation.
- **Proper Storage:** Store the heat gun in a dry, secure place, out of reach of children.



Image illustrating the security lock setting, which prevents accidental activation when the heat gun is stored or transported.

Package Contents

Verify that all items are present in the package:

- 1 x SEEKONE Cordless Mini Heat Gun
- 1 x Reflector Nozzle
- 1 x USB Charging Cable
- 1 x User Manual

Product Features

- **4 Temperature Settings & Memory Function:** Offers four precise temperature levels (150°C, 250°C, 350°C, 450°C) with an automatic memory function that recalls the last used setting.
- **LCD Screen & Battery Level Indicator:** A clear LCD displays the current temperature and real-time battery capacity, allowing for efficient work planning.
- **Convenient USB Charging:** Supports both PD fast charging and normal charging via USB, adapting automatically for optimal charging. Features a built-in 3.6V 5.0Ah high-capacity lithium battery.
- **Compact and Portable Design:** Lightweight and small, ideal for flexible use in confined spaces or outdoors without the need for power cords.
- **Fast Heating:** Quickly reaches desired temperatures for efficient operation.

FAST HEATING



Diagram showing the internal fast heating element of the heat gun, capable of reaching up to 450°C.

Setup

1. **Initial Unlocking:** The heat gun is factory-locked. Upon first use, the LCD screen will display "GGG" flashing. To unlock, quickly press the "+" button three times within 1 second.
2. **Initial Charging:** Ensure the heat gun is fully charged before its first use. Connect the provided USB charging cable to the heat gun's charging port and a suitable USB power adapter. The LCD will indicate charging status.

TYPE-C PD **FAST CHARGING** & NORMAL CHARGING



Illustration of the heat gun being charged via a USB Type-C cable, highlighting its fast charging capability and battery level visualization.

3. **Attach Nozzle:** If required for your application, attach the reflector nozzle to the heat gun's output.

Operating Instructions

1. **Power On/Off:** After unlocking, press and hold the power button (usually the '+' button or a dedicated power button if present) to turn the unit on. Press and hold again to turn off.
2. **Adjusting Temperature:** Use the "+" and "-" buttons to cycle through the four temperature settings: 150°C, 250°C, 350°C, and 450°C. The selected temperature will be displayed on the LCD screen.

4 TEMPERATURE SETTINGS



Visual representation of the four available temperature settings (150°C, 250°C, 350°C, 450°C) and the temperature memory function.

3. **Temperature Unit Conversion (°C/°F):** To switch between Celsius (°C) and Fahrenheit (°F), quickly press the " button three times within 1 second.

°C/°F CONVERSION



Demonstration of how to convert temperature units between Celsius and Fahrenheit by pressing the '-' button three times.

4. **Memory Function:** The heat gun automatically remembers the last temperature setting used, improving efficiency for repetitive tasks.
5. **Safety Lock:** To lock the heat gun for storage or transport, quickly press the "⚡" button three times within 1 second. The LCD will display "GGG" flashing, indicating it is locked. Unlock using the same method.
6. **Application:** Direct the hot air stream towards the material you wish to heat. Maintain a safe distance to prevent overheating or damage to the material.

Maintenance

- **Battery Care:** If the heat gun will not be used for an extended period (e.g., 3-6 months), ensure it is charged periodically to maintain battery health.
- **Cleaning:** Keep the air intake and exhaust vents clean and free of dust and debris. Use a soft, dry cloth to wipe down the exterior of the unit. Do not use abrasive cleaners or solvents.
- **Storage:** Store the heat gun in a cool, dry place, away from direct sunlight and extreme temperatures. Ensure it is locked before storage or transport.

Troubleshooting

Problem	Possible Cause	Solution
Heat gun does not turn on.	Unit is locked. Battery is depleted.	Quickly press the "+" button three times within 1 second to unlock. Charge the battery fully.
Heat gun shuts off during operation.	Overheat protection activated.	Allow the unit to cool down. Ensure air vents are not blocked.
Temperature display is incorrect or erratic.	Sensor issue or low battery.	Ensure battery is charged. If problem persists, contact customer support.

Specifications

Attribute	Detail
Model Number	HG2466-NEW
Manufacturer	SEEKONE
Dimensions (Package)	21.8 x 9.7 x 4.4 cm
Weight (Product)	250 grams (0.55 lbs)
Battery Type	Lithium-ion
Battery Voltage	3.6 V
Battery Capacity	5.0 Ah (5000mAh)
Power Source	Battery Powered (USB Charging)
Temperature Settings	150°C, 250°C, 350°C, 450°C
Display	LCD (Temperature, Battery Level)
Country of Origin	China

SMALL & PRECISE



WEIGHT: 0.83 lb



LENGTH: 8.07 inch



WIDTH: 3.7 inch



Detailed dimensions of the compact and precise SEEKONE Cordless Mini Heat Gun, showing its length and width.

Warranty Information

Specific warranty details for the SEEKONE Cordless Mini Heat Gun are not provided in this manual. Please refer to the product packaging, the manufacturer's official website, or contact the seller for comprehensive warranty information and terms.

Customer Support

For any questions, technical assistance, or support regarding your SEEKONE Cordless Mini Heat Gun, please contact the manufacturer, SEEKONE, or the authorized seller from whom you purchased the product. Contact information can typically be found on the product packaging or their respective websites.

