Xvive HUB

Xvive More You USB Audio Interface (HUB) Instruction Manual

Model: HUB

INTRODUCTION

The Xvive More You USB Audio Interface (HUB) is an expandable audio interface designed for recording, producing, and engineering. It offers seamless scalability, high-precision audio performance, and comprehensive connectivity to adapt to various professional audio workflows. This manual provides detailed instructions for setting up, operating, and maintaining your More You HUB.

Your browser does not support the video tag.

Official Xvive More You Audio Interface Overview: This video demonstrates the features, setup, and use cases of the More You system, including its expandability, monitoring capabilities, and connectivity options.

PRODUCT OVERVIEW & KEY FEATURES

The Xvive More You HUB is engineered to provide musicians and audio professionals with unparalleled control and flexibility. Its innovative design allows for expansion and integration into complex setups.

Figure 1: Top view of the Xvive More You HUB audio interface, showcasing its intuitive controls and display.

Highlighted Features:

- **Scalable Design:** Supports up to 8 expansion units (including MORE YOU 2X, 4X, and 8X units) for multi-user recording environments.
- **High-Precision Audio:** Features TRUE GAIN mic preamps (up to 60 dB gain in 1 dB increments) and supports 24-bit, 44.1kHz, 48kHz, or 96kHz audio.
- **Zero-Latency Monitoring:** Blends input signals with post-DAW playback for seamless monitoring during overdubbing and live tracking.
- **Comprehensive Connectivity:** Includes 2 XLR/TRS combo inputs, 8 ADAT inputs, MIDI I/O, 1/4" and 1/8" headphone jacks, TRS monitor outputs, and a MORE PORT XLR for expansion.
- **Intuitive Workflow:** USB-C connectivity to DAW, LCD screen, dual encoder knobs, and auto-save functionality.
- **Portable and Versatile:** Rugged, compact design with mic stand mounting options, suitable for studio, rehearsal, and podcasting.

SETUP

Setting up your Xvive More You HUB is designed to be straightforward, allowing you to quickly integrate it into your audio production environment.

Connecting the More You System:

The More You system is built for scalability. You can start with a single HUB and add additional units as your needs grow. Each musician or singer can have their own More You HUB or 2X unit, perfect for connecting a vocal microphone and an instrument.

MORE PORT

Expansion	Power Supply	Data Transmission
Connects your Hub/2X to other units, transmitting digital audio via standard XLR cables One XLR cable carries up to 24 inputs and 20 outputs.	provide power to external devices, especially when the device is designed to work with other modules or accessories. Connecting 2 to 4 expansion units requires a 35W USB-C power adapter, while connecting 5 to 7 units requires a 65W USB-C power input	support high-speed data transmission for syncing audio, MIDI, or other digital signals

Figure 2: The More Port allows seamless connection between the HUB and expansion units using a single XLR cable for audio, power, and talkback.

The unique **MORE PORT** connects all units with a single XLR cable, transferring audio input, 18-channel discrete headphone mix, power, and talkback between units. This simplifies complex setups and reduces cable clutter.

Initial Connection:

1. Connect your Xvive More You HUB to your computer via the provided USB-C cable. This connection streams audio directly to your Digital Audio Workstation (DAW).
2. For studio monitoring, connect your studio monitors to the HUB's TRS monitor outputs.
3. Plug in your microphones or instruments into the XLR/TRS combo inputs.
4. If using expansion units, connect them via the MORE PORT XLR cables.

OPERATION

The Xvive More You HUB is designed for intuitive operation, providing direct control over your audio.

True Gain Mic Preamps:

TRUE GAIN MIC PREAMPS
60 DB OF GAIN IN 1 DB STEPS FOR PRECISE GAIN SETTING AND RECALL

Figure 3: Adjusting the True Gain mic preamps for precise input levels.

The HUB features TRUE GAIN mic preamps, offering up to 60 dB of gain in precise 1 dB increments. This allows for accurate gain setting and recall. The gain level is displayed on the LCD screen for quick visual feedback.

Zero-Latency Monitoring:

Figure 4: The More You HUB provides zero-latency monitoring for musicians.

Musicians can hear their direct signal with zero latency in the More You Live Mix. Each input has its own dedicated monitoring control, offering ultimate flexibility. You can also instantly select any channel to monitor post-DAW, such as a guitar amp plugin or vocal effect.

DAW Integration:

Figure 5: Seamless integration with your Digital Audio Workstation (DAW).

When connected to your computer via USB-C, the More You HUB streams audio directly to your DAW, allowing you to record all inputs. A dedicated button allows you to switch between the DAW mix and the More You Live Mix. This enables engineers to work on the mix in studio monitors or solo channels in the DAW without affecting what the musicians hear.

Talkback System:

The built-in talkback system facilitates instant communication between musicians. No more shouting across the room or removing headphones to speak with band members.

Auto-Gain Feature:

The More You HUB features an advanced auto-gain system. Whether you need to auto-gain on individual channels or across the entire system, it simplifies the process with the touch of a button.

CONNECTIVITY

The More You HUB offers extensive input/output options to support diverse recording and performance needs.

Figure 6: Detailed view of the Xvive More You HUB's inputs, outputs, and controls.

1. Hi-Z Input	2. Direct Monitoring
3. Highpass Filter	4. 48V Phantom Power
5. Phase Reverse	6. Color Display
7. Headphone Volume	8. Encoders
9. Monitor Source	10. Line Out Volume
11. Talkback	12. Monitor Reverb
13. Monitor Volume	14. Input Jack (Combo Style)
15. Headphone Jack	16. Power Buttom

17. "More Port" Expansion Out	
18. "More Port" Expansion In	19. USB-C Data/Power
20. USB-C Power	21. ADAT IN
22 Line Output	23. 1/4" TRS MIDI

Input/Output Ports:

- **XLR/TRS Combo Inputs:** 2 inputs for microphones or instruments.
- **ADAT In:** 8 channels (1-8) for expanding input count up to 24 by connecting any 8-channel mic preamp unit.
- **MIDI I/O:** Seamless connection to keyboards, MIDI drum gear, and other MIDI devices.
- **Headphone Jacks:** 1/4" and 1/8" outputs.
- **TRS Monitor Outputs:** For connecting studio monitors.
- **MORE PORT XLR:** For system expansion and power distribution.
- **USB-C:** For data and power connection to a computer.

MAINTENANCE

To ensure the longevity and optimal performance of your Xvive More You HUB, follow these maintenance guidelines:

- Keep the device clean by wiping it with a soft, dry cloth. Avoid using abrasive cleaners or solvents.
- Store the device in a cool, dry place away from direct sunlight and extreme temperatures.

- Ensure all cables are securely connected but do not overtighten.
- Avoid exposing the device to moisture or liquids.

TROUBLESHOOTING

If you encounter any issues with your Xvive More You HUB, refer to the following common troubleshooting steps:

- **No Power:** Ensure the USB-C cable is securely connected to both the HUB and a power source/computer. Check if the power source is functioning correctly.
- **No Audio Output:** Verify that the monitor volume and headphone volume are turned up. Check all audio cable connections. Ensure the correct output is selected on the HUB and in your DAW.
- **No Input Signal:** Check microphone/instrument cable connections. Ensure phantom power (48V) is enabled for condenser microphones. Verify gain levels are appropriately set.
- **Connectivity Issues:** Try a different USB-C port or cable. Restart your computer and the More You HUB. Ensure your DAW and operating system drivers are up to date.
- **Distorted Audio:** Reduce input gain to prevent clipping. Check cable integrity. Ensure sample rates match between the HUB and your DAW.

For persistent issues, please contact Xvive customer support.

SPECIFICATIONS

Feature	Detail
Item Weight	2 pounds
Package Dimensions	2 x 2 x 1 inches
Country of Origin	China
ASIN	B0DRWXYPM6
Item model number	HUB
Date First Available	December 31, 2024
Compatible Devices	Laptop, Microphone, Keyboard, Personal Computer, Headphone
Supported Software	Support all major DAW software, including Pro Tools, Ableton Live, Logic Pro, Cubase, FL Studio, and Reaper.
Operating System	Windows, macOS
Brand	Xvive
Connectivity Technology	XLR
Number of Channels	10

WARRANTY AND SUPPORT

The Xvive More You HUB comes with a standard manufacturer's warranty. Please refer to the product packaging or the official Xvive website for specific warranty terms and conditions.

For technical support, product inquiries, or warranty claims, please visit the Xvive official support page or contact their customer service team directly. Contact information can typically be found on the Xvive website or in the product's original

packaging.