Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

JYX T11T

JYX Bluetooth Karaoke Machine Instruction Manual

Model: **T11T** | Brand: **JYX**

Introduction

This manual provides detailed instructions for the setup, operation, and maintenance of your JYX T11T Bluetooth Karaoke Machine. Designed for powerful audio performance and versatile entertainment, this PA system features dual 6.5-inch subwoofers, two wireless microphones, TWS stereo sound, and dynamic RGB lighting. Please read this manual thoroughly to ensure proper use and to maximize your product's potential.

What's in the Box

- JYX T11T Karaoke Machine
- 2 Wireless Microphones
- Power Cable
- User Manual (this document)

Key Features

- **Superior Stereo Sound & Deep Bass Boost:** Equipped with dual 6.5-inch 4Ω 60W external magnet speakers, delivering powerful stereo sound with enhanced bass. The built-in Bass Boost function enriches low frequencies for a dynamic audio experience.
- **Rechargeable and Long-lasting Battery:** Features a high-efficiency 12000mAh rechargeable battery for extended non-stop music playback.
- **Dual Wireless Microphones & Karaoke Fun:** Includes two UHF wireless microphones with stable signal transmission, ideal for karaoke, speeches, and gatherings. Supports Bluetooth recording.
- **TWS Function for True Wireless Stereo:** Pair two JYX T11-T speakers wirelessly to create a synchronized, wider stereo soundstage.
- **Dynamic RGB Lights & Party Ambience:** Built-in multi-color ambient lights sync with music, creating an exciting party atmosphere.
- **Bluetooth & Multiple Connectivity Options:** Latest Bluetooth 5.0 technology ensures fast and stable connection. Also supports USB flash drive, TF card, AUX-in, wired microphone, and guitar input.



Figure 1: Internal speaker components highlighting powerful bass and sound output.

Product Overview



Figure 2: The JYX T11T Karaoke Machine and its included accessories.

The JYX T11T is a portable karaoke and PA system designed for various audio needs. It features a robust build with an integrated handle for easy transport. The front panel showcases dynamic RGB lighting, while the top panel houses all control buttons and input ports.

Setup

1. Powering On/Off

Locate the ON/OFF switch on the top control panel. Flip the switch to the "ON" position to power on the device. Flip it to

the "OFF" position to power off.



Figure 3: The main control panel with power switch and input options.

Your browser does not support the video tag.

Video 1: Demonstrates the power switch and various input connections (0:23 - 0:29).

2. Connecting Microphones

The JYX T11T comes with two wireless UHF microphones. Ensure the microphones are powered on. They should automatically pair with the speaker. For wired microphones, connect them to the "MIC 1" or "MIC 2" 6.35mm input jacks on the control panel.

3. Connecting Audio Sources

- **Bluetooth:** Turn on the speaker and activate Bluetooth on your device (smartphone, tablet, etc.). Search for "JYX-T11T" in your device's Bluetooth settings and pair. The speaker will indicate a successful connection.
- **AUX-in:** Connect an external audio device using a 3.5mm AUX cable to the "AUX" port.
- **USB/TF Card:** Insert a USB flash drive or TF (microSD) card into the respective ports. The speaker will automatically

detect and play audio files.

4. TWS (True Wireless Stereo) Pairing

To achieve true wireless stereo sound, you can pair two JYX T11T speakers:

1. Ensure both JYX T11T speakers are powered on and in Bluetooth mode.
2. On one speaker (this will be the primary speaker), press and hold the "TWS" button. You will hear a prompt indicating TWS pairing mode.
3. The primary speaker will automatically search for and connect to the second speaker. Once connected, you will hear a confirmation sound.
4. Connect your Bluetooth device to the primary speaker. Audio will now play in stereo across both speakers.



Figure 4: Two JYX T11T speakers paired for TWS stereo sound.

Your browser does not support the video tag.

Video 2: Demonstrates TWS pairing functionality (0:30 - 0:32).

Operating Instructions

Control Panel Functions

The top panel of the JYX T11T provides comprehensive controls for audio adjustment and feature activation. Refer to Figure 3 for the layout.

Button/Control	Function
TWS	Initiates True Wireless Stereo pairing with another JYX T11T speaker.
Recording Icon (Mic with Trash Can)	Activates the recording function for microphone input.
Lighting Modes (Sun Icon)	Cycles through different dynamic RGB lighting effects.
Bass Boost	Enhances low-frequency audio output for deeper bass.
MIC VOL (+/-)	Adjusts the volume level of the connected microphones.
MIC REVERB (+/-)	Adjusts the reverb effect for the microphones.
TREBLE (+/-)	Adjusts the high-frequency audio output.
BASS (+/-)	Adjusts the low-frequency audio output.
VOL (+/-)	Adjusts the overall master volume of the speaker.
Modes (M)	Switches between input modes (Bluetooth, AUX, USB, TF Card, FM).
Play/Pause (▶■)	Plays or pauses the current audio track.
Previous Song (◀◀)	Skips to the previous audio track.
Next Song (▶▶)	Skips to the next audio track.

Dynamic RGB Lighting

The JYX T11T features multi-color ambient lights that synchronize with the beat of your music. Press the "Lighting Modes" button (sun icon) on the control panel to cycle through various light patterns and effects, enhancing your party atmosphere.



Figure 5: Examples of dynamic RGB lighting themes.

Battery Information

The JYX T11T is equipped with a high-capacity 12000mAh rechargeable battery, providing extended playback time. Battery life varies depending on volume level and light usage. To charge, connect the included power cable to the "DC IN" port on the control panel and plug it into a power outlet.



Figure 6: Illustration of the 12000mAh battery capacity for extended use.

Your browser does not support the video tag.

Video 3: Illustrates the long-lasting battery performance (0:33 - 0:37).

Specifications

Attribute	Detail
Brand	JYX
Model Number	T11T
Item Weight	17.81 pounds
Product Dimensions	12.5 x 11.7 x 25.3 inches
Color	Black

Attribute	Detail
Speaker Count	2
Output Wattage	60 Watts (per speaker, total 120W)
Power Source	Battery Powered
Compatible Devices	Smartphone, USB devices, TF cards, AUX devices, Wired Microphones, Guitars
Connector Type	Bluetooth 5.0, 3.5 mm Jack, USB, TF Card
Special Features	Built-In Handle, Echo Effect, Indicator Light, Portable, TWS, Recording

Maintenance

- Keep the speaker away from water, moisture, and direct sunlight.
- Clean the surface with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- Store the speaker in a cool, dry place when not in use for extended periods.
- Avoid dropping or subjecting the speaker to strong impacts.

Troubleshooting

Problem	Possible Solution
No Power	Ensure the power cable is securely connected and the battery is charged. Check the ON/OFF switch.
No Sound	Check the master volume (VOL) and source device volume. Ensure the correct input mode is selected (Bluetooth, AUX, USB, TF). For microphones, check MIC VOL.
Bluetooth Disconnection	Ensure the speaker and device are within the effective range (approx. 10 meters). Disconnect and re-pair the device. Avoid obstacles between the speaker and device.
Microphone Not Working	Ensure microphones are powered on and have fresh batteries. Check MIC VOL. For wireless mics, ensure they are paired.
TWS Pairing Fails	Ensure both speakers are JYX T11T models and are in Bluetooth mode before initiating TWS pairing. Try resetting both speakers and repeating the pairing process.

Warranty and Support

JYX provides comprehensive support for your product:

- **Warranty Service:** 360 Days Warranty Service.
- **After-sales Center:** US Local After-sales Center available.
- **Technical Support:** Lifetime Technical Support.

If you have any questions or encounter issues, please contact our customer support team for professional and timely assistance:

Email: service@jyxspeaker.com



Figure 7: JYX customer support and warranty details.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DT3STP4D

More documents and user manuals: **https://manuals.plus/**