Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

APBEAMLighting FS8858

APBEAMLighting FS8858 28-Inch Retractable LED Ceiling Fan with Light User Manual

Model: FS8858

1. Introduction

This manual provides detailed instructions for the safe installation, operation, and maintenance of your APBEAMLighting FS8858 28-inch retractable LED ceiling fan with light. Please read this manual thoroughly before installation and retain it for future reference. This modern fandelier features retractable ABS blades, dimmable LED lighting with three color temperatures, six fan speeds, a reversible motor, and control via both remote and a dedicated app.

2. Safety Information

WARNING: To reduce the risk of fire, electric shock, or personal injury, always follow these basic precautions:

- Turn off power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or national electrical codes. If you are unfamiliar with electrical wiring, consult a qualified electrician.
- Ensure the installation site can support the weight of the fan.
- Do not operate the fan with damaged blades or housing.
- Avoid placing objects in the path of the fan blades.
- This product is designed for indoor use only.

3. Package Contents

Verify that all components listed below are included in your package:

- LED Ceiling Fan Unit
- Light Kit
- Mounting Hardware
- Remote Control
- Shade
- English User Manual

4. Specifications

Brand	APBEAMLighting
Model Number	FS8858
Color	Brushed Nickel
Material	Acrylic, Acrylonitrile Butadiene Styrene, Iron
Product Dimensions (L x W x H)	43.2L x 33W x 15.2H Centimetres
Fan Diameter (Blades Extended)	28 inches (71.1 cm)
Lampshade Diameter	30.5 cm
Power Source	DC
Voltage	24 Volts (DC)
Wattage	24 watts
Light Source	LED
Brightness	1680 Lumens (Max)
Color Temperature	Adjustable (Warm, Natural, White - up to 6500K)
Control Method	Remote Control, App Control (Bluetooth)
Special Features	6 Speed, App Operable, LED Light, Remote Controlled, Timer, Retractable Blades, Reversible Motor



Figure 1: Product Dimensions and Room Size Reference. The fan has a total diameter of 28 inches when blades are extended, with a lampshade diameter of 11.8 inches and a height of 11.4 inches. Suitable for rooms between 6 sq ft to 80 sq ft.

5. Setup and Installation

5.1 Pre-Installation Checklist

- Ensure power is disconnected at the main circuit breaker.
- Confirm all package contents are present and undamaged.
- Gather necessary tools: screwdriver, wire strippers, electrical tape, ladder.
- Consult a qualified electrician if you are unsure about wiring procedures.

5.2 Installation Steps

The APBEAMLighting FS8858 is designed for simple installation. Follow the instructions provided in the included English manual. For visual guidance, an installation video is available:

▶ **Watch video online**
Installation demonstration and functional demonstration

Video 1: Installation and Functional Demonstration. This video provides a step-by-step guide for installing the ceiling fan and demonstrates its various functions.

General installation typically involves:

1. Mounting the bracket to the ceiling junction box.
2. Connecting the electrical wires (live, neutral, ground) according to color codes.
3. Attaching the fan motor assembly to the mounting bracket.
4. Connecting the light kit wires and securing the lampshade.
5. Restoring power and testing the fan and light functions.

6. Operating Instructions

6.1 Remote Control

The included remote control allows full functionality of the fan and light. Ensure batteries are correctly inserted. The remote can control power, fan speed, light brightness, color temperature, fan direction, and timer settings.

6.2 Light Functions

The integrated LED light offers adjustable brightness and three color temperature options:

- **Warm Light (3000K):** Ideal for creating a cozy and relaxing atmosphere.
- **Natural Light (4500K):** A balanced light suitable for general tasks.
- **White Light (6500K):** Bright and clear, suitable for focused work or reading.

Brightness can be adjusted from 10% to 100% for each color temperature.



Figure 2: Adjustable 3 Color Temperature and Brightness. The fan light offers warm, natural, and cool light options, with brightness adjustable from 10% to 100%.

6.3 Fan Functions

The fan features retractable blades and a reversible motor for year-round comfort.

- **6 Fan Speeds:** Adjust airflow from a gentle breeze (speeds 1-2) for relaxation, moderate ventilation (speeds 3-4) for cooling, to strong airflow (speeds 5-6) for rapid heat dissipation.
- **Reversible Motor:** The forward mode creates a downward airflow for cooling during warmer months. The reverse mode creates an upward airflow to circulate warm air during colder months.
- **Retractable Blades:** The ABS blades can be retracted when the fan function is not needed, transforming the unit into a sleek ceiling light fixture.



Figure 3: 6 Wind Speed Settings. The fan offers six speeds for various comfort levels, from gentle to strong airflow.



Figure 4: Reversible Function. The fan can operate in forward mode for cooling or reverse mode for improved air circulation.

6.4 Timer Function

Set the fan and/or light to turn off automatically after 1, 4, or 8 hours using the remote control or app. This function allows for energy saving and convenience.

6.5 App Control

Download the dedicated app to control all fan and light functions from your smartphone or tablet via Bluetooth connectivity. The app provides an alternative control method to the remote control.

7. Maintenance

Regular maintenance ensures optimal performance and longevity of your ceiling fan.

- **Cleaning:** Turn off power before cleaning. Use a soft, damp cloth to wipe down the fan housing and blades. Do not use abrasive cleaners or solvents.
- **Blade Inspection:** Periodically check the retractable blades for any signs of damage or wear.

- **Tighten Fasteners:** Over time, some fasteners may become loose. Check and tighten all screws and connections annually.
- **Light Source:** The LED light source is designed for long life and is not user-replaceable. If the LED light fails, contact customer support.

8. Troubleshooting

Before attempting any repairs, ensure power is disconnected at the circuit breaker.

Problem	Possible Cause	Solution
Fan does not start	No power supply; Loose wire connections; Remote control battery low.	Check circuit breaker; Ensure all wires are securely connected; Replace remote control batteries.
Light does not turn on	No power supply; Loose wire connections; LED driver issue.	Check circuit breaker; Ensure all wires are securely connected; Contact customer support if LED driver is suspected.
Remote control not working	Batteries are dead or incorrectly inserted; Remote not paired.	Replace batteries, ensuring correct polarity; Refer to pairing instructions in the full manual.
Excessive wobbling	Loose mounting bracket; Unbalanced blades.	Ensure mounting bracket is securely fastened; Check for any obstructions or damage to blades.

9. Warranty Information

Warranty details for the APBEAMLighting FS8858 ceiling fan are typically provided with the product packaging or can be obtained by contacting APBEAMLighting customer support. Please retain your proof of purchase for warranty claims.

10. Customer Support

For any questions, concerns, or technical assistance regarding your APBEAMLighting FS8858 ceiling fan, please contact our professional support team. Your satisfaction is our priority.
Contact Information: Please refer to the contact details provided in your product packaging or visit the official APBEAMLighting website for support options.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DTPQ3DLF

More documents and user manuals: **https://manuals.plus/**