

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Ozone](#) /

› [Ozone Elite HD Camera Smart Door Lock \(Model OZLK00915\) User Manual](#)

Ozone OZLK00915

Ozone Elite HD Camera Smart Door Lock User Manual

Model: OZLK00915

1. INTRODUCTION

Thank you for choosing the Ozone Elite HD Camera Smart Door Lock. This manual provides essential information for the proper installation, operation, and maintenance of your smart lock. Please read it thoroughly before use to ensure optimal performance and security.

2. PRODUCT OVERVIEW

The Ozone Elite HD Camera Smart Door Lock offers advanced security and convenience features, including multiple unlocking methods and an integrated HD camera for enhanced monitoring.

Key Features:

- **Advanced Biometric Technology:** Fingerprint recognition for quick and secure access.
- **Mobile App Control:** Manage access, view history, and unlock remotely via the OzoLife App (Wi-Fi enabled).
- **Multiple Access Methods:** Supports up to 100 fingerprints, 100 passwords, and 100 RFID cards, plus emergency keys.
- **Integrated HD Camera:** Provides real-time video feed and two-way communication.
- **Durable Construction:** Made from high-quality Acrylonitrile Butadiene Styrene and Aluminium for long-lasting performance.
- **Reversible Handle:** Suitable for both left and right-handed doors.

Components:

The package includes the main lock body, a user manual, a warranty card, two emergency keys, and two RFID cards.



Image: Overview of the Ozone Elite HD Camera Smart Door Lock and its included components.

3. SETUP AND INSTALLATION

This smart door lock is designed to fit wooden and metal doors with a thickness ranging from 35mm to 110mm. Professional installation is recommended for optimal performance.

3.1 Physical Installation:

- 1. Prepare the Door:** Ensure your door meets the specified thickness requirements. Refer to the detailed drilling template in the included user manual for precise hole placement.
- 2. Install Mortise Lock:** Insert the mortise lock into the door edge and secure it with screws.
- 3. Install Front Panel:** Connect the necessary cables from the front panel to the mortise lock. Position the front panel on the exterior side of the door.
- 4. Install Rear Panel:** Connect the cables from the front panel to the rear panel. Secure the rear panel on the interior side of the door using the provided screws.
- 5. Insert Batteries:** Open the battery cover on the rear panel and insert the required batteries (not included).
- 6. Test Operation:** Verify that the handle operates smoothly and the latch retracts correctly.



Image: The smart door lock fully installed on a wooden door, showcasing its sleek design.

3.2 App Pairing (OzoLife App):

- 1. Download App:** Download the OzoLife App from your smartphone's app store.
- 2. Create Account:** Register for a new account or log in if you already have one.
- 3. Add Device:** Follow the in-app instructions to add your Ozone Smart Door Lock. Ensure your phone is connected to a 2.4GHz Wi-Fi network during the pairing process.
- 4. Configure Settings:** Once paired, you can configure user access, passwords, RFID cards, and other settings through the app.

4. OPERATING THE SMART DOOR LOCK

The Ozone Elite HD Camera Smart Door Lock offers multiple convenient ways to unlock your door.

4.1 Unlocking Methods:


- Fingerprint:** Place your registered finger on the fingerprint sensor. The lock will unlock upon successful recognition.
- Password:** Enter your registered password on the keypad, followed by the '#' key.

- **RFID Card:** Present your registered RFID card to the card reader area on the lock.
- **OzoLife App:** Use the OzoLife App on your smartphone to remotely unlock the door via Wi-Fi.
- **Emergency Key:** In case of power failure or other emergencies, use the physical emergency key to unlock the door.

5-WAYS TO ACCESS YOUR DOOR



Fingerprint



Password



RFID Card



OzoLife App



Emergency Key

Image: Visual representation of the five available access methods for the smart lock.

4.2 HD Camera and Communication:

- **Real-time Monitoring:** View live video feed from the integrated HD camera through the OzoLife App.
- **Two-Way Communication:** Engage in real-time audio communication with visitors at your door using the app.
- **Doorbell Function:** Visitors can press the doorbell button on the lock, sending a notification to your smartphone.



SEE WHO'S AT YOUR DOOR,
ANYTIME, ANYWHERE.

Image: Remote viewing and interaction with visitors via the OzoLife App.

4.3 Additional Functions:

- **Night Latch:** Engage the night latch for added security from the inside.
- **Passage Mode:** Temporarily disable automatic locking for continuous access during specific periods.
- **Child Safety Button:** Prevents accidental unlocking from the inside by children.
- **Break-in Alarm:** The lock will trigger an alarm if tampering or forced entry is detected.

5. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your smart door lock.

- **Cleaning:** Wipe the lock's surface with a soft, dry cloth. Avoid using abrasive cleaners or solvents that may damage the finish or electronic components.
- **Battery Replacement:** The lock features a low battery indicator. Replace all batteries promptly when the indicator appears to avoid being locked out. Use high-quality alkaline batteries.
- **Sensor Care:** Keep the fingerprint sensor and camera lens clean and free from dust or smudges for accurate operation.

- **Mechanical Check:** Periodically check that all screws are tight and the handle operates smoothly.

6. TROUBLESHOOTING

If you encounter issues with your smart door lock, refer to the following common problems and solutions:

- **Lock not responding:** Check battery levels. If batteries are low or depleted, replace them. Use the emergency key if necessary.
- **Fingerprint not recognized:** Ensure your finger is clean and dry. Re-register your fingerprint if the issue persists.
- **App connectivity issues:** Verify your Wi-Fi connection. Ensure the lock is within range of your Wi-Fi router. Restart the app and the lock if needed.
- **Incorrect password/RFID card:** Double-check the entered password or ensure the RFID card is correctly registered.
- **Handle not engaging:** Check for any obstructions in the door frame or latch mechanism. Ensure the lock is properly installed.

For further assistance, please contact Ozone customer support.

7. SPECIFICATIONS

Feature	Specification
Brand	Ozone
Model Name	OZ-FDL-02-LIFE-NXT-i BLACK
Item Model Number	OZLK00915
Lock Type	Biometric
Special Features	Fingerprint, Mobile App, Password Unlocking, RFID Card, HD Camera
Material	Acrylonitrile Butadiene Styrene, Aluminium
Item Dimensions (L x W x H)	20 x 72 x 388 Millimeters
Item Weight	3.5 Kilograms
Connectivity Protocol	Wi-Fi
Control Method	App, Google Assistant
Door Thickness Compatibility	35-110 mm

8. WARRANTY AND SUPPORT

Your Ozone Elite HD Camera Smart Door Lock comes with a warranty. Please refer to the included Warranty Card for detailed terms and conditions.

Customer Support:

For any queries, technical assistance, or service requests, please contact Ozone customer support:

- **Phone:** +91-9310012300
- **Email:** customercare@ozone.in

Manufacturer: Ozone Secutech PVT LTD
Address: H-40; Bali Nagar; New Delhi-110015