

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Moukey](#) /

› [Moukey MAMP1 Stereo Receiver User Manual](#)

Moukey MAMP1

Moukey MAMP1 Stereo Receiver User Manual

Model: MAMP1 | Brand: Moukey

INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your Moukey MAMP1 2.0 Channel Bluetooth Stereo Receiver. This amplifier is designed to deliver powerful, high-quality audio for various applications, including home theater systems, acoustic setups, and karaoke. Please read this manual thoroughly before using the device to ensure proper and safe operation.

SAFETY INSTRUCTIONS

- Do not expose this unit to rain or moisture to prevent fire or shock hazards.
- Do not open the casing. There are no user-serviceable parts inside. Refer all servicing to qualified service personnel.
- Ensure proper ventilation. Do not block ventilation openings.
- Place the unit on a stable, flat surface away from direct sunlight, heat sources, or excessive dust.
- Use only the specified power supply voltage.
- Disconnect the power cord from the outlet if the unit will not be used for a long period.
- Keep out of reach of children.

PACKAGE CONTENTS

Please check that all items are present in the package:

- Moukey MAMP1 Stereo Receiver
- Remote Controller
- FM Antenna
- User Manual (this document)

PRODUCT OVERVIEW

Front Panel Controls and Inputs



Figure 1: Front view of the Moukey MAMP1 Stereo Receiver, showing all controls, inputs, and the included remote control.

The front panel of the MAMP1 receiver provides access to all primary controls and convenient input options:

1. **Power Switch:** Toggles the unit on/off.
2. **USB / SD Card Slots:** For playing audio files from USB drives (up to 32GB) and SD cards (up to 16GB).
3. **Mode Button:** Cycles through input modes (Bluetooth, USB, SD, AUX, FM).
4. **BT Button:** Directly switches to Bluetooth mode.
5. **Prev/Next Buttons:** For track navigation in USB/SD/Bluetooth modes or station tuning in FM mode.
6. **Play / Pause Button:** Controls playback for USB/SD/Bluetooth.
7. **LED Display:** Shows current mode, track information, and FM frequency.
8. **Folder / Track Knob:** Navigates folders and tracks on USB/SD.
9. **Master Volume Knob:** Adjusts the overall output volume.
10. **Headphone Jack (1/4"):** For private listening.
11. **Microphone Inputs (MIC 1, MIC 2 - 1/4"):** Connect microphones for karaoke or public address.
12. **Microphone Volume Knob:** Adjusts the volume of connected microphones.
13. **Echo Knob:** Controls the echo effect for microphones.
14. **Bass Knob:** Adjusts the low-frequency audio output.
15. **Treble Knob:** Adjusts the high-frequency audio output.

16. **Balance Knob:** Adjusts the left/right channel balance.
17. **AUX Input Jack (3.5mm):** For connecting external audio devices.
18. **Input Selector Knob:** Selects between CD/DVD RCA inputs and the front panel AUX/MP3/FM/BT inputs.



Figure 2: Detailed diagram of the Moukey MAMP1 front panel, labeling each control and input.

EXPANDED COMPATIBILITY




Figure 3: Visual representation of the Moukey MAMP1's expanded compatibility, showing various input types like FM, USB, SD, AUX, CD/DVD, Microphone, Headphones, Speakers, and Bluetooth.

Rear Panel Connections




Figure 4: Rear view of the Moukey MAMP1 Stereo Receiver, showing all input and output connections.

The rear panel provides essential connections for your audio system:

- 1. Audio Input Jack for DVD (RCA):** Connect audio output from a DVD player or similar source.
- 2. Audio Input Jack for CD (RCA):** Connect audio output from a CD player or similar source.
- 3. Line Out Jack (RCA):** Provides an audio output signal for connecting to another amplifier or recording device.
- 4. FM Antenna Jack:** Connect the included FM antenna for radio reception.
- 5. Speaker Output Jacks (Banana Plug/Binding Post):** Connect your passive speakers.
- 6. Voltage Selector:** Allows selection between 110V and 220V power input (ensure this matches your local voltage before connecting power).
- 7. Power Cable Input:** Connect the AC power cord.

SETUP

Speaker Connection

The MAMP1 uses banana plug/binding post terminals for speaker connections. Ensure your speakers are passive and match the impedance requirements (typically 4-16 ohms).



Figure 5: Diagram illustrating how to connect speaker wires to the Moukey MAMP1 receiver.

- 1. Prepare Wires:** If using bare speaker wire, strip approximately 10mm (0.4 inches) of insulation from the ends of each wire. Twist the exposed strands tightly.
- 2. Loosen Terminal:** Rotate and loosen the speaker knob on the rear panel.
- 3. Insert Wire:** Insert the bare wire into the hole in the center of the binding post. Ensure no stray strands touch the other terminal.
- 4. Tighten Terminal:** Tighten the knob to secure the wire firmly.
- 5. Polarity:** Ensure correct polarity (+ to + and - to -) for both speakers and the receiver to avoid phase issues.

Connecting Audio Sources

- RCA Inputs (CD/DVD):** Connect audio output from your CD player, DVD player, or other audio sources using RCA cables to the corresponding "CD" or "DVD" input jacks on the rear panel.

- **AUX Input (3.5mm):** Connect smartphones, tablets, or other devices with a 3.5mm audio output to the "AUX" jack on the front panel.
- **USB/SD Card:** Insert a USB flash drive (up to 32GB) or an SD card (up to 16GB) into the respective slots on the front panel.
- **Microphones:** Plug 1/4" microphones into the "MIC 1" or "MIC 2" inputs on the front panel.
- **FM Antenna:** Connect the included FM antenna to the "FM ANTENNA" jack on the rear panel for radio reception.

Power Connection

Before connecting power, ensure the Voltage Selector on the rear panel is set to match your local power supply (110V or 220V). Then, connect the power cable to the receiver and plug it into a wall outlet.

OPERATING INSTRUCTIONS

Power On/Off

Press the "POWER" switch on the front panel to turn the unit on or off. The LED display will illuminate when the unit is powered on.

Input Selection

Use the "MODE" button on the front panel or the "Input Selector" knob to choose your desired audio source (Bluetooth, USB, SD, AUX, FM, CD, DVD).

Bluetooth Operation

BLUETOOTH 5.0 FOR HI-FI STREAMING



Figure 6: The Moukey MAMP1 receiver demonstrating Bluetooth 5.0 connectivity with a smartphone.

1. Press the "BT" button or cycle the "MODE" button until "BLUE" appears on the LED display.
2. On your smartphone or Bluetooth-enabled device, search for "Moukey MAMP1" in the Bluetooth settings.
3. Select "Moukey MAMP1" to pair. Once connected, you will hear a confirmation tone.
4. You can now stream audio wirelessly from your device to the receiver. Control playback (play/pause, next/prev track) using the buttons on the receiver or your connected device.

USB/SD Card Playback

Insert a USB drive or SD card with audio files into the corresponding slot. The unit will automatically switch to USB/SD mode and begin playback. Use the "Prev/Next" and "Play/Pause" buttons to control playback. The "Folder/Track" knob allows navigation through folders and tracks.

Note: The unit supports USB drives up to 32GB and SD cards up to 16GB. Larger capacities may not be recognized.

FM Radio Operation

Ensure the FM antenna is connected. Press the "MODE" button until "FM" appears on the display.

- **Auto Scan:** Press and hold the "Play/Pause" button to initiate an auto-scan for available FM stations. The unit will save detected stations.
- **Manual Tuning:** Use the "Prev/Next" buttons to manually tune to specific frequencies or cycle through saved stations.

Microphone and Karaoke Functions

DUAL MIC INPUT



Figure 7: Two individuals using microphones connected to the Moukey MAMP1 receiver for a karaoke session.

Connect up to two 1/4" microphones to the "MIC 1" and "MIC 2" inputs on the front panel.

- **MIC VOL:** Adjusts the overall volume of both microphones.
- **ECHO:** Adjusts the echo effect applied to the microphone audio.
- Ensure the main "Master Volume" is also adjusted appropriately for the desired output level.



Figure 8: Close-up view of the Moukey MAMP1's Bass and Treble adjustment knobs.

- **BASS:** Rotate the Bass knob to increase or decrease the low-frequency response of the audio.
- **TREBLE:** Rotate the Treble knob to increase or decrease the high-frequency response of the audio.
- **BALANCE:** Adjust the Balance knob to shift the audio output between the left and right speakers.

MAINTENANCE

- Cleaning:** Use a soft, dry cloth to clean the exterior of the unit. Do not use liquid cleaners or aerosols.
- Ventilation:** Ensure the ventilation openings are clear of dust and debris to prevent overheating.
- Storage:** If storing the unit for an extended period, disconnect it from power and store it in a cool, dry place.

TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Power cord not connected; Power switch off; Voltage selector incorrect.	Ensure power cord is securely plugged in. Turn power switch ON. Verify voltage selector matches local power.
No sound output	Incorrect input selected; Volume too low; Speakers not connected properly; Source device issue.	Select correct input. Increase Master Volume. Check speaker connections and polarity. Verify source device is playing audio.
Bluetooth not connecting	Not in Bluetooth mode; Device too far; Device already connected to another unit.	Switch to Bluetooth mode. Ensure device is within 40ft range. Disconnect from other Bluetooth devices and try pairing again.
USB/SD card not recognized	Card/drive capacity too large; Incorrect file format; Card/drive not inserted correctly.	Ensure capacity is within limits (USB 32GB, SD 16GB). Use supported audio formats. Reinsert card/drive firmly.
Microphone echo/volume issues	MIC VOL or ECHO knobs incorrectly set.	Adjust MIC VOL and ECHO knobs to desired levels.
Poor FM reception	Antenna not connected or positioned poorly.	Connect FM antenna securely. Adjust antenna position for better signal.

SPECIFICATIONS

Feature	Detail
Brand	Moukey
Model Number	MAMP1
Peak Power Output	220 Watts
Number of Channels	2.0
Connectivity Technology	RCA, Bluetooth 5.0, USB, SD, 3.5mm AUX
Compatible Devices	Smartphone, Tablet, iPad, iPhone, Computer, Speaker

Feature	Detail
Audio Output Mode	Stereo
Microphone Inputs	2 x 1/4" with Echo Control
USB/SD Card Support	USB up to 32GB, SD up to 16GB
FM Radio	Built-in with LED screen
Dimensions (L x W x H)	Approx. 10 x 8 x 4 inches (25 x 21.3 x 9.5 cm)
Item Weight	6.87 pounds

COMPACT BUT POWERFUL



Figure 9: The Moukey MAMP1 receiver with its compact dimensions highlighted.

WARRANTY AND SUPPORT


Moukey products typically come with a standard manufacturer's warranty. For specific warranty details, including duration and coverage, please refer to the warranty card included with your product or visit the official Moukey website. For technical support, troubleshooting assistance beyond this manual, or warranty claims, please contact Moukey customer service through their official channels.

You can often find support contact information on the manufacturer's website or on the product packaging.

© 2025 Moukey. All rights reserved.

Related Documents - MAMP1

	<p>Moukey MAMP1 Digital Karaoke Amplifier User Manual</p> <p>Comprehensive user manual for the Moukey MAMP1 Digital Karaoke Amplifier, detailing features, operation, controls, and safety instructions for home theater systems.</p>
	<p>Moukey MAMP1 Amplifier Safety Instructions and Cautions</p> <p>This document provides essential safety instructions and operating precautions for the Moukey MAMP1 Amplifier (Model MAMP1). It covers warnings related to electrical hazards, water, fire, proper assembly, placement, connection, operation, and maintenance. Includes regulatory compliance information (FCC, IC, CE) and manufacturer details.</p>
	<p>Moukey MAMP1 Stereo Power Amplifier User Manual</p> <p>This user manual provides detailed instructions for operating the Moukey MAMP1 Stereo Power Amplifier, covering features, safety, connections, basic operation, and troubleshooting.</p>
	<p>Moukey MAMP1 Amplifier Safety Instructions and Cautions</p> <p>Comprehensive safety instructions and cautions for the Moukey MAMP1 amplifier, covering power, operation, maintenance, and important warnings for safe use.</p>
	<p>Moukey MAMP1 Troubleshooting Guide</p> <p>Troubleshooting common issues with the Moukey MAMP1 amplifier, including sound quality, compatibility, product not working, and buzzing feedback.</p>



Moukey MAMP1 Troubleshooting Guide

Troubleshooting common issues with the Moukey MAMP1 amplifier, including low volume, sound quality problems, compatibility, product not working, and buzzing feedback.

Documents - Moukey – MAMP1



[\[pdf\] User Manual](#)

MAMP1 2 20211208 Administrator user manual p2 GUANGZHOU RANTION TECHNOLOGY CO LTD MAMP1 Power amplifier 2AV7N 2AV7NMAMP1 mamp1


Espaol MODELO:**MAMP1** W Sistema estreo de cine en casa, Transmision por Conexin Inalambrica,Lectores de MP3 / USB / SD, Radio FM, Receptor amplificador hibrido MANUAL DE USUARIO 24 Espaol Lea las instrucciones antes de usar.. Te familiarizarn completamente con sus caractersticas. El producto adopta tc...
lang:es score:39 filesize: 3.98 M page_count: 24 document date: 2022-02-25



[Moukey MAMP1 Digital Karaoke Amplifier User Manual](#)

Comprehensive user manual for the Moukey MAMP1 Digital Karaoke Amplifier, detailing features, operation, controls, and safety instructions for home theater systems.


lang:en score:37 filesize: 3.25 M page_count: 25 document date: 2022-03-10



[Moukey MAMP1 Amplifier Safety Instructions and Cautions](#)

Comprehensive safety instructions and cautions for the Moukey MAMP1 amplifier, covering power, operation, maintenance, and important warnings for safe use.


lang:en score:33 filesize: 1.2 M page_count: 8 document date: 2024-11-06



[Moukey MAMP1 Amplifier Safety Instructions and Cautions](#)

This document provides essential safety instructions and operating precautions for the Moukey MAMP1 Amplifier (Model MAMP1). It covers warnings related to electrical hazards, water, fire, proper assembly, placement, connection, operation, and maintenance. Includes regulatory compliance information (FCC, IC, CE) and manufacturer details.

lang:en score:32 filesize: 1.2 M page_count: 8 document date: 2024-11-06




[\[pdf\] Frequently Asked Questions SAR Rating](#)

FAQ Amplificatore Audio Stereo 220W Bluetooth 5.0 Moukey 2 Canali HiFi Portatile per Casa con USB SD AUX RCA MIC in Echo Radio LED MAMP1 Amazon it Elettronica 71ob0m4ZdeL m media amazon images I |||

MOUKEY MAMP1 FAQ I canali radio non possono essere salvati quando si utilizza il telecomando per la ricerca: A: Quando si utilizza il telecomando, possibile inserire direttamente la frequenza per cercare un canale radio ma non pu essere salvato . Inoltre, non necessario cercare in anticipo i canali radio per salvare...

lang:en score:31 filesize: 155.27 K page_count: 1 document date: 2023-10-20




[\[pdf\] Frequently Asked Questions](#)

FAQ Amazon Moukey Home Audio Amplifier Stereo Receivers with Bluetooth 5.0 220W 2 Channel Power System w USB SD AUX RCA MIC in Echo LED for Karaoke Theater Speakers MAMP1 Electronics 61rFbss FBL m media amazon images I |||

MOUKEY MAMP1 FAQ The radio channels can not be saved when using the remote for searching: A: When using the remote, you can directly enter the frequency to search for a radio channel But it cannot be saved . In addition, there is no need to search for radio channels on the amplifier in advance and...


lang:en score:31 filesize: 74.17 K page_count: 1 document date: 2023-10-20



[Moukey MAMP1 Troubleshooting Guide](#)

Troubleshooting common issues with the Moukey MAMP1 amplifier, including low volume, sound quality problems, compatibility, product not working, and buzzing feedback.

lang:en score:30 filesize: 66.83 K page_count: 1 document date: 2025-07-08



[\[pdf\]](#)

Statement USER model difference letter GUANGZHOU RANTION TECHNOLOGY CO LTD MAMP1

Power amplifier 2AV7N 2AV7NMAMP1 mamp1

GUANGZHOU RANTION TECHNOLOGY CO., LTD. Room 432, Building 4, No. 50 Nanxiang 1st Road, Huangpu District, Guangzhou, China Statement Product: Power amplifier Model: **MAMP1** Additional Model: **MAMP2, MAMP3, MAMP4, MAMP6, MAMP7, MAMP8, MAMP9, MAMP10, MK0114, MK0101, MK0152, MK0215, MK0173** Trademark: Moukey

lang:tl score:29 filesize: 86.28 K page_count: 1 document date: 2022-03-10

MOUKEY MAMP1
FAQ

▶ リモコンで操作したラジオチャンネルは保存できません:

A.
リモコンを使用する場合、別途電源直通入力してラジオチャンネルを設定することができます。また、本機にアンプでラジオチャンネルを設定して保存する場合はできません。

▶ 接続したマイクが動作しません:

A.
マイクのインピーダンスは 400Ω以上である必要があります。400Ωを超えると動作が悪くなることがあります。

[pdf] Frequently Asked Questions

MOUKEY MAMP1 FAQ > A

amazon images | |||

MOUKEY MAMP1 FAQ : A : A: 600600 ...

lang:tl score:29 filesize: 122.77 K page_count: 1 document date: 2023-10-20

MouKey



Audio Amplifier

MAMP5

Operation Safety Instructions and Caution. | Consignes de Sécurité et Précautions
Sicherheitshinweise und Vorsichtsmahnahmen | Instrucciones de seguridad y precauciones
Norme di Sicurezza e Precauzioni d'Uso | 安全上のご注意と使用上の注意

Monkey MAMP1

TROUBLESHOOTING

▶ The volume of the speaker is very low and sound quality not as good as expected.
A.
1. Speaker Connection: Ensure your speakers match the amplifier's output: 20W RMS per channel.
2. Phono/Line Connection: A separate phono (not included) is required for proper volume when connecting to a phono/line RCA connection is not recommended.

▶ The amplifier is not compatible with their existing setup.
A.
1. Speaker Connection: Ensure your speakers match the amplifier's output: 20W RMS per channel.
2. Line Input Selection: Please select the corresponding mode correctly before FM / Bluetooth / MP3, etc.

▶ Product stopped working.
A.
1. The product is connected to a power source (AC): 115V / 60Hz
2. Prevent product overheat. If you connect 4 speakers with low impedance and high power, and turn up the volume very high, the product may be damaged.

▶ The amplifier has a buzzing feedback issue.
A.
Turning off the amplifier via the remote does not cut off the power supply. Please disconnect the power supply via the small button on the socket after turning off to avoid buzzing noise.

Moukey MAMP1 Troubleshooting Guide

Troubleshooting common issues with the Moukey MAMP1 amplifier, including sound quality, compatibility, product not working, and buzzing feedback.

lang:en score:19 filesize: 66.83 K page_count: 1 document date: 2025-07-08