**Saved from manuals.plus.**
**Open the live page for links to other documents and user manuals.**



### Weejector R2CT

# Weejector 4K Projector User Manual

Model: R2CT

## 1. Introduction

Thank you for purchasing the Weejector 4K Projector. This manual provides essential information for setting up, operating, and maintaining your projector. Please read this manual thoroughly before use to ensure proper operation and to maximize your viewing experience. Keep this manual for future reference.




Image 1.1: Weejector 4K Projector with its integrated smart system and streaming capabilities.

## 2. Safety Information

To ensure safe operation and prevent damage, please observe the following safety precautions:

- Do not block the ventilation openings. Ensure adequate airflow around the projector.
- Do not expose the projector to rain or moisture to avoid electric shock or fire.
- Use only the power adapter supplied with the projector.
- Avoid looking directly into the projector lens when the lamp is on.
- Place the projector on a stable, level surface.

- Do not attempt to disassemble or repair the projector yourself. Contact qualified service personnel.

## 3. Package Contents

Verify that all items are present in your package:

- Weejector 4K Projector
- HDMI Cable
- User Manual
- Warranty Card
- Remote Control
- Power Adapter

## 4. Product Overview

The Weejector 4K Projector is designed for versatile home cinema and presentation use, featuring an integrated smart operating system, advanced connectivity, and flexible projection options.




Image 4.1: Overview of the Weejector 4K Projector's key features.

## 5. Setup

### 5.1 Placement Options

The Weejector 4K Projector offers multiple placement options to suit your environment:

- **Table Placement:** Position the projector on a flat, stable surface.
- **Ceiling Mount:** The projector can be inverted and mounted to the ceiling for a permanent setup.
- **Tripod Mount:** Utilize the tripod screw hole for flexible positioning with a compatible tripod.




Image 5.1: Various placement options for the projector, illustrating screen size flexibility.

## 5.2 Power Connection

Connect the power adapter to the projector's power input port and then plug it into a wall outlet. The projector will power on or enter standby mode.

## 5.3 Initial Image Adjustment (Focus, Keystone, Zoom)

After powering on, adjust the image for clarity and shape using the remote control:

- **Electric Focus:** Use the remote to achieve a sharp image.
- **4P/4D Keystone Correction:** Correct distorted images (trapezoidal effect) from off-angle projections. This allows individual adjustment of the four corners or four points of the screen.
- **Electric Zoom:** Adjust the screen size from 1% to 100% using the remote without moving the projector.




Image 5.2: Adjusting focus, keystone, and zoom using the remote control.

## 6. Operating Instructions

### 6.1 Smart Operating System and Built-in Apps

The projector features an integrated smart operating system, allowing direct access to various streaming applications without external devices. You can download and use over 1000 applications, including Netflix, YouTube, Prime Video, Hulu, and Disney+.




Image 6.1: The projector's interface showing a selection of built-in streaming applications.

*Note: Due to copyright restrictions, some applications may not be directly usable on the projector and may require an external TV stick (not included).*

## 6.2 Connectivity (WiFi 6 and Bluetooth 5.2)

The projector supports advanced wireless connectivity for seamless integration with your devices.

- **WiFi 6:** Supports both 2.4GHz and 5GHz bands, offering faster speeds, improved performance, and greater efficiency compared to WiFi 5. This ensures smoother streaming and gaming.
- **Bluetooth 5.2:** Dual-channel Bluetooth allows connection to external audio devices like soundbars or headphones for an enhanced audio experience. You can also use the projector as a standalone Bluetooth speaker.




Image 6.2: Wireless connectivity options including WiFi 6 and Bluetooth 5.2.

## 6.3 Input Sources

The projector is equipped with multiple interfaces for connecting various devices:

- **HDMI:** Connect laptops, gaming consoles (PS5), Blu-ray players, etc.
- **USB:** Play media directly from USB drives.
- **3.5mm Audio:** Connect external speakers or headphones.

## 6.4 180° Rotation Feature

The projector's unique 180° rotation capability allows you to project images onto walls, ceilings, or floors, providing maximum flexibility for viewing angles and room layouts.




Image 6.3: The projector's 180° rotation feature for flexible projection.

## 7. Maintenance

Proper maintenance ensures the longevity and optimal performance of your projector.

- **Cleaning the Lens:** Use a soft, lint-free cloth specifically designed for optical lenses. Do not use abrasive cleaners.
- **Cleaning the Exterior:** Wipe the projector's exterior with a soft, dry cloth. For stubborn stains, use a slightly damp cloth and then dry thoroughly.
- **Ventilation:** Regularly check that the ventilation openings are clear of dust and debris to prevent overheating.
- **Storage:** When not in use for extended periods, store the projector in a cool, dry place, away from direct sunlight and extreme temperatures.

## 8. Troubleshooting

If you encounter issues with your Weejector 4K Projector, refer to the following common problems and solutions:

| Problem | Possible Cause | Solution |
|---|---|---|
| No image projected | Power cable disconnected; Input source not selected; Projector in standby mode. | Check power connection; Select correct input source (HDMI, USB); Press power button on remote/projector. |
| Image is blurry | Focus not adjusted; Projector too close/far from screen. | Adjust electric focus using the remote control. Ensure projector is within optimal projection distance. |
| Image is distorted (trapezoid) | Projector not perpendicular to screen. | Use 4P/4D keystone correction to adjust the image shape. |
| No sound | Volume too low; External audio device not connected properly; Mute enabled. | Increase volume; Check Bluetooth connection or 3.5mm cable; Disable mute. |
| Cannot connect to Wi-Fi/Bluetooth | Incorrect password; Device out of range; Network issue. | Verify password; Move projector closer to router/device; Restart projector and router. |

## 9. Specifications

| Feature | Description |
|---|---|
| Brand | Weejector |
| Model Number | R2CT |
| Native Resolution | 1920 x 1080 (Full HD) |
| Supported Resolution | 4K |
| Brightness | 26000 Lumens |
| Contrast Ratio | 20000:1 |
| Display Type | LCD |
| Connectivity Technology | Wi-Fi 6 (2.4G + 5G), Bluetooth 5.2 |
| Hardware Interface | HDMI, USB, 3.5mm Audio |
| Compatibility | Speaker, Laptop, Smartphone, Television |
| Dimensions (L x W x H) | 17 x 12.7 x 21.5 cm |
| Product Weight | 1640 Grams |
| Special Features | Integrated 3D, Digital Keystone Correction, Built-in Speaker, Integrated Media Player, Portable, 180° Rotation, Electric Focus, Electric Zoom |

| Feature | Description |
| --- | --- |
| Recommended Uses | Business, Home Cinema, Gaming, Education |

## 10. Warranty and Support

The Weejector 4K Projector comes with a **2-year manufacturer's warranty**. For technical support, warranty claims, or any questions regarding your product, please contact Weejector customer service through the retailer's platform or the official Weejector support channels.
Please retain your proof of purchase for warranty validation.

© 2025 Weejector. All rights reserved.


### Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

**Name**

Anonymous

**Email**

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

**Question**

Example: How do I reset this device or fix this error?

**Details**

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question



**Open the live page**

**https://manuals.plus/asin/B0DZNQBF4M**

More documents and user manuals: **https://manuals.plus/**