

[Manuals+](#)

[Q & A](#) | [Deep Search](#) | [Upload](#)

QIAYA DJJ-SE10

QIAYA 10-in-1 Nut Milk Maker User Manual

Model: DJJ-SE10

1. INTRODUCTION

Thank you for choosing the QIAYA 10-in-1 Nut Milk Maker. This versatile appliance is designed to simplify the preparation of various homemade beverages and foods, including nut milks, juices, soups, and milkshakes. With its multi-functional capabilities, delay start, and self-cleaning features, it offers convenience and efficiency for your daily needs. Please read this manual thoroughly before first use to ensure safe and optimal operation.



Figure 1.1: The QIAYA 10-in-1 Nut Milk Maker shown with included accessories such as a measuring cup, cleaning brush, fine mesh filter, and nut milk bag.

2. IMPORTANT SAFETY INFORMATION

To reduce the risk of fire, electric shock, or injury, basic safety precautions should always be followed:

- Read all instructions before using the appliance.
- Do not immerse the main unit, cord, or plug in water or other liquids.
- Close supervision is necessary when any appliance is used by or near children.
- Unplug from outlet when not in use and before cleaning. Allow to cool before putting on or taking off parts.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- The use of accessory attachments not recommended by the appliance manufacturer may cause injuries.
- Do not use outdoors.

- Do not let cord hang over edge of table or counter, or touch hot surfaces.
- Do not place on or near a hot gas or electric burner, or in a heated oven.
- Always attach plug to appliance first, then plug cord into the wall outlet. To disconnect, turn any control to 'off', then remove plug from wall outlet.
- Do not use appliance for other than intended use.
- Exercise extreme caution when moving an appliance containing hot oil or other hot liquids.
- Ensure the lid is securely in place before operating the machine.
- Avoid contact with moving parts.

3. PRODUCT OVERVIEW

3.1 Components

The QIAYA Nut Milk Maker package includes the following items:

- QIAYA Nut Milk Maker (Main Unit)
- Recipe Book
- User Manual (this document)
- Measuring Cup
- Cleaning Brush
- Fine Mesh Filter
- Nut Milk Bag
- Power Cable

3.2 Key Features

- **Multi-Function:** Offers 10 functions including Nut Milk, Oat Milk, Soy Milk, Juice, Soup, Milkshake, and Boil Water.
- **Large Capacity:** 40oz (1.2L) capacity, suitable for preparing beverages for multiple servings.
- **Powerful Motor & Blades:** Equipped with an 800-watt motor and 10-tip stainless steel blades for efficient blending.
- **Delay Start:** Program the start time up to 12 hours in advance.
- **Keep Warm:** Automatically maintains temperature for up to 2 hours after preparation.
- **Self-Cleaning:** One-touch self-cleaning mode for convenient maintenance.
- **Safety Features:** Auto Shut Off and safety interlocks to prevent operation if not properly assembled.

40oz Large Capacity

Meets the drinking needs of 2-4 people



Figure 3.1: The 10-in-1 Multi-Function display, illustrating various beverage and food preparation options.

Delay Star Time

Up to 12 Hours



Figure 3.2: The 40oz (1.2L) capacity of the appliance, designed to meet the needs of 2-4 people.



Self-Cleaning

Free your hands for easier cleaning

Figure 3.3: The robust 10-tip stainless steel blades, engineered for efficient blending of various ingredients.

4. SETUP

4.1 Unpacking

Carefully remove all components from the packaging. Retain the packaging materials for future storage or transport. Verify that all listed components in Section 3.1 are present and undamaged.

4.2 Placement

Place the nut milk maker on a stable, flat, and dry surface. Ensure there is adequate ventilation around the appliance. Keep it away from heat sources and direct sunlight.

4.3 Initial Cleaning

Before first use, clean all parts that will come into contact with food. Wipe the exterior of the main unit with a damp cloth. For the interior, add water up to the MAX fill line and run the 'Cleaning' cycle once. Discard the water and rinse thoroughly.

Ensure all parts are dry before assembly.

5. OPERATING INSTRUCTIONS

5.1 Basic Operation

1. Add desired ingredients and water to the pitcher. Do not exceed the MAX fill line.
2. Securely place the lid on the pitcher. The machine will not operate if the lid is not properly seated.
3. Plug the power cable into a standard 120V AC outlet.
4. Press the 'Menu' button to cycle through the available functions (Soy Milk, Nut Milk, Oat Milk, Juice, Soup, Milkshake, Boil Water, Cleaning).
5. Once the desired function is selected, press the 'Start/Cancel' button to begin the operation.
6. The machine will automatically complete the cycle and beep when finished.
7. Unplug the appliance and carefully pour out the contents.

5.2 Specific Functions

The QIAYA Nut Milk Maker offers dedicated programs for various preparations:

- **Nut Milk / Oat Milk / Soy Milk:** These programs are optimized for processing nuts, oats, or soybeans into smooth, creamy plant-based milks. Follow the recipe book for recommended ingredient ratios.
- **Juice:** For blending fruits and vegetables into fresh juices.
- **Soup:** Designed for preparing hot soups, blending ingredients while heating.
- **Milkshake:** For creating thick, blended milkshakes.
- **Boil Water:** Functions as an electric kettle to boil water.

5.3 Delay Start Function

The delay start function allows you to set a deferred start time for your program, up to 12 hours in advance. This is ideal for preparing ingredients the night before and waking up to fresh milk or juice.

1. Add ingredients to the pitcher and secure the lid.
2. Select your desired function using the 'Menu' button.
3. Press the 'Timer' button. Each press will increase the delay time.
4. Once the desired delay time is set, press 'Start/Cancel' to confirm. The machine will display the countdown and begin operation after the set delay.

10 Stainless Steel Blades

Efficiently and easily blends health and flavor



Figure 5.1: The Delay Start feature allows programming the machine up to 12 hours in advance for convenient preparation.

5.4 Keep Warm Function

After certain hot programs (e.g., Soy Milk, Soup), the machine will automatically enter a 'Keep Warm' mode for up to 2 hours, maintaining the temperature of the contents. This feature ensures your beverages or soups remain warm and ready to serve.



10-In-1 Multi-Function

Meet your various needs



Nut Milk



Juice



Soy Milk



Boil Water



Oat Milk



Milkshake



Soup



Keep Warm



Cleaning



Timer

Figure 5.2: The control panel, showing the 'Menu' and 'Timer' buttons for function selection and delay programming.

6. CLEANING AND MAINTENANCE

6.1 Self-Cleaning Mode

The QIAYA Nut Milk Maker features a convenient one-touch self-cleaning mode:

1. After pouring out the beverage, immediately add water to the pitcher, up to the MAX fill line. A small amount of dish soap can be added for better cleaning.
2. Secure the lid.
3. Select the 'Cleaning' function using the 'Menu' button.
4. Press 'Start/Cancel' to begin the self-cleaning cycle.
5. Once the cycle is complete, discard the water and rinse the interior thoroughly with clean water.



Figure 6.1: The self-cleaning function in action, simplifying post-use cleanup.

6.2 Manual Cleaning

- **Exterior:** Wipe the exterior of the main unit with a soft, damp cloth. Do not use abrasive cleaners or immerse the main unit in water.
- **Lid and Accessories:** The lid, measuring cup, cleaning brush, fine mesh filter, and nut milk bag can be washed with warm, soapy water. Rinse thoroughly and allow to air dry completely before storing.
- Use the provided cleaning brush to remove any stubborn residue from the interior or around the blades.

6.3 Storage

Ensure the appliance is clean and dry before storing. Store in a cool, dry place, away from direct sunlight and out of reach of children.

7. TROUBLESHOOTING

If you encounter issues with your QIAYA Nut Milk Maker, please refer to the following common problems and solutions:

| Problem | Possible Cause | Solution |
|----------------------------------|---|--|
| Appliance does not turn on. | Not plugged in; power outlet issue; lid not properly secured. | Ensure power cord is securely plugged into a working outlet. Check that the lid is correctly and firmly seated on the pitcher. |
| Machine stops mid-cycle. | Overheating; insufficient water; ingredients too dense. | Unplug and let cool for 15-20 minutes. Ensure water level is between MIN and MAX lines. Reduce ingredient quantity or add more liquid. |
| Loud noise during operation. | Hard ingredients; machine not stable; foreign object. | Ensure ingredients are appropriate for blending. Place machine on a stable, flat surface. Check for any foreign objects inside the pitcher before operation. |
| Milk/Juice is not smooth enough. | Insufficient blending time; too many solids; ingredients not soaked (for some recipes). | Run the cycle again or use the 'Blend' function if available. Reduce the amount of solids. For certain nuts/beans, pre-soaking may improve texture. Use the fine mesh filter or nut milk bag for smoother results. |
| Self-cleaning not effective. | Residue dried; insufficient water. | Run self-cleaning immediately after use. Add water up to MAX line. For stubborn residue, use the cleaning brush manually. |

If the problem persists after attempting these solutions, please contact QIAYA customer support.

8. SPECIFICATIONS

| Feature | Specification |
|--------------------------------|---|
| Brand | QIAYA |
| Model Number | DJJ-SE10 |
| Color | White |
| Capacity | 40 Fluid Ounces (1.2 Liters) |
| Product Dimensions (D x W x H) | 7.87"D x 7.87"W x 13.77"H |
| Item Weight | 5.99 pounds |
| Power Source | AC |
| Voltage | 120 Volts |
| Motor Wattage | 800 Watts (implied by powerful motor description) |
| Blade Material | Stainless Steel |

| Feature | Specification |
|------------------|---|
| Special Features | Auto Shut Off, Automatic Cleaning, Keep Warm Setting, Multiple Speeds, Portable |

9. WARRANTY AND SUPPORT

9.1 Warranty Information

The QIAYA 10-in-1 Nut Milk Maker comes with a **2 Year Limited Warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from misuse, accident, alteration, neglect, or unauthorized repair.

9.2 Customer Support

For technical assistance, warranty claims, or any questions regarding your QIAYA Nut Milk Maker, please contact QIAYA customer support. Refer to the contact information provided on the product packaging or the official QIAYA website. Please have your model number (DJJ-SE10) and purchase date available when contacting support.