

Macap MI40 Touch

Macap MI40 Touch Instant Burr Coffee Grinder User Manual

Model: MI40 Touch

Brand: Macap

1. PRODUCT OVERVIEW

The Macap MI40 Touch Instant Burr Coffee Grinder is a high-performance appliance designed for precise and consistent coffee grinding. Featuring 65mm flat burrs, a responsive 3.5-inch touchscreen, and multiple operating modes, it is suitable for various brewing methods from espresso to cold brew. Its robust construction ensures quiet operation and stability.





Front view of the Macap MI40 Touch Instant Burr Coffee Grinder, showcasing its sleek chrome finish and integrated touchscreen display.


2. SAFETY INFORMATION

Please read all safety instructions carefully before operating the grinder to prevent injury or damage.

- Always unplug the grinder from the power outlet before cleaning, maintenance, or if it will be left unattended.
- Do not immerse the grinder, power cord, or plug in water or any other liquid.
- Keep hands and utensils out of the bean hopper and grind chute during operation.
- Ensure the bean hopper lid is securely in place before grinding.
- This appliance is intended for grinding whole roasted coffee beans only. Do not grind other substances.
- Do not operate the grinder with a damaged cord or plug, or if the appliance malfunctions or has been damaged in any manner.
- Keep the appliance out of reach of children.

3. COMPONENTS

Familiarize yourself with the main components of your MI40 Touch coffee grinder:



Bean Hopper: Transparent container for holding whole coffee beans. Capacity: 1.2 Kilograms.



3.5" Touchscreen Display: Intuitive interface for controlling grind settings, dose programming, and operating modes.



Grind Adjustment Collar: Stepless micrometric adjustment for precise control over grind particle size.



Portafilter Fork & Drip Tray: Adjustable fork to hold your portafilter for hands-free grinding, with a removable drip tray for easy cleaning.

4. SETUP

Follow these steps to set up your Macap MI40 Touch grinder:

1. **Unpacking:** Carefully remove the grinder and all accessories from the packaging. Retain the packaging for future transport or storage.
2. **Placement:** Place the grinder on a stable, flat, and dry surface. Ensure there is adequate ventilation around the unit.
3. **Hopper Installation:** Place the bean hopper onto the grinder body, aligning the tabs. Rotate the hopper clockwise until it locks securely into place.
4. **Drip Tray Installation:** Slide the removable drip tray into its designated slot at the base of the grinder.
5. **Power Connection:** Plug the power cord into a grounded electrical outlet.
6. **Initial Cleaning:** Before first use, wipe down the exterior with a damp cloth. Ensure the burrs and grind chute are free of any packing debris.



Side view of the Macap MI40 Touch grinder, illustrating its compact design and the placement of the bean hopper and drip tray.

5. OPERATING INSTRUCTIONS

5.1. Grind Adjustment

The MI40 Touch features stepless micrometric grind adjustment, allowing for precise control over particle size. To adjust the grind:

1. Ensure the grinder is off or not actively grinding.
2. Rotate the grind adjustment collar located below the bean hopper.
3. Rotate *clockwise* for a finer grind (e.g., for espresso).
4. Rotate *counter-clockwise* for a coarser grind (e.g., for drip, French press, or cold brew).
5. Make small adjustments and test the grind to achieve the desired consistency for your brewing method.



Close-up view of the grind adjustment collar, showing the numerical markings for reference.

5.2. Touchscreen Interface

The 3.5-inch touchscreen allows for intuitive control and customization of your grinding experience. It features four programmable dose buttons and various settings.



The 3.5-inch touchscreen display showing the main interface with programmable dose buttons. For a detailed demonstration of the touchscreen interface and its functionalities, please refer to the official video below:

This video demonstrates the various features and customization options of the 3.5-inch touchscreen interface on the Macap MI Series coffee grinders, including dose programming, color customization, and different operating modes.

5.3. Operating Modes

The MI40 Touch offers three primary operating modes:

- **Standard Mode:** Allows you to select a pre-programmed dose by pressing the corresponding button on the touchscreen. The grinder will dispense the set amount of coffee.
- **Push and Grind Mode:** Grinding starts when the portafilter activates the button on the fork and stops when the portafilter is removed. This mode is ideal for manual control.
- **Barista Hands-Free Mode:** Similar to Push and Grind, but designed for continuous grinding as long as the portafilter is in place, allowing baristas to multitask.

6. MAINTENANCE AND CLEANING

Regular cleaning and maintenance will ensure optimal performance and longevity of your grinder.

6.1. Daily Cleaning

- **Grind Chute:** Use a brush or vacuum to clear any residual coffee grounds from the grind chute after each use.
- **Drip Tray:** Remove and empty the drip tray regularly. Wipe it clean with a damp cloth and dry thoroughly.
- **Exterior:** Wipe the exterior of the grinder with a soft, damp cloth. Do not use abrasive cleaners or solvents.



The removable drip tray and portafilter fork area, designed for easy cleaning.

6.2. Deep Cleaning (Weekly/Bi-Weekly)

- **Unplug the grinder.**
- **Remove Bean Hopper:** Empty any remaining beans. Rotate the hopper counter-clockwise to unlock and

remove it.

- **Clean Burrs:** Use a stiff brush or a specialized grinder brush to remove accumulated coffee oils and grounds from the burrs. You may need to remove the upper burr for thorough cleaning (refer to specific instructions in the full manual for burr removal).
- **Clean Grind Chamber:** Use a vacuum cleaner with a narrow attachment to remove grounds from the grind chamber.
- **Reassemble:** Reinstall the burrs (if removed) and the bean hopper securely.

7. TROUBLESHOOTING

If you encounter issues with your MI40 Touch grinder, refer to the table below for common problems and solutions.

Problem	Possible Cause	Solution
Grinder does not turn on.	Not plugged in; power switch off; circuit breaker tripped.	Check power connection; ensure power switch is on; reset circuit breaker.
No coffee dispenses.	Hopper empty; grind chute clogged; burrs jammed.	Fill hopper; clean grind chute; clear any foreign objects from burrs (unplug first).
Inconsistent grind.	Burrs dirty or worn; grind setting too coarse/fine.	Clean burrs thoroughly; adjust grind setting incrementally. Consider burr replacement if worn.
Grinder is excessively noisy.	Foreign object in burrs; loose components.	Unplug and inspect burrs for foreign objects; check for loose parts. If noise persists, contact support.
Touchscreen unresponsive.	Temporary software glitch; power issue.	Unplug the grinder for 30 seconds, then plug back in. If issue persists, contact support.

8. SPECIFICATIONS

Key technical specifications for the Macap MI40 Touch Instant Burr Coffee Grinder:

Feature	Specification
Model	MI40 Touch
Burr Type	Flat Burrs
Burr Diameter	65mm



Feature	Specification
Motor Power	480W
Hopper Capacity	1.2 Kilograms
Grind Adjustment	Stepless Micrometric
Display	3.5" Touchscreen
Product Dimensions (L x W x H)	12" x 7.63" x 22"
Item Weight	19.58 pounds
Country of Origin	Italy





9. WARRANTY AND SUPPORT

Macap products are manufactured to high standards and undergo rigorous quality control. For warranty information, technical support, or service inquiries, please refer to the warranty card included with your product or visit the official Macap website. Please have your model number (MI40 Touch) and purchase date available when contacting support.

© 2025 Macap. All rights reserved.

Related Documents - MI40 Touch

	<p>Macap MI40 Luxe Coffee Grinder: Grinding and Filter Holder Adjustment Guide</p> <p>Detailed instructions on adjusting the grind size and filter holder height for the Macap MI40 Luxe coffee grinder, ensuring optimal espresso extraction.</p>
	<p>MACAP Coffee Grinders: M7, MX, M5, M4, MC, A3 Series - User Manual and Technical Specifications</p> <p>This document provides comprehensive instructions, safety information, technical specifications, and operational guidance for MACAP coffee grinders, including models M7, MX, M5, M4, MC, and A3 series. It details features, maintenance, and disposal procedures for professional use.</p>

	<p>Manuale Utente Macchine da Caffè MACAP Serie M7D, MXD, M5D, M4D</p> <p>Questo manuale ufficiale fornisce una guida completa per le macchine da caffè professionali MACAP serie M7D, MXD, M5D, M4D e MXD Xtreme. Dettaglia installazione, funzionamento, manutenzione e specifiche tecniche per uso commerciale.</p>
	<p>MACAP M42, MC42, M42M, M42D, M6D Coffee Grinder Manual</p> <p>Official instruction manual for MACAP M42, MC42, M42M, M42D, and M6D series coffee grinders. Covers safety, installation, operation, maintenance, and technical specifications for professional use.</p>
	<p>MACAP L70M L70D: Manuale d'Uso e Manutenzione</p> <p>Scopri come utilizzare al meglio il tuo macinacaffè istantaneo MACAP L70M e L70D con questo manuale completo. Troverai istruzioni dettagliate su installazione, funzionamento, pulizia, manutenzione e risoluzione dei problemi, oltre alle funzionalità di programmazione specifiche per il modello L70D.</p>
	<p>MACAP M2 Series Coffee Grinder User Manual</p> <p>Comprehensive user manual for the MACAP M2 Series coffee grinders, covering general warnings, appliance description, technical data, safety information, installation, operation, maintenance, cleaning, disposal, noise levels, and warranty.</p>