



Manuals.plus /

› DOGOITM /

› GPS Wireless Dog Fence, Electric Fence Collar with 3 Warning Modes, Wireless Dog Fence for Outdoor Use, Range 65-3290 FT, Waterproof & Rechargeable Pet Containment System for Most of Dogs

## DOGOITM GM08

# DOGOITM GPS Wireless Dog Fence User Manual

Model: GM08

## INTRODUCTION

This user manual provides comprehensive instructions for the DOGOITM GPS Wireless Dog Fence, an electric fence collar designed for outdoor use. It features three warning modes (beep, vibration, and shock) and offers a wide adjustable range for pet containment. This system is waterproof and rechargeable, making it suitable for most dogs.

## KEY FEATURES

- **GPS-Based Wireless Boundary:** Establishes a circular containment area without physical wires.
- **Adjustable Range:** Customizable radius from 65 feet to 3290 feet (20m to 1000m).
- **Three Training Modes:** Features audible beep, vibration, and static shock (adjustable levels) for effective training.
- **Waterproof Design (IPX6):** Suitable for use in various weather conditions, including swimming and rain.
- **Rechargeable Collar:** Convenient charging for continuous use.
- **Adjustable Collar Size:** Fits dogs with neck lengths from 10-30 inches and weights from 10-120 lbs.
- **Easy Setup:** No app, subscription fees, or digging required.

## PACKAGE CONTENTS

- GPS Wireless Dog Fence Collar (with adjustable strap)
- Remote Control Transmitter
- USB Charging Cable (dual output for collar and remote)
- Contact Points (short and long)
- Silicone Covers for Contact Points
- Test Light Tool
- User Manual

## SETUP GUIDE

## 1. Prepare the Collar

Ensure the collar unit is fully charged before first use. Connect the charging cable to the collar's charging port and a power source. The indicator light will show charging status.

# Adjustable Collar for Most of Dogs

Neck length: 10-30 inches / Weight: 10-120 lbs



Duale buckle



0-30 inches



Image: The adjustable collar band and buckle, suitable for various dog sizes.

Adjust the collar strap to fit your dog's neck comfortably. It should be snug enough for the contact points to touch the skin, but not so tight as to cause discomfort. The collar is designed for dogs with neck lengths between 10-30 inches and weighing 10-120 lbs.

## How to Test Electric Shock



Image: Visual guide on how to thread and adjust the collar strap through the device and buckle.

## 2. Install Contact Points

Select the appropriate length of contact points (short for short-haired dogs, long for long-haired dogs) and screw them firmly into the collar unit. Place the silicone covers over the contact points for added comfort and to prevent irritation.

## How to Set Up the Collar



Image: Step-by-step illustration of installing the contact points onto the collar unit.

## 3. Power On and GPS Positioning

Press and hold the power button on the collar unit to turn it on. Take the collar outdoors to an open area to allow it to acquire a GPS signal. The GPS icon on the display will indicate signal strength.



Image: A dog wearing the GPS collar, with a satellite icon indicating GPS connection and a red circular boundary on the ground.

#### 4. Set Boundary Distance

Press the 'M' key on the collar unit to enter the distance setting mode. Use the up and down keys to adjust the desired radius for your wireless fence. The range can be set from 65 feet to 3290 feet.

### 3 Effective Training Modes

#### Training



**Beep**  
( 0-1 level )



**Vibration**  
( 0-5 level )



**Shock**  
( 0-10 level )



Image: A golden retriever running in a grassy yard, with concentric circles indicating the adjustable boundary range up to 3290 feet.

**Control Distance Radius Cover  
from 65ft to 3290ft**

**3290 FT**



Image: An aerial view illustrating the GPS center point, safe zone, wireless boundary, and warning zone for pet containment.

## **5. Set Warning Mode**

Press the 'M' key again to enter the warning mode setting. Use the up and down keys to select the desired training mode (Beep, Vibration, or Shock) and adjust its intensity level.

# Easy set up



No App, No Subscription Fee, No Traditional Fence,  
No Transmitter, No Dig.

Image: A boy and a man training a golden retriever, with icons showing the three training modes: Beep (0-1 level), Vibration (0-5 level), and Shock (0-10 level).

## OPERATING INSTRUCTIONS

### Remote Control Usage

The remote control allows you to manually activate the training modes. It has a large range for effective communication with the collar. Use the mode selection buttons to switch between beep, vibration, and shock, and the intensity dial to adjust levels.

The remote control can be paired with multiple collars, indicated by numbers on the collars and a selection option on the remote's display.

### Testing Electric Shock (Optional)

To test the static shock function, place the provided test light tool across the contact points. Press the shock button on the remote. If the test light illuminates, the shock function is working correctly.



Image: Three steps demonstrating how to use the test tool to verify the electric shock function of the collar.

## Training Your Dog

Begin training in a familiar, open area. Introduce the warning modes gradually, starting with the beep, then vibration, and finally static shock if necessary. Always pair the correction with a verbal command or a recall cue.

When your dog approaches the boundary, the collar will activate the chosen warning mode. Guide your dog back into the safe zone. Positive reinforcement (praise, treats) is crucial when your dog responds correctly.

Consistency is key. Regular, short training sessions will help your dog understand the boundaries and respond to the collar's cues.

## MAINTENANCE

- **Cleaning:** Regularly clean the collar and contact points with a damp cloth. Ensure the contact points are free of dirt or debris to maintain proper function.
- **Waterproof Feature:** The collar is IPX6 waterproof, meaning it can withstand strong jets of water and is suitable for swimming, bathing, and use in rainy conditions. However, ensure the charging port cover is securely closed when exposed to water.

# IPX6 Waterproof



Swimming



Bathing



Raining



Image: A golden retriever swimming underwater, illustrating the IPX6 waterproof rating of the collar, suitable for swimming, bathing, and rain.

- **Battery Life:** Charge the collar and remote regularly. Battery life can vary based on usage and environmental factors.
- **Storage:** Store the device in a cool, dry place when not in use.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
Collar not responding to remote.	Low battery on collar or remote; out of range; not paired correctly.	Charge both devices. Ensure you are within the effective range. Re-pair the collar and remote according to the manual.
Inconsistent boundary.	Poor GPS signal; environmental interference (dense trees, tall buildings).	Ensure the collar has a clear view of the sky. Re-establish the center point in an open area. Avoid areas with heavy obstructions.
Collar not delivering correction.	Contact points not touching skin; incorrect mode/intensity setting; faulty contact points.	Adjust collar fit. Check mode and intensity levels. Use the test light tool. Ensure contact points are clean.
Short battery life.	Frequent use of high-intensity modes; aging battery.	Reduce intensity levels if possible. Ensure full charge cycles. Consider battery replacement if issues persist after extended use.

## SPECIFICATIONS

- **Model Number:** GM08
- **Brand:** DOGOITM
- **Item Weight:** 10.2 ounces
- **Product Dimensions:** 4 x 2 x 5.3 inches
- **Wireless Range:** 65 - 3290 feet (20 - 1000 meters)
- **Training Modes:** Beep (1 level), Vibration (5 levels), Static Shock (10 levels)
- **Waterproof Rating:** IPX6
- **Collar Neck Length:** 10 - 30 inches
- **Recommended Dog Weight:** 10 - 120 lbs

## SAFETY INFORMATION

- Do not leave the collar on your dog for more than 12 consecutive hours.
- Regularly check your dog's neck for signs of irritation or sores from the contact points.
- This device is for training purposes and should not be used as a primary restraint.
- Ensure proper fit to prevent discomfort and ensure effective operation.
- Not suitable for aggressive dogs or dogs with health issues without consulting a veterinarian or professional trainer.
- Keep out of reach of children.

## WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the product packaging or contact DOGOITM customer service directly. Details are typically provided with your purchase.