

Mivi Fort H160

Mivi Fort H160 Soundbar User Manual

Model: Fort H160

1. INTRODUCTION

Thank you for choosing the Mivi Fort H160 Soundbar. This 2.1 channel sound system is designed to enhance your audio experience with powerful sound and versatile connectivity. This manual provides essential information for the safe and efficient use of your soundbar, including setup, operation, maintenance, and troubleshooting.

2. PACKAGE CONTENTS

Carefully unpack all items and ensure you have received the following components:

- Mivi Fort H160 Soundbar
- Wired Subwoofer
- Remote Control (with 2 AAA batteries included)
- Power Adapter
- Auxiliary Cable
- User Manual



Image: The Mivi Fort H160 Soundbar and its accompanying wired subwoofer, showcasing their design and relative sizes.

3. PRODUCT OVERVIEW

3.1 Soundbar and Subwoofer

The Mivi Fort H160 system consists of a main soundbar unit with two integrated full-range speakers and a separate wired subwoofer. The soundbar features a metallic mesh grill and a matte finish cabinet, designed for a minimalistic aesthetic.

3.2 Input Ports

The rear panel of the soundbar provides various input options for connecting to different audio sources.



Crafted by Mivi Design Studio in India

A Blend of Form and Functionality

Image: The rear panel of the Mivi Fort H160 Soundbar, displaying the various input ports including Optical (OPT), DC 24V power input, Auxiliary (AUX), HDMI TV (ARC), USB, and Coaxial connections.

- **OPT (Optical):** For digital audio connection from compatible devices.
- **DC 24V:** Power input port.
- **AUX:** For analog audio connection using a 3.5mm auxiliary cable.
- **HDMI TV (ARC):** For digital audio connection from a TV supporting Audio Return Channel.
- **USB:** For playing audio files from a USB storage device.
- **COAXIAL:** For digital audio connection from compatible devices.

4. SETUP

4.1 Placement

Place the soundbar on a stable, flat surface directly in front of your television. Position the wired subwoofer on the floor near the soundbar for optimal bass response.

4.2 Connections

1. **Connect the Subwoofer:** Connect the wired subwoofer cable to the dedicated subwoofer output port on the soundbar.
2. **Connect to Audio Source:** Choose one of the following methods to connect your soundbar to your TV or other audio device:
 - **HDMI (ARC):** Connect an HDMI cable from the HDMI TV (ARC) port on the soundbar to the HDMI ARC port on your TV.
 - **Optical:** Connect an optical cable from the OPT port on the soundbar to the optical output port on your TV or audio device.
 - **Coaxial:** Connect a coaxial cable from the COAXIAL port on the soundbar to the coaxial output port on your TV or audio device.
 - **AUX:** Connect the provided 3.5mm auxiliary cable from the AUX port on the soundbar to the headphone jack or AUX output on your TV or audio device.
 - **USB:** Insert a USB drive into the USB port for direct media playback.
3. **Connect Power:** Connect the power adapter to the DC 24V port on the soundbar, then plug the adapter into a wall outlet.

4.3 Power On

Press the power button on the soundbar or the remote control to turn on the device. The indicator light will illuminate.

5. OPERATING INSTRUCTIONS

5.1 Power On/Off

Press the **Power** button on the remote control or the soundbar's control panel to turn the soundbar on or off.

5.2 Input Mode Selection

Press the **INPUT** button on the remote control or the soundbar to cycle through the available input modes: HDMI, Optical, Coaxial, AUX, USB, and Bluetooth. The current mode will be indicated on the soundbar's display.

5.3 Volume Control

Use the **VOL+** and **VOL-** buttons on the remote control or the soundbar to adjust the master volume. Use the **BASS+** and **BASS-** buttons to adjust the subwoofer's bass level.

5.4 EQ Modes

The Mivi Fort H160 Soundbar offers multiple Equalizer (EQ) modes to optimize audio for different content types. Use the dedicated EQ buttons on the remote control to switch between modes.



4 Unique EQ Modes Now in Your Palms

Switch among Different EQ Modes with the Mivi Remote

Image: The Mivi Fort H160 Soundbar with its remote control, highlighting the buttons for selecting different EQ modes: Movies, Music, 3D, and News.

- **Movies:** Enhances dialogue clarity and cinematic effects.
- **Music:** Provides a balanced audio profile for music playback.
- **3D:** Creates a wider, more immersive soundstage.
- **News:** Optimizes for clear vocal reproduction.

5.5 Bluetooth Pairing

1. Turn on the soundbar and select the Bluetooth input mode. The soundbar will enter pairing mode, indicated by a flashing light or display message.
2. Enable Bluetooth on your mobile device or computer.
3. Search for "Mivi Fort H160" in the list of available devices and select it to pair.
4. Once paired, the soundbar will confirm the connection, and you can play audio from your device.

6. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the surfaces of the soundbar and subwoofer. Do not use liquid

cleaners or abrasive materials.

- **Storage:** If storing the unit for an extended period, disconnect it from power and store it in a cool, dry place.
- **Ventilation:** Ensure proper ventilation around the soundbar and subwoofer to prevent overheating. Do not block any ventilation openings.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Power cable not connected; Power outlet not active	Ensure power cable is securely connected; Try a different power outlet.
No sound	Incorrect input mode; Volume too low; Muted; Incorrect cable connection	Select the correct input mode; Increase volume; Unmute the soundbar; Check all cable connections.
Bluetooth pairing fails	Soundbar not in pairing mode; Device too far; Interference	Ensure soundbar is in Bluetooth pairing mode; Move device closer; Restart both devices.
Remote control not working	Batteries depleted; Obstruction; Remote out of range	Replace batteries; Remove any obstructions between remote and soundbar; Ensure remote is within operating range.

8. SPECIFICATIONS

Brand	Mivi
Model Number	Mivi Fort H160-cr
Speaker Configuration	2.1 Channel (Soundbar with 2 in-built speakers + 1 wired external subwoofer)
Maximum Output Power	160 Watts
Connectivity Technology	Auxiliary, Bluetooth, HDMI (ARC), USB, Optical, Coaxial
Wireless Technology Type	Bluetooth
Power Source	Corded Electric
Mounting Type	Tabletop Mount
Material	Metallic
Colour	Black
Item Weight	2 Kilograms (approx.)
Batteries for Remote	2 AAA batteries (included)

9. WARRANTY INFORMATION

This Mivi Fort H160 Soundbar comes with a **6-month seller warranty** from the date of purchase. This warranty covers manufacturing defects and issues arising from normal use. Please retain your proof of purchase for warranty claims. The warranty does not cover damage caused by misuse, accidents, unauthorized modifications, or normal wear and tear.

10. CUSTOMER SUPPORT

If you encounter any issues or have questions regarding your Mivi Fort H160 Soundbar that are not addressed in this manual, please contact your seller or refer to the official Mivi support channels for assistance.