

YESKAMOO CX7

YESKAMOO 5MP Wireless Outdoor Security Camera System User Manual

Model: CX7 | Brand: YESKAMOO

[Product Overview](#) [What's in the Box](#) [Setup Guide](#) [Operating](#)
[Instructions](#) [Maintenance](#) [Troubleshooting](#) [Specifications](#) [Warranty & Support](#)

1. PRODUCT OVERVIEW

The YESKAMOO 5MP Wireless Outdoor Security Camera System (Model CX7) provides comprehensive surveillance for your home or business. This system includes a 10-inch integrated monitor NVR and four 5MP wireless cameras, offering high-resolution video, advanced AI human detection, two-way audio communication, and robust weatherproofing.

- **Integrated 10-inch Monitor NVR:** Space-saving design with a portable 10-inch NVR, supporting both desktop and wall-mounted installations.
- **Next-Generation Wi-Fi 6:** Significantly reduces signal interference, ensuring ultra-stable connections and expanding placement flexibility. Supports up to 8MP cameras for clear, high-quality images.
- **Two-Way Audio:** Communicate directly through the monitor or the mobile app.
- **Plug-and-Play Setup:** Cameras and NVR automatically pair upon power-up, allowing for local monitoring without internet connection.
- **High-Performance 5MP Cameras with PTZ:** Equipped with 5-megapixel image sensors and f=3.6mm wide-angle lenses, offering 8x digital zoom. Pan (350°), Tilt (90°), and Zoom functions provide 360° blind-spot-free coverage.
- **Advanced Night Vision & AI Human Detection:** Features four infrared lights and LED lights for clear full-color night vision up to 18m. AI human detection minimizes false alarms from leaves or animals.
- **Dedicated HDD & Continuous Recording:** Includes a dedicated HDD for 24/7 continuous recording. Supports up to 10 cameras and offers continuous, motion-detection, and scheduled recording modes.
- **IP66 Waterproof & H.265+ Compression:** IP66-rated for outdoor use in harsh weather. H.265+ video compression saves storage space and bandwidth.

- **Remote Monitoring:** View camera feeds from PC or smartphone (iOS/Android) via the dedicated YESKAMO app.

2. WHAT'S IN THE BOX

Please verify that all components are present and in good condition upon unboxing.

- カメラ本体*4
- 10インチモニター
- 取付用ネジなど
- 録画機用12v2A電源
- カメラ用12v1A電源*4
- ユーザーガイド\
- スタンド



Image: All components included in the YESKAMOO 5MP Wireless Outdoor Security Camera System package.

- 1 x 10-inch Monitor NVR
- 4 x 5MP Wireless Outdoor Cameras
- 1 x NVR Power Adapter (12V 2A)
- 4 x Camera Power Adapters (12V 1A)
- 1 x USB Mouse

- 1 x User Guide
- Mounting Screws and Anchors
- Warning Stickers

Your browser does not support the video tag.

Video: Unboxing and component overview of the WK-10V-4HS02-AT system. This video demonstrates the contents of the package and highlights the main components, including the NVR, cameras, and accessories.

3. SETUP GUIDE

3.1 Initial System Connection

1. **Connect NVR to Power:** Plug the 12V 2A power adapter into the NVR's DC12V port and then into a power outlet.



Image: Connecting the NVR to its power source.

2. **Connect Cameras to Power:** Plug each camera's 12V 1A power adapter into the camera and then into a power outlet.



Image: Connecting a camera to its power source.

3. **Automatic Pairing:** The cameras and NVR are pre-paired at the factory. Once both are powered on, the camera feeds should automatically appear on the NVR monitor.



Image: The NVR monitor displaying live feeds after automatic pairing.

Your browser does not support the video tag.

Video: Simple setup and immediate use of the security camera system. This video demonstrates the plug-and-play functionality, showing how the system automatically connects once powered on.

3.2 Network Configuration (Optional for Remote Viewing)

To enable remote viewing via smartphone or PC, connect the NVR to your home network.

1. **Wired Connection:** Connect an Ethernet cable from your router to the LAN port on the NVR.



Image: Connecting the NVR to Wi-Fi, which is also applicable for wired LAN connection.

2. **Wireless Connection (Wi-Fi 6):** Access the NVR's system settings, navigate to network settings, and select your Wi-Fi network. Enter the password to connect. The system supports Wi-Fi 6 for enhanced stability.

Your browser does not support the video tag.

Video: Demonstration of connecting the OHWOAI monitor-integrated wireless security camera system. This video guides users through the process of connecting the system and setting it up for operation.

3.3 Mobile App Setup (EseeCloud)

Download the "EseeCloud" app from your smartphone's app store (iOS/Android). Register an account and follow the in-app instructions to add your NVR by scanning the QR code displayed on the NVR monitor or the device itself.

Your browser does not support the video tag.

Video: Demonstration of connecting the OHWOAI monitor-integrated wireless security camera system. This video guides users through the process of connecting the system and setting it up for operation.

3.4 Camera Installation

The cameras are IP66 waterproof and dustproof, suitable for outdoor installation. Choose a location that provides optimal coverage and a stable Wi-Fi signal.



Image: A YESKAMOO outdoor camera demonstrating its IP66 waterproof rating under rain.

1. **Mounting:** Use the provided screws and anchors to securely mount the cameras to a wall or ceiling. Ensure the camera is positioned to capture the desired area.



Image: An example of a YESKAMOO camera mounted on a wall, showing its adjustable angle.

2. **Adjust Angle:** Adjust the camera's pan and tilt to achieve the desired viewing angle. The PTZ function allows for 350° pan and 90° tilt.

Your browser does not support the video tag.

Video: Demonstration of the PTZ (Pan-Tilt-Zoom) function of the outdoor security camera. This video highlights how the camera detects movement and triggers alerts.

4. OPERATING INSTRUCTIONS

4.1 Live View and Playback

Once the system is set up, you can view live feeds on the 10-inch NVR monitor or remotely via the EseeCloud app. The NVR supports full-screen, 4-screen, 8-screen, and 10-screen display modes.

データ暗号化でプライバシー保護可能



Image: The NVR monitor displaying multiple camera feeds simultaneously, illustrating various display options.

To review recorded footage, access the playback function on the NVR or through the mobile app. The system records continuously to the dedicated HDD, with older data automatically overwritten when full.



Image: The NVR interface showing the timeline for recorded video playback, indicating continuous recording.

4.2 Two-Way Audio Communication

The integrated microphone and speaker on the cameras and NVR allow for two-way audio. You can speak through the NVR monitor or the mobile app to communicate with individuals near the cameras.

10インチ画面専用設計

のHDD採用、長期間の使用にも安心



Image: A person speaking into a smartphone, with a speech bubble indicating two-way audio communication through the camera system.

4.3 AI Human Detection and Alarms

The system features AI human detection to accurately identify human figures, reducing false alarms. When a person is detected, the system can:

- Send push notifications to your smartphone.
- Activate a loud siren.
- Trigger floodlight illumination.
- Initiate automatic tracking (PTZ cameras).

遠隔操作可能

人はモニターの前にはないとスマホで監視カメラのリアルタイム映像を見られます。

様々なシステム対応




Image: Two children detected by the camera, with a smartphone notification indicating motion detection, showcasing the AI human detection feature.



Image: A person being detected by the camera at night, triggering a floodlight and an alarm, with icons for push notification, auto-

tracking, alarm, light alarm, and sound alarm.

Your browser does not support the video tag.

Video: Demonstration of the motion detection function of the YESKAMOO NK series security camera set. This video highlights how the camera detects movement and triggers alerts.

4.4 Remote Monitoring

With the EseeCloud app, you can monitor your property from anywhere using your smartphone or tablet. The app supports iOS and Android devices.



Image: A person viewing live camera footage on a smartphone, demonstrating remote monitoring capabilities.

5. MAINTENANCE

- **Regular Cleaning:** Periodically clean the camera lenses and housing with a soft, damp cloth to ensure clear

image quality. Avoid abrasive cleaners.

- **Firmware Updates:** Check the EseeCloud app or YESKAMOO website for firmware updates to ensure optimal performance and security.
- **Storage Management:** The NVR's dedicated HDD automatically overwrites old footage. Regularly back up important recordings if needed.
- **Power Supply:** Ensure all power adapters are securely connected and free from damage.

6. TROUBLESHOOTING

• No Image on Monitor:

- Check if the NVR and cameras are properly powered on.
- Verify that the NVR and cameras are within range and have successfully paired.
- Ensure the monitor's input source is correctly selected if using an external display.

• Poor Wi-Fi Signal/Connectivity:

- Ensure cameras are within range of the NVR or a Wi-Fi repeater.
- Minimize obstacles (thick walls, metal structures) between cameras and the NVR.
- Consider using a Wi-Fi repeater (not included) to extend the signal range, especially in large areas.



Image: Diagram illustrating how a Wi-Fi repeater can extend the wireless range of the security camera system in a multi-story building.

• False Alarms:

- Adjust the AI human detection sensitivity in the app settings.
- Ensure the camera's field of view is clear of moving objects like tree branches or flags that might trigger motion.

• Remote Viewing Issues:

- Verify the NVR is connected to the internet (wired or Wi-Fi).
- Check your smartphone's internet connection.
- Ensure the EseeCloud app is updated to the latest version.

7. SPECIFICATIONS

Feature	Detail
Brand	YESKAMOO
Product Model Number	CX7
Product Dimensions	10 x 10 x 10 cm
Item Weight	3.76 kg
Video Capture Resolution	1920p (5MP)
Recommended Use	Outdoor
Included Components	1 (System includes NVR, 4 cameras, adapters, mouse, manual)
ASIN	B0F2FW1RDF

8. WARRANTY & SUPPORT

YESKAMOO is committed to providing high-quality products and customer satisfaction. This product has obtained technical standards certification (TELEC) and undergoes strict inspection before shipment.

- **30-Day Free Exchange:** For initial defects.
- **60-Day Money-Back Guarantee:** If you are not satisfied with the product.
- **1-Year Free Exchange:** For product issues within one year of purchase.
- **3-Year Long-Term Warranty:** Comprehensive warranty coverage for three years.
- **Customer Support:** If you have any questions or concerns during use, please feel free to contact us via email or LINE.