

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

> [IRRADIO](#) /

> [IRRADIO IR-GT710V Portable Speaker User Manual](#)

## IRRADIO IR-GT710V

# IRRADIO IR-GT710V Portable Speaker User Manual

Model: IR-GT710V | Brand: IRRADIO

## INTRODUCTION

---

Thank you for choosing the IRRADIO IR-GT710V Portable Speaker. This manual provides essential information for the safe and efficient operation of your device. Please read it carefully before use and retain it for future reference.

## SAFETY INFORMATION

---

- Do not expose the speaker to extreme temperatures, direct sunlight, or open flames.
- Avoid dropping or subjecting the speaker to strong impacts.
- Do not disassemble, repair, or modify the speaker yourself. Contact qualified service personnel for any repairs.
- Keep the speaker away from medical devices.
- Ensure the charging port is dry before connecting the charger.
- This speaker has an IPX6 water resistance rating, meaning it is protected against high-pressure water jets from any direction. It is not designed for submersion.

## PACKAGE CONTENTS

---

- IRRADIO IR-GT710V Portable Speaker
- Charger
- User Manual

## PRODUCT OVERVIEW

---

Familiarize yourself with the various parts and controls of your IRRADIO IR-GT710V speaker.



**Figure 1:** Front view of the IRRADIO IR-GT710V speaker. The speaker features a black mesh grille covering the front, with the IRRADIO logo illuminated by RGB lights on the left side. A sturdy handle is visible on top.



**Figure 2:** Top view of the IRRADIO IR-GT710V speaker. This image highlights the integrated carrying handle and the control panel located on the top surface. The control panel includes buttons for power, Bluetooth pairing, volume control, play/pause, and LED light modes.

## Control Panel Functions

- **Power Button (⏻):** Press and hold to power on/off.
- **Bluetooth Pairing Button (📶):** Press to enter Bluetooth pairing mode.
- **Volume Down (-):** Decrease volume.

- **Volume Up (+):** Increase volume.
- **Play/Pause Button (▶):** Play or pause audio playback.
- **LED Light Mode Button (\*):** Cycle through different RGB LED light modes.
- **Bass Booster Button:** Activate or deactivate enhanced bass.

## Ports and Connections

- **Ingresso AUX stereo Mini Jack** da 3,5mm
- **Risposta in frequenza:** 45 Hz – 20 KHz
- **Batteria integrata:** 11,1 V 7.500 mAh, 83,25 W/h
- **Durata della ricarica:** 4:30 ore



**Figure 3:** Rear panel of the IRRADIO IR-GT710V speaker. This image shows the various input ports, including a 3.5mm AUX input, a USB port for media playback, and the DC 5V 3A charging port.

- **DC 5V 3A Charging Port:** For connecting the power adapter to charge the speaker.
- **USB Port:** For playing audio files directly from a USB drive.

- **AUX 3.5mm Input:** For connecting external audio devices via a 3.5mm audio cable.

## SETUP

---

### Charging the Speaker

1. Connect the provided charger to the DC 5V 3A charging port on the speaker.
2. Plug the charger into a power outlet.
3. The charging indicator light will illuminate.
4. A full charge takes approximately 4.5 hours. The indicator light will change or turn off once charging is complete.

The integrated 7500 mAh battery provides up to 12 hours of continuous playback at 50% volume.

### Power On/Off

- To power on, press and hold the Power button ( ) for a few seconds until you hear an audible prompt or see the indicator lights activate.
- To power off, press and hold the Power button ( ) again for a few seconds until the speaker powers down.

## OPERATING INSTRUCTIONS

---

### Bluetooth Pairing

1. Ensure the speaker is powered on and within 10 meters of your Bluetooth device.
2. The speaker will automatically enter Bluetooth pairing mode, indicated by a flashing Bluetooth indicator light. If not, press the Bluetooth Pairing button ( ).
3. Enable Bluetooth on your device (smartphone, tablet, etc.) and search for available devices.
4. Select "IRRADIO IR-GT710V" from the list of devices.
5. Once paired, the Bluetooth indicator light will stop flashing and remain solid, and you will hear a confirmation sound.

### True Wireless Stereo (TWS) Pairing

The TWS function allows you to connect two IRRADIO IR-GT710V speakers for a more immersive stereo sound experience.

1. Ensure both IR-GT710V speakers are powered on and not connected to any Bluetooth device.
2. On one of the speakers (this will be the primary speaker), press and hold the Bluetooth Pairing button ( ) for a few seconds until you hear a TWS pairing prompt.
3. The primary speaker will automatically search for the secondary speaker.
4. Once successfully paired, you will hear a confirmation sound, and the Bluetooth indicator lights on both speakers will synchronize.
5. Now, connect your Bluetooth device to the primary speaker as described in the "Bluetooth Pairing" section. Both speakers will play audio in stereo.

### Audio Playback (USB & AUX)

#### USB Playback

- Insert a USB flash drive containing MP3 or WAV audio files into the USB port.
- The speaker will automatically detect the USB drive and begin playing audio.

- Use the Play/Pause and Volume buttons on the speaker to control playback.

### AUX Playback

- Connect one end of a 3.5mm audio cable to the AUX input port on the speaker.
- Connect the other end of the cable to the audio output jack of your external device (e.g., MP3 player, computer).
- The speaker will automatically switch to AUX mode.
- Control playback and volume primarily from your external device.

### LED Light Modes

The IR-GT710V features dynamic RGB LED lighting. Press the LED Light Mode button (\*) to cycle through various lighting effects. The lights can synchronize with the music or display ambient patterns.



**IR-GT710V**  
Wireless Speaker

**Caratteristiche**

- Funzione True Wireless Stereo
- Grado di impermeabilizzazione: IPX6
- LED RGB
- Potenza 100W

Figure 4: The IRRADIO IR-GT710V speaker shown outdoors, emphasizing its key features. These include True Wireless Stereo functionality, IPX6 water resistance, vibrant RGB LED lighting, and a powerful 100W audio output.

### Bass Booster Function

Press the Bass Booster button to enhance the bass output for a deeper, more impactful sound. Press it again to deactivate the function.

## MAINTENANCE

---

- Clean the speaker with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- If the speaker gets wet, wipe it dry thoroughly before charging or using it again.
- Store the speaker in a cool, dry place when not in use for extended periods.
- Charge the battery at least once every three months to maintain its lifespan.

## TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Speaker does not power on.	Battery is depleted.	Charge the speaker for at least 30 minutes.
Cannot pair via Bluetooth.	Speaker is not in pairing mode or already connected to another device.	Ensure the speaker is in pairing mode (flashing indicator). Disconnect from other devices. Restart both speaker and Bluetooth device.
No sound during playback.	Volume is too low or muted. Incorrect input source.	Increase volume on both the speaker and the connected device. Ensure the correct input mode (Bluetooth, USB, AUX) is selected.
TWS pairing fails.	Speakers are too far apart or already paired.	Ensure both speakers are close to each other and not connected to any other Bluetooth device. Try resetting both speakers.
USB playback not working.	Unsupported file format or corrupted USB drive.	Ensure files are MP3 or WAV format. Try a different USB drive or reformat the current one.

## SPECIFICATIONS

---

La cassa è equipaggiata con la versione **wireless 5.0**, il diffusore garantisce una **connessione stabile e senza interruzioni**



Figure 5: Dimensions of the IRRADIO IR-GT710V speaker. The speaker measures 49.6 cm in width and 21.4 cm in height.

Feature	Specification
Brand	IRRADIO
Model	IR-GT710V
Speaker Type	Boombox
Power Output	100W RMS
Connectivity	Bluetooth 5.0, USB, AUX 3.5mm
Bluetooth Range	Up to 10 meters (33 feet)
Water Resistance	IPX6

Feature	Specification
Battery Capacity	11.1V 7500 mAh (83.25 Wh)
Playback Time	Up to 12 hours (at 50% volume)
Charging Time	Approximately 4.5 hours
Frequency Response	45 Hz - 20 KHz
Supported Audio Formats	MP3, WAV
Product Dimensions (L x W x H)	49.6 x 21.4 x 21.4 cm (19.5 x 8.4 x 8.4 inches)
Net Weight	6.22 kg (13.7 lbs)
Included Components	Charger
Power Plug Type	Type D – 3-pin (India)

## WARRANTY AND SUPPORT

---

IRRADIO products are designed and manufactured to the highest quality standards. For warranty information, technical support, or service inquiries, please refer to the warranty card included with your product or visit the official IRRADIO website. Please retain your proof of purchase for warranty claims.