

G6 Instant

Ubiquiti G6 Instant Surveillance Camera User Manual

Model: G6 Instant | Brand: Generic

INTRODUCTION

This manual provides comprehensive instructions for the setup, operation, maintenance, and troubleshooting of your Ubiquiti G6 Instant Surveillance Camera. Please read this manual carefully before using the product to ensure proper functionality and safety.



Figure 1: The Ubiquiti G6 Instant Surveillance Camera. This image shows the compact, white camera unit with its prominent black lens, designed for discreet placement.

PACKAGE CONTENTS

Verify that all items are present in your package:

- Ubiquiti G6 Instant Surveillance Camera
- Mounting Hardware
- Quick Start Guide

SETUP

1. Unpacking and Initial Inspection

Carefully remove the camera and all accessories from the packaging. Inspect for any signs of damage. If any components are missing or damaged, contact customer support immediately.

2. Choosing a Location

The G6 Instant is designed for *Indoor* use. Select a location that provides the desired viewing angle and is within range of your wired network connection. Ensure the camera is placed on a stable surface or securely mounted.

3. Powering On and Network Connection

Connect the camera to a power source using the provided power adapter. Connect the camera to your network using an Ethernet cable. The camera utilizes a **Wired Connectivity Protocol** for stable data transmission.

4. Software Installation and Configuration

For initial setup and configuration, download the Ubiquiti UniFi Protect application on your mobile device or access the web interface. Follow the on-screen instructions for device discovery and pairing. The *Easy Setup* feature facilitates quick deployment and automatic configuration.

OPERATING INSTRUCTIONS

1. Live View and Recording

Access the live feed from your camera through the UniFi Protect application or web interface. You can initiate manual recordings or configure continuous recording schedules.

2. AI-Powered Motion Detection

The camera features **AI-Powered Motion Detection**. Configure detection zones and sensitivity settings within the application. Smart algorithms help reduce false alarms by distinguishing between humans, animals, and objects.

3. Instant Alerts

Enable **Instant Alerts** to receive real-time notifications via mobile or email when motion is detected. Customize alert preferences in the settings.

4. Playback and Export

Review recorded footage using the playback feature. You can easily navigate through timelines and export specific video clips for archiving or sharing.

5. Resolution Settings

The camera supports **Ultra HD Resolution**. Adjust the resolution settings (e.g., 4K or 1080p) based on your storage capacity and network bandwidth requirements.

MAINTENANCE

1. Cleaning the Camera

Gently wipe the camera lens and body with a soft, dry, lint-free cloth. Do not use harsh chemicals or abrasive cleaners. Ensure the camera is powered off before cleaning.

2. Firmware Updates

Regularly check for and install firmware updates through the UniFi Protect application or web interface. Firmware updates often include performance improvements, new features, and security enhancements.

3. Environmental Considerations

While the camera is *Durable and Weather-Resistant*, it is primarily recommended for *Indoor* use. Avoid exposing it to extreme temperatures, direct sunlight for prolonged periods, or excessive moisture.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Camera not powering on	No power supply; faulty adapter	Check power connection; try a different outlet; ensure adapter is working.

Problem	Possible Cause	Solution
No video feed	Network connectivity issue; camera offline	Verify Ethernet cable connection; restart camera and router; check network settings in application.
Frequent false motion alerts	Sensitivity too high; improper detection zone	Adjust motion detection sensitivity; refine detection zones in the application.
Poor video quality	Low resolution setting; dirty lens; insufficient lighting	Increase resolution setting; clean the camera lens; ensure adequate lighting in the monitored area.

SPECIFICATIONS

Model: G6 Instant

Brand: Generic (Manufacturer: Ubiquiti)

ASIN: B0F5BPXGPQ

Connectivity Technology: Wired

Connectivity Protocol: Wired

Special Feature: HD Resolution (Supports Ultra HD Resolution)

Indoor/Outdoor Usage: Indoor

Recommended Uses: Indoor Security

Included Components: Camera

Package Dimensions: 6 x 4 x 3 inches

Date First Available: April 17, 2025

WARRANTY INFORMATION

Specific warranty details for the Ubiquiti G6 Instant Surveillance Camera are typically provided at the point of purchase or within the product packaging. Please refer to the warranty card included with your product for terms and conditions. Generally, Ubiquiti products come with a limited warranty covering manufacturing defects for a specified period from the date of purchase. Keep your proof of purchase for warranty claims.

CUSTOMER SUPPORT

For technical assistance, product inquiries, or warranty claims, please visit the official Ubiquiti support website or contact their customer service. You may need your product model (G6 Instant) and ASIN (B0F5BPXGPQ) when contacting support.

Online Resources: www.ui.com/support