

TECKNET TK-KB005

TECKNET TK-KB005 Bluetooth Keyboard Instruction Manual

Model: TK-KB005 | Brand: TECKNET

1. INTRODUCTION

Thank you for choosing the TECKNET TK-KB005 Bluetooth Keyboard. This full-size wireless keyboard is designed for multi-device connectivity, offering a seamless typing experience across various operating systems. Please read this manual carefully to ensure proper setup and optimal performance.

2. PACKAGE CONTENTS

- 1 × TECKNET TK-KB005 Multi-device Bluetooth Keyboard
- 1 × USB-C Charging Cable
- 1 × User Manual

3. PRODUCT FEATURES

- **4 Modes Connection:** Connects up to four devices (3 Bluetooth modes + 1 2.4G wireless mode) with easy switching.
- **Rechargeable Battery:** Built-in 500mAh battery provides up to 180 days of use on a 2-hour charge (based on 2 hours daily use). Features auto-sleep mode for power saving.

- **Quiet & Fluid Typing:** 110 upgraded scissor-switch keys offer 90% noise reduction and a comfortable 2mm key travel.
- **Ergonomic Design:** Crafted for comfort with adjustable tilt angles (3° - 7°) and 5 non-slip pads for stability.
- **Wide Compatibility:** Compatible with Windows, iOS, macOS, and Android devices including PCs, laptops, tablets, smartphones, and smart TVs.
- **12 Multimedia Keys:** Enhances productivity with dedicated multimedia functions.

4. SETUP AND CONNECTION

4.1 Initial Setup

1. Ensure the keyboard is fully charged before first use.
2. Turn on the keyboard using the ON/OFF switch located on the back.

4.2 Connecting via Bluetooth (BT1/BT2/BT3)

1. On the keyboard, press and hold one of the Bluetooth channel buttons (BT1, BT2, or BT3) for 3-5 seconds until the corresponding LED indicator flashes quickly. This indicates pairing mode.
2. On your device (PC, laptop, tablet, smartphone), go to Bluetooth settings and enable Bluetooth.
3. Search for "TK-KB005" in the list of available devices and select it to pair.
4. Once connected, the LED indicator on the keyboard will stop flashing and remain solid for 2 seconds before turning off.

4.3 Connecting via 2.4G USB Receiver

1. Locate the 2.4G USB receiver stored in the slot on the back of the keyboard.
2. Plug the USB receiver into an available USB-A port on your computer.
3. On the keyboard, press the 2.4G channel button (indicated by a lightning bolt icon). The LED indicator will light up.
4. The keyboard should automatically connect to your device.

4.4 Switching Between Devices

To switch between connected devices, simply press the corresponding channel button (BT1, BT2, BT3, or 2.4G) on the keyboard. The keyboard will connect to the selected device within seconds.



Image: Diagram illustrating the 4 modes of connection (3 Bluetooth, 1 2.4G USB) and how to switch between devices like a tablet, phone, laptop, and desktop computer.

Your browser does not support the video tag.

Video: Official TECKNET video demonstrating the Bluetooth Wireless Keyboard's rechargeable feature and general overview.

5. OPERATING INSTRUCTIONS

5.1 System Compatibility and Switching

The keyboard is designed to automatically detect and adapt to different operating systems. However, if certain keys do not function as expected, you can manually switch the system mode:

- For Android devices: Press **Fn + Q**
- For Windows devices: Press **Fn + W**
- For iOS/macOS devices: Press **Fn + E**

Note: Due to differences in systems, key functions may vary. Generally, the system will automatically switch in Bluetooth mode, but use the shortcut keys if needed.



Image: Visual guide for switching keyboard layouts between Android, Windows, and iOS/macOS using Fn key combinations.

5.2 Multimedia Keys

The keyboard features 12 multimedia keys (F1-F12) that provide quick access to various functions such as volume control, media playback, and more. These functions are typically accessed by pressing the Fn key in combination with the desired F-key.

Your browser does not support the video tag.

Video: Official TECKNET video showcasing the 4-Device Switch Bluetooth Keyboard's features and multi-device connectivity.

6. CHARGING

The TECKNET TK-KB005 keyboard is equipped with a built-in 500mAh rechargeable battery. To charge the keyboard:

1. Connect the provided USB-C charging cable to the USB-C port on the back of the keyboard.
2. Plug the other end of the USB-C cable into a USB power source (e.g., computer USB port, USB wall adapter).
3. The charging indicator light will illuminate during charging and turn off once fully charged. A full charge typically takes 2 hours.

The keyboard automatically enters sleep mode after 30 minutes of inactivity to conserve battery. Press any key to wake it up instantly.



Multi-device Connectivity

One-key switching between 4 devices for more efficient usage

Image: Close-up of the keyboard's USB-C charging port with a cable connected, highlighting the quick charge feature.

7. MAINTENANCE

- Clean the keyboard regularly with a soft, dry cloth.
- Avoid using harsh chemicals or abrasive materials.
- Keep the keyboard away from liquids and extreme temperatures.
- Store the 2.4G USB receiver in its designated slot on the back of the keyboard when not in use to

prevent loss.

1. Please make sure your keyboard is fully charged. Charge the keyboard before use & ensure that it is used within a range of 49ft/15M.
2. Remove/delete all Bluetooth connection records on your device, turn off Bluetooth.
3. Turn on the device's Bluetooth again, reconnect the keyboard according to the user manual.

If the above method does not work, please try the following forced pairing method:

Bluetooth forced pairing method:

1. Please bring the keyboard close to the device, turn on the device's Bluetooth.
2. Short press the Bluetooth channel button corresponding to the device (the light will light up).
3. Long press the channel button for more than 3 seconds until the green LED light flashes quickly, complete the pairing of the device and the keyboard within 2 minutes.
4. The LED of the channel turns off after being on for 2 seconds, indicating that the device and the keyboard have been successfully paired.

2.4G forced pairing method:

1. Please bring the keyboard close to the device, short press the 2.4G channel button (the light will light up),
2. Long press for more than 3 seconds until the red LED flashes quickly.
3. Insert the USB Dongle within 20 seconds (make sure the keyboard is close to the receiver).
3. The LED of the 2.4G channel turns off after being on for 2 seconds, indicating that the device and the keyboard are paired successfully.

Note: If none of the above solutions work, please contact our service team for additional support.

Image: Diagram of the keyboard's back panel, showing the adjustable support buckles, power switch, USB-C charging port, USB receiver storage, and anti-slip pads.

8. TROUBLESHOOTING

If you encounter any issues with your keyboard, please try the following solutions:

1. **Ensure full charge:** Make sure your keyboard is fully charged. Charge the keyboard before use and ensure it is used within a range of 15 meters (49 feet).
2. **Reconnect Bluetooth:** Remove/delete all Bluetooth connection records on your device, turn off Bluetooth, then turn it back on and reconnect the keyboard according to the user manual.
3. **Computer Lag:** If the issue is caused by computer lag, please restart your computer and reconnect the keyboard.
4. **Signal Interference:** The keyboard signal may be interfered with. Try to stay away from metal obstacles or other radio signals.
5. **2.4G Connection Issue:** If you are using 2.4G to connect, unplug the USB receiver and re-insert it into the device.

If none of the above solutions work, please contact our professional customer service team for additional support.

1. For Android devices: Press Fn+Q
2. For Windows devices: Press Fn+W
3. For iOS devices: Press Fn+E

Note:

1. Due to differences in systems, key differences will occur. To ensure that your keys can be used effectively, please switch according to the system used by your device.
2. Generally speaking, the system will automatically switch in Bluetooth mode, but if some keys cannot be used, please use the above shortcut keys to switch systems.

Image: Text-based troubleshooting guide for common keyboard issues, including battery, connection, and signal problems.

9. SPECIFICATIONS

Feature	Detail
Brand	TECKNET
Model Number	TK-KB005
Connectivity Technology	Bluetooth, 2.4G USB-A
Compatible Devices	Laptop, PC, Smart TV, Smartphone, Tablet, iPad
Keyboard Layout	QWERTY, Full Size (110 keys)
Special Features	12 Multimedia Keys, 90% Noise Reduction, Ergonomic, Low-Profile Key, Rechargeable
Battery Capacity	500mAh
Product Dimensions	17.13"L x 5.12"W x 0.57"H
Item Weight	568 Grams

Material	Plastic
----------	---------

10. WARRANTY AND SUPPORT

TECKNET offers up to 36-month support for this product (registration may be required). If you encounter any problems or have questions regarding your TK-KB005 keyboard, please do not hesitate to contact our customer service team. We are committed to providing friendly and helpful assistance.

For customer service inquiries, please refer to the contact information provided in your product packaging or visit the official TECKNET website.