

Manuals.plus /

> NPET /

> NPET Automatic Pet Feeder 4L - Instruction Manual

NPET PETPFF010BK-US-Ali

NPET Automatic Pet Feeder 4L

Model: PETPFF010BK-US-Ali | Brand: NPET

INTRODUCTION

The NPET Automatic Pet Feeder is designed to provide a convenient and reliable solution for feeding your pets. This programmable food dispenser allows you to customize feeding schedules with precise portion control, ensuring your pet receives fresh food at designated times, whether you are at home or away. Its dual power supply system guarantees continuous operation, even during power outages.

Key features include:

- Customizable feeding schedule: Program up to 4 meals per day with adjustable portion sizes (0-9 levels per meal).
- Extended freshness storage: 4-liter airtight container preserves kibble freshness for up to 20 days.
- Reliable dual power supply: USB adapter for primary power and 3 AA batteries (not included) for backup.
- Easy setup and cleaning: Intuitive LCD screen for programming and dishwasher-safe removable components.
- Pet-proof and quiet operation: Secure locking mechanism and low-noise dispensing.

SAFETY INFORMATION

Important Safety Precautions:

- This feeder is designed for **dry food only**. Do not use with wet, canned, or moist pet food.
- Keep out of reach of children.
- Ensure the feeder is placed on a stable, level surface to prevent tipping.
- Do not immerse the main unit in water or any other liquid.
- Always unplug the feeder before cleaning.
- Use only the provided USB adapter or recommended batteries.
- Regularly check for any damage to the power cord or feeder components.

PACKAGE CONTENTS

Please check the package to ensure all items are present:

- NPET Automatic Pet Feeder Main Unit

- Food Storage Container with Lid
- Food Dispenser Base
- Stainless Steel Food Bowl
- USB Power Adapter and Cable
- User Manual

PRODUCT OVERVIEW



The NPET Automatic Pet Feeder, fully assembled and ready for use, showcasing its sleek black design and integrated food bowl.

USER-FRIENDLY CONTROL PANEL

Clearly, detailed instructions of setting process



Detailed view of the feeder's internal structure, highlighting the 45-degree gravity-fed design for smooth food dispensing and the secure twist-lock lid for freshness.

The NPET Automatic Pet Feeder consists of a main base unit with an integrated control panel, a transparent food storage container, and a removable food bowl. The container features a twist-lock lid to maintain food freshness and prevent spills. The internal design ensures smooth food flow, minimizing clogs.

NEVER MISS A MEAL

No matter where you are



At home



Short Trip



Overtime



A close-up of the feeder's control panel, showing the LCD display and clearly labeled buttons for time setting, meal setting, bee sound, and confirmation (OK).

DUAL POWER SUPPLY

Your pet will get food consistently



An illustration demonstrating the dual power supply options: a 5V AC adapter for primary power and a compartment for 3 AA batteries (not included) for backup.

SETUP GUIDE

1. **Assemble the Feeder:** Place the food storage container securely onto the base unit. Ensure it clicks into place.
2. **Attach the Food Bowl:** Slide the stainless steel food bowl into the designated slot at the front of the feeder base.
3. **Power Connection:**
 - **Primary Power:** Connect the USB cable to the feeder's power port and plug the adapter into a wall outlet.
 - **Battery Backup (Optional but Recommended):** Open the battery compartment on the bottom of the feeder and insert 3 new AA batteries (not included). This ensures the feeder continues to operate during power outages.
4. **Fill with Dry Food:** Open the twist-lock lid on top of the food container. Pour dry pet kibble into the container. Ensure the lid is securely closed after filling.

OPERATING INSTRUCTIONS

The feeder's control panel allows for easy programming of feeding times and portions.



An illustrative graphic demonstrating the flexibility of setting customized meal times throughout the day and adjusting portion sizes from 1 to 9 levels.

1. Set Current Time:

- Press the **Time Setting** button (clock icon).
- Use the **Up/Down** buttons (usually 1 and 2 or dedicated arrows) to adjust the hour. Press **OK** to confirm.
- Repeat for minutes.

2. Program Meal Times and Portions:

- Press the **Meal Setting** button (food bowl icon). The display will show '1' for the first meal.
- Use the **Up/Down** buttons to set the desired feeding time for Meal 1. Press **OK**.
- Next, set the portion size for Meal 1 (0-9 levels) using the **Up/Down** buttons. Press **OK**.

- Repeat steps for Meal 2, Meal 3, and Meal 4 as needed. If a meal is not required, set its portion size to '0'.

3. Manual Feeding:

- To dispense food immediately, press and hold the **OK** button for a few seconds.
- The feeder will dispense one portion. Repeat as necessary for additional portions.

4. Bee Sound (Optional):

- Some models may have a 'Bee Sound' button. Pressing this button may activate a sound notification before dispensing food to alert your pet. Refer to your specific model's detailed instructions for this feature.

MAINTENANCE AND CLEANING

Regular cleaning ensures hygiene and extends the life of your pet feeder.



The removable food container and stainless steel bowl are shown being cleaned, emphasizing the feeder's easy-to-clean design.

- **Disassembly:** Unplug the feeder from power. Remove the food bowl, then detach the food storage container from

the base.

- **Cleaning Components:** The food storage container and the stainless steel food bowl are dishwasher-safe or can be washed by hand with mild soap and water. Rinse thoroughly.
- **Cleaning the Base Unit:** Wipe the main base unit with a soft, damp cloth.**Do not immerse the base unit in water.**
- **Drying:** Ensure all components are completely dry before reassembling and refilling with food.
- **Regular Inspection:** Periodically check the food chute for any blockages or residue buildup.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Feeder not dispensing food.	No power; Food chute clogged; Container empty; Incorrect programming.	Check power connection and battery backup. Clear any food blockages. Refill food container. Verify meal times and portion settings.
Display not working.	No power; Batteries drained.	Ensure power adapter is securely plugged in. Replace AA batteries if using backup power.
Food not fresh.	Lid not sealed properly.	Ensure the twist-lock lid is securely closed and sealed after refilling.
Pet accessing food prematurely.	Feeder not securely locked.	Ensure the food container is properly locked onto the base to prevent pet access.

SPECIFICATIONS



A visual representation of the feeder's dimensions, including height, width, and depth, for proper placement and space planning.

Feature	Detail
Model Name	PETPFF010BK-US-Ali
Capacity	4 Liters (approx. 140.8 oz)
Material	BPA Free ABS
Dimensions (L x W x H)	8.66 x 7.48 x 7.48 inches
Item Weight	2.7 Pounds
Power Supply	5V AC Adapter (USB) + 3 AA Batteries (backup)
Meals Per Day	Up to 4
Portions Per Meal	0-9 levels

Feature	Detail
Target Species	Cats, Small Dogs

WARRANTY AND SUPPORT

This NPET Automatic Pet Feeder comes with a 1-year limited warranty from the date of purchase. This warranty covers manufacturing defects and workmanship under normal use.

For technical support, warranty claims, or any questions regarding your product, please contact NPET customer service through their official website or the contact information provided with your purchase. Please have your model number (PETPFF010BK-US-Ali) and proof of purchase ready when contacting support.

For more information, visit the official NPET Store: [NPET Store on Amazon](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Email

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Details

Submit question

Open the live page

<https://manuals.plus/asin/B0F5WT2BN8>

More documents and user manuals: <https://manuals.plus/>