Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

GOFJAJHQ VVN3

GOFJAJHQ 25.2V 5000mAh VVN3 Lithium Ion Battery User Manual

For Dreame Handheld Cordless Vacuum Cleaners (V8, V9, V10, V9P, XR, VVN3)

1. Introduction

This manual provides essential information for the safe and effective use of your GOFJAJHQ 25.2V 5000mAh VVN3 Lithium Ion Battery. This replacement battery is designed to be compatible with various Dreame handheld cordless vacuum cleaner models, including V8, V9, V10, V9P, XR, and VVN3. Please read this manual thoroughly before installation and operation to ensure optimal performance and safety.

2. Safety Information

Lithium-ion batteries require careful handling. Adhere to the following safety guidelines:

- **Do not disassemble:** Attempting to disassemble the battery can lead to electric shock, fire, or explosion.
- **Avoid extreme temperatures:** Do not expose the battery to direct sunlight, heat sources, or temperatures below 0°C (32°F) or above 45°C (113°F).
- **Prevent short circuits:** Do not allow metal objects to come into contact with the battery terminals.
- **Keep dry:** Do not expose the battery to water or other liquids.
- **Use compatible chargers:** Only use the original vacuum cleaner charger or a compatible charger specified for lithium-ion batteries.
- **Dispose properly:** Do not dispose of batteries in household waste. Follow local regulations for recycling lithium-ion batteries.
- **Inspect for damage:** If the battery appears damaged, swollen, or leaking, discontinue use immediately and dispose of it safely.

3. Product Overview

The GOFJAJHQ 25.2V 5000mAh VVN3 Lithium Ion Battery is a high-capacity replacement designed to restore or enhance the performance of your compatible Dreame cordless vacuum cleaner. It features a robust design and advanced cell technology to provide reliable power.



Image 1: Front view of the GOFJAJHQ VVN3 Lithium Ion Battery.

Key Features:

- **High Capacity:** 5000mAh for extended cleaning sessions.
- **Voltage:** 25.2V, matching original specifications.
- **Compatibility:** Designed for Dreame V8, V9, V10, V9P, XR, and VVN3 models.
- **Enhanced Performance:** Provides sufficient power for continuous operation, preventing interruptions due to power exhaustion.
- **Longevity:** Reduces motor load and wear, potentially extending the vacuum cleaner's lifespan.
- **Safety:** Replaces aging batteries to mitigate risks such as bulging or liquid leakage.



Image 2: Diagram illustrating the internal structure and high capacity features of the battery.

4. Installation (Setup)

Follow these general steps to replace the battery in your compatible Dreame handheld cordless vacuum cleaner. Specific steps may vary slightly by vacuum model. Always refer to your vacuum cleaner's original manual for detailed instructions.

1. **Power Off and Unplug:** Ensure your vacuum cleaner is turned off and unplugged from any charging source.
2. **Locate Battery:** Identify the battery compartment on your vacuum cleaner. This is typically at the base of the handle or main body.
3. **Remove Old Battery:** Depending on your model, you may need to press a release button, slide a latch, or unscrew retaining screws to remove the old battery. Carefully pull the old battery out.
4. **Insert New Battery:** Align the GOFJAJHQ VVN3 battery with the compartment and slide it into place. Ensure it clicks securely or that any screws are re-fastened.
5. **Charge Fully:** After installation, place the vacuum cleaner on its charging dock or connect the charger to fully charge the new battery before first use.



Image 3: The replacement battery shown with a compatible vacuum cleaner, illustrating its intended use.

5. Operating Instructions

Once installed and fully charged, the GOFJAJHQ VVN3 battery operates seamlessly with your Dreame vacuum cleaner.

- **Charging:** Always use the original or a compatible charger. A full charge typically takes several hours. Avoid overcharging by disconnecting the charger once the battery indicator shows full.
- **Discharge:** Use the vacuum cleaner as normal. The battery is designed to provide consistent power until depleted.
- **First Use:** For optimal battery life, it is recommended to fully charge the battery before its first use and then fully discharge it during operation.

6. Maintenance

Proper maintenance can extend the lifespan and performance of your battery.

- **Regular Charging:** Do not leave the battery completely discharged for extended periods. Charge it regularly, even if not in frequent use.
- **Storage:** If storing the battery for a long time, charge it to about 50-60% and store it in a cool, dry place away from direct sunlight. Recharge every 3-6 months.
- **Cleaning:** Keep the battery terminals clean and free of dust or debris. Use a dry cloth to wipe the battery exterior.
- **Avoid Impact:** Protect the battery from physical shocks or drops.

7. Troubleshooting

If you encounter issues with your GOFJAJHQ VVN3 battery, consider the following common solutions:

Problem	Possible Cause	Solution
Battery not charging	Charger not connected, faulty charger, or battery not seated correctly.	Ensure charger is properly connected. Test charger with another device if possible. Re-seat the battery firmly.
Vacuum cleaner not powering on	Battery fully discharged, battery not installed correctly, or vacuum cleaner fault.	Charge the battery fully. Check battery installation. If issue persists, consult your vacuum cleaner's manual.
Reduced run time	Battery not fully charged, or operating in high-power mode.	Ensure battery is fully charged before use. Reduce power mode if extended run time is needed.
Battery feels hot during charging/use	Normal operation (slight warmth), or potential overheating.	Slight warmth is normal. If excessively hot, disconnect immediately and allow to cool. Do not use if overheating persists.

8. Specifications

- **Model:** VVN3
- **Nominal Capacity:** 5000mAh
- **Voltage:** 25.2V
- **Type:** Li-Ion (Lithium-Ion)
- **Weight:** Approximately 500g (1.1 lbs)
- **Certifications:** CE, FCC, RoHS, UL, KC
- **Compatible Models:** Dreame V8, V9, V10, V9P, XR, VVN3 Handheld Cordless Vacuum Cleaners



Image 4: Side view of the battery, highlighting its connection interface.

9. Warranty and Support

For warranty information and customer support, please refer to the seller or the original purchase documentation. Keep your proof of purchase for any warranty claims.

© 2025 GOFJAJHQ. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0F92P8ZK7

More documents and user manuals: **https://manuals.plus/**