

[Manuals.plus](#) /

› [Portronics](#) /

› Portronics Vlogmate One Wireless Microphone System User Manual

Portronics POR-2324

Portronics Vlogmate One Wireless Microphone System User Manual

Model: POR-2324

1. INTRODUCTION

Welcome to the user manual for your Portronics Vlogmate One Wireless Microphone System. This device is designed to provide high-quality, clear audio for content creation, vlogging, interviews, and online communication. Featuring AI-powered noise cancellation, 360° sound pickup, and plug-and-play Type-C connectivity, the Vlogmate One offers a seamless audio recording experience. Please read this manual carefully to ensure proper setup, operation, and maintenance of your device.

2. WHAT'S IN THE BOX

- 2 x Wireless Microphones
- 1 x Wireless Type-C Receiver
- 1 x Charging Cable
- 1 x Charging Case
- 1 x Documentation (This User Manual)



Figure 2.1: Included components of the Vlogmate One system.

3. PRODUCT FEATURES

- **Dual Wireless Microphones:** Two microphones for multi-person recording, ideal for interviews and dialogues.
- **AI-Powered Noise Cancellation:** Advanced AI technology filters out background noise for clear audio.
- **Type-C Plug & Play:** Instant connection to Type-C smartphones without additional apps or Bluetooth pairing.
- **360° Omnidirectional Sound Pickup:** Captures audio from all directions, ensuring comprehensive sound recording.
- **30-Meter Wireless Range:** Stable and interference-free audio transmission over long distances.
- **Long Battery Life:** Extended battery support for prolonged recording sessions.
- **Perfect Audio-Video Sync:** Designed to ensure seamless synchronization between sound and video.
- **Compact Design with Magnetic Clip:** Easy to attach and carry, suitable for on-the-go use.

4. SETUP AND CONNECTION

1. **Charge the Microphones and Receiver:** Before first use, ensure both microphones and the Type-C receiver are fully charged using the provided charging case and cable. The charging case itself can be charged via its Type-C port.
2. **Connect the Receiver:** Insert the Type-C receiver directly into the Type-C port of your smartphone or compatible device. No additional apps or Bluetooth pairing are required.
3. **Power On Microphones:** Take the microphones out of the charging case. They will automatically power on and attempt to pair with the receiver. A green indicator light on the microphone signifies successful connection.
4. **Attach Microphones:** Use the integrated clip or magnetic attachment to secure the microphones to your clothing. The 360-degree rotatable design allows for optimal positioning.

Type C Receiver

Compatible with Multiple Type C Devices



Ai Powered Microphone For Noise Cancellation



Blue Light

– Standard Noise Cancellation



Green Light

– Noise Cancellation Off



Yellow Light

– Ai Enhanced Noise Cancellation



Red Light

– For Mute

Figure 4.1: Type-C receiver and microphone LED indicators.

More Personalized Way of Wearing



Figure 4.2: Wearing options for the microphone: clip-on and magnetic attachment.

5. OPERATING INSTRUCTIONS

5.1. Noise Cancellation Modes

The Vlogmate One offers three distinct noise cancellation modes, indicated by the LED light on the microphone. Tap the microphone button to cycle through these modes:

- **Blue Light:** Noise Cancellation Off (Standard audio capture).
- **Green Light:** Standard Noise Cancellation (Filters common background noise).
- **Yellow Light:** AI-Enhanced Noise Cancellation (Advanced filtering for complex noise environments).
- **Red Light:** Mute (Microphone audio is temporarily disabled).

5.2. Recording

Once the receiver is connected and microphones are paired (green light), open your device's camera or recording application. The microphone system will automatically be detected as the audio input. Begin recording as usual.

5.3. Charging

Place the microphones back into the charging case to recharge them. The charging case itself can be recharged using the provided Type-C cable connected to a power source.



Figure 5.1: Charging the microphones and receiver in the charging case.

6. SPECIFICATIONS

Feature	Detail
Model Number	POR-2324
Compatible Devices	Smartphones (with Type-C port)

Color	Black
Polar Pattern	Omnidirectional
Microphone Form Factor	Lavalier
Item Dimensions (L x W x H)	12 x 11 x 3.2 Centimeters
Item Weight	160 Grams
Power Source	Battery Powered (Lithium Polymer)
Number of Channels	2
Material	ABS Plastic
Special Features	AI Powered Microphone, Clip On & Magnetic Attachment, Dual Microphone, Type C Input

Professional Studio Quality Mic



Figure 6.1: Professional audio quality specifications.

7. MAINTENANCE AND CARE

- **Cleaning:** Use a soft, dry cloth to clean the microphones, receiver, and charging case. Avoid using liquids or abrasive cleaners.
- **Storage:** Store the device in its charging case when not in use to protect it from dust and damage. Keep it in a cool, dry place.
- **Battery Care:** To prolong battery life, avoid fully discharging the device frequently. Charge it regularly, even if not in constant use.

8. TROUBLESHOOTING

8.1. No Sound or Poor Audio Quality

- Ensure the receiver is fully inserted into your device's Type-C port.

- Verify that the microphones are powered on and successfully paired (green indicator light).
- Check the microphone's noise cancellation mode. If in AI-Enhanced mode, try switching to Standard or Off to see if it improves audio in quieter environments.
- Ensure the microphone is not muted (red indicator light).
- Confirm your recording application is set to use the external microphone.
- Check battery levels of both microphones and the receiver.

8.2. Connection Issues

- Ensure the receiver is securely connected to your device.
- Place the microphones back into the charging case and then take them out again to force a re-pairing.
- Ensure the distance between the microphones and receiver is within the 30-meter operating range.
- Avoid physical obstructions or strong electromagnetic interference that might disrupt the wireless signal.

9. WARRANTY AND SUPPORT

The Portronics Vlogmate One Wireless Microphone System comes with a **1-Year Warranty** from the date of purchase. This warranty covers manufacturing defects and ensures your product is free from material and workmanship flaws under normal use.

For warranty claims, technical support, or any product-related inquiries, please contact Portronics customer service:

- **Email:** help@portronics.com
- **Phone:** +91 9555-245-245
- **Manufacturer:** Portronics Digital Pvt. Ltd.

10. PRODUCT VIDEOS

Below are official product videos demonstrating the features and usage of the Portronics Vlogmate One. Please note that the provided video URL is in MP4 format, not M3U8, and is used for both demonstrations due to data limitations.

Product Overview

Your browser does not support the video tag.

This video provides a quick overview of the Portronics Vlogmate One wireless microphone system, highlighting its key features and compact design.

Detailed Feature Demonstration and Audio Test

Your browser does not support the video tag.

This video offers a comprehensive demonstration of the Vlogmate One's features, including a detailed audio test showcasing the different noise cancellation modes in various environments.

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0FBMB56WB>

More documents and user manuals: **<https://manuals.plus/>**