

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [uwant](#) /
- › [uwant M600 Futon Cleaner Instruction Manual](#)

uwant M600

uwant M600 Futon Cleaner Instruction Manual

Model: M600

1. INTRODUCTION

Thank you for purchasing the uwant M600 Futon Cleaner. This manual provides essential information for the safe and effective use, maintenance, and troubleshooting of your device. Please read this manual thoroughly before use and keep it for future reference.

18kPa吸引力 × 500W高出力モーター

高周波たたきでダニ・毛・ホコリ・
アレル物質を除去。



Image 1.1: The uwant M600 Futon Cleaner.

2. PACKAGE CONTENTS

Verify that all items listed below are included in your package. If any items are missing or damaged, please contact customer support.

- uwant M600 Futon Cleaner Main Unit
- Filter Sponges (3 total, 1 pre-installed)
- User Manual (this document)
- Warranty Card

- Small Cleaning Brush



Image 2.1: All components included in the uwant M600 package.

3. SETUP

1. **Unpacking:** Carefully remove all components from the packaging.
2. **Filter Installation:** Ensure the filter sponge and cyclone unit are correctly installed in the dust cup. One filter sponge is typically pre-installed.
3. **Dust Cup Attachment:** Align the dust cup with the main unit's suction port and press firmly until it clicks into place.
4. **Power Connection:** Plug the power cord into a suitable electrical outlet. The device is corded electric and does not use batteries.

4. OPERATING INSTRUCTIONS

4.1 Power On/Off

Press the power button located on the handle to turn the device on or off. The device will start with its default settings.

4.2 Cleaning Modes and Features

The uwant M600 combines several technologies for effective cleaning:

- **Powerful Suction (18KPa):** The strong suction power effectively removes mites, hair, and fine dust from deep within fabrics.
- **High-Performance Metal Beater:** A newly developed metal beating bar delivers up to 60,000 high-speed beats per minute to dislodge embedded mites and dust.
- **UV Sterilization:** A 253.7nm high-transmittance UV light sterilizes surfaces. For safety, the UV light only activates when the device is in contact with a surface, preventing accidental exposure to humans or pets.
- **Ultrasonic Mite Suppression:** Ultrasonic waves are emitted to help suppress mite reproduction.
- **65°C Hot Air Drying:** A downward-facing air outlet at the bottom of the unit transfers motor heat to bedding, providing 65°C hot air drying. This helps to dehumidify and prevent mite reproduction, creating a comfortable sleeping environment.
- **Smart Mite Detection System:** An integrated system monitors cleaning status in real-time. A green light indicates a clean state, while a red light warns of excessive mites, guiding you to more precise and

efficient cleaning.



Image 4.1: The cleaner demonstrating its powerful suction and beating action.



Image 4.2: The UV light function for sterilization.



Image 4.3: The hot air drying feature in operation.



ダニ数値をリアルタイムで可視化

ホコリ感知センサー×LED表示で、除ダニの進行状況を可視化。

Image 4.4: The smart display indicating cleaning status (green for clean, red for high mite presence).



新強化たたきバー搭載

UWANT従来モデルと比べて、強化バー+幅広・厚手の防絡シリコンでたたき力66.6%アップ。除ダニ効率が大幅向上。



Image 4.5: Detail of the high-performance metal beating bar.

4.3 Versatile Use

The uwant M600 is designed for various surfaces beyond futons, making it suitable for:

- Sofas
- Pillows
- Stuffed Animals
- Carpets
- Car Seats
- Pet Mats

実際の購入者体験が証明する高品質



Image 4.6: The cleaner being used on different household items.

5. MAINTENANCE

Regular maintenance ensures optimal performance and longevity of your uwant M600 Futon Cleaner.

5.1 Dust Cup and Filter Cleaning

The device features a 6-layer filter system, including a HEPA filter, for thorough dust capture.

1. **Remove Dust Cup:** Press the dust cup release button on the handle and lift the dust cup from the main unit.
2. **Empty Dust Cup:** Open the dust cup cover and empty collected dust and debris into a trash bin.
3. **Disassemble Filters:** Remove the cyclone unit and filter sponge from the dust cup.
4. **Wash Components:** The dust cup, filter sponge, cyclone unit, and roller brush unit are washable. Rinse them thoroughly with water. Warm water can make cleaning more efficient.
5. **Dry Completely:** Ensure all washed components are completely dry before reassembling. Do not use the device with wet filters.
6. **Reassemble:** Reinsert the filter sponge into the cyclone unit, then place it back into the dust cup. Close the dust cup cover and reattach the dust cup to the main unit.

6重フィルターシステム

- ① サイクロンコーンフィルター
- ② HEPAスポンジフィルター
- ③ ダストカップ
- ④ シリコンフィルター
- ⑤ 円錐型サイクロン
- ⑥ 排気フィルター



Image 5.1: Exploded view of the 6-layer filter system.

5.2 Roller Brush Cleaning

1. **Remove Roller Brush Cover:** Slide the two bottom plate locks simultaneously to release and lift the roller brush cover.
2. **Remove Brush Unit:** Take out the roller brush unit.
3. **Clean:** Carefully wipe away any accumulated dust or hair from the brush and the brush compartment.
4. **Reinstall:** Insert one end of the roller brush unit first, then push the other end into place. Reattach the roller brush cover, ensuring it clicks securely.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device does not turn on	Power cord not properly plugged in	Check power connection to outlet and device.
Weak suction power	Dust cup is full or filters are clogged	Empty the dust cup and clean/wash the filters. Ensure they are completely dry before reassembly.
UV light not activating	Device not in contact with surface or lifted at an angle	Ensure the device is flat against the surface. The UV light has a gravity sensor and will turn off if lifted more than 30 degrees.
Red light on smart display	High concentration of mites/dust detected	Continue cleaning the area until the light turns green, indicating a clean state.
Device overheating	Prolonged use or blocked air vents	Turn off the device and allow it to cool down. Check for any blockages in the air vents.

7. SPECIFICATIONS

Feature	Detail
Brand	uwant
Model Number	M600
Manufacturer	CINDERSON TECH (SUZHOU) CO., LTD
Color	Silver and Purple
Power Source	Corded Electric
Suction Power	18KPa
Hot Air Temperature	65°C
Beating Frequency	Up to 60,000 beats/minute
Filter Type	HEPA Filter (6-layer system)
Dust Cup Capacity	0.36 liters

Feature	Detail
Package Weight	2.2 kilograms
Package Dimensions	32.5 x 29.7 x 20.2 cm
Special Features	UV light, Ultrasonic, Washable filter, Compact, Lightweight, Smart Mite Detection
Recommended Use	Futons, mattresses, carpets, pet beds, stuffed animals, sofas, car seats

8. WARRANTY AND SUPPORT

8.1 Manufacturer's Warranty

The uwant M600 Futon Cleaner comes with a **2-year manufacturer's warranty** for the main unit, covering major malfunctions under normal use. Please refer to the included warranty card for detailed terms and conditions.

8.2 Customer Support

For any questions, technical assistance, or warranty claims, please contact uwant customer support through the official website or the contact information provided on your warranty card. When contacting support, please have your model number (M600) and purchase date available.

9. SAFETY PRECAUTIONS

- Always unplug the device before cleaning or performing maintenance.
- Do not use the device on wet surfaces or to pick up liquids.
- Keep the device away from direct sunlight and humid environments when not in use. Store it in a well-ventilated area.
- Do not allow children to operate the device unsupervised.
- Ensure all filters are completely dry before reassembling and using the device.
- Do not look directly at the UV light when it is active. The safety mechanism is designed to prevent exposure during normal use.