

SHANLING ME600

SHANLING ME600 In-Ear Earphones User Manual

Model: ME600

1. INTRODUCTION

Thank you for choosing the SHANLING ME600 In-Ear Earphones. The ME600 features a sophisticated 2 Dynamic Driver + 3 Balanced Armature hybrid design, engineered for high-fidelity audio reproduction. This manual provides essential information for the proper setup, operation, and maintenance of your earphones to ensure optimal performance and longevity.

2. PACKAGE CONTENTS

Please verify that all items listed below are present in your package:

- SHANLING ME600 In-Ear Earphones (1 pair)
- Detachable Audio Cable with MMCX connectors and interchangeable 3.5mm/4.4mm plugs
- Assorted Silicone and Foam Ear Tips (various sizes)
- Interchangeable Sound Tuning Nozzles (3 pairs)
- Storage Case
- Cleaning Tool



Image 1: SHANLING ME600 In-Ear Earphones. This image displays the two earphone units connected to their braided audio cables, showcasing their black, contoured stainless steel bodies and the twisted cable design.

3. SETUP

3.1 Connecting the Cable

1. Identify the left (L) and right (R) earphone units and cable connectors. The cable connectors are typically marked.
2. Align the MMCX connector on the cable with the receptacle on the earphone unit.
3. Gently push the connector straight into the receptacle until you feel a click. Do not force the connection.
4. To disconnect, firmly grasp the cable connector (not the cable itself) and pull it straight out from the earphone unit. Avoid twisting.

3.2 Selecting Ear Tips

Proper ear tip selection is crucial for sound quality, bass response, and comfort. Experiment with the included ear tips (silicone and foam, various sizes) to find the best fit for your ears. A good seal will block external noise and provide optimal audio performance.

3.3 Wearing the Earphones

The SHANLING ME600 earphones are designed to be worn with the cable over the ear. This provides a secure fit and reduces microphonics (cable noise).

1. Insert the earphone unit into your ear canal.

2. Loop the cable gently over the top of your ear.
3. Adjust the earphone and cable for a comfortable and secure fit.

3.4 Connecting to an Audio Source

The ME600 cable features interchangeable plugs (3.5mm and 4.4mm balanced). Select the appropriate plug for your audio device.

- **3.5mm Single-Ended Plug:** Compatible with most smartphones, laptops, and portable audio players.
- **4.4mm Balanced Plug:** For use with compatible balanced audio outputs on high-resolution audio players and amplifiers, offering improved power and channel separation.

Ensure the plug is fully inserted into your audio device's output jack.

4. OPERATING THE EARPHONES

4.1 Basic Audio Playback

Once connected to an audio source, begin playback from your device. Adjust the volume to a comfortable listening level. Avoid excessively high volumes to prevent hearing damage.

4.2 Interchangeable Sound Tuning Nozzles

The SHANLING ME600 includes three pairs of interchangeable sound tuning nozzles, allowing you to customize the sound signature to your preference. Each nozzle type is designed to subtly alter the frequency response.

1. Carefully unscrew the currently installed nozzle from the earphone unit.
2. Select your desired tuning nozzle.
3. Gently screw the new nozzle onto the earphone unit until it is secure. Do not overtighten.
4. Reattach the ear tips.

Experiment with different nozzles to discover the sound profile that best suits your listening preferences and music genres.

5. MAINTENANCE

5.1 Cleaning the Earphones and Ear Tips

- Regularly clean the ear tips with a soft, damp cloth. For silicone tips, they can be removed and washed with mild soap and water, then thoroughly dried before reattaching.
- Use the provided cleaning tool to gently remove any earwax or debris from the earphone nozzles and grilles. Ensure no moisture enters the earphone body.
- Wipe the earphone bodies with a soft, dry, lint-free cloth.

5.2 Cable Care

- Avoid sharp bends or excessive pulling on the cable.
- When storing, coil the cable loosely.
- Keep the cable away from extreme temperatures and direct sunlight.

5.3 Storage

When not in use, store your SHANLING ME600 earphones in the provided storage case to protect them

from dust, moisture, and physical damage.

6. TROUBLESHOOTING

- **No Sound or Intermittent Sound:**
 - Ensure the cable is securely connected to both the earphones and the audio source.
 - Check the volume level on your audio device.
 - Test with a different audio source or cable if possible to isolate the issue.
 - Verify that the correct audio output is selected on your device.
- **Poor Sound Quality or Lack of Bass:**
 - This often indicates an improper seal. Try different sizes or types of ear tips to achieve a snug fit.
 - Ensure the earphone nozzles are free from earwax or debris.
 - Check if the interchangeable tuning nozzles are securely attached.
- **Earphones Feel Uncomfortable:**
 - Experiment with different ear tip sizes and materials.
 - Adjust the angle and depth of insertion until a comfortable fit is achieved.

If you continue to experience issues, please refer to the support information in Section 8.

7. SPECIFICATIONS

Type	In-ear
Drivers	2 Dynamic & 3 Balanced Armature (per side)
Impedance	16Ω
Sensitivity	100±3dB
Frequency Response	12-40000Hz
Cable	Monocrystalline copper silver-plated, detachable MMCX
Connectors	Interchangeable 3.5mm & 4.4mm plugs
Cable Length	1.3 meters
Weight (per earphone)	Approximately 12.5g
Body Material	Hand-Polished Gold-Plated Stainless Steel (Black variant)

8. WARRANTY AND SUPPORT

SHANLING products are manufactured to high quality standards. For information regarding warranty coverage, please refer to the warranty card included with your product or visit the official SHANLING website. If you encounter any issues or require technical assistance, please contact SHANLING customer support through their official channels or the retailer from whom you purchased the product.

Official SHANLING Website: www.shanling.com

